

## 16-bit Proprietary Microcontroller

CMOS

# F<sup>2</sup>MC-16LX MB90595/595G Series

## MB90598/598G/F598/F598G/V595/V595G

### ■ DESCRIPTION

The MB90595/595G series with FULL-CAN<sup>\*1</sup> interface and FLASH ROM is especially designed for automotive and industrial applications. Its main features are two on board CAN Interfaces, which conform to V2.0 Part A and Part B, while supporting a very flexible message buffer scheme and so offering more functions than a normal full CAN approach.

The instruction set of F<sup>2</sup>MC-16LX CPU core inherits an AT architecture of the F<sup>2</sup>MC<sup>\*2</sup> family with additional instruction sets for high-level languages, extended addressing mode, enhanced multiplication/division instructions, and enhanced bit manipulation instructions. The microcontroller has a 32-bit accumulator for processing long word data.


The MB90595/595G series has peripheral resources of 8/10-bit A/D converters, UART (SCI), extended I/O serial interface, 8/16-bit PPG timer, I/O timer (input capture (ICU), output compare (OCU)) and stepping motor controller.

\*1: Controller Area Network (CAN) - License of Robert Bosch GmbH

\*2: F<sup>2</sup>MC stands for FUJITSU Flexible Microcontroller.

### ■ PACKAGE

100-pin Plastic QFP



(FPT-100P-M06)

# MB90595/595G Series

## ■ FEATURES

- Clock
  - Embedded PLL clock multiplication circuit
  - Operating clock (PLL clock) can be selected from divided-by-2 of oscillation or one to four times the oscillation (at oscillation of 4 MHz, 4 MHz to 16 MHz).
  - Minimum instruction execution time: 62.5 ns (operation at oscillation of 4 MHz, four times the oscillation clock, V<sub>CC</sub> of 5.0 V)
- Instruction set to optimize controller applications
  - Rich data types (bit, byte, word, long word)
  - Rich addressing mode (23 types)
  - Enhanced signed multiplication/division instruction and RETI instruction functions
  - Enhanced precision calculation realized by the 32-bit accumulator
- Instruction set designed for high level language (C language) and multi-task operations
  - Adoption of system stack pointer
  - Enhanced pointer indirect instructions
  - Barrel shift instructions
- Program patch function (for two address pointers)
- Enhanced execution speed: 4-byte instruction queue
- Enhanced interrupt function: 8 levels, 34 factors
- Automatic data transmission function independent of CPU operation
  - Extended intelligent I/O service function (EI<sup>2</sup>OS): Up to 10 channels
- Embedded ROM size and types
  - Mask ROM: 128 Kbytes
  - Flash ROM: 128 Kbytes
  - Embedded RAM size: 4 Kbytes (MB90V595/595G: 6 Kbytes)
- Flash ROM
  - Supports automatic programming, Embedded Algorithm TM\*
  - Write/Erase/Erase-Suspend/Resume commands
  - A flag indicating completion of the algorithm
  - Hard-wired reset vector available in order to point to a fixed boot sector
  - Erase can be performed on each block
  - Block protection with external programming voltage
- Low-power consumption (stand-by) mode
  - Sleep mode (mode in which CPU operating clock is stopped)
  - Stop mode (mode in which oscillation is stopped)
  - CPU intermittent operation mode
  - Hardware stand-by mode
- Process: 0.5  $\mu$ m CMOS technology
- I/O port
  - General-purpose I/O ports: 78 ports
  - Push-pull output and Schmitt trigger input.
  - Programmable on each bit as I/O or signal for peripherals.
- Timer
  - Watchdog timer: 1 channel
  - 8/16-bit PPG timer: 8/16-bit  $\times$  6 channels
  - 16-bit re-load timer: 2 channels

(Continued)

# MB90595/595G Series

*(Continued)*

- 16-bit I/O timer
  - Input capture: 4 channels
  - Output compare: 4 channels
- Extended I/O serial interface: 1 channel
- UART0
  - With full-duplex double buffer (8-bit length)
  - Clock asynchronous or clock synchronized (with start/stop bit) transmission can be selectively used.
- UART1 (SCI)
  - With full-duplex double buffer (8-bit length)
  - Clock asynchronous or clock synchronized serial transmission (I/O extended transmission) can be selectively used.
- Stepping motor controller (4 channels)
- External interrupt circuit (8 channels)
  - A module for starting an extended intelligent I/O service (EI<sup>2</sup>OS) and generating an external interrupt which is triggered by an external input.
- Delayed interrupt generation module: Generates an interrupt request for switching tasks.
- 8/10-bit A/D converter (8 channels)
  - 8/10-bit resolution can be selectively used.
  - Starting by an external trigger input.
- FULL-CAN interface: 1 channel
  - Conforming to Version 2.0 Part A and Part B
  - Flexible message buffering (mailbox and FIFO buffering can be mixed)
- 18-bit Time-base counter
- External bus interface: Maximum address space 16 Mbytes

\*: Embedded Algorithm is a trademark of Advanced Micro Devices Inc.

# MB90595/595G Series

## ■ PRODUCT LINEUP

Features	MB90598/598G	MB90F598/F598G	MB90V595/V595G
Classification	Mask ROM product	Flash ROM product	Evaluation product
ROM size	128 Kbytes Boot block Hard-wired reset vector	128 Kbytes Boot block Hard-wired reset vector	None
RAM size	4 Kbytes	4 Kbytes	6 Kbytes
Emulator-specific power supply <sup>*1</sup>	—	—	None
CPU functions	The number of instructions: 351 Instruction bit length: 8 bits, 16 bits Instruction length: 1 byte to 7 bytes Data bit length: 1 bit, 8 bits, 16 bits Minimum execution time: 62.5 ns (at machine clock frequency of 16 MHz) Interrupt processing time: 1.5 $\mu$ s (at machine clock frequency of 16 MHz, minimum value)	The number of instructions: 351 Instruction bit length: 8 bits, 16 bits Instruction length: 1 byte to 7 bytes Data bit length: 1 bit, 8 bits, 16 bits Minimum execution time: 62.5 ns (at machine clock frequency of 16 MHz) Interrupt processing time: 1.5 $\mu$ s (at machine clock frequency of 16 MHz, minimum value)	The number of instructions: 351 Instruction bit length: 8 bits, 16 bits Instruction length: 1 byte to 7 bytes Data bit length: 1 bit, 8 bits, 16 bits Minimum execution time: 62.5 ns (at machine clock frequency of 16 MHz) Interrupt processing time: 1.5 $\mu$ s (at machine clock frequency of 16 MHz, minimum value)
UART0	Clock synchronized transmission (500 K/1 M/2 Mbps) Clock asynchronous transmission (4808/5208/9615/10417/19230/38460/62500 /500000 bps at machine clock frequency of 16 MHz) Transmission can be performed by bi-directional serial transmission or by master/slave connection.	Clock synchronized transmission (500 K/1 M/2 Mbps) Clock asynchronous transmission (4808/5208/9615/10417/19230/38460/62500 /500000 bps at machine clock frequency of 16 MHz) Transmission can be performed by bi-directional serial transmission or by master/slave connection.	Clock synchronized transmission (500 K/1 M/2 Mbps) Clock asynchronous transmission (4808/5208/9615/10417/19230/38460/62500 /500000 bps at machine clock frequency of 16 MHz) Transmission can be performed by bi-directional serial transmission or by master/slave connection.
UART1(SCI)	Clock synchronized transmission (62.5 K/125 K/250 K/500 K/1 Mbps) Clock asynchronous transmission (1202/2404/4808/9615/31250 bps) Transmission can be performed by bi-directional serial transmission or by master/slave connection.	Clock synchronized transmission (62.5 K/125 K/250 K/500 K/1 Mbps) Clock asynchronous transmission (1202/2404/4808/9615/31250 bps) Transmission can be performed by bi-directional serial transmission or by master/slave connection.	Clock synchronized transmission (62.5 K/125 K/250 K/500 K/1 Mbps) Clock asynchronous transmission (1202/2404/4808/9615/31250 bps) Transmission can be performed by bi-directional serial transmission or by master/slave connection.
8/10-bit A/D converter	Conversion precision: 8/10-bit can be selectively used. Number of inputs: 8 One-shot conversion mode (converts selected channel once only) Scan conversion mode (converts two or more successive channels and can program up to 8 channels) Continuous conversion mode (converts selected channel continuously) Stop conversion mode (converts selected channel and stop operation repeatedly)	Conversion precision: 8/10-bit can be selectively used. Number of inputs: 8 One-shot conversion mode (converts selected channel once only) Scan conversion mode (converts two or more successive channels and can program up to 8 channels) Continuous conversion mode (converts selected channel continuously) Stop conversion mode (converts selected channel and stop operation repeatedly)	Conversion precision: 8/10-bit can be selectively used. Number of inputs: 8 One-shot conversion mode (converts selected channel once only) Scan conversion mode (converts two or more successive channels and can program up to 8 channels) Continuous conversion mode (converts selected channel continuously) Stop conversion mode (converts selected channel and stop operation repeatedly)
8/16-bit PPG timers (6 channels)	Number of channels: 6 (8/16-bit $\times$ 6 channels) PPG operation of 8-bit or 16-bit A pulse wave of given intervals and given duty ratios can be output. Pulse interval: $f_{sys}$ , $f_{sys}/2^1$ , $f_{sys}/2^2$ , $f_{sys}/2^3$ , $f_{sys}/2^4$ ( $f_{sys}$ = system clock frequency) 128 $\mu$ s ( $f_{osc}$ = 4MHz: oscillation clock frequency)	Number of channels: 6 (8/16-bit $\times$ 6 channels) PPG operation of 8-bit or 16-bit A pulse wave of given intervals and given duty ratios can be output. Pulse interval: $f_{sys}$ , $f_{sys}/2^1$ , $f_{sys}/2^3$ , $f_{sys}/2^5$ ( $f_{sys}$ = System clock frequency) 128 $\mu$ s ( $f_{osc}$ = 4MHz: oscillation clock frequency)	Number of channels: 6 (8/16-bit $\times$ 6 channels) PPG operation of 8-bit or 16-bit A pulse wave of given intervals and given duty ratios can be output. Pulse interval: $f_{sys}$ , $f_{sys}/2^1$ , $f_{sys}/2^3$ , $f_{sys}/2^5$ ( $f_{sys}$ = System clock frequency) 128 $\mu$ s ( $f_{osc}$ = 4MHz: oscillation clock frequency)
16-bit Reload timer	Number of channels: 2 Operation clock frequency: $f_{sys}/2^1$ , $f_{sys}/2^3$ , $f_{sys}/2^5$ ( $f_{sys}$ = System clock frequency) Supports External Event Count function	Number of channels: 2 Operation clock frequency: $f_{sys}/2^1$ , $f_{sys}/2^3$ , $f_{sys}/2^5$ ( $f_{sys}$ = System clock frequency) Supports External Event Count function	Number of channels: 2 Operation clock frequency: $f_{sys}/2^1$ , $f_{sys}/2^3$ , $f_{sys}/2^5$ ( $f_{sys}$ = System clock frequency) Supports External Event Count function
16-bit I/O timer	16-bit Output compares	Number of channels: 4 Pin input factor: A match signal of compare register	Number of channels: 4 Pin input factor: A match signal of compare register
	Input captures	Number of channels: 4 Rewriting a register value upon a pin input (rising, falling, or both edges)	Number of channels: 4 Rewriting a register value upon a pin input (rising, falling, or both edges)

(Continued)

# MB90595/595G Series

(Continued)

Features	MB90598/598G	MB90F598/F598G	MB90V595/V595G
CAN Interface	Number of channels: 1 Conforms to CAN Specification Version 2.0 Part A and B Automatic re-transmission in case of error Automatic transmission responding to Remote Frame Prioritized 16 message buffers for data and ID's Supports multiple messages Flexible configuration of acceptance filtering: Full bit compare / Full bit mask / Two partial bit masks Supports up to 1Mbps CAN bit timing setting: MB90xxx:TSEG2 $\geq$ RSJW+2TQ MB90xxxG:TSEG2 $\geq$ RSJW		
Stepping motor controller (4 channels)	Four high current outputs for each channel Synchronized two 8-bit PWM's for each channel		
External interrupt circuit	Number of inputs: 8 Started by a rising edge, a falling edge, an "H" level input, or an "L" level input.		
Serial IO	Clock synchronized transmission (31.25 K/62.5 K/125 K/500 K/1 Mbps at system clock frequency of 16 MHz) LSB first/MSB first		
Watchdog timer	Reset generation interval: 3.58 ms, 14.33 ms, 57.23 ms, 458.75 ms (at oscillation of 4 MHz, minimum value)		
Flash Memory	Supports automatic programming, Embedded Algorithm™ and Write/Erase/Erase-Suspend/Resume commands A flag indicating completion of the algorithm Hard-wired reset vector available in order to point to a fixed boot sector in Flash Memory Boot block configuration Erase can be performed on each block Block protection with external programming voltage Flash Writer from Minato Electronics Inc.		
Low-power consumption (stand-by) mode	Sleep/stop/CPU intermittent operation/clock timer/hardware stand-by		
Process	CMOS		
Power supply voltage for operation* <sup>2</sup>		+5 V $\pm$ 10 %	
Package	QFP-100	PGA-256	

\*1: It is setting of DIP switch S2 when Emulation pod (MB2145-507) is used.


Please refer to the MB2145-507 hardware manual (2.7 Emulator-specific Power Pin) about details.

\*2: Varies with conditions such as the operating frequency. (See section "■ ELECTRICAL CHARACTERISTICS.")

# MB90595/595G Series

## ■ PIN ASSIGNMENT

(Top view)



(FPT-100P-M06)

# MB90595/595G Series

## ■ PIN DESCRIPTION

Pin no.	Pin name	Circuit type	Function
82	X0	A	Oscillator pin
83	X1		
77	$\overline{RST}$	B	Reset input
52	$\overline{HST}$	C	Hardware standby input
85 to 88	P00 to P03	G	General purpose IO
	IN0 to IN3		Inputs for the Input Captures
89 to 92	P04 to P07	G	General purpose IO
	OUT0 to OUT3		Outputs for the Output Compares.
93 to 98	P10 to P15	D	General purpose IO
	PPG0 to PPG5		Outputs for the Programmable Pulse Generators
99	P16	D	General purpose IO
	TIN1		TIN input for the 16-bit Reload Timer 1
100	P17	D	General purpose IO
	TOT1		TOT output for the 16-bit Reload Timer 1
1 to 8	P20 to P27	G	General purpose IO
9 to 10	P30 to P31	G	General purpose IO
12 to 16	P32 to P36	G	General purpose IO
17	P37	D	General purpose IO
18	P40	G	General purpose IO
	SOT0		SOT output for UART 0
19	P41	G	General purpose IO
	SCK0		SCK input/output for UART 0
20	P42	G	General purpose IO
	SIN0		SIN input for UART 0
21	P43	G	General purpose IO
	SIN1		SIN input for UART 1
22	P44	G	General purpose IO
	SCK1		SCK input/output for UART 1
24	P45	G	General purpose IO
	SOT1		SOT output for UART 1
25	P46	G	General purpose IO
	SOT2		SOT output for the Serial IO
26	P47	G	General purpose IO
	SCK2		SCK input/output for the Serial IO

(Continued)

# MB90595/595G Series

Pin no.	Pin name	Circuit type	Function
28	P50	D	General purpose IO
	SIN2		SIN Input for the Serial IO
29 to 32	P51 to P54	D	General purpose IO
	INT4 to INT7		External interrupt input for INT4 to INT7
33	P55	D	General purpose IO
	ADTG		Input for the external trigger of the A/D Converter
38 to 41	P60 to P63	E	General purpose IO
	AN0 to AN3		Inputs for the A/D Converter
43 to 46	P64 to P67	E	General purpose IO
	AN4 to AN7		Inputs for the A/D Converter
47	P56	D	General purpose IO
	TIN0		TIN input for the 16-bit Reload Timer 0
48	P57	D	General purpose IO
	TOT0		TOT output for the 16-bit Reload Timer 0
54 to 57	P70 to P73	F	General purpose IO
	PWM1P0 PWM1M0 PWM2P0 PWM2M0		Output for Stepper Motor Controller channel 0
59 to 62	P74 to P77	F	General purpose IO
	PWM1P1 PWM1M1 PWM2P1 PWM2M1		Output for Stepper Motor Controller channel 1
64 to 67	P80 to P83	F	General purpose IO
	PWM1P2 PWM1M2 PWM2P2 PWM2M2		Output for Stepper Motor Controller channel 2
69 to 72	P84 to P87	F	General purpose IO
	PWM1P3 PWM1M3 PWM2P3 PWM2M3		Output for Stepper Motor Controller channel 3
74	P90	D	General purpose IO
	TX		TX output for CAN Interface
75	P91	D	General purpose IO
	RX		RX input for CAN Interface

(Continued)






# MB90595/595G Series

(Continued)

Pin no.	Pin name	Circuit type	Function
76	P92	D	General purpose IO
	INT0		External interrupt input for INT0
78 to 80	P93 to P95	D	General purpose IO
	INT1 to INT3		External interrupt input for INT1 to INT3
58, 68	DV <sub>cc</sub>	—	Dedicated power supply pins for the high current output buffers (Pin No. 54 to 72)
53, 63, 73	DV <sub>ss</sub>	—	Dedicated ground pins for the high current output buffers (Pin No. 54 to 72)
34	AV <sub>cc</sub>	Power supply	Dedicated power supply pin for the A/D Converter
37	AV <sub>ss</sub>	Power supply	Dedicated ground pin for the A/D Converter
35	AVRH	Power supply	Upper reference voltage input for the A/D Converter
36	AVRL	Power supply	Lower reference voltage input for the A/D Converter
49, 50	MD0 MD1	C	Operating mode selection input pins. These pins should be connected to V <sub>cc</sub> or V <sub>ss</sub> .
51	MD2	H	Operating mode selection input pin. This pin should be connected to V <sub>cc</sub> or V <sub>ss</sub> .
27	C	—	External capacitor pin. A capacitor of 0.1μF should be connected to this pin and V <sub>ss</sub> .
23, 84	V <sub>cc</sub>	Power supply	Power supply pins (5.0 V).
11, 42, 81	V <sub>ss</sub>	Power supply	Ground pins (0.0 V).

# MB90595/595G Series

## ■ I/O CIRCUIT TYPE

Circuit Type	Circuit	Remarks
A	 <p>Hard, Soft Standby control</p>	<ul style="list-style-type: none"> <li>• Oscillation feedback resistor: 1 MΩ approx.</li> </ul>
B	 <p>HYS</p>	<ul style="list-style-type: none"> <li>• Hysteresis input with pull-up Resistor: 50 kΩ approx.</li> </ul>
C	 <p>HYS</p>	<ul style="list-style-type: none"> <li>• Hysteresis input</li> </ul>
D	 <p>HYS</p>	<ul style="list-style-type: none"> <li>• CMOS output</li> <li>• CMOS Hysteresis input</li> </ul>
E	 <p>Analog input</p> <p>HYS</p>	<ul style="list-style-type: none"> <li>• CMOS output</li> <li>• CMOS Hysteresis input</li> <li>• Analog input</li> </ul>

(Continued)

# MB90595/595G Series

(Continued)

Circuit Type	Circuit	Remarks
F		<ul style="list-style-type: none"> <li>CMOS high current output</li> <li>CMOS Hysteresis input</li> </ul>
G		<ul style="list-style-type: none"> <li>CMOS output</li> <li>CMOS Hysteresis input</li> <li>TTL input (MB90F598/F598G, only in Flash mode)</li> </ul>
H		<ul style="list-style-type: none"> <li>Hysteresis input Pull-down Resistor: 50 Ω approx. (except MB90F598/F598G)</li> </ul>

# MB90595/595G Series

## ■ HANDLING DEVICES

### (1) Make Sure that the Voltage not Exceed the Maximum Rating (to Avoid a Latch-up).

In CMOS ICs, a latch-up phenomenon is caused when an voltage exceeding  $V_{cc}$  or an voltage below  $V_{ss}$  is applied to input or output pins or a voltage exceeding the rating is applied across  $V_{cc}$  and  $V_{ss}$ .

When a latch-up is caused, the power supply current may be dramatically increased causing resultant thermal break-down of devices. To avoid the latch-up, make sure that the voltage not exceed the maximum rating.

In turning on/turning off the analog power supply, make sure the analog power voltage ( $AV_{cc}$ ,  $AV_{RH}$ ,  $DV_{cc}$ ) and analog input voltages not exceed the digital voltage ( $V_{cc}$ ).

### (2) Treatment of Unused Pins


Unused input pins left open may cause abnormal operation, or latch-up leading to permanent damage. Unused input pins should be pulled up or pulled down through at least  $2\text{ k}\Omega$  resistance.

Unused input/output pins may be left open in output state, but if such pins are in input state they should be handled in the same way as input pins.

### (3) Using external clock

In using the external clock, drive X0 pin only and leave X1 pin unconnected.

#### Using external clock




### (4) Power supply pins ( $V_{cc}$ / $V_{ss}$ )

In products with multiple  $V_{cc}$  or  $V_{ss}$  pins, pins with the same potential are internally connected in the device to avoid abnormal operations including latch-up. However, you must connect the pins to an external power and a ground line to lower the electro-magnetic emission level, to prevent abnormal operation of strobe signals caused by the rise in the ground level, and to conform to the total current rating (See the figure below.)

Make sure to connect  $V_{cc}$  and  $V_{ss}$  pins via lowest impedance to power lines.

It is recommended to provide a bypass capacitor of around  $0.1\text{ }\mu\text{F}$  between  $V_{cc}$  and  $V_{ss}$  pins near the device.



# MB90595/595G Series

## (5) Pull-up/down resistors

The MB90595 Series does not support internal pull-up/down resistors. Use external components where needed.

## (6) Crystal Oscillator Circuit

Noises around X0 or X1 pins may cause abnormal operations. Make sure to provide bypass capacitors via shortest distance from X0, X1 pins, crystal oscillator (or ceramic resonator) and ground lines, and make sure that lines of oscillation circuit not cross the lines of other circuits.

A printed circuit board artwork surrounding the X0 and X1 pins with ground area for stabilizing the operation is highly recommended.

## (7) Turning-on Sequence of Power Supply to A/D Converter and Analog Inputs

Make sure to turn on the A/D converter power supply (AV<sub>cc</sub>, AVR<sub>H</sub>, AVR<sub>L</sub>) and analog inputs (AN0 to AN7) after turning-on the digital power supply (V<sub>cc</sub>).

Turn-off the digital power after turning off the A/D converter supply and analog inputs. In this case, make sure that the voltage does not exceed AVR<sub>H</sub> or AV<sub>cc</sub> (turning on/off the analog and digital power supplies simultaneously is acceptable).

## (8) Connection of Unused Pins of A/D Converter

Connect unused pins of A/D converter to AV<sub>cc</sub> = V<sub>cc</sub>, AV<sub>ss</sub> = AVR<sub>H</sub> = DV<sub>cc</sub> = V<sub>ss</sub>.

## (9) N.C. Pin

The N.C. (internally connected) pin must be opened for use.

## (10) Notes on Energization


To prevent the internal regulator circuit from malfunctioning, set the voltage rise time during energization at 50  $\mu$ s or more (0.2 V to 2.7 V).

## (11) Indeterminate outputs from ports 0 and 1 (MB90598/F598/V595/V595G only)


During oscillation setting time of step-down circuit (during a power-on reset) after the power is turned on, the outputs from ports 0 and 1 become following state.

- If  $\overline{RST}$  pin is "H", the outputs become indeterminate.
- If  $\overline{RST}$  pin is "L", the outputs become high-impedance.

Pay attention to the port output timing shown as follow.



# MB90595/595G Series



## (12) Initialization

The device contains internal registers which are initialized only by a power-on reset. To initialize these registers, please turn on the power again.

## (13) Directions of “DIV A, Ri” and “DIVW A, RWi” instructions

In the signed multiplication and division instructions (“DIV A, Ri” and “DIVW A, RWi”), the value of the corresponding bank register (DTB, ADB, USB, SSB) is set in “00H”.

If the values of the corresponding bank register (DTB, ADB, USB, SSB) are set to other than “00H”, the remainder by the execution result of the instruction is not stored in the register of the instruction operand.

## (14) Using REALOS


The use of EI<sup>2</sup>OS is not possible with the REALOS real time operating system.

## (15) Caution on Operations during PLL Clock Mode

If the PLL clock mode is selected in the microcontroller, it may attempt to continue the operation using the free-running frequency of the automatic oscillating circuit in the PLL circuitry even if the oscillator is out of place or the clock input is stopped. Performance of this operation, however, cannot be guaranteed.

# MB90595/595G Series


## ■ BLOCK DIAGRAM



# MB90595/595G Series

## ■ MEMORY SPACE

The memory space of the MB90595 Series is shown below



Note: The ROM data of bank FF is reflected in the upper address of bank 00, realizing effective use of the C compiler small model. The lower 16-bit of bank FF and the lower 16-bit of bank 00 are assigned to the same address, enabling reference of the table on the ROM without stating “far”.

For example, if an attempt has been made to access  $00C000H$ , the contents of the ROM at  $FFC000H$  are accessed. Since the ROM area of the FF bank exceeds 48 Kbytes, the whole area cannot be reflected in the image for the 00 bank. The ROM data at  $FF4000H$  to  $FFFFFH$  looks, therefore, as if it were the image for  $004000H$  to  $00FFFFH$ . Thus, it is recommended that the ROM data table be stored in the area of  $FF4000H$  to  $FFFFFH$ .

# MB90595/595G Series

## ■ I/O MAP

Address	Register	Abbreviation	Access	Peripheral	Initial value
00 <sub>H</sub>	Port 0 Data Register	PDR0	R/W	Port 0	XXXXXXXX <sub>B</sub>
01 <sub>H</sub>	Port 1 Data Register	PDR1	R/W	Port 1	XXXXXXXX <sub>B</sub>
02 <sub>H</sub>	Port 2 Data Register	PDR2	R/W	Port 2	XXXXXXXX <sub>B</sub>
03 <sub>H</sub>	Port 3 Data Register	PDR3	R/W	Port 3	XXXXXXXX <sub>B</sub>
04 <sub>H</sub>	Port 4 Data Register	PDR4	R/W	Port 4	XXXXXXXX <sub>B</sub>
05 <sub>H</sub>	Port 5 Data Register	PDR5	R/W	Port 5	XXXXXXXX <sub>B</sub>
06 <sub>H</sub>	Port 6 Data Register	PDR6	R/W	Port 6	XXXXXXXX <sub>B</sub>
07 <sub>H</sub>	Port 7 Data Register	PDR7	R/W	Port 7	XXXXXXXX <sub>B</sub>
08 <sub>H</sub>	Port 8 Data Register	PDR8	R/W	Port 8	XXXXXXXX <sub>B</sub>
09 <sub>H</sub>	Port 9 Data Register	PDR9	R/W	Port 9	__ XXXXXX <sub>B</sub>
0A <sub>H</sub> to 0F <sub>H</sub>	Reserved				
10 <sub>H</sub>	Port 0 Direction Register	DDR0	R/W	Port 0	0 0 0 0 0 0 0 0 <sub>B</sub>
11 <sub>H</sub>	Port 1 Direction Register	DDR1	R/W	Port 1	0 0 0 0 0 0 0 0 <sub>B</sub>
12 <sub>H</sub>	Port 2 Direction Register	DDR2	R/W	Port 2	0 0 0 0 0 0 0 0 <sub>B</sub>
13 <sub>H</sub>	Port 3 Direction Register	DDR3	R/W	Port 3	0 0 0 0 0 0 0 0 <sub>B</sub>
14 <sub>H</sub>	Port 4 Direction Register	DDR4	R/W	Port 4	0 0 0 0 0 0 0 0 <sub>B</sub>
15 <sub>H</sub>	Port 5 Direction Register	DDR5	R/W	Port 5	0 0 0 0 0 0 0 0 <sub>B</sub>
16 <sub>H</sub>	Port 6 Direction Register	DDR6	R/W	Port 6	0 0 0 0 0 0 0 0 <sub>B</sub>
17 <sub>H</sub>	Port 7 Direction Register	DDR7	R/W	Port 7	0 0 0 0 0 0 0 0 <sub>B</sub>
18 <sub>H</sub>	Port 8 Direction Register	DDR8	R/W	Port 8	0 0 0 0 0 0 0 0 <sub>B</sub>
19 <sub>H</sub>	Port 9 Direction Register	DDR9	R/W	Port 9	__ 0 0 0 0 0 0 <sub>B</sub>
1A <sub>H</sub>	Reserved				
1B <sub>H</sub>	Analog Input Enable Register	ADER	R/W	Port 6, A/D	1 1 1 1 1 1 1 1 <sub>B</sub>
1C <sub>H</sub> to 1F <sub>H</sub>	Reserved				
20 <sub>H</sub>	Serial Mode Control Register 0	UMC0	R/W	UART0	0 0 0 0 0 1 0 0 <sub>B</sub>
21 <sub>H</sub>	Serial status Register 0	USR0	R/W		0 0 0 1 0 0 0 0 <sub>B</sub>
22 <sub>H</sub>	Serial Input/Output Data Register 0	UIDR0/ UODR0	R/W		XXXXXXXX <sub>B</sub>
23 <sub>H</sub>	Rate and Data Register 0	URD0	R/W		0 0 0 0 0 0 0 X <sub>B</sub>
24 <sub>H</sub>	Serial Mode Register 1	SMR1	R/W	UART1	0 0 0 0 0 0 0 0 <sub>B</sub>
25 <sub>H</sub>	Serial Control Register 1	SCR1	R/W		0 0 0 0 0 1 0 0 <sub>B</sub>
26 <sub>H</sub>	Serial Input/Output Data Register 1	SIDR1/ SODR1	R/W		XXXXXXXX <sub>B</sub>
27 <sub>H</sub>	Serial Status Register 1	SSR1	R/W		0 0 0 0 1 _ 0 0 <sub>B</sub>
28 <sub>H</sub>	UART1 Prescaler Control Register	U1CDCR	R/W		0 __ _ 1 1 1 1 <sub>B</sub>

(Continued)

# MB90595/595G Series

Address	Register	Abbreviation	Access	Peripheral	Initial value
29 <sub>H</sub> to 2A <sub>H</sub>	Reserved				
2B <sub>H</sub>	Serial IO Prescaler	SCDCR	R/W	Serial IO	0_ _ _ 1 1 1 1 <sub>B</sub>
2C <sub>H</sub>	Serial Mode Control Register (low-order)	SMCS	R/W		— _ _ _ 0 0 0 0 <sub>B</sub>
2D <sub>H</sub>	Serial Mode Control Register (high-order)	SMCS	R/W		0 0 0 0 0 0 1 0 <sub>B</sub>
2E <sub>H</sub>	Serial Data Register	SDR	R/W		XXXXXXX <sub>B</sub>
2F <sub>H</sub>	Edge Selector	SES	R/W		— _ _ _ _ 0 <sub>B</sub>
30 <sub>H</sub>	External Interrupt Enable Register	ENIR	R/W	External Interrupt	0 0 0 0 0 0 0 0 <sub>B</sub>
31 <sub>H</sub>	External Interrupt Request Register	EIRR	R/W		XXXXXXX <sub>B</sub>
32 <sub>H</sub>	External Interrupt Level Register	ELVR	R/W		0 0 0 0 0 0 0 0 <sub>B</sub>
33 <sub>H</sub>	External Interrupt Level Register	ELVR	R/W		0 0 0 0 0 0 0 0 <sub>B</sub>
34 <sub>H</sub>	A/D Control Status Register 0	ADCS0	R/W	A/D Converter	0 0 0 0 0 0 0 0 <sub>B</sub>
35 <sub>H</sub>	A/D Control Status Register 1	ADCS1	R/W		0 0 0 0 0 0 0 0 <sub>B</sub>
36 <sub>H</sub>	A/D Data Register 0	ADCR0	R		XXXXXXX <sub>B</sub>
37 <sub>H</sub>	A/D Data Register 1	ADCR1	R/W		0 0 0 1 _ XX <sub>B</sub>
38 <sub>H</sub>	PPG0 Operation Mode Control Register	PPGC0	R/W	16-bit Program- mable Pulse Generator 0/1	0 _ 0 0 _ _ 1 <sub>B</sub>
39 <sub>H</sub>	PPG1 Operation Mode Control Register	PPGC1	R/W		0 _ 0 0 0 0 1 <sub>B</sub>
3A <sub>H</sub>	PPG0, 1 Output Pin Control Register	PPG01	R/W		0 0 0 0 0 _ _ <sub>B</sub>
3B <sub>H</sub>	Reserved				
3C <sub>H</sub>	PPG2 Operation Mode Control Register	PPGC2	R/W	16-bit Program- mable Pulse Generator 2/3	0 _ 0 0 _ _ 1 <sub>B</sub>
3D <sub>H</sub>	PPG3 Operation Mode Control Register	PPGC3	R/W		0 _ 0 0 0 0 1 <sub>B</sub>
3E <sub>H</sub>	PPG2, 3 Output Pin Control Register	PPG23	R/W		0 0 0 0 0 _ _ <sub>B</sub>
3F <sub>H</sub>	Reserved				
40 <sub>H</sub>	PPG4 Operation Mode Control Register	PPGC4	R/W	16-bit Program- mable Pulse Generator 4/5	0 _ 0 0 _ _ 1 <sub>B</sub>
41 <sub>H</sub>	PPG5 Operation Mode Control Register	PPGC5	R/W		0 _ 0 0 0 0 1 <sub>B</sub>
42 <sub>H</sub>	PPG4, 5 Output Pin Control Register	PPG45	R/W		0 0 0 0 0 _ _ <sub>B</sub>
43 <sub>H</sub>	Reserved				
44 <sub>H</sub>	PPG6 Operation Mode Control Register	PPGC6	R/W	16-bit Program- mable Pulse Generator 6/7	0 _ 0 0 _ _ 1 <sub>B</sub>
45 <sub>H</sub>	PPG7 Operation Mode Control Register	PPGC7	R/W		0 _ 0 0 0 0 1 <sub>B</sub>
46 <sub>H</sub>	PPG6, 7 Output Pin Control Register	PPG67	R/W		0 0 0 0 0 _ _ <sub>B</sub>
47 <sub>H</sub>	Reserved				
48 <sub>H</sub>	PPG8 Operation Mode Control Register	PPGC8	R/W	16-bit Program- mable Pulse Generator 8/9	0 _ 0 0 _ _ 1 <sub>B</sub>
49 <sub>H</sub>	PPG9 Operation Mode Control Register	PPGC9	R/W		0 _ 0 0 0 0 1 <sub>B</sub>
4A <sub>H</sub>	PPG8, 9 Output Pin Control Register	PPG89	R/W		0 0 0 0 0 _ _ <sub>B</sub>
4B <sub>H</sub>	Reserved				

(Continued)

# MB90595/595G Series

Address	Register	Abbreviation	Access	Peripheral	Initial value
4C <sub>H</sub>	PPGA Operation Mode Control Register	PPGCA	R/W	16-bit Programmable Pulse Generator A/B	0_000_001 <sub>B</sub>
4D <sub>H</sub>	PPGB Operation Mode Control Register	PPGCB	R/W		0_000001 <sub>B</sub>
4E <sub>H</sub>	PPGA, B Output Pin Control Register	PPGAB	R/W		000000_00 <sub>B</sub>
4F <sub>H</sub>	Reserved				
50 <sub>H</sub>	Timer Control Status Register 0	TMCSR0	R/W	16-bit Reload Timer 0	000000000 <sub>B</sub>
51 <sub>H</sub>	Timer Control Status Register 0	TMCSR0	R/W		000000000 <sub>B</sub>
52 <sub>H</sub>	Timer 0/Reload Register 0	TMR0/ TMRLR0	R/W		XXXXXXXX <sub>B</sub>
53 <sub>H</sub>	Timer 0/Reload Register 0	TMR0/ TMRLR0	R/W		XXXXXXXX <sub>B</sub>
54 <sub>H</sub>	Timer Control Status Register 1	TMCSR1	R/W	16-bit Reload Timer 1	000000000 <sub>B</sub>
55 <sub>H</sub>	Timer Control Status Register 1	TMCSR1	R/W		000000000 <sub>B</sub>
56 <sub>H</sub>	Timer Register 1/Reload Register 1	TMR1/ TMRLR1	R/W		XXXXXXXX <sub>B</sub>
57 <sub>H</sub>	Timer Register 1/Reload Register 1	TMR1/ TMRLR1	R/W		XXXXXXXX <sub>B</sub>
58 <sub>H</sub>	Output Compare Control Status Register 0	OCS0	R/W	Output Compare 0/1	0000_0000 <sub>B</sub>
59 <sub>H</sub>	Output Compare Control Status Register 1	OCS1	R/W		0000_0000 <sub>B</sub>
5A <sub>H</sub>	Output Compare Control Status Register 2	OCS2	R/W	Output Compare 2/3	0000_0000 <sub>B</sub>
5B <sub>H</sub>	Output Compare Control Status Register 3	OCS3	R/W		0000_0000 <sub>B</sub>
5C <sub>H</sub>	Input Capture Control Status Register 0/1	ICS01	R/W	Input Capture 0/1	000000000 <sub>B</sub>
5D <sub>H</sub>	Input Capture Control Status Register 2/3	ICS23	R/W	Input Capture 2/3	000000000 <sub>B</sub>
5E <sub>H</sub>	PWM Control Register 0	PWC0	R/W	Stepping Motor Controller 0	00000_00 <sub>B</sub>
5F <sub>H</sub>	Reserved				
60 <sub>H</sub>	PWM Control Register 1	PWC1	R/W	Stepping Motor Controller 1	00000_00 <sub>B</sub>
61 <sub>H</sub>	Reserved				
62 <sub>H</sub>	PWM Control Register 2	PWC2	R/W	Stepping Motor Controller 2	00000_00 <sub>B</sub>
63 <sub>H</sub>	Reserved				
64 <sub>H</sub>	PWM Control Register 3	PWC3	R/W	Stepping Motor Controller 3	00000_00 <sub>B</sub>
65 <sub>H</sub>	Reserved				
66 <sub>H</sub>	Timer Data Register (low-order)	TCDT	R/W	IO Timer	000000000 <sub>B</sub>
67 <sub>H</sub>	Timer Data Register (high-order)	TCDT	R/W		000000000 <sub>B</sub>
68 <sub>H</sub>	Timer Control Status Register	TCCS	R/W		000000000 <sub>B</sub>
69 <sub>H</sub> to 6E <sub>H</sub>	Reserved				

(Continued)

# MB90595/595G Series

Address	Register	Abbreviation	Access	Peripheral	Initial value	
6F <sub>H</sub>	ROM Mirror Function Selection Register	ROMM	R/W	ROM Mirror	-----1 <sub>B</sub>	
70 <sub>H</sub>	PWM1 Compare Register 0	PWC10	R/W	Stepping Motor Controller 0	XXXXXXXX <sub>B</sub>	
71 <sub>H</sub>	PWM2 Compare Register 0	PWC20	R/W		XXXXXXXX <sub>B</sub>	
72 <sub>H</sub>	PWM1 Select Register 0	PWS10	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
73 <sub>H</sub>	PWM2 Select Register 0	PWS20	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
74 <sub>H</sub>	PWM1 Compare Register 1	PWC11	R/W	Stepping Motor Controller 1	XXXXXXXX <sub>B</sub>	
75 <sub>H</sub>	PWM2 Compare Register 1	PWC21	R/W		XXXXXXXX <sub>B</sub>	
76 <sub>H</sub>	PWM1 Select Register 1	PWS11	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
77 <sub>H</sub>	PWM2 Select Register 1	PWS21	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
78 <sub>H</sub>	PWM1 Compare Register 2	PWC12	R/W	Stepping Motor Controller 2	XXXXXXXX <sub>B</sub>	
79 <sub>H</sub>	PWM2 Compare Register 2	PWC22	R/W		XXXXXXXX <sub>B</sub>	
7A <sub>H</sub>	PWM1 Select Register 2	PWS12	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
7B <sub>H</sub>	PWM2 Select Register 2	PWS22	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
7C <sub>H</sub>	PWM1 Compare Register 3	PWC13	R/W	Stepping Motor Controller 3	XXXXXXXX <sub>B</sub>	
7D <sub>H</sub>	PWM2 Compare Register 3	PWC23	R/W		XXXXXXXX <sub>B</sub>	
7E <sub>H</sub>	PWM1 Select Register 3	PWS13	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
7F <sub>H</sub>	PWM2 Select Register 3	PWS23	R/W		_ _ 0 0 0 0 0 0 <sub>B</sub>	
80 <sub>H</sub> to 8F <sub>H</sub>	CAN Controller. Refer to section about CAN Controller					
90 <sub>H</sub> to 9D <sub>H</sub>	Reserved					
9E <sub>H</sub>	Program Address Detection Control Status Register	PACSR	R/W	Address Match Detection Function	0 0 0 0 0 0 0 0 <sub>B</sub>	
9F <sub>H</sub>	Delayed Interrupt/Request Register	DIRR	R/W	Delayed Interrupt	-----0 <sub>B</sub>	
A0 <sub>H</sub>	Low-Power Mode Control Register	LPMCR	R/W	Low Power Controller	0 0 0 1 1 0 0 0 <sub>B</sub>	
A1 <sub>H</sub>	Clock Selection Register	CKSCR	R/W	Low Power Controller	1 1 1 1 1 1 0 0 <sub>B</sub>	
A2 <sub>H</sub> to A7 <sub>H</sub>	Reserved					
A8 <sub>H</sub>	Watchdog Timer Control Register	WDTC	R/W	Watchdog Timer	XXXXX 1 1 1 <sub>B</sub>	
A9 <sub>H</sub>	Time Base Timer Control Register	TBTC	R/W	Time Base Timer	1 _ _ 0 0 1 0 0 <sub>B</sub>	
AA <sub>H</sub> to AD <sub>H</sub>	Reserved					
AE <sub>H</sub>	Flash Memory Control Status Register (MB90F598/F598G only. Otherwise reserved)	FMCS	R/W	Flash Memory	0 0 0 X 0 0 0 0 <sub>B</sub>	
AF <sub>H</sub>	Reserved					

(Continued)

# MB90595/595G Series

Address	Register	Abbreviation	Access	Peripheral	Initial value
B0 <sub>H</sub>	Interrupt Control Register 00	ICR00	R/W	Interrupt controller	0 0 0 0 0 1 1 1 <sub>B</sub>
B1 <sub>H</sub>	Interrupt Control Register 01	ICR01	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B2 <sub>H</sub>	Interrupt Control Register 02	ICR02	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B3 <sub>H</sub>	Interrupt Control Register 03	ICR03	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B4 <sub>H</sub>	Interrupt Control Register 04	ICR04	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B5 <sub>H</sub>	Interrupt Control Register 05	ICR05	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B6 <sub>H</sub>	Interrupt Control Register 06	ICR06	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B7 <sub>H</sub>	Interrupt Control Register 07	ICR07	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B8 <sub>H</sub>	Interrupt Control Register 08	ICR08	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
B9 <sub>H</sub>	Interrupt Control Register 09	ICR09	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
BA <sub>H</sub>	Interrupt Control Register 10	ICR10	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
BB <sub>H</sub>	Interrupt Control Register 11	ICR11	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
BC <sub>H</sub>	Interrupt Control Register 12	ICR12	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
BD <sub>H</sub>	Interrupt Control Register 13	ICR13	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
BE <sub>H</sub>	Interrupt Control Register 14	ICR14	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
BF <sub>H</sub>	Interrupt Control Register 15	ICR15	R/W		0 0 0 0 0 1 1 1 <sub>B</sub>
C0 <sub>H</sub> to FF <sub>H</sub>	Reserved				
1900 <sub>H</sub>	Reload Register L	PRLLO	R/W	16-bit Programmable Pulse Generator 0/1	XXXXXXXX <sub>B</sub>
1901 <sub>H</sub>	Reload Register H	PRLH0	R/W		XXXXXXXX <sub>B</sub>
1902 <sub>H</sub>	Reload Register L	PRLL1	R/W		XXXXXXXX <sub>B</sub>
1903 <sub>H</sub>	Reload Register H	PRLH1	R/W		XXXXXXXX <sub>B</sub>
1904 <sub>H</sub>	Reload Register L	PRLL2	R/W	16-bit Programmable Pulse Generator 2/3	XXXXXXXX <sub>B</sub>
1905 <sub>H</sub>	Reload Register H	PRLH2	R/W		XXXXXXXX <sub>B</sub>
1906 <sub>H</sub>	Reload Register L	PRLL3	R/W		XXXXXXXX <sub>B</sub>
1907 <sub>H</sub>	Reload Register H	PRLH3	R/W		XXXXXXXX <sub>B</sub>
1908 <sub>H</sub>	Reload Register L	PRLL4	R/W	16-bit Programmable Pulse Generator 4/5	XXXXXXXX <sub>B</sub>
1909 <sub>H</sub>	Reload Register H	PRLH4	R/W		XXXXXXXX <sub>B</sub>
190A <sub>H</sub>	Reload Register L	PRLL5	R/W		XXXXXXXX <sub>B</sub>
190B <sub>H</sub>	Reload Register H	PRLH5	R/W		XXXXXXXX <sub>B</sub>
190C <sub>H</sub>	Reload Register L	PRLL6	R/W	16-bit Programmable Pulse Generator 6/7	XXXXXXXX <sub>B</sub>
190D <sub>H</sub>	Reload Register H	PRLH6	R/W		XXXXXXXX <sub>B</sub>
190E <sub>H</sub>	Reload Register L	PRLL7	R/W		XXXXXXXX <sub>B</sub>
190F <sub>H</sub>	Reload Register H	PRLH7	R/W		XXXXXXXX <sub>B</sub>

(Continued)

# MB90595/595G Series

Address	Register	Abbreviation	Access	Peripheral	Initial value
1910 <sub>H</sub>	Reload Register L	PRLL8	R/W	16-bit Programmable Pulse Generator 8/9	XXXXXXXX <sub>B</sub>
1911 <sub>H</sub>	Reload Register H	PRLH8	R/W		XXXXXXXX <sub>B</sub>
1912 <sub>H</sub>	Reload Register L	PRLL9	R/W		XXXXXXXX <sub>B</sub>
1913 <sub>H</sub>	Reload Register H	PRLH9	R/W		XXXXXXXX <sub>B</sub>
1914 <sub>H</sub>	Reload Register L	PRLLA	R/W	16-bit Programmable Pulse Generator A/B	XXXXXXXX <sub>B</sub>
1915 <sub>H</sub>	Reload Register H	PRLHA	R/W		XXXXXXXX <sub>B</sub>
1916 <sub>H</sub>	Reload Register L	PRLLB	R/W	16-bit Programmable Pulse Generator A/B	XXXXXXXX <sub>B</sub>
1917 <sub>H</sub>	Reload Register H	PRLHB	R/W		XXXXXXXX <sub>B</sub>
1918 <sub>H</sub> to 191F <sub>H</sub>	Reserved				
1920 <sub>H</sub>	Input Capture Register 0 (low-order)	IPCP0	R	Input Capture 0/1	XXXXXXXX <sub>B</sub>
1921 <sub>H</sub>	Input Capture Register 0 (high-order)	IPCP0	R		XXXXXXXX <sub>B</sub>
1922 <sub>H</sub>	Input Capture Register 1 (low-order)	IPCP1	R		XXXXXXXX <sub>B</sub>
1923 <sub>H</sub>	Input Capture Register 1 (high-order)	IPCP1	R		XXXXXXXX <sub>B</sub>
1924 <sub>H</sub>	Input Capture Register 2 (low-order)	IPCP2	R	Input Capture 2/3	XXXXXXXX <sub>B</sub>
1925 <sub>H</sub>	Input Capture Register 2 (high-order)	IPCP2	R		XXXXXXXX <sub>B</sub>
1926 <sub>H</sub>	Input Capture Register 3 (low-order)	IPCP3	R		XXXXXXXX <sub>B</sub>
1927 <sub>H</sub>	Input Capture Register 3 (high-order)	IPCP3	R		XXXXXXXX <sub>B</sub>
1928 <sub>H</sub>	Output Compare Register 0 (low-order)	OCCP0	R/W	Output Compare 0/1	XXXXXXXX <sub>B</sub>
1929 <sub>H</sub>	Output Compare Register 0 (high-order)	OCCP0	R/W		XXXXXXXX <sub>B</sub>
192A <sub>H</sub>	Output Compare Register 1 (low-order)	OCCP1	R/W		XXXXXXXX <sub>B</sub>
192B <sub>H</sub>	Output Compare Register 1 (high-order)	OCCP1	R/W		XXXXXXXX <sub>B</sub>

(Continued)

# MB90595/595G Series

(Continued)

Address	Register	Abbreviation	Access	Peripheral	Initial value	
192C <sub>H</sub>	Output Compare Register 2 (low-order)	OCCP2	R/W	Output Compare 2/3	XXXXXXXX <sub>B</sub>	
192D <sub>H</sub>	Output Compare Register 2 (high-order)	OCCP2	R/W		XXXXXXXX <sub>B</sub>	
192E <sub>H</sub>	Output Compare Register 3 (low-order)	OCCP3	R/W		XXXXXXXX <sub>B</sub>	
192F <sub>H</sub>	Output Compare Register 3 (high-order)	OCCP3	R/W		XXXXXXXX <sub>B</sub>	
1930 <sub>H</sub> to 19FF <sub>H</sub>	Reserved					
1A00 <sub>H</sub> to 1AFF <sub>H</sub>	CAN Controller. Refer to section about CAN Controller					
1B00 <sub>H</sub> to 1BFF <sub>H</sub>	CAN Controller. Refer to section about CAN Controller					
1C00 <sub>H</sub> to 1EFF <sub>H</sub>	Reserved					
1FF0 <sub>H</sub>	Program Address Detection Register 0 (low-order)	PADR0	R/W	Address Match Detection Function	XXXXXXXX <sub>B</sub>	
1FF1 <sub>H</sub>	Program Address Detection Register 0 (middle-order)				XXXXXXXX <sub>B</sub>	
1FF2 <sub>H</sub>	Program Address Detection Register 0 (high-order)				XXXXXXXX <sub>B</sub>	
1FF3 <sub>H</sub>	Program Address Detection Register 1 (low-order)	PADR1	R/W	Address Match Detection Function	XXXXXXXX <sub>B</sub>	
1FF4 <sub>H</sub>	Program Address Detection Register 1 (middle-order)				XXXXXXXX <sub>B</sub>	
1FF5 <sub>H</sub>	Program Address Detection Register 1 (high-order)				XXXXXXXX <sub>B</sub>	
1FF6 <sub>H</sub> to 1FFF <sub>H</sub>	Reserved					

Note: Initial value of “\_” represents unused bit; “X” represents unknown value.

Addresses in the range 0000<sub>H</sub> to 00FF<sub>H</sub>, which are not listed in the table, are reserved for the primary functions of the MCU. A read access to these reserved addresses results in reading “X”, and any write access should not be performed.

# MB90595/595G Series

## ■ CAN CONTROLLER

The CAN controller has the following features:

- Conforms to CAN Specification Version 2.0 Part A and B
  - Supports transmission/reception in standard frame and extended frame formats
- Supports transmission of data frames by receiving remote frames
- 16 transmitting/receiving message buffers
  - 29-bit ID and 8-byte data
  - Multi-level message buffer configuration
- Provides full-bit comparison, full-bit mask, acceptance register 0/acceptance register 1 for each message buffer as 1D acceptance mask
  - Two acceptance mask registers in either standard frame format or extended frame formats
- Bit rate programmable from 10 Kbit/s to 2 Mbit/s (when input clock is at 16 MHz)

**List of Control Registers**

Address	Register	Abbreviation	Access	Initial Value
000080 <sub>H</sub>	Message buffer valid register	BVALR	R/W	00000000 00000000 <sub>B</sub>
000081 <sub>H</sub>				
000082 <sub>H</sub>	Transmit request register	TREQR	R/W	00000000 00000000 <sub>B</sub>
000083 <sub>H</sub>				
000084 <sub>H</sub>	Transmit cancel register	TCANR	W	00000000 00000000 <sub>B</sub>
000085 <sub>H</sub>				
000086 <sub>H</sub>	Transmit complete register	TCR	R/W	00000000 00000000 <sub>B</sub>
000087 <sub>H</sub>				
000088 <sub>H</sub>	Receive complete register	RCR	R/W	00000000 00000000 <sub>B</sub>
000089 <sub>H</sub>				
00008A <sub>H</sub>	Remote request receiving register	RRTRR	R/W	00000000 00000000 <sub>B</sub>
00008B <sub>H</sub>				
00008C <sub>H</sub>	Receive overrun register	ROVRR	R/W	00000000 00000000 <sub>B</sub>
00008D <sub>H</sub>				
00008E <sub>H</sub>	Receive interrupt enable register	RIER	R/W	00000000 00000000 <sub>B</sub>
00008F <sub>H</sub>				
001B00 <sub>H</sub>	Control status register	CSR	R/W, R	00---000 0----0-1 <sub>B</sub>
001B01 <sub>H</sub>				
001B02 <sub>H</sub>	Last event indicator register	LEIR	R/W	----- 000-0000 <sub>B</sub>
001B03 <sub>H</sub>				
001B04 <sub>H</sub>	Receive/transmit error counter	RTEC	R	00000000 00000000 <sub>B</sub>
001B05 <sub>H</sub>				
001B06 <sub>H</sub>	Bit timing register	BTR	R/W	-1111111 11111111 <sub>B</sub>
001B07 <sub>H</sub>				

*(Continued)*

# MB90595/595G Series

(Continued)

Address	Register	Abbreviation	Access	Initial Value
001B08 <sub>H</sub>	IDE register	IDER	R/W	XXXXXXXX XXXXXXXX <sub>B</sub>
001B09 <sub>H</sub>				
001B0A <sub>H</sub>	Transmit RTR register	TRTRR	R/W	00000000 00000000 <sub>B</sub>
001B0B <sub>H</sub>				
001B0C <sub>H</sub>	Remote frame receive waiting register	RFWTR	R/W	XXXXXXXX XXXXXXXX <sub>B</sub>
001B0D <sub>H</sub>				
001B0E <sub>H</sub>	Transmit interrupt enable register	TIER	R/W	00000000 00000000 <sub>B</sub>
001B0F <sub>H</sub>				
001B10 <sub>H</sub>	Acceptance mask select register	AMSR	R/W	XXXXXXXX XXXXXXXX <sub>B</sub>
001B11 <sub>H</sub>				
001B12 <sub>H</sub>				XXXXXXXX XXXXXXXX <sub>B</sub>
001B13 <sub>H</sub>				
001B14 <sub>H</sub>	Acceptance mask register 0	AMR0	R/W	XXXXXXXX XXXXXXXX <sub>B</sub>
001B15 <sub>H</sub>				
001B16 <sub>H</sub>				XXXXX--- XXXXXXXX <sub>B</sub>
001B17 <sub>H</sub>				
001B18 <sub>H</sub>	Acceptance mask register 1	AMR1	R/W	XXXXXXXX XXXXXXXX <sub>B</sub>
001B19 <sub>H</sub>				
001B1A <sub>H</sub>				XXXXX--- XXXXXXXX <sub>B</sub>
001B1B <sub>H</sub>				

# MB90595/595G Series

List of Message Buffers (ID Registers)

Address	Register	Abbreviation	Access	Initial Value
001A00 <sub>H</sub> to 001A1F <sub>H</sub>	General-purpose RAM	--	R/W	XXXXXXXXXXXX <sub>B</sub> to XXXXXXXXXXXX <sub>B</sub>
001A20 <sub>H</sub>	ID register 0	IDR0	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A21 <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A22 <sub>H</sub>				
001A23 <sub>H</sub>				
001A24 <sub>H</sub>	ID register 1	IDR1	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A25 <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A26 <sub>H</sub>				
001A27 <sub>H</sub>				
001A28 <sub>H</sub>	ID register 2	IDR2	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A29 <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A2A <sub>H</sub>				
001A2B <sub>H</sub>				
001A2C <sub>H</sub>	ID register 3	IDR3	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A2D <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A2E <sub>H</sub>				
001A2F <sub>H</sub>				
001A30 <sub>H</sub>	ID register 4	IDR4	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A31 <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A32 <sub>H</sub>				
001A33 <sub>H</sub>				
001A34 <sub>H</sub>	ID register 5	IDR5	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A35 <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A36 <sub>H</sub>				
001A37 <sub>H</sub>				
001A38 <sub>H</sub>	ID register 6	IDR6	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A39 <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A3A <sub>H</sub>				
001A3B <sub>H</sub>				
001A3C <sub>H</sub>	ID register 7	IDR7	R/W	XXXXXXXX XXXXXXXXXXX <sub>B</sub>
001A3D <sub>H</sub>				XXXXXX--- XXXXXXXXXXX <sub>B</sub>
001A3E <sub>H</sub>				
001A3F <sub>H</sub>				

(Continued)

# MB90595/595G Series

(Continued)

Address	Register	Abbreviation	Access	Initial Value
001A40 <sub>H</sub>	ID register 8	IDR8	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A41 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A42 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A43 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A44 <sub>H</sub>	ID register 9	IDR9	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A45 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A46 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A47 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A48 <sub>H</sub>	ID register 10	IDR10	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A49 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A4A <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A4B <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A4C <sub>H</sub>	ID register 11	IDR11	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A4D <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A4E <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A4F <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A50 <sub>H</sub>	ID register 12	IDR12	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A51 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A52 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A53 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A54 <sub>H</sub>	ID register 13	IDR13	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A55 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A56 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A57 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A58 <sub>H</sub>	ID register 14	IDR14	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A59 <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A5A <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A5B <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A5C <sub>H</sub>	ID register 15	IDR15	R/W	XXXXXXXX XXXXXXXXX <sub>B</sub>
001A5D <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A5E <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>
001A5F <sub>H</sub>				XXXXXX--- XXXXXXXXX <sub>B</sub>

# MB90595/595G Series

List of Message Buffers (DLC Registers and Data Registers)

Address	Register	Abbreviation	Access	Initial Value
001A60 <sub>H</sub>	DLC register 0	DLCR0	R/W	----XXXX <sub>B</sub>
001A61 <sub>H</sub>				
001A62 <sub>H</sub>	DLC register 1	DLCR1	R/W	----XXXX <sub>B</sub>
001A63 <sub>H</sub>				
001A64 <sub>H</sub>	DLC register 2	DLCR2	R/W	----XXXX <sub>B</sub>
001A65 <sub>H</sub>				
001A66 <sub>H</sub>	DLC register 3	DLCR3	R/W	----XXXX <sub>B</sub>
001A67 <sub>H</sub>				
001A68 <sub>H</sub>	DLC register 4	DLCR4	R/W	----XXXX <sub>B</sub>
001A69 <sub>H</sub>				
001A6A <sub>H</sub>	DLC register 5	DLCR5	R/W	----XXXX <sub>B</sub>
001A6B <sub>H</sub>				
001A6C <sub>H</sub>	DLC register 6	DLCR6	R/W	----XXXX <sub>B</sub>
001A6D <sub>H</sub>				
001A6E <sub>H</sub>	DLC register 7	DLCR7	R/W	----XXXX <sub>B</sub>
001A6F <sub>H</sub>				
001A70 <sub>H</sub>	DLC register 8	DLCR8	R/W	----XXXX
001A71 <sub>H</sub>				
001A72 <sub>H</sub>	DLC register 9	DLCR9	R/W	----XXXX <sub>B</sub>
001A73 <sub>H</sub>				
001A74 <sub>H</sub>	DLC register 10	DLCR10	R/W	----XXXX <sub>B</sub>
001A75 <sub>H</sub>				
001A76 <sub>H</sub>	DLC register 11	DLCR11	R/W	----XXXX <sub>B</sub>
001A77 <sub>H</sub>				
001A78 <sub>H</sub>	DLC register 12	DLCR12	R/W	----XXXX <sub>B</sub>
001A79 <sub>H</sub>				
001A7A <sub>H</sub>	DLC register 13	DLCR13	R/W	----XXXX <sub>B</sub>
001A7B <sub>H</sub>				
001A7C <sub>H</sub>	DLC register 14	DLCR14	R/W	----XXXX <sub>B</sub>
001A7D <sub>H</sub>				
001A7E <sub>H</sub>	DLC register 15	DLCR15	R/W	----XXXX <sub>B</sub>
001A7F <sub>H</sub>				
001A80 <sub>H</sub> to 001A87 <sub>H</sub>	Data register 0 (8 bytes)	DTR0	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>

(Continued)

# MB90595/595G Series

(Continued)

Address	Register	Abbreviation	Access	Initial Value
001A88 <sub>H</sub> to 001A8F <sub>H</sub>	Data register 1 (8 bytes)	DTR1	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001A90 <sub>H</sub> to 001A97 <sub>H</sub>	Data register 2 (8 bytes)	DTR2	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001A98 <sub>H</sub> to 001A9F <sub>H</sub>	Data register 3 (8 bytes)	DTR3	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AA0 <sub>H</sub> to 001AA7 <sub>H</sub>	Data register 4 (8 bytes)	DTR4	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AA8 <sub>H</sub> to 001AAF <sub>H</sub>	Data register 5 (8 bytes)	DTR5	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AB0 <sub>H</sub> to 001AB7 <sub>H</sub>	Data register 6 (8 bytes)	DTR6	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AB8 <sub>H</sub> to 001ABF <sub>H</sub>	Data register 7 (8 bytes)	DTR7	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AC0 <sub>H</sub> to 001AC7 <sub>H</sub>	Data register 8 (8 bytes)	DTR8	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AC8 <sub>H</sub> to 001ACF <sub>H</sub>	Data register 9 (8 bytes)	DTR9	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AD0 <sub>H</sub> to 001AD7 <sub>H</sub>	Data register 10 (8 bytes)	DTR10	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AD8 <sub>H</sub> to 001ADF <sub>H</sub>	Data register 11 (8 bytes)	DTR11	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AE0 <sub>H</sub> to 001AE7 <sub>H</sub>	Data register 12 (8 bytes)	DTR12	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AE8 <sub>H</sub> to 001AEF <sub>H</sub>	Data register 13 (8 bytes)	DTR13	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AF0 <sub>H</sub> to 001AF7 <sub>H</sub>	Data register 14 (8 bytes)	DTR14	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>
001AF8 <sub>H</sub> to 001AFF <sub>H</sub>	Data register 15 (8 bytes)	DTR15	R/W	XXXXXXXX <sub>B</sub> to XXXXXXXX <sub>B</sub>

# MB90595/595G Series

## ■ INTERRUPT MAP

Interrupt source	EI <sup>2</sup> OS clear	Interrupt vector		Interrupt control register	
		Number	Address	Number	Address
Reset	N/A	# 08	FFFFFDCH	—	—
INT9 instruction	N/A	# 09	FFFFFD8H	—	—
Exception	N/A	# 10	FFFFFD4H	—	—
CAN RX	N/A	# 11	FFFFFD0H	ICR00	0000B0H
CAN TX/NS	N/A	# 12	FFFFFCCH		
External Interrupt (INT0/INT1)	*1	# 13	FFFFFC8H	ICR01	0000B1H
Time Base Timer	N/A	# 14	FFFFFC4H		
16-bit Reload Timer 0	*1	# 15	FFFFFC0H	ICR02	0000B2H
8/10-bit A/D Converter	*1	# 16	FFFFFBCH		
I/O Timer	N/A	# 17	FFFFFB8H	ICR03	0000B3H
External Interrupt (INT2/INT3)	*1	# 18	FFFFFB4H		
Serial I/O	*1	# 19	FFFFFB0H	ICR04	0000B4H
External Interrupt (INT4/INT5)	*1	# 20	FFFFFACH		
Input Capture 0	*1	# 21	FFFFFA8H	ICR05	0000B5H
8/16-bit PPG 0/1	N/A	# 22	FFFFFA4H		
Output Compare 0	*1	# 23	FFFFFA0H	ICR06	0000B6H
8/16-bit PPG 2/3	N/A	# 24	FFFF9CH		
External Interrupt (INT6/INT7)	*1	# 25	FFFF98H	ICR07	0000B7H
Input Capture 1	*1	# 26	FFFF94H		
8/16-bit PPG 4/5	N/A	# 27	FFFF90H	ICR08	0000B8H
Output Compare 1	*1	# 28	FFFF8CH		
8/16-bit PPG 6/7	N/A	# 29	FFFF88H	ICR09	0000B9H
Input Capture 2	*1	# 30	FFFF84H		
8/16-bit PPG 8/9	N/A	# 31	FFFF80H	ICR10	0000BAH
Output Compare 2	*1	# 32	FFFF7CH		
Input Capture 3	*1	# 33	FFFF78H	ICR11	0000BBH
8/16-bit PPG A/B	N/A	# 34	FFFF74H		
Output Compare 3	*1	# 35	FFFF70H	ICR12	0000BCH
16-bit Reload Timer 1	*1	# 36	FFFF6CH		
UART 0 RX	*2	# 37	FFFF68H	ICR13	0000BDH
UART 0 TX	*1	# 38	FFFF64H		
UART 1 RX	*2	# 39	FFFF60H	ICR14	0000BEH
UART 1 TX	*1	# 40	FFFF5CH		
Flash Memory	N/A	# 41	FFFF58H	ICR15	0000BFH
Delayed interrupt	N/A	# 42	FFFF54H		

# MB90595/595G Series

\*1: The interrupt request flag is cleared by the EI<sup>2</sup>OS interrupt clear signal.

\*2: The interrupt request flag is cleared by the EI<sup>2</sup>OS interrupt clear signal. A stop request is available.

N/A: The interrupt request flag is not cleared by the EI<sup>2</sup>OS interrupt clear signal.

Notes:

- For a peripheral module with two interrupt for a single interrupt number, both interrupt request flags are cleared by the EI<sup>2</sup>OS interrupt clear signal.
- At the end of EI<sup>2</sup>OS, the EI<sup>2</sup>OS clear signal will be asserted for all the interrupt flags assigned to the same interrupt number. If one interrupt flag starts the EI<sup>2</sup>OS and in the meantime another interrupt flag is set by hardware event, the later event is lost because the flag is cleared by the EI<sup>2</sup>OS clear signal caused by the first event. So it is recommended not to use the EI<sup>2</sup>OS for this interrupt number.
- If EI<sup>2</sup>OS is enabled, EI<sup>2</sup>OS is initiated when one of the two interrupt signals in the same interrupt control register (ICR) is asserted. This means that different interrupt sources share the same EI<sup>2</sup>OS Descriptor which should be unique for each interrupt source. For this reason, when one interrupt source uses the EI<sup>2</sup>OS, the other interrupt should be disabled.

# MB90595/595G Series

## ■ ELECTRICAL CHARACTERISTICS

### 1. Absolute Maximum Ratings

( $V_{SS} = AV_{SS} = 0.0$  V)

Parameter	Symbol	Rating		Unit	Remarks
		Min	Max		
Power supply voltage	$V_{CC}$	$V_{SS} - 0.3$	$V_{SS} + 6.0$	V	
	$AV_{CC}$	$V_{SS} - 0.3$	$V_{SS} + 6.0$	V	$V_{CC} = AV_{CC}$ *1
	$AVRH, AVRL$	$V_{SS} - 0.3$	$V_{SS} + 6.0$	V	$AV_{CC} \geq AVRH/L, AVRH \geq AVRL$ *1
	$DV_{CC}$	$V_{SS} - 0.3$	$V_{SS} + 6.0$	V	$V_{CC} \geq DV_{CC}$
Input voltage	$V_I$	$V_{SS} - 0.3$	$V_{SS} + 6.0$	V	*2
Output voltage	$V_O$	$V_{SS} - 0.3$	$V_{SS} + 6.0$	V	*2
Maximum Clamp Current	$I_{CLAMP}$	-2.0	2.0	mA	*6
Maximum Total Clamp Current	$\sum  I_{CLAMP} $	—	20	mA	*6
“L” level Max. output current	$I_{OL1}$	—	15	mA	Normal output *3
“L” level Avg. output current	$I_{OLAV1}$	—	4	mA	Normal output, average value *4
“L” level Max. output current	$I_{OL2}$	—	40	mA	High current output *3
“L” level Avg. output current	$I_{OLAV2}$	—	30	mA	High current output, average value *4
“L” level Max. overall output current	$\sum I_{OL1}$	—	100	mA	Total normal output
“L” level Max. overall output current	$\sum I_{OL2}$	—	330	mA	Total high current output
“L” level Avg. overall output current	$\sum I_{OLAV1}$	—	50	mA	Total normal output, average value *5
“L” level Avg. overall output current	$\sum I_{OLAV2}$	—	250	mA	Total high current output, average value *5
“H” level Max. output current	$I_{OH1}$	—	-15	mA	Normal output *3
“H” level Avg. output current	$I_{OHAV1}$	—	-4	mA	Normal output, average value *4
“H” level Max. output current	$I_{OH2}$	—	-40	mA	High current output *3
“H” level Avg. output current	$I_{OHAV2}$	—	-30	mA	High current output, average value *4
“H” level Max. overall output current	$\sum I_{OH1}$	—	-100	mA	Total normal output
“H” level Max. overall output current	$\sum I_{OH2}$	—	-330	mA	Total high current output
“H” level Avg. overall output current	$\sum I_{OHAV1}$	—	-50	mA	Total normal output, average value *5
“H” level Avg. overall output current	$\sum I_{OHAV2}$	—	-250	mA	Total high current output, average value *5
Power consumption	$P_D$	—	500	mW	MB90F598/F598G
		—	400	mW	MB90598/598G
Operating temperature	$T_A$	-40	+85	°C	
Storage temperature	$T_{STG}$	-55	+150	°C	

\*1:  $AV_{CC}$ ,  $AVRH$ ,  $AVRL$  and  $DV_{CC}$  shall not exceed  $V_{CC}$ .  $AVRH$  and  $AVRL$  shall not exceed  $AV_{CC}$ .  
Also,  $AVRL$  shall never exceed  $AVRH$ .

\*2:  $V_I$  and  $V_O$  should not exceed  $V_{CC} + 0.3V$ .  $V_I$  should not exceed the specified ratings. However if the maximum current to/from an input is limited by some means with external components, the  $I_{CLAMP}$  rating supersedes the  $V_I$  rating.

\*3: The maximum output current is a peak value for a corresponding pin.

\*4: Average output current is an average current value observed for a 100 ms period for a corresponding pin.

\*5: Total average current is an average current value observed for a 100 ms period for all corresponding pins.

(Continued)


# MB90595/595G Series

(Continued)

\*6: • Applicable to pins : P00 to P07, P10 to P17, P20 to P27, P30 to P37, P40 to P47, P50 to P57, P70 to P77, P80 to P87, P90 to P95

- Use within recommended operating conditions.
- Use at DC voltage (current).
- The +B signal should always be applied with a limiting resistance placed between the +B signal and the microcontroller.
- The value of the limiting resistance should be set so that when the +B signal is applied the input current to the microcontroller pin does not exceed rated values, either instantaneously or for prolonged periods.
- Note that when the microcontroller drive current is low, such as in the power saving modes, the +B input potential may pass through the protective diode and increase the potential at the V<sub>cc</sub> pin, and this may affect other devices.
- Note that if a +B signal is input when the microcontroller current is off (not fixed at 0 V), the power supply is provided from the pins, so that incomplete operation may result.
- Note that if the +B input is applied during power-on, the power supply is provided from the pins and the resulting supply voltage may not be sufficient to operate the power-on result.
- Care must be taken not to leave the +B input pin open.
- Note that analog system input/output pins other than the A/D input pins (LCD drive pins, comparator input pins, etc.) cannot accept +B signal input.
- Sample recommended circuits :

• **Input/Output Equivalent circuits**



Note: Average output current = operating current × operating efficiency

**WARNING:** Semiconductor devices can be permanently damaged by application of stress (voltage, current, temperature, etc.) in excess of absolute maximum ratings. Do not exceed these ratings.

# MB90595/595G Series

## 2. Recommended Conditions

( $V_{ss} = AV_{ss} = 0.0$  V)

Parameter	Symbol	Value			Unit	Remarks
		Min	Typ	Max		
Power supply voltage	$V_{cc}$ $AV_{cc}$	4.5	5.0	5.5	V	Under normal operation
		3.0	—	5.5	V	Maintains RAM data in stop mode
Smooth capacitor	$C_s$	0.022	0.1	1.0	$\mu F$	*
Operating temperature	$T_A$	-40	—	+85	$^{\circ}C$	


\*: Use a ceramic capacitor or a capacitor with equivalent frequency characteristics. The smoothing capacitor to be connected to the  $V_{cc}$  pin must have a capacitance value higher than  $C_s$ .

**WARNING:** The recommended operating conditions are required in order to ensure the normal operation of the semiconductor device. All of the device's electrical characteristics are warranted when the device is operated within these ranges.

Always use semiconductor devices within their recommended operating condition ranges. Operation outside these ranges may adversely affect reliability and could result in device failure.

No warranty is made with respect to uses, operating conditions, or combinations not represented on the data sheet. Users considering application outside the listed conditions are advised to contact their FUJITSU representatives beforehand.

### • C Pin Connection Diagram



# MB90595/595G Series

### 3. DC Characteristics

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^\circ\text{C}$  to  $+85 \text{ }^\circ\text{C}$ )

Parameter	Symbol	Pin name	Condition	Value			Unit	Remarks
				Min	Typ	Max		
Input H voltage	$V_{IHs}$	CMOS hysteresis input pin	—	0.8 $V_{CC}$	—	$V_{CC} + 0.3$	V	
	$V_{IHM}$	MD input pin	—	$V_{CC} - 0.3$	—	$V_{CC} + 0.3$	V	
Input L voltage	$V_{ILs}$	CMOS hysteresis input pin	—	$V_{SS} - 0.3$	—	0.2 $V_{CC}$	V	
	$V_{ILM}$	MD input pin	—	$V_{SS} - 0.3$	—	$V_{SS} + 0.3$	V	
Output H voltage	$V_{OH1}$	Output pins except P70 to P87	$V_{CC} = 4.5 \text{ V}$ , $I_{OH1} = -4.0 \text{ mA}$	$V_{CC} - 0.5$	—	—	V	
Output H voltage	$V_{OH2}$	P70 to P87	$V_{CC} = 4.5 \text{ V}$ , $I_{OH2} = -30.0 \text{ mA}$	$V_{CC} - 0.5$	—	—	V	
Output L voltage	$V_{OL1}$	Output pins except P70 to P87	$V_{CC} = 4.5 \text{ V}$ , $I_{OL1} = 4.0 \text{ mA}$	—	—	0.4	V	
Output L voltage	$V_{OL2}$	P70 to P87	$V_{CC} = 4.5 \text{ V}$ , $I_{OL2} = 30.0 \text{ mA}$	—	—	0.5	V	
Input leak current	$I_{IL}$		$V_{CC} = 5.5 \text{ V}$ , $V_{SS} < V_I < V_{CC}$	-5	—	5	$\mu\text{A}$	
Power supply current *	$I_{CC}$	$V_{CC}$	$V_{CC} = 5.0 \text{ V} \pm 10\%$ , Internal frequency: 16 MHz, At normal operating	—	35	60	mA	MB90598, MB90598G
	$I_{CCS}$			—	50	90	mA	MB90F598
	$I_{CTS}$			—	40	60	mA	MB90F598G
	$I_{CCH}$	$V_{CC}$	$V_{CC} = 5.0 \text{ V} \pm 10\%$ , Internal frequency: 16 MHz, At sleep	—	11	18	mA	
	$I_{CCH2}$		$V_{CC} = 5.0 \text{ V} \pm 1\%$ , Internal frequency: 2 MHz, At timer mode	—	0.3	0.6	mA	

(Continued)

# MB90595/595G Series

(Continued)

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^{\circ}\text{C}$  to  $+85 \text{ }^{\circ}\text{C}$ )

Parameter	Symbol	Pin name	Condition	Value			Unit	Remarks
				Min	Typ	Max		
Input capacity	$C_{IN}$	Other than C, AV <sub>CC</sub> , AV <sub>SS</sub> , AVR <sub>H</sub> , AVR <sub>L</sub> , V <sub>CC</sub> , V <sub>SS</sub> , DV <sub>CC</sub> , DV <sub>SS</sub> , P70 to P87	—	—	5	15	pF	
		P70 to P87	—	—	15	30	pF	
Pull-up resistance	$R_{UP}$	$\overline{RST}$	—	25	50	100	k $\Omega$	
Pull-down resistance	$R_{DOWN}$	MD2	—	25	50	100	k $\Omega$	

\* : The power supply current testing conditions are when using the external clock.

# MB90595/595G Series

## 4. AC Characteristics


### (1) Clock Timing

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^{\circ}\text{C}$  to  $+85 \text{ }^{\circ}\text{C}$ )


Parameter	Symbol	Pin name	Value			Unit	Remarks
			Min	Typ	Max		
Oscillation frequency	$f_C$	X0, X1	3	—	16	MHz	
Oscillation cycle time	$t_{CYL}$	X0, X1	62.5	—	333	ns	
Frequency deviation with PLL *	$\Delta f$	—	—	—	5	%	
Input clock pulse width	$P_{WH}, P_{WL}$	X0	10	—	—	ns	Duty ratio is about 30 to 70%.
Input clock rise and fall time	$t_{CR}, t_{CF}$	X0	—	—	5	ns	When using external clock
Machine clock frequency	$f_{CP}$	—	1.5	—	16	MHz	
Machine clock cycle time	$t_{CP}$	—	62.5	—	666	ns	

\*: Frequency deviation indicates the maximum frequency difference from the target frequency when using a multiplied clock.


$$\Delta f = \frac{|\alpha|}{f_0} \times 100\%$$



### • Clock Timing




Example of Oscillation circuit




# MB90595/595G Series

- **Guaranteed operation range**




- **Oscillation frequency and machine clock frequency**



AC characteristics are set to the measured reference voltage values below.


- **Input signal waveform**

**Hysteresis Input Pin**



- **Output signal waveform**

**Output Pin**



# MB90595/595G Series

## (2) Reset and Hardware Standby Input

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^{\circ}\text{C}$  to  $+85 \text{ }^{\circ}\text{C}$ )

Parameter	Symbol	Pin name	Value		Unit	Remarks
			Min	Max		
Reset input time	$t_{RSTL}$	$\overline{RST}$	16 $t_{CP}^*$ <sup>1</sup>	—	ns	Under normal operation
			Oscillation time of oscillator <sup>2</sup> + 16 $t_{CP}^*$ <sup>1</sup>	—	ms	In stop mode
Hardware standby input time	$t_{HSTL}$	$\overline{HST}$	16 $t_{CP}^*$ <sup>1</sup>	—	ns	Under normal operation
			Oscillation time of oscillator <sup>2</sup> + 16 $t_{CP}^*$ <sup>1</sup>	—	ms	In stop mode


\*1: “ $t_{CP}$ ” represents one cycle time of the machine clock.

No reset can fully initialize the Flash Memory if it is performing the automatic algorithm.


\*2: Oscillation time of oscillator is time that the amplitude reached the 90%.

In the crystal oscillator, the oscillation time is between several ms to tens of ms. In FAR / ceramic oscillator, the oscillation time is between hundreds of  $\mu\text{s}$  to several ms. In the external clock, the oscillation time is 0 ms.

### Under Normal Operation



### In Stop Mode



# MB90595/595G Series

## (3)Power On Reset


( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^{\circ}\text{C}$  to  $+85 \text{ }^{\circ}\text{C}$ )

Parameter	Symbol	Pin name	Condition	Value		Unit	Remarks
				Min	Max		
Power on rise time	$t_R$	$V_{CC}$	—	0.05	30	ms	*
Power off time	$t_{OFF}$	$V_{CC}$		50	—	ms	Due to repetitive operation

\*:  $V_{CC}$  must be kept lower than 0.2 V before power-on.

Notes: • The above values are used for creating a power-on reset.


- Some registers in the device are initialized only upon a power-on reset. To initialize these register, turn on the power supply using the above values.



Sudden changes in the power supply voltage may cause a power-on reset.

To change the power supply voltage while the device is in operation, it is recommended to raise the voltage smoothly to suppress fluctuations as shown below.

In this case, change the supply voltage with the PLL clock not used. If the voltage drop is 1 V or fewer per second, however, you can use the PLL clock.



# MB90595/595G Series


## (4) UART0/1, Serial I/O Timing

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^{\circ}\text{C}$  to  $+85 \text{ }^{\circ}\text{C}$ )

Parameter	Symbol	Pin name	Condition	Value		Unit	Remarks
				Min	Max		
Serial clock cycle time	$t_{SCYC}$	SCK0 to SCK2	Internal clock operation output pins are $C_L = 80 \text{ pF} + 1 \text{ TTL}$ .	8 $t_{CP}$	—	ns	
SCK $\downarrow \Rightarrow$ SOT delay time	$t_{SLOV}$	SCK0 to SCK2, SOT0 to SOT2		—80	80	ns	
Valid SIN $\Rightarrow$ SCK $\uparrow$	$t_{IVSH}$	SCK0 to SCK2, SIN0 to SIN2		100	—	ns	
SCK $\uparrow \Rightarrow$ Valid SIN hold time	$t_{SHIX}$	SCK0 to SCK2, SIN0 to SIN2		60	—	ns	
Serial clock "H" pulse width	$t_{SHSL}$	SCK0 to SCK2	External clock operation output pins are $C_L = 80 \text{ pF} + 1 \text{ TTL}$ .	4 $t_{CP}$	—	ns	
Serial clock "L" pulse width	$t_{SLSH}$	SCK0 to SCK2		4 $t_{CP}$	—	ns	
SCK $\downarrow \Rightarrow$ SOT delay time	$t_{SLOV}$	SCK0 to SCK2, SOT0 to SOT2		—	150	ns	
Valid SIN $\Rightarrow$ SCK $\uparrow$	$t_{IVSH}$	SCK0 to SCK2, SIN0 to SIN2		60	—	ns	
SCK $\uparrow \Rightarrow$ Valid SIN hold time	$t_{SHIX}$	SCK0 to SCK2, SIN0 to SIN2		60	—	ns	


Notes: • AC characteristic in CLK synchronized mode.  
•  $C_L$  is load capacity value of pins when testing.  
•  $t_{CP}$  is the machine cycle (Unit: ns).

### • Internal Shift Clock Mode



# MB90595/595G Series

- External Shift Clock Mode




## (5) Timer Input Timing

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^\circ\text{C}$  to  $+85 \text{ }^\circ\text{C}$ )

Parameter	Symbol	Pin name	Condition	Value		Unit	Remarks
				Min	Max		
Input pulse width	$t_{TIWH}$	TIN0, TIN1	—	4 $t_{CP}$	—	ns	
	$t_{TIWL}$	IN0 to IN3					

- Timer Input Timing




# MB90595/595G Series

## (6) Trigger Input Timing

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^\circ\text{C}$  to  $+85 \text{ }^\circ\text{C}$ )

Parameter	Symbol	Pin name	Condition	Value		Unit	Remarks
				Min	Max		
Input pulse width	$t_{TRGH}$	INT0 to INT7, ADTG	—	5 $t_{CP}$	—	ns	Under normal operation
	$t_{TRGL}$			1	—	$\mu\text{s}$	In stop mode

- Trigger Input Timing




## (7) Slew Rate High Current Outputs (MB90598, MB90598G, MB90F598G only)

( $V_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $T_A = -40 \text{ }^\circ\text{C}$  to  $+85 \text{ }^\circ\text{C}$ )

Parameter	Symbol	Pin name	Condition	Value			Unit	Remarks
				Min	Typ	Max		
Output Rise/Fall time	$t_{R2}$ $t_{F2}$	Port P70 to P77, Port P80 to P87	—	15	40	150	ns	

- Slew Rate Output Timing



# MB90595/595G Series

## 5. A/D Converter

( $V_{CC} = AV_{CC} = 5.0 \text{ V} \pm 10\%$ ,  $V_{SS} = AV_{SS} = 0.0 \text{ V}$ ,  $3.0 \text{ V} \leq AVRH - AVRL$ ,  $T_A = -40 \text{ }^{\circ}\text{C}$  to  $+85 \text{ }^{\circ}\text{C}$ )

Parameter	Symbol	Pin name	Value			Unit	Remarks
			Min	Typ	Max		
Resolution	—	—	—	—	10	bit	
Conversion error	—	—	—	—	$\pm 5.0$	LSB	
Nonlinearity error	—	—	—	—	$\pm 2.5$	LSB	
Differential linearity error	—	—	—	—	$\pm 1.9$	LSB	
Zero transition voltage	$V_{OT}$	AN0 to AN7	AVRL - 3.5	AVRL + 0.5	AVRL + 4.5	mV	
Full scale transition voltage	$V_{FST}$	AN0 to AN7	AVRH - 6.5	AVRH - 1.5	AVRH + 1.5	mV	
Conversion time	—	—	—	$352t_{CP}$	—	ns	
Sampling time	—	—	—	$64t_{CP}$	—	ns	
Analog port input current	$I_{AIN}$	AN0 to AN7	-10	—	10	$\mu\text{A}$	
Analog input voltage range	$V_{AIN}$	AN0 to AN7	AVRL	—	AVRH	V	
Reference voltage range	—	AVRH	AVRL + 3.0	—	AV <sub>CC</sub>	V	
	—	AVRL	0	—	AVRH - 3.0	V	
Power supply current	$I_A$	AV <sub>CC</sub>	—	5	—	mA	
	$I_{AH}$	AV <sub>CC</sub>	—	—	5	$\mu\text{A}$	*
Reference voltage current	$I_R$	AVRH	—	400	600	$\mu\text{A}$	MB90V595, MB90V595G, MB90F598, MB90F598G
			—	140	600	$\mu\text{A}$	MB90598, MB90598G
	$I_{RH}$	AVRH	—	—	5	$\mu\text{A}$	*
Offset between input channels	—	AN0 to AN7	—	—	4	LSB	

\* : When not operating A/D converter, this is the current ( $V_{CC} = AV_{CC} = AVRH = 5.0 \text{ V}$ ) when the CPU is stopped.


## 6. A/D Converter Glossary

Resolution: Analog changes that are identifiable with the A/D converter

Linearity error: The deviation of the straight line connecting the zero transition point ("00 0000 0000"  $\leftrightarrow$  "00 0000 0001") with the full-scale transition point ("11 1111 1110"  $\leftrightarrow$  "11 1111 1111") from actual conversion characteristics

Differential linearity error: The deviation of input voltage needed to change the output code by 1 LSB from the theoretical value

Total error: The total error is defined as a difference between the actual value and the theoretical value, which includes zero-transition error/full-scale transition error and linearity error.



$$1 \text{ LSB} = (\text{Theoretical value}) \frac{\text{AVRH} - \text{AVRL}}{1024} [\text{V}]$$

$$\text{Total error for digital output } N = \frac{V_{NT} - \{1 \text{ LSB} \times (N - 1) + 0.5 \text{ LSB}\}}{1 \text{ LSB}} [\text{LSB}]$$

$$V_{OT} \text{ (Theoretical value)} = \text{AVRL} + 0.5 \text{ LSB} [\text{V}]$$


$V_{NT}$ : Voltage at a transition of digital output from  $(N - 1)$  to  $N$

$$V_{FST} \text{ (Theoretical value)} = \text{AVRH} - 1.5 \text{ LSB} [\text{V}]$$

(Continued)

# MB90595/595G Series

(Continued)




## 7. Notes on Using A/D Converter

Select the output impedance value for the external circuit of analog input according to the following conditions.:

- Output impedance values of the external circuit of 15 kΩ or lower are recommended.
- When capacitors are connected to external pins, the capacitance of several thousand times the internal capacitor value is recommended to minimize the effect of voltage distribution between the external capacitor and internal capacitor.

When the output impedance of the external circuit is too high, the sampling period for analog voltages may not be sufficient (sampling period = 4.00 μs @ machine clock of 16 MHz).

### • Equipment of analog input circuit model



### • Error

The smaller the  $|AVRH - AVRL|$ , the greater the error would become relatively.

# MB90595/595G Series

## 8. Flash memory



- Erase and programming performance

Parameter	Condition	Value			Unit	Remarks	
		Min	Typ	Max			
Sector erase time	$T_A = +25^\circ\text{C}$ , $V_{cc} = 5.0\text{ V}$	—	1	15	s	MB90F598G	Excludes 00H programming prior erasure
Chip erase time		—	1.5	30	s	MB90F598	
Word (16-bit) programming time	$T_A = +25^\circ\text{C}$ , $V_{cc} = 5.0\text{ V}$	—	5	—	s	MB90F598G	Excludes 00H programming prior
		—	10.5	—	s	MB90F598	
Erase/Program cycle	—	—	16	3600	$\mu\text{s}$	MB90F598G	Excludes system-level overhead
		—	32	1000	$\mu\text{s}$	MB90F598	
Erase/Program cycle	—	10000	—	—	cycle		



# MB90595/595G Series

## ■ EXAMPLE CHARACTERISTICS


- “H” Level Output Voltage



- “L” Level Input Voltage








- “H” Level Input Voltage/“L” Level Input Voltage  
(Hysteresis Input)



# MB90595/595G Series

## • Supply Current



# MB90595/595G Series


## ■ ORDERING INFORMATION

Part number	Package	Remarks
MB90598PF MB90598GPF MB90F598PF MB90F598GPF	100-pin Plastic QFP (FPT-100P-M06)	
MB90V595CR MB90V595GCR	256-pin Ceramic PGA (PGA-256C-A01)	For evaluation

# MB90595/595G Series

## ■ PACKAGE DIMENSIONS

100-pin plastic QFP  
(FPT-100P-M06)



© 2001 FUJITSU LIMITED F100008S-c-4-4

Dimensions in mm (inches)

# MB90595/595G Series

## FUJITSU LIMITED

All Rights Reserved.

The contents of this document are subject to change without notice. Customers are advised to consult with FUJITSU sales representatives before ordering.

The information and circuit diagrams in this document are presented as examples of semiconductor device applications, and are not intended to be incorporated in devices for actual use. Also, FUJITSU is unable to assume responsibility for infringement of any patent rights or other rights of third parties arising from the use of this information or circuit diagrams.

The products described in this document are designed, developed and manufactured as contemplated for general use, including without limitation, ordinary industrial use, general office use, personal use, and household use, but are not designed, developed and manufactured as contemplated (1) for use accompanying fatal risks or dangers that, unless extremely high safety is secured, could have a serious effect to the public, and could lead directly to death, personal injury, severe physical damage or other loss (i.e., nuclear reaction control in nuclear facility, aircraft flight control, air traffic control, mass transport control, medical life support system, missile launch control in weapon system), or (2) for use requiring extremely high reliability (i.e., submersible repeater and artificial satellite).

Please note that Fujitsu will not be liable against you and/or any third party for any claims or damages arising in connection with above-mentioned uses of the products.

Any semiconductor devices have an inherent chance of failure. You must protect against injury, damage or loss from such failures by incorporating safety design measures into your facility and equipment such as redundancy, fire protection, and prevention of over-current levels and other abnormal operating conditions.

If any products described in this document represent goods or technologies subject to certain restrictions on export under the Foreign Exchange and Foreign Trade Law of Japan, the prior authorization by Japanese government will be required for export of those products from Japan.