



# Multiformat Video Encoder, Six 12-Bit Noise Shaped Video® DACs

## ADV7340/ADV7341

### FEATURES

**74.25 MHz 20-/30-bit high definition input support**  
Compliant with SMPTE 274 M (1080i), 296 M (720p), and 240 M (1035i)

**6 Noise Shaped Video (NSV) 12-bit video DACs**  
16x (216 MHz) DAC oversampling for SD  
8x (216 MHz) DAC oversampling for ED  
4x (297 MHz) DAC oversampling for HD  
37 mA maximum DAC output current

**NTSC M, PAL B/D/G/H/I/M/N, PAL 60 support**  
NTSC and PAL square pixel operation (24.54 MHz/29.5 MHz)

**Multiformat video input support**  
4:2:2 YCrCb (SD, ED, and HD)  
4:4:4 YCrCb (ED and HD)  
4:4:4 RGB (SD, ED, and HD)

**Multiformat video output support**  
Composite (CVBS) and S-Video (Y/C)  
Component YPrPb (SD, ED, and HD)  
Component RGB (SD, ED, and HD)

**Macrovision® Rev 7.1.L1 (SD) and Rev 1.2 (ED) compliant**  
Simultaneous SD and ED/HD operation

### EIA/CEA-861B compliance support

#### Programmable features

- Luma and chroma filter responses
- Vertical blanking interval (VBI)
- Subcarrier frequency ( $F_{SC}$ ) and phase
- Luma delay

#### Copy generation management system (CGMS)

- Closed captioning and wide screen signaling (WSS)
- Integrated subcarrier locking to external video source

#### Complete on-chip video timing generator

#### On-chip test pattern generation

#### On-board voltage reference (optional external input)

#### Serial MPU interface with dual I<sup>2</sup>C® and SPI® compatibility

#### 3.3 V analog operation

#### 1.8 V digital operation

#### 3.3 V I/O operation

#### Temperature range: -40°C to +85°C

### APPLICATIONS

DVD recorders and players

High definition Blu-ray DVD players

HD-DVD players

### FUNCTIONAL BLOCK DIAGRAM




Figure 1.

06398-001

Protected by U.S. Patent Numbers 5,343,196 and 5,442,355 and other intellectual property rights.

Protected by U.S. Patent Numbers 4,631,603, 4,577,216, 4,819,098 and other intellectual property rights.

Rev. 0

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices.

**TABLE OF CONTENTS**

|  |    |  |    |
|--|----|--|----|
| Features .....   | 1  | SD Subcarrier Frequency Lock, Subcarrier Phase Reset, and Timing Reset ..... | 50 |
| Applications .....   | 1  | SD VCR FF/RW Sync .....  | 51 |
| Functional Block Diagram .....   | 1  | Vertical Blanking Interval .....   | 51 |
| Revision History .....   | 3  | SD Subcarrier Frequency Registers .....                                      | 51 |
| Detailed Features .....  | 4  | SD Noninterlaced Mode .....  | 52 |
| General Description .....  | 4  | SD Square Pixel Mode .....   | 52 |
| Specifications .....   | 5  | Filters .....  | 53 |
| Power Supply and Voltage Specifications .....                                  | 5  | ED/HD Test Pattern Color Controls .....                                      | 54 |
| Voltage Reference Specifications .....   | 5  | Color Space Conversion Matrix .....  | 54 |
| Input Clock Specifications .....   | 5  | SD Luma and Color Control .....  | 55 |
| Analog Output Specifications .....   | 6  | SD Hue Adjust Control .....  | 56 |
| Digital Input/Output Specifications .....                                      | 6  | SD Brightness Detect .....   | 56 |
| Digital Timing Specifications .....  | 7  | SD Brightness Control .....  | 56 |
| MPU Port Timing Specifications .....   | 8  | SD Input Standard Auto Detection .....                                       | 56 |
| Power Specifications .....   | 8  | Double Buffering .....   | 57 |
| Video Performance Specifications .....   | 9  | Programmable DAC Gain Control .....  | 57 |
| Timing Diagrams .....  | 10 | Gamma Correction .....   | 57 |
| Absolute Maximum Ratings .....   | 18 | ED/HD Sharpness Filter and Adaptive Filter Controls .....                    | 59 |
| Thermal Resistance .....   | 18 | ED/HD Sharpness Filter and Adaptive Filter Application Examples .....        | 60 |
| ESD Caution .....  | 18 | SD Digital Noise Reduction .....   | 61 |
| Pin Configuration and Function Descriptions .....                              | 19 | SD Active Video Edge Control .....   | 62 |
| Typical Performance Characteristics .....                                      | 21 | External Horizontal and Vertical Synchronization Control .....               | 64 |
| MPU Port Description .....   | 26 | Low Power Mode .....   | 65 |
| I <sup>2</sup> C Operation .....   | 26 | Cable Detection .....  | 65 |
| SPI Operation .....  | 27 | DAC Auto Power-Down .....  | 65 |
| Register Map Access .....  | 28 | Pixel and Control Port Readback .....  | 65 |
| Register Programming .....   | 28 | Reset Mechanism .....  | 65 |
| Subaddress Register (SR7 to SR0) .....   | 28 | Printed Circuit Board Layout and Design .....                                | 66 |
| Input Configuration .....  | 45 | DAC Configurations .....   | 66 |
| Standard Definition Only .....   | 45 | Voltage Reference .....  | 66 |
| Enhanced Definition/High Definition Only .....                                 | 46 | Video Output Buffer and Optional Output Filter .....                         | 66 |
| Simultaneous Standard Definition and Enhanced Definition/High Definition ..... | 46 | Printed Circuit Board (PCB) Layout .....                                     | 67 |
| Enhanced Definition Only (at 54 MHz) .....                                     | 47 | Typical Application Circuit .....  | 69 |
| Output Configuration .....   | 48 | Appendix 1—Copy Generation Management System .....                           | 70 |
| Features .....   | 49 | SD CGMS .....  | 70 |
| Output Oversampling .....  | 49 | ED CGMS .....  | 70 |
| ED/HD Nonstandard Timing Mode .....  | 49 | HD CGMS .....  | 70 |
| ED/HD Timing Reset .....   | 50 | CGMS CRC Functionality .....   | 70 |

|   |    |   |    |
|---|----|---|----|
| Appendix 2—SD Wide Screen Signaling .....         | 73 | SD YPrPb Output Levels—SMPTE/EBU N10..... | 82 |
| Appendix 3—SD Closed Captioning.....              | 74 | ED/HD YPrPb Output Levels .....           | 83 |
| Appendix 4—Internal Test Pattern Generation ..... | 75 | SD/ED/HD RGB Output Levels.....           | 84 |
| SD Test Patterns.....                             | 75 | SD Output Plots .....                     | 85 |
| ED/HD Test Patterns .....                         | 75 | Appendix 8—Video Standards .....          | 86 |
| Appendix 5—SD Timing.....                         | 76 | Outline Dimensions.....                   | 88 |
| Appendix 6—HD Timing .....                        | 81 | Ordering Guide .....                      | 88 |
| Appendix 7—Video Output Levels.....               | 82 |   |    |

REVISION HISTORY

10/06—Revision 0: Initial Version

# ADV7340/ADV7341

## DETAILED FEATURES

### High definition (HD) programmable features (720p/1080i/1035i)

4× oversampling (297 MHz)

Internal test pattern generator

Fully programmable YCrCb to RGB matrix

Gamma correction

Programmable adaptive filter control

Programmable sharpness filter control

CGMS (720p/1080i) and CGMS Type B (720p/1080i)

Undershoot limiter

Dual data rate (DDR) input support

EIA/CEA-861B compliance support

### Enhanced definition(ED) programmable features (525p/625p)

8× oversampling (216 MHz output)

Internal test pattern generator

Color and black bar, hatch, flat field/frame

Individual Y and PrPb output delay

Gamma correction

Programmable adaptive filter control

Fully programmable YCrCb to RGB matrix

Undershoot limiter

Macrovision Rev 1.2 (525p/625p)

CGMS (525p/625p) and CGMS Type B (525p)

Dual data rate (DDR) input support

EIA/CEA-861B compliance support

### Standard definition (SD) programmable features

16× oversampling (216 MHz)

Internal test pattern generator

Color and black bar

Controlled edge rates for start and end of active video

Individual Y and PrPb output delay

Undershoot limiter

Gamma correction

Digital noise reduction (DNR)

Multiple chroma and luma filters

Luma-SSAF™ filter with programmable gain/attenuation

PrPb SSAF™

Separate pedestal control on component and  
composite/S-Video output

VCR FF/RW sync mode

Macrovision Rev 7.1.L1

Copy generation management system (CGMS)

Wide screen signaling

Closed captioning

EIA/CEA-861B compliance support

## GENERAL DESCRIPTION

The ADV7340/ADV7341 are high speed, digital-to-analog video encoders in a 64-lead LQFP package. Six high speed, NSV, 3.3 V, 12-bit video DACs provide support for composite (CVBS), S-Video (Y/C), and component (YPrPb/RGB) analog outputs in either standard definition (SD), enhanced definition (ED), or high definition (HD) video formats.

The ADV7340/ADV7341 each have a 30-bit pixel input port that can be configured in a variety of ways. SD video formats are supported over a SDR interface and ED/HD video formats are supported over SDR and DDR interfaces. Pixel data can be supplied in either the YCrCb or RGB color spaces.

The parts also support embedded EAV/SAV timing codes, external video synchronization signals, and I²C and SPI communication protocols.

In addition, simultaneous SD and ED/HD input and output are supported. 216 MHz (SD and ED) and 297 MHz (HD) oversampling ensures that external output filtering is not required, while full-drive DACs ensure that external output buffering is not required.

Cable detection and DAC auto power-down features keep power consumption to a minimum.

Table 1 lists the video standards directly supported by the ADV7340/ADV7341.

**Table 1. Standards Directly Supported by the ADV7340/ADV7341<sup>1</sup>**

| Resolution  | I/P <sup>2</sup> | Frame Rate (Hz)           | Clock Input (MHz) | Standard             |
|-------------|------------------|---------------------------|-------------------|----------------------|
| 720 × 240   | P                | 59.94                     | 27                | ITU-R<br>BT.601/656  |
| 720 × 288   | P                | 50                        | 27                |                      |
| 720 × 480   | I                | 29.97                     | 27                |                      |
| 720 × 576   | I                | 25                        | 27                | ITU-R<br>BT.601/656  |
| 720 × 480   | I                | 29.97                     | 24.54             | NTSC Square<br>Pixel |
| 720 × 576   | I                | 25                        | 29.5              | PAL Square<br>Pixel  |
| 720 × 483   | P                | 59.94                     | 27                | SMPTE 293M           |
| 720 × 483   | P                | 59.94                     | 27                | BTA T-1004           |
| 720 × 483   | P                | 59.94                     | 27                | ITU-R BT.1358        |
| 720 × 576   | P                | 50                        | 27                | ITU-R BT.1358        |
| 720 × 483   | P                | 59.94                     | 27                | ITU-R BT.1362        |
| 720 × 576   | P                | 50                        | 27                | ITU-R BT.1362        |
| 1920 × 1035 | I                | 30                        | 74.25             | SMPTE 240M           |
| 1920 × 1035 | I                | 29.97                     | 74.1758           | SMPTE 240M           |
| 1280 × 720  | P                | 60, 50, 30,<br>25, 24     | 74.25             | SMPTE 296M           |
| 1280 × 720  | P                | 23.97,<br>59.94,<br>29.97 | 74.1758           | SMPTE 296M           |
| 1920 × 1080 | I                | 30, 25                    | 74.25             | SMPTE 274M           |
| 1920 × 1080 | I                | 29.97                     | 74.1758           | SMPTE 274M           |
| 1920 × 1080 | P                | 30, 25, 24                | 74.25             | SMPTE 274M           |
| 1920 × 1080 | P                | 23.98,<br>29.97           | 74.1758           | SMPTE 274M           |
| 1920 × 1080 | P                | 24                        | 74.25             | ITU-R BT.709-5       |

<sup>1</sup> Other standards are supported in the ED/HD nonstandard timing mode.

<sup>2</sup> I = interlaced, P = progressive.

## SPECIFICATIONS

### POWER SUPPLY AND VOLTAGE SPECIFICATIONS

All specifications  $T_{MIN}$  to  $T_{MAX}$  ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ), unless otherwise noted.

Table 2.

| Parameter                    | Conditions | Min  | Typ   | Max   | Unit |
|------------------------------|------------|------|-------|-------|------|
| SUPPLY VOLTAGES              |            |      |       |       |      |
| $V_{DD}$                     |            | 1.71 | 1.8   | 1.89  | V    |
| $V_{DD\_IO}$                 |            | 2.97 | 3.3   | 3.63  | V    |
| $PV_{DD}$                    |            | 1.71 | 1.8   | 1.89  | V    |
| $V_{AA}$                     |            | 2.6  | 3.3   | 3.465 | V    |
| POWER SUPPLY REJECTION RATIO |            |      | 0.002 |       | %/%  |

### VOLTAGE REFERENCE SPECIFICATIONS

All specifications  $T_{MIN}$  to  $T_{MAX}$  ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ), unless otherwise noted.

Table 3.

| Parameter                               | Conditions | Min   | Typ      | Max  | Unit          |
|---|------------|-------|----------|------|---------------|
| Internal Reference Range, $V_{REF}$     |            | 1.186 | 1.248    | 1.31 | V             |
| External Reference Range, $V_{REF}$     |            | 1.15  | 1.235    | 1.31 | V             |
| External $V_{REF}$ Current <sup>1</sup> |            |       | $\pm 10$ |      | $\mu\text{A}$ |

<sup>1</sup> External current required to overdrive internal  $V_{REF}$ .

### INPUT CLOCK SPECIFICATIONS

$V_{DD} = 1.71\text{ V}$  to  $1.89\text{ V}$ .  $PV_{DD} = 1.71\text{ V}$  to  $1.89\text{ V}$ .  $V_{AA} = 2.6\text{ V}$  to  $3.465\text{ V}$ .  $V_{DD\_IO} = 2.97\text{ V}$  to  $3.63\text{ V}$ .

All specifications  $T_{MIN}$  to  $T_{MAX}$  ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ), unless otherwise noted.

Table 4.

| Parameter                             | Conditions <sup>1</sup> | Min | Typ   | Max | Unit                 |
|---------------------------------------|-------------------------|-----|-------|-----|----------------------|
| $f_{CLKIN\_A}$                        | SD/ED                   |     | 27    |     | MHz                  |
| $f_{CLKIN\_A}$                        | ED (at 54 MHz)          |     | 54    |     | MHz                  |
| $f_{CLKIN\_A}$                        | HD                      |     | 74.25 |     | MHz                  |
| $f_{CLKIN\_B}$                        | ED                      |     | 27    |     | MHz                  |
| $f_{CLKIN\_B}$                        | HD                      |     | 74.25 |     | MHz                  |
| CLKIN_A High Time, $t_9$              |                         | 40  |       |     | % of one clock cycle |
| CLKIN_A Low Time, $t_{10}$            |                         | 40  |       |     | % of one clock cycle |
| CLKIN_B High Time, $t_9$              |                         | 40  |       |     | % of one clock cycle |
| CLKIN_B Low Time, $t_{10}$            |                         | 40  |       |     | % of one clock cycle |
| CLKIN_A Peak-to-Peak Jitter Tolerance |                         |     | 2     |     | $\pm\text{ns}$       |
| CLKIN_B Peak-to-Peak Jitter Tolerance |                         |     | 2     |     | $\pm\text{ns}$       |

<sup>1</sup> SD = standard definition, ED = enhanced definition (525p/625p), HD = high definition.

# ADV7340/ADV7341

## ANALOG OUTPUT SPECIFICATIONS

$V_{DD} = 1.71 \text{ V to } 1.89 \text{ V}$ .  $PV_{DD} = 1.71 \text{ V to } 1.89 \text{ V}$ .  $V_{AA} = 2.6 \text{ V to } 3.465 \text{ V}$ .  $V_{DD\_IO} = 2.97 \text{ V to } 3.63 \text{ V}$ .  $V_{REF} = 1.235 \text{ V}$  (driven externally).

All specifications  $T_{MIN}$  to  $T_{MAX}$  ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ), unless otherwise noted.

Table 5.

| Parameter   | Conditions  | Min | Typ  | Max | Unit |
|---|---|-----|------|-----|------|
| Full-Drive Output Current (Full-Scale) <sup>1</sup> | $R_{SET} = 510 \Omega$ , $R_L = 37.5 \Omega$          | 33  | 34.6 | 37  | mA   |
| Low Drive Output Current (Full-Scale) <sup>2</sup>  | $R_{SET} = 4.12 \text{ k}\Omega$ , $R_L = 300 \Omega$ | 4.1 | 4.3  | 4.5 | mA   |
| DAC-to-DAC Matching                                 | DAC 1 to DAC 6  |     | 1.0  |     | %    |
| Output Compliance, $V_{OC}$                         |   | 0   |      | 1.4 | V    |
| Output Capacitance, $C_{OUT}$                       | DAC 1, DAC 2, DAC 3                                   |     | 10   |     | pF   |
|   | DAC 4, DAC 5, DAC 6                                   |     | 6    |     | pF   |
| Analog Output Delay <sup>3</sup>                    | DAC 1, DAC 2, DAC 3                                   |     | 8    |     | ns   |
|   | DAC 4, DAC 5, DAC 6                                   |     | 6    |     | ns   |
| DAC Analog Output Skew                              | DAC 1, DAC 2, DAC 3                                   |     | 2    |     | ns   |
|   | DAC 4, DAC 5, DAC 6                                   |     | 1    |     | ns   |

<sup>1</sup> Applicable to full-drive capable DACs only, that is, DAC 1, DAC 2, DAC 3.

<sup>2</sup> Applicable to all DACs.

<sup>3</sup> Output delay measured from the 50% point of the rising edge of the input clock to the 50% point of the DAC output full-scale transition.

## DIGITAL INPUT/OUTPUT SPECIFICATIONS

$V_{DD} = 1.71 \text{ V to } 1.89 \text{ V}$ .  $PV_{DD} = 1.71 \text{ V to } 1.89 \text{ V}$ .  $V_{AA} = 2.6 \text{ V to } 3.465 \text{ V}$ .  $V_{DD\_IO} = 2.97 \text{ V to } 3.63 \text{ V}$ .

All specifications  $T_{MIN}$  to  $T_{MAX}$  ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ), unless otherwise noted.

Table 6.

| Parameter                       | Conditions                              | Min | Typ | Max       | Unit          |
|---------------------------------|---|-----|-----|-----------|---------------|
| Input High Voltage, $V_{IH}$    |   | 2.0 |     |           | V             |
| Input Low Voltage, $V_{IL}$     |   |     |     | 0.8       | V             |
| Input Leakage Current, $I_{IN}$ | $V_{IN} = V_{DD\_IO}$                   |     |     | $\pm 10$  | $\mu\text{A}$ |
| Input Capacitance, $C_{IN}$     |   |     | 4   |           | pF            |
| Output High Voltage, $V_{OH}$   | $I_{SOURCE} = 400 \mu\text{A}$          | 2.4 |     |           | V             |
| Output Low Voltage, $V_{OL}$    | $I_{SINK} = 3.2 \text{ mA}$             |     |     | 0.4       | V             |
| Three-State Leakage Current     | $V_{IN} = 0.4 \text{ V}, 2.4 \text{ V}$ |     |     | $\pm 1.0$ | $\mu\text{A}$ |
| Three-State Output Capacitance  |   |     | 4   |           | pF            |

**DIGITAL TIMING SPECIFICATIONS**

$V_{DD} = 1.71\text{ V to }1.89\text{ V}$ ,  $PV_{DD} = 1.71\text{ V to }1.89\text{ V}$ ,  $V_{AA} = 2.6\text{ V to }3.465\text{ V}$ ,  $V_{DD\_IO} = 2.97\text{ V to }3.63\text{ V}$ .

All specifications  $T_{MIN}$  to  $T_{MAX}$  ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ), unless otherwise noted.

**Table 7.**

| Parameter   | Conditions <sup>1</sup>                | Min | Typ | Max | Unit         |
|---|--|-----|-----|-----|--------------|
| VIDEO DATA AND VIDEO CONTROL PORT <sup>2, 3</sup> |  |     |     |     |              |
| Data Setup Time, $t_{11}$ <sup>4</sup>            | SD                                     | 2.1 |     |     | ns           |
|   | ED/HD-SDR                              | 2.3 |     |     | ns           |
|   | ED/HD-DDR                              | 2.3 |     |     | ns           |
|   | ED (at 54 MHz)                         | 1.7 |     |     | ns           |
| Data Hold Time, $t_{12}$ <sup>4</sup>             | SD                                     | 1.0 |     |     | ns           |
|   | ED/HD-SDR                              | 1.1 |     |     | ns           |
|   | ED/HD-DDR                              | 1.1 |     |     | ns           |
|   | ED (at 54 MHz)                         | 1.0 |     |     | ns           |
| Control Setup Time, $t_{11}$ <sup>4</sup>         | SD                                     | 2.1 |     |     | ns           |
|   | ED/HD-SDR or ED/HD-DDR                 | 2.3 |     |     | ns           |
|   | ED (at 54 MHz)                         | 1.7 |     |     | ns           |
| Control Hold Time, $t_{12}$ <sup>4</sup>          | SD                                     | 1.0 |     |     | ns           |
|   | ED/HD-SDR or ED/HD-DDR                 | 1.1 |     |     | ns           |
|   | ED (at 54 MHz)                         | 1.0 |     |     | ns           |
| Digital Output Access Time, $t_{13}$ <sup>4</sup> | SD                                     |     |     | 12  | ns           |
|   | ED/HD-SDR, ED/HD-DDR or ED (at 54 MHz) |     |     | 10  | ns           |
| Digital Output Hold Time, $t_{14}$ <sup>4</sup>   | SD                                     | 4.0 |     |     | ns           |
|   | ED/HD-SDR, ED/HD-DDR or ED (at 54 MHz) | 3.5 |     |     | ns           |
| PIPELINE DELAY <sup>5</sup>                       |  |     |     |     |              |
| SD <sup>1</sup>                                   |  |     |     |     |              |
| CVBS/YC Outputs (2×)                              | SD oversampling disabled               |     | 68  |     | clock cycles |
| CVBS/YC Outputs (16×)                             | SD oversampling enabled                |     | 67  |     | clock cycles |
| Component Outputs (2×)                            | SD oversampling disabled               |     | 78  |     | clock cycles |
| Component Outputs (16×)                           | SD oversampling enabled                |     | 84  |     | clock cycles |
| ED <sup>1</sup>                                   |  |     |     |     |              |
| Component Outputs (1×)                            | ED oversampling disabled               |     | 41  |     | clock cycles |
| Component Outputs (8×)                            | ED oversampling enabled                |     | 46  |     | clock cycles |
| HD <sup>1</sup>                                   |  |     |     |     |              |
| Component Outputs (1×)                            | HD oversampling disabled               |     | 40  |     | clock cycles |
| Component Outputs (4×)                            | HD oversampling enabled                |     | 44  |     | clock cycles |

<sup>1</sup> SD = standard definition, ED = enhanced definition (525p/625p), HD = high definition, SDR = single data rate, DDR = dual data rate.

<sup>2</sup> Video data: C[9:0], Y[9:0], and S[9:0].

<sup>3</sup> Video control: P\_HSYNC, P\_VSYNC, P\_BLANK, S\_HSYNC, and S\_VSYNC.

<sup>4</sup> Guaranteed by characterization.

<sup>5</sup> Guaranteed by design.

# ADV7340/ADV7341

## MPU PORT TIMING SPECIFICATIONS

$V_{DD} = 1.71 \text{ V}$  to  $1.89 \text{ V}$ .  $PV_{DD} = 1.71 \text{ V}$  to  $1.89 \text{ V}$ .  $V_{AA} = 2.6 \text{ V}$  to  $3.465 \text{ V}$ .  $V_{DD\_IO} = 2.97 \text{ V}$  to  $3.63 \text{ V}$ .

All specifications  $T_{MIN}$  to  $T_{MAX}$  ( $-40^{\circ}\text{C}$  to  $+85^{\circ}\text{C}$ ), unless otherwise noted.

Table 8.

| Parameter   | Conditions    | Min | Typ | Max | Unit          |
|---|---------------|-----|-----|-----|---------------|
| MPU PORT, I <sup>2</sup> C MODE <sup>1</sup>              | See Figure 19 |     |     |     |               |
| SCL Frequency   |               | 0   |     | 400 | kHz           |
| SCL High Pulse Width, $t_1$                               |               | 0.6 |     |     | $\mu\text{s}$ |
| SCL Low Pulse Width, $t_2$                                |               | 1.3 |     |     | $\mu\text{s}$ |
| Hold Time (Start Condition), $t_3$                        |               | 0.6 |     |     | $\mu\text{s}$ |
| Setup Time (Start Condition), $t_4$                       |               | 0.6 |     |     | $\mu\text{s}$ |
| Data Setup Time, $t_5$                                    |               | 100 |     |     | ns            |
| SDA, SCL Rise Time, $t_6$                                 |               |     |     | 300 | ns            |
| SDA, SCL Fall Time, $t_7$                                 |               |     |     | 300 | ns            |
| Setup Time (Stop Condition), $t_8$                        |               | 0.6 |     |     | $\mu\text{s}$ |
| MPU PORT, SPI MODE <sup>1</sup>                           | See Figure 20 |     |     |     |               |
| SCLK Frequency  |               | 0   |     | 10  | MHz           |
| $\overline{\text{SPI\_SS}}$ to SCLK Setup Time, $t_1$     |               | 20  |     |     | ns            |
| SCLK High Pulse Width, $t_2$                              |               | 50  |     |     | ns            |
| SCLK Low Pulse Width, $t_3$                               |               | 50  |     |     | ns            |
| Data Access Time after SCLK Falling Edge, $t_4$           |               |     |     | 35  | ns            |
| Data Setup Time prior to SCLK Rising Edge, $t_5$          |               | 20  |     |     | ns            |
| Data Hold Time after SCLK Rising Edge, $t_6$              |               | 0   |     |     | ns            |
| $\overline{\text{SPI\_SS}}$ to SCLK Hold Time, $t_7$      |               | 0   |     |     | ns            |
| $\overline{\text{SPI\_SS}}$ to MISO High Impedance, $t_8$ |               |     |     | 40  | ns            |

<sup>1</sup> Guaranteed by characterization.

## POWER SPECIFICATIONS

$V_{DD} = 1.8 \text{ V}$ ,  $PV_{DD} = 1.8 \text{ V}$ ,  $V_{AA} = 3.3 \text{ V}$ ,  $V_{DD\_IO} = 3.3 \text{ V}$ ,  $T_A = 25^{\circ}\text{C}$ .

Table 9.

| Parameter                         | Conditions                                      | Min | Typ | Max | Unit          |
|-----------------------------------|---|-----|-----|-----|---------------|
| NORMAL POWER MODE <sup>1, 2</sup> |   |     |     |     |               |
| $I_{DD}$ <sup>3</sup>             | SD only (16× oversampling)                      |     | 90  |     | mA            |
|                                   | ED only (8× oversampling) <sup>4</sup>          |     | 65  |     | mA            |
|                                   | HD only (4× oversampling) <sup>4</sup>          |     | 91  |     | mA            |
|                                   | SD (16× oversampling) and ED (8× oversampling)  |     | 95  |     | mA            |
|                                   | SD (16× oversampling) and HD (4× oversampling)  |     | 122 |     | mA            |
| $I_{DD\_IO}$                      |   |     | 1   |     | mA            |
| $I_{AA}$                          | 3 DACs enabled (ED/HD only)                     |     | 124 |     | mA            |
|                                   | 6 DACs enabled (SD only and simultaneous modes) |     | 140 |     | mA            |
| $I_{PLL}$                         | SD only, ED only or HD only modes               |     | 5   |     | mA            |
|                                   | Simultaneous modes                              |     | 10  |     | mA            |
| SLEEP MODE                        |   |     |     |     |               |
| $I_{DD}$                          |   |     | 5   |     | $\mu\text{A}$ |
| $I_{AA}$                          |   |     | 0.3 |     | $\mu\text{A}$ |
| $I_{DD\_IO}$                      |   |     | 0.2 |     | $\mu\text{A}$ |
| $I_{PLL}$                         |   |     | 0.1 |     | $\mu\text{A}$ |

<sup>1</sup>  $R_{SET1} = 510 \Omega$  (DAC 1, DAC 2, and DAC 3 operating in full-drive mode).  $R_{SET2} = 4.12 \text{ k}\Omega$  (DAC 4, DAC 5, and DAC 6 operating in low drive mode).

<sup>2</sup> 75% color bar test pattern applied to pixel data pins.

<sup>3</sup>  $I_{DD}$  is the continuous current required to drive the digital core.

<sup>4</sup> Applicable to both single data rate (SDR) and dual data rate (DDR) input modes.



**VIDEO PERFORMANCE SPECIFICATIONS**

$V_{DD} = 1.8\text{ V}$ ,  $PV_{DD} = 1.8\text{ V}$ ,  $V_{AA} = 3.3\text{ V}$ ,  $V_{DD\_IO} = 3.3\text{ V}$ ,  $T_A = 25^\circ\text{C}$ ,  $V_{REF}$  driven externally.

**Table 10.**

| Parameter                                  | Conditions  | Min | Typ   | Max | Unit    |
|--|---|-----|-------|-----|---------|
| STATIC PERFORMANCE                         |   |     |       |     |         |
| Resolution                                 |   |     | 12    |     | Bits    |
| Integral Nonlinearity                      | $R_{SET1} = 510\ \Omega$ , $R_{L1} = 37.5\ \Omega$        |     | 0.75  |     | LSBs    |
|  | $R_{SET2} = 4.12\text{ k}\Omega$ , $R_{L2} = 300\ \Omega$ |     | 1     |     | LSBs    |
| Differential Nonlinearity <sup>1</sup> +ve | $R_{SET1} = 510\ \Omega$ , $R_{L1} = 37.5\ \Omega$        |     | 0.25  |     | LSBs    |
|  | $R_{SET2} = 4.12\text{ k}\Omega$ , $R_{L2} = 300\ \Omega$ |     | 0.8   |     | LSBs    |
| Differential Nonlinearity <sup>1</sup> –ve | $R_{SET1} = 510\ \Omega$ , $R_{L1} = 37.5\ \Omega$        |     | 0.43  |     | LSBs    |
|  | $R_{SET2} = 4.12\text{ k}\Omega$ , $R_{L2} = 300\ \Omega$ |     | 0.35  |     | LSBs    |
| STANDARD DEFINITION (SD) MODE              |   |     |       |     |         |
| Luminance Nonlinearity                     |   |     | 0.35  |     | ±%      |
| Differential Gain                          | NTSC  |     | 0.3   |     | %       |
| Differential Phase                         | NTSC  |     | 0.4   |     | Degrees |
| SNR  | Luma ramp   |     | 63    |     | dB      |
| SNR  | Flat field full bandwidth                                 |     | 79.5  |     | dB      |
| ENHANCED DEFINITION (ED) MODE              |   |     |       |     |         |
| Luma Bandwidth                             |   |     | 12.5  |     | MHz     |
| Chroma Bandwidth                           |   |     | 5.8   |     | MHz     |
| HIGH DEFINITION (HD) MODE                  |   |     |       |     |         |
| Luma Bandwidth                             |   |     | 30    |     | MHz     |
| Chroma Bandwidth                           |   |     | 13.75 |     | MHz     |

<sup>1</sup> Differential nonlinearity (DNL) measures the deviation of the actual DAC output voltage step from the ideal. For +ve DNL, the actual step value lies above the ideal step value. For –ve DNL, the actual step value lies below the ideal step value.


## TIMING DIAGRAMS

The following abbreviations are used in Figure 2 to Figure 13:

- $t_9$  = Clock high time
- $t_{10}$  = Clock low time
- $t_{11}$  = Data setup time
- $t_{12}$  = Data hold time


- $t_{13}$  = Control output access time
- $t_{14}$  = Control output hold time

In addition, refer to Table 31 for the ADV7340/ADV7341 input configuration.



\*SELECTED BY SUBADDRESS 0x01, BIT 7.

Figure 2. SD Only, 8-/10-Bit, 4:2:2 YCrCb Pixel Input Mode (Input Mode 000)



\*SELECTED BY SUBADDRESS 0x01, BIT 7.

Figure 3. SD Only, 16-/20-Bit, 4:2:2 YCrCb Pixel Input Mode (Input Mode 000)




Figure 4. SD Only, 24-/30-Bit, 4:4:4 RGB Pixel Input Mode (Input Mode 000)




Figure 5. ED/HD-SDR Only, 16-/20-Bit, 4:2:2 YCrCb Pixel Input Mode (Input Mode 001)




Figure 6. ED/HD-SDR Only, 24-/30-Bit, 4:4:4 YCrCb Pixel Input Mode (Input Mode 001)

# ADV7340/ADV7341






Figure 7. ED/HD-SDR Only, 24-/30-Bit, 4:4:4 RGB Pixel Input Mode (Input Mode 001)



\*LUMA/CHROMA CLOCK RELATIONSHIP CAN BE INVERTED  
USING SUBADDRESS 0x01, BITS 1 AND 2.

Figure 8. ED/HD-DDR Only, 8-/10-Bit, 4:2:2 YCrCb (HSYNC/VSYNC) Pixel Input Mode (Input Mode 010)



\*LUMA/CHROMA CLOCK RELATIONSHIP CAN BE INVERTED  
USING SUBADDRESS 0x01, BITS 1 AND 2.

Figure 9. ED/HD-DDR Only, 8-/10-Bit, 4:2:2 YCrCb (EAV/SAV) Pixel Input Mode (Input Mode 010)




Figure 10. SD, ED/HD-SDR Input Mode, 16-/20-Bit, 4:2:2 ED/HD and 8-/10-Bit, SD Pixel Input Mode (Input Mode 011)




Figure 11. SD, ED/HD-DDR Input Mode, 8-/10-Bit, 4:2:2 ED/HD and 8-/10-Bit, SD Pixel Input Mode (Input Mode 100)




Figure 12. ED Only (at 54 MHz), 8-/10-Bit, 4:2:2 YCrCb (HSYNC/VSYNC) Pixel Input Mode (Input Mode 111)

# ADV7340/ADV7341





Figure 13. ED Only (at 54 MHz), 8-/10-Bit, 4:2:2 YCrCb (EAV/SAV) Pixel Input Mode (Input Mode 111)




a AND b AS PER RELEVANT STANDARD.

c = PIPELINE DELAY. PLEASE REFER TO RELEVANT PIPELINE DELAY. THIS CAN BE FOUND IN THE DIGITAL TIMING SPECIFICATION SECTION OF THE DATA SHEET.

A FALLING EDGE OF HSYNC INTO THE ENCODER GENERATES A SYNC FALLING EDGE ON THE OUTPUT AFTER A TIME EQUAL TO THE PIPELINE DELAY.

Figure 14. ED-SDR, 16-/20-Bit, 4:2:2 YCrCb (HSYNC/VSYNC) Input Timing Diagram




a = 32 CLKCYCLES FOR 525p  
a = 24 CLKCYCLES FOR 625p  
AS RECOMMENDED BY STANDARD

b(MIN) = 244 CLKCYCLES FOR 525p  
b(MIN) = 264 CLKCYCLES FOR 625p

c = PIPELINE DELAY. PLEASE REFER TO RELEVANT PIPELINE DELAY. THIS CAN BE FOUND IN THE DIGITAL TIMING SPECIFICATION SECTION OF THE DATA SHEET.

A FALLING EDGE OF  $\overline{\text{HSYNC}}$  INTO THE ENCODER GENERATES A SYNC FALLING EDGE ON THE OUTPUT AFTER A TIME EQUAL TO THE PIPELINE DELAY.

Figure 15. ED-DDR, 8-/10-Bit, 4:2:2 YCrCb ( $\overline{\text{HSYNC}}$ / $\overline{\text{VSYNC}}$ ) Input Timing Diagram




a AND b AS PER RELEVANT STANDARD.

c = PIPELINE DELAY. PLEASE REFER TO RELEVANT PIPELINE DELAY. THIS CAN BE FOUND IN THE DIGITAL TIMING SPECIFICATION SECTION OF THE DATA SHEET.

A FALLING EDGE OF  $\overline{\text{HSYNC}}$  INTO THE ENCODER GENERATES A FALLING EDGE OF TRI-LEVEL SYNC ON THE OUTPUT AFTER A TIME EQUAL TO THE PIPELINE DELAY.

Figure 16. HD-SDR, 16-/20-Bit, 4:2:2 YCrCb ( $\overline{\text{HSYNC}}$ / $\overline{\text{VSYNC}}$ ) Input Timing Diagram

# ADV7340/ADV7341




a AND b AS PER RELEVANT STANDARD.

c = PIPELINE DELAY. PLEASE REFER TO RELEVANT PIPELINE DELAY. THIS CAN BE FOUND IN THE DIGITAL TIMING SPECIFICATION SECTION OF THE DATA SHEET.

A FALLING EDGE OF  $\overline{\text{HSYNC}}$  INTO THE ENCODER GENERATES A FALLING EDGE OF TRI-LEVEL SYNC ON THE OUTPUT AFTER A TIME EQUAL TO THE PIPELINE DELAY.

Figure 17. HD-DDR, 8-/10-Bit, 4:2:2 YCrCb ( $\overline{\text{HSYNC}}/\overline{\text{VSYNC}}$ ) Input Timing Diagram



\*SELECTED BY SUBADDRESS 0x01, BIT 7.

PAL = 264 CLOCK CYCLES  
NTSC = 244 CLOCK CYCLES

Figure 18. SD Input Timing Diagram (Timing Mode 1)






Figure 19. MPU Port Timing Diagram (I<sup>2</sup>C Mode)




Figure 20. MPU Port Timing Diagram (SPI Mode)

# ADV7340/ADV7341

## ABSOLUTE MAXIMUM RATINGS

Table 11.

| Parameter <sup>1</sup>                      | Rating                               |
|---|--------------------------------------|
| V <sub>AA</sub> to AGND                     | –0.3 V to +3.9 V                     |
| V <sub>DD</sub> to DGND                     | –0.3 V to +2.3 V                     |
| PV <sub>DD</sub> to PGND                    | –0.3 V to +2.3 V                     |
| V <sub>DD_IO</sub> to GND_IO                | –0.3 V to +3.9 V                     |
| V <sub>AA</sub> to V <sub>DD</sub>          | –0.3 V to +2.2 V                     |
| V <sub>DD</sub> to PV <sub>DD</sub>         | –0.3 V to +0.3 V                     |
| V <sub>DD_IO</sub> to V <sub>DD</sub>       | –0.3 V to +2.2 V                     |
| AGND to DGND                                | –0.3 V to +0.3 V                     |
| AGND to PGND                                | –0.3 V to +0.3 V                     |
| AGND to GND_IO                              | –0.3 V to +0.3 V                     |
| DGND to PGND                                | –0.3 V to +0.3 V                     |
| DGND to GND_IO                              | –0.3 V to +0.3 V                     |
| PGND to GND_IO                              | –0.3 V to +0.3 V                     |
| Digital Input Voltage to GND_IO             | –0.3 V to V <sub>DD_IO</sub> + 0.3 V |
| Analog Outputs to AGND                      | –0.3 V to V <sub>AA</sub>            |
| Storage Temperature Range (T <sub>s</sub> ) | –65°C to +150°C                      |
| Junction Temperature (T <sub>j</sub> )      | 150°C                                |
| Lead Temperature (Soldering, 10 sec)        | 260°C                                |

<sup>1</sup> Analog output short circuit to any power supply or common can be of an indefinite duration.

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

The ADV7340/ADV7341 are high performance integrated circuits with an ESD rating of <1 kV, and it is ESD sensitive. Proper precautions should be taken for handling and assembly.

## THERMAL RESISTANCE

θ<sub>JA</sub> is specified for the worst-case conditions, that is, a device soldered in a circuit board for surface-mount packages.

Table 12. Thermal Resistance<sup>1</sup>


| Package Type | θ <sub>JA</sub> | θ <sub>JC</sub> | Unit |
|--------------|-----------------|-----------------|------|
| 64-Lead LQFP | 47              | 11              | °C/W |

<sup>1</sup> Values are based on a JEDEC 4 layer test board.

The ADV7340/ADV7341 are Pb-free products. The lead finish is 100% pure Sn electroplate. The device is RoHS compliant, suitable for Pb-free applications up to 255°C (±5°C) IR reflow (JEDEC STD-20).

Each part is backward-compatible with conventional SnPb soldering processes. The electroplated Sn coating can be soldered with Sn/Pb solder paste at conventional reflow temperatures of 220°C to 235°C.

## ESD CAUTION

|   |   |
|---|---|
|  | <p><b>ESD (electrostatic discharge) sensitive device.</b> Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.</p> |
|---|---|

## PIN CONFIGURATION AND FUNCTION DESCRIPTIONS




Figure 21. Pin Configuration

Table 13. Pin Function Descriptions

| Pin No.               | Mnemonic              | Input/<br>Output | Description   |
|-----------------------|-----------------------|------------------|---|
| 13, 12,<br>9 to 2     | Y9 to Y0              | I                | 10-Bit Pixel Port (Y9 to Y0). Y0 is the LSB. Refer to Table 31 for input modes.   |
| 29 to 25,<br>18 to 14 | C9 to C0              | I                | 10-Bit Pixel Port (C9 to C0). C0 is the LSB. Refer to Table 31 for input modes.   |
| 62 to 58,<br>55 to 51 | S9 to S0              | I                | 10-Bit Pixel Port (S9 to S0). S0 is the LSB. Refer to Table 31 for input modes.   |
| 30                    | CLKIN_A               | I                | Pixel Clock Input for HD Only (74.25 MHz), ED <sup>1</sup> Only (27 MHz or 54 MHz), or SD Only (27 MHz).  |
| 63                    | CLKIN_B               | I                | Pixel Clock Input for Dual Modes Only. Requires a 27 MHz reference clock for ED operation or a 74.25 MHz reference clock for HD operation.  |
| 50                    | $\overline{S\_HSYNC}$ | I/O              | SD Horizontal Synchronization Signal. This pin can also be configured to output an SD, ED, or HD horizontal synchronization signal. See the External Horizontal and Vertical Synchronization Control section.   |
| 49                    | $\overline{S\_VSYNC}$ | I/O              | SD Vertical Synchronization Signal. This pin can also be configured to output an SD, ED, or HD vertical synchronization signal. See the External Horizontal and Vertical Synchronization Control section.   |
| 22                    | $\overline{P\_HSYNC}$ | I                | ED/HD Horizontal Synchronization Signal. See the External Horizontal and Vertical Synchronization Control section.  |
| 23                    | $\overline{P\_VSYNC}$ | I                | ED/HD Vertical Synchronization Signal. See the External Horizontal and Vertical Synchronization Control section.  |
| 24                    | $\overline{P\_BLANK}$ | I                | ED/HD Blanking Signal. See the External Horizontal and Vertical Synchronization Control section.  |
| 48                    | SFL/MISO              | I/O              | Multifunctional Pin: Subcarrier Frequency Lock (SFL) Input/SPI Data Output. The SFL input is used to drive the color subcarrier DDS system, timing reset, or subcarrier reset.  |
| 47                    | RSET1                 | I                | This pin is used to control the amplitudes of the DAC 1, DAC 2, and DAC 3 outputs. For full-drive operation (for example, into a 37.5 $\Omega$ load), a 510 $\Omega$ resistor must be connected from RSET1 to AGND. For low drive operation (for example, into a 300 $\Omega$ load), a 4.12 k $\Omega$ resistor must be connected from RSET1 to AGND. |
| 36                    | RSET2                 | I                | This pin is used to control the amplitudes of the DAC 4, DAC 5, and DAC 6 outputs. A 4.12 k $\Omega$ resistor must be connected from RSET2 to AGND.   |

## ADV7340/ADV7341

| Pin No.    | Mnemonic               | Input/<br>Output | Description  |
|------------|------------------------|------------------|--|
| 45, 35     | COMP1,<br>COMP2        | O                | Compensation Pins. Connect a 2.2 nF capacitor from both COMP pins to V <sub>AA</sub> .   |
| 44, 43, 42 | DAC 1, DAC 2,<br>DAC 3 | O                | DAC Outputs. Full and low drive capable DACs.  |
| 39, 38, 37 | DAC 4, DAC 5,<br>DAC 6 | O                | DAC Outputs. Low drive only capable DACs.  |
| 21         | SCL/MOSI               | I                | Multifunctional Pin: I <sup>2</sup> C Clock Input/SPI Data Input.  |
| 20         | SDA/SCLK               | I/O              | Multifunctional Pin: I <sup>2</sup> C Data Input/Output. Also, SPI clock input.  |
| 19         | ALSB/SPI_SS            | I                | Multifunctional Pin: This signal sets up the LSB <sup>2</sup> of the MPU I <sup>2</sup> C address. Also, SPI slave select.   |
| 46         | V <sub>REF</sub>       |                  | Optional External Voltage Reference Input for DACs or Voltage Reference Output.  |
| 41         | V <sub>AA</sub>        | P                | Analog Power Supply (3.3 V).   |
| 10, 56     | V <sub>DD</sub>        | P                | Digital Power Supply (1.8 V). For dual-supply configurations, V <sub>DD</sub> can be connected to other 1.8 V supplies through a ferrite bead or suitable filtering. |
| 1          | V <sub>DD_IO</sub>     | P                | Input/Output Digital Power Supply (3.3 V).   |
| 34         | PV <sub>DD</sub>       | P                | PLL Power Supply (1.8 V). For dual-supply configurations, PV <sub>DD</sub> can be connected to other 1.8 V supplies through a ferrite bead or suitable filtering.    |
| 33         | EXT_LF1                | I                | External Loop Filter for On-Chip PLL 1.  |
| 31         | EXT_LF2                | I                | External Loop Filter for On-Chip PLL 2.  |
| 32         | PGND                   | G                | PLL Ground Pin.  |
| 40         | AGND                   | G                | Analog Ground Pin.   |
| 11, 57     | DGND                   | G                | Digital Ground Pin.  |
| 64         | GND_IO                 | G                | Input/Output Supply Ground Pin.  |

<sup>1</sup> ED = enhanced definition = 525p and 625p.

<sup>2</sup> LSB = least significant bit. In the ADV7340, setting the LSB to 0 sets the I<sup>2</sup>C address to 0xD4. Setting it to 1 sets the I<sup>2</sup>C address to 0xD6. In the ADV7341, setting the LSB to 0 sets the I<sup>2</sup>C address to 0x54. Setting it to 1 sets the I<sup>2</sup>C address to 0x56.

## TYPICAL PERFORMANCE CHARACTERISTICS




Figure 22. ED 8x Oversampling, Pr/Pb Filter (Linear) Response




Figure 25. ED 8x Oversampling, Y Filter Response (Focus on Pass Band)




Figure 23. ED 8x Oversampling, Pr/Pb Filter (SSAF) Response




Figure 26. HD 4x Oversampling, Pr/Pb (SSAF) Filter Response (4:2:2 Input)




Figure 24. ED 8x Oversampling, Y Filter Response




Figure 27. HD 4x Oversampling, Pr/Pb (SSAF) Filter Response (4:4:4 Input)

# ADV7340/ADV7341




Figure 28. HD 4x Oversampling, Y Filter Response




Figure 31. SD PAL, Luma Low-Pass Filter Response




Figure 29. HD 4x Oversampling, Y Filter Response (Focus on Pass Band)




Figure 32. SD NTSC, Luma Notch Filter Response




Figure 30. SD NTSC, Luma Low-Pass Filter Response




Figure 33. SD PAL, Luma Notch Filter Response




Figure 34. SD, 16x Oversampling, Y Filter Response




Figure 37. SD Luma SSAF Filter, Programmable Gain




Figure 35. SD Luma SSAF Filter Response up to 12 MHz




Figure 38. SD Luma SSAF Filter, Programmable Attenuation




Figure 36. SD Luma SSAF Filter, Programmable Responses




Figure 39. SD Luma CIF Low-Pass Filter Response

# ADV7340/ADV7341




Figure 40. SD Luma QCIF Low-Pass Filter Response




Figure 43. SD Chroma 1.3 MHz Low-Pass Filter Response




Figure 41. SD Chroma 3.0 MHz Low-Pass Filter Response




Figure 44. SD Chroma 1.0 MHz Low-Pass Filter Response




Figure 42. SD Chroma 2.0 MHz Low-Pass Filter Response




Figure 45. SD Chroma 0.65 MHz Low-Pass Filter Response






Figure 46. SD Chroma CIF Low-Pass Filter Response




Figure 47. SD Chroma QCIF Low-Pass Filter Response

# ADV7340/ADV7341

## MPU PORT DESCRIPTION

Devices such as a microprocessor can communicate with the ADV7340/ADV7341 through one of the following protocols:

- 2-wire serial (I<sup>2</sup>C-compatible) bus
- 4-wire serial (SPI-compatible) bus

After power-up or reset, the MPU port is configured for I<sup>2</sup>C operation. SPI operation can be invoked at any time by following the procedure outlined in the SPI Operation section.

### I<sup>2</sup>C OPERATION

The ADV7340/ADV7341 support a 2-wire serial (I<sup>2</sup>C-compatible) microprocessor bus driving multiple peripherals. This port operates in an open-drain configuration. Two inputs, serial data (SDA) and serial clock (SCL), carry information between any device connected to the bus and the ADV7340/ADV7341. Each slave device is recognized by a unique address. The ADV7340/ADV7341 have four possible slave addresses for both read and write operations. These are unique addresses for each device and are illustrated in Figure 48. The LSB either sets a read or write operation. Logic 1 corresponds to a read operation, while Logic 0 corresponds to a write operation. A1 is controlled by setting the ALSB/SPI\_SS pin of the ADV7340/ADV7341 to Logic 0 or Logic 1.




Figure 48. ADV7340 Slave Address = 0xD4 or 0xD6

To control the various devices on the bus, use the following protocol. The master initiates a data transfer by establishing a start condition, defined by a high-to-low transition on SDA while SCL remains high. This indicates that an address/data stream follows. All peripherals respond to the start condition and shift the next eight bits (7-bit address + R/W bit). The bits are transferred from MSB down to LSB. The peripheral that recognizes the transmitted address responds by pulling the data

line low during the ninth clock pulse. This is known as an acknowledge bit. All other devices withdraw from the bus at this point and maintain an idle condition. The idle condition occurs when the device monitors the SDA and SCL lines waiting for the start condition and the correct transmitted address. The R/W bit determines the direction of the data.

Logic 0 on the LSB of the first byte means that the master writes information to the peripheral. Logic 1 on the LSB of the first byte means that the master reads information from the peripheral.

The ADV7340/ADV7341 act as a standard slave device on the bus. The data on the SDA pin is eight bits long, supporting the 7-bit addresses plus the R/W bit. It interprets the first byte as the device address and the second byte as the starting subaddress. There is a subaddress auto-increment facility. This allows data to be written to or read from registers in ascending subaddress sequence starting at any valid subaddress. A data transfer is always terminated by a stop condition. The user can also access any unique subaddress register on a one-by-one basis without updating all the registers.

Stop and start conditions can be detected at any stage during the data transfer. If these conditions are asserted out of sequence with normal read and write operations, they cause an immediate jump to the idle condition. During a given SCL high period, the user should issue only a start condition, a stop condition, or a stop condition followed by a start condition. If an invalid subaddress is issued by the user, the ADV7340/ADV7341 do not issue an acknowledge and do return to the idle condition. If the user utilizes the auto-increment method of addressing the encoder and exceeds the highest subaddress, the following actions are taken:

- In read mode, the highest subaddress register contents are output until the master device issues a no acknowledge. This indicates the end of a read. A no acknowledge condition occurs when the SDA line is not pulled low on the ninth pulse.
- In write mode, the data for the invalid byte is not loaded into any subaddress register, a no acknowledge is issued by the ADV7340/ADV7341, and the parts return to the idle condition.

Figure 49 shows an example of data transfer for a write sequence and the start and stop conditions. Figure 50 shows bus write and read sequences.




Figure 49. I²C Data Transfer




Figure 50. I²C Read and Write Sequence

## SPI OPERATION

The ADV7340/ADV7341 support a 4-wire serial (SPI-compatible) bus connecting multiple peripherals. Two inputs, master out slave in (MOSI) and serial clock (SCLK), and one output, master in slave out (MISO), carry information between a master SPI peripheral on the bus and the ADV7340/ADV7341. Each slave device on the bus has a slave select pin that is connected to the master SPI peripheral by a unique slave select line. As such, slave device addressing is not required.

To invoke SPI operation, a master SPI peripheral (for example, a microprocessor) should issue three low pulses on the ADV7340/ADV7341 ALSB/SPI\_SS pin. When the encoder detects the third rising edge on the ALSB/SPI\_SS pin, it automatically switches to SPI communication mode. The ADV7340/ADV7341 remain in SPI communication mode until a reset or power-down occurs.

To control the ADV7340/ADV7341, use the following protocol for both read and write transactions. First, the master initiates a data transfer by driving and holding the ADV7340/ADV7341 ALSB/SPI\_SS pin low. On the first SCLK rising edge after ALSB/SPI\_SS has been driven low, the write command, defined as 0xD4, is written to the ADV7340/ADV7341 over the MOSI line. The second byte written to the MOSI line is interpreted as the starting subaddress. Data on the MOSI line is written MSB first and clocked on the rising edge of SCLK.

There is a subaddress auto-increment facility. This allows data to be written to or read from registers in ascending subaddress sequence starting at any valid subaddress. The user can also access any unique subaddress register on a one-by-one basis.

In a write data transfer, 8-bit data bytes are written to the ADV7340/ADV7341, MSB first, on the MOSI line immediately after the starting subaddress. The data bytes are clocked into the ADV7340/ADV7341 on the rising edge of SCLK. When all data bytes have been written, the master completes the transfer by driving and holding the ADV7340/ADV7341 ALSB/SPI\_SS pin high.

In a read data transfer, after the subaddress has been clocked in on the MOSI line, the ALSB/SPI\_SS pin is driven and held high for at least one clock cycle. Then, the ALSB/SPI\_SS pin is driven and held low again. On the first SCLK rising edge after ALSB/SPI\_SS has been driven low, the read command, defined as 0xD5, is written, MSB first, to the ADV7340/ADV7341 over the MOSI line. Subsequently, 8-bit data bytes are read from the ADV7340/ADV7341, MSB first, on the MISO line. The data bytes are clocked out of the ADV7340/ADV7341 on the falling edge of SCLK. When all data bytes have been read, the master completes the transfer by driving and holding the ADV7340/ADV7341 ALSB/SPI\_SS pin high.

# ADV7340/ADV7341

## REGISTER MAP ACCESS

A microprocessor can read from or write to all registers of the ADV7340/ADV7341 via the MPU port, except for registers that are specified as read-only or write-only registers.

The subaddress register determines which register the next read or write operation accesses. All communication through the MPU port starts with an access to the subaddress register. A read/write operation is then performed from/to the target address, which increments to the next address until the transaction is complete.

## REGISTER PROGRAMMING

Table 14 to Table 28 describe the functionality of each register. All registers can be read from as well as written to, unless otherwise stated.

### SUBADDRESS REGISTER (SR7 TO SR0)

The subaddress register is an 8-bit write-only register. After the MPU port is accessed and a read/write operation is selected, the subaddress is set up. The subaddress register determines to or from which register the operation takes place.

Table 14. Register 0x00

| SR7 to SR0 | Register            | Bit Description   | Bit Number |   |   |   |   |   |   |   | Register Setting | Reset Value |
|------------|---------------------|---|------------|---|---|---|---|---|---|---|------------------|-------------|
|            |                     |   | 7          | 6 | 5 | 4 | 3 | 2 | 1 | 0 |                  |             |
| 0x00       | Power Mode Register | Sleep Mode. With this control enabled, the current consumption is reduced to $\mu$ A level. All DACs and the internal PLL circuit are disabled. I <sup>2</sup> C registers can be read from and written to in sleep mode.<br><br>PLL and Oversampling Control. This control allows the internal PLL circuit to be powered down and the oversampling to be switched off.<br>DAC 3: Power on/off.<br><br>DAC 2: Power on/off.<br><br>DAC 1: Power on/off.<br><br>DAC 6: Power on/off.<br><br>DAC 5: Power on/off.<br><br>DAC 4: Power on/off. |            |   |   |   |   |   |   | 0 | Sleep mode off.  | 0x12        |
|            |                     |   |            |   |   |   |   |   |   | 1 | Sleep mode on.   |             |
|            |                     |   |            |   |   |   |   |   | 0 |   | PLL on.          |             |
|            |                     |   |            |   |   |   |   |   | 1 |   | PLL off.         |             |
|            |                     |   |            |   |   |   |   | 0 |   |   | DAC 3 off.       |             |
|            |                     |   |            |   |   |   |   | 1 |   |   | DAC 3 on.        |             |
|            |                     |   |            |   |   |   | 0 |   |   |   | DAC 2 off.       |             |
|            |                     |   |            |   |   |   | 1 |   |   |   | DAC 2 on.        |             |
|            |                     |   |            |   |   | 0 |   |   |   |   | DAC 1 off.       |             |
|            |                     |   |            |   |   | 1 |   |   |   |   | DAC 1 on.        |             |
|            |                     |   |            |   | 0 |   |   |   |   |   | DAC 6 off.       |             |
|            |                     |   |            |   | 1 |   |   |   |   |   | DAC 6 on.        |             |
|            |                     |   |            | 0 |   |   |   |   |   |   | DAC 5 off.       |             |
|            |                     |   |            | 1 |   |   |   |   |   |   | DAC 5 on.        |             |
|            |                     |   | 0          |   |   |   |   |   |   |   | DAC 4 off.       |             |
|            |                     |   | 1          |   |   |   |   |   |   |   | DAC 4 on.        |             |

Table 15. Register 0x01 to Register 0x09

| SR7 to<br>SR0 | Register                | Bit Description   | Bit Number |   |   |   |   |   |   | Register Setting   | Reset<br>Value |
|---------------|-------------------------|---|------------|---|---|---|---|---|---|--|----------------|
|               |                         |   | 7          | 6 | 5 | 4 | 3 | 2 | 1 | 0  |                |
| 0x01          | Mode Select<br>Register | Reserved.   |            |   |   |   |   |   |   | 0  | 0x00           |
|               |                         | DDR Clock Edge Alignment.<br>Note: Only used for ED <sup>1</sup> and<br>HD DDR modes. |            |   |   |   |   | 0 | 0 | Chroma clocked in on rising clock edge;<br>luma clocked in on falling clock edge.<br>Reserved.<br>Reserved.<br>Luma clocked in on rising clock edge;<br>chroma clocked in on falling clock edge. |                |
|               |                         |   |            |   |   |   |   | 0 | 1 |  |                |
|               |                         |   |            |   |   |   |   | 1 | 0 |  |                |
|               |                         |   |            |   |   |   |   | 1 | 1 |  |                |
|               |                         | Reserved.   |            |   |   |   | 0 |   |   |  |                |
|               |                         | Input Mode.<br>Note: See Reg. 0x30, Bits[7:3]<br>for ED/HD format selection.          |            | 0 | 0 | 0 |   |   |   |  |                |
| 0x02          | Mode<br>Register 0      |   |            | 0 | 0 | 1 |   |   |   |  | 0x20           |
|               |                         |   |            | 0 | 1 | 0 |   |   |   |  |                |
|               |                         |   |            | 0 | 1 | 1 |   |   |   |  |                |
|               |                         |   |            | 1 | 0 | 0 |   |   |   |  |                |
|               |                         |   |            | 1 | 0 | 1 |   |   |   |  |                |
|               |                         |   |            | 1 | 1 | 0 |   |   |   |  |                |
|               |                         |   |            | 1 | 1 | 1 |   |   |   |  |                |
| 0x03          | ED/HD CSC<br>Matrix 0   | Y/C/S Bus Swap.   | 0          |   |   |   |   |   |   |  | 0x03           |
|               |                         |   | 1          |   |   |   |   |   |   |  |                |
|               |                         | Reserved.   |            |   |   |   |   |   | 0 | 0  |                |
|               |                         | Test Pattern Black Bar. <sup>2</sup>  |            |   |   |   |   | 0 |   |  |                |
|               |                         |   |            |   |   |   |   | 1 |   |  |                |
|               |                         | Manual CSC Matrix Adjust.   |            |   |   |   | 0 |   |   |  |                |
|               |                         |   |            |   |   |   | 1 |   |   |  |                |
| 0x04          | ED/HD CSC<br>Matrix 1   | Sync on RGB.  |            |   |   | 0 |   |   |   |  | 0xF0           |
|               |                         |   |            |   |   | 1 |   |   |   |  |                |
|               |                         | RGB/YPrPb Output Select.  |            |   | 0 |   |   |   |   |  |                |
|               |                         |   |            |   | 1 |   |   |   |   |  |                |
|               |                         | SD Sync Output Enable.  |            | 0 |   |   |   |   |   |  |                |
|               |                         |   |            | 1 |   |   |   |   |   |  |                |
|               |                         | ED/HD Sync Output Enable.   | 0          |   |   |   |   |   |   |  |                |
| 0x05          | ED/HD CSC<br>Matrix 2   |   | 1          |   |   |   |   |   |   |  | 0x4E           |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
| 0x06          | ED/HD CSC<br>Matrix 3   |   |            |   |   |   |   |   |   |  | 0x0E           |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
| 0x07          | ED/HD CSC<br>Matrix 4   |   |            |   |   |   |   |   |   |  | 0x24           |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
| 0x08          | ED/HD CSC<br>Matrix 5   |   |            |   |   |   |   |   |   |  | 0x92           |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
| 0x09          | ED/HD CSC<br>Matrix 6   |   |            |   |   |   |   |   |   |  | 0x7C           |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |
|               |                         |   |            |   |   |   |   |   |   |  |                |

<sup>1</sup> ED = enhanced definition = 525p and 625p.<sup>2</sup> Subaddress 0x31, Bit 2 must also be enabled (ED/HD). Subaddress 0x84, Bit 6 must also be enabled (SD).

# ADV7340/ADV7341

Table 16. Register 0x0A to Register 0x10

| SR7 to<br>SR0 | Register                             | Bit Description                         | Bit Number |     |     |     |     |     |     |     | Register Setting               | Reset<br>Value |
|---------------|--------------------------------------|---|------------|-----|-----|-----|-----|-----|-----|-----|--------------------------------|----------------|
|               |                                      |   | 7          | 6   | 5   | 4   | 3   | 2   | 1   | 0   |                                |                |
| 0x0A          | DAC 4, DAC 5, DAC 6<br>Output Levels | Positive Gain to<br>DAC Output Voltage. | 0          | 0   | 0   | 0   | 0   | 0   | 0   | 0   | 0%                             | 0x00           |
|               |                                      |   | 0          | 0   | 0   | 0   | 0   | 0   | 0   | 1   | +0.018%                        |                |
|               |                                      |   | 0          | 0   | 0   | 0   | 0   | 0   | 1   | 0   | +0.036%                        |                |
|               |                                      |   | ...        | ... | ... | ... | ... | ... | ... | ... | ...                            |                |
|               |                                      |   | 0          | 0   | 1   | 1   | 1   | 1   | 1   | 1   | +7.382%                        |                |
|               |                                      |   | 0          | 1   | 0   | 0   | 0   | 0   | 0   | 0   | +7.5%                          |                |
|               |                                      | Negative Gain to<br>DAC Output Voltage. | 1          | 1   | 0   | 0   | 0   | 0   | 0   | 0   | −7.5%                          |                |
|               |                                      |   | 1          | 1   | 0   | 0   | 0   | 0   | 0   | 1   | −7.382%                        |                |
|               |                                      |   | 1          | 0   | 0   | 0   | 0   | 0   | 1   | 0   | −7.364%                        |                |
|               |                                      |   | ...        | ... | ... | ... | ... | ... | ... | ... | ...                            |                |
|               |                                      |   | 1          | 1   | 1   | 1   | 1   | 1   | 1   | 1   | −0.018%                        |                |
| 0x0B          | DAC 1, DAC 2, DAC 3<br>Output Levels | Positive Gain to<br>DAC Output Voltage. | 0          | 0   | 0   | 0   | 0   | 0   | 0   | 0   | 0%                             | 0x00           |
|               |                                      |   | 0          | 0   | 0   | 0   | 0   | 0   | 0   | 1   | +0.018%                        |                |
|               |                                      |   | 0          | 0   | 0   | 0   | 0   | 0   | 1   | 0   | +0.036%                        |                |
|               |                                      |   | ...        | ... | ... | ... | ... | ... | ... | ... | ...                            |                |
|               |                                      |   | 0          | 0   | 1   | 1   | 1   | 1   | 1   | 1   | +7.382%                        |                |
|               |                                      |   | 0          | 1   | 0   | 0   | 0   | 0   | 0   | 0   | +7.5%                          |                |
|               |                                      | Negative Gain to<br>DAC Output Voltage. | 1          | 1   | 0   | 0   | 0   | 0   | 0   | 0   | −7.5%                          |                |
|               |                                      |   | 1          | 1   | 0   | 0   | 0   | 0   | 0   | 1   | −7.382%                        |                |
|               |                                      |   | 1          | 0   | 0   | 0   | 0   | 0   | 1   | 0   | −7.364%                        |                |
|               |                                      |   | ...        | ... | ... | ... | ... | ... | ... | ... | ...                            |                |
|               |                                      |   | 1          | 1   | 1   | 1   | 1   | 1   | 1   | 1   | −0.018%                        |                |
| 0x0D          | DAC Power Mode                       | DAC 1 Low Power Enable.                 |            |     |     |     |     |     |     | 0   | DAC 1 low power disabled       | 0x00           |
|               |                                      |   |            |     |     |     |     |     |     | 1   | DAC 1 low power enabled        |                |
|               |                                      | DAC 2 Low Power Enable.                 |            |     |     |     |     |     | 0   |     | DAC 2 low power disabled       |                |
|               |                                      |   |            |     |     |     |     |     | 1   |     | DAC 2 low power enabled        |                |
|               |                                      | DAC 3 Low Power Enable.                 |            |     |     |     |     | 0   |     |     | DAC 3 low power disabled       |                |
| 0x10          | Cable Detection                      |   |            |     |     |     |     | 1   |     |     | DAC 3 low power enabled        |                |
|               |                                      | Reserved.                               | 0          | 0   | 0   | 0   | 0   |     |     |     |                                |                |
|               |                                      | DAC 1 Cable Detect<br>(Read Only).      |            |     |     |     |     |     |     | 0   | Cable detected on DAC 1        | 0x00           |
|               |                                      |   |            |     |     |     |     |     |     | 1   | DAC 1 unconnected              |                |
|               |                                      | DAC 2 Cable Detect<br>(Read Only).      |            |     |     |     |     |     | 0   |     | Cable detected on DAC 2        |                |
| 0x10          | Cable Detection                      |   |            |     |     |     |     |     | 1   |     | DAC 2 unconnected              |                |
|               |                                      | Reserved.                               |            |     |     |     | 0   | 0   |     |     |                                |                |
|               |                                      | Unconnected DAC<br>Auto Power-Down.     |            |     |     | 0   |     |     |     |     | DAC auto power-down<br>disable |                |
|               |                                      |   |            |     |     | 1   |     |     |     |     | DAC auto power-down<br>enable  |                |
|               |                                      | Reserved.                               | 0          | 0   | 0   |     |     |     |     |     |                                |                |

Table 17. Register 0x12 to Register 0x17

| SR7 to<br>SR0 | Register                                   | Bit Description  | Bit Number |   |   |   |   |   |        |   | Register Setting  | Reset Value |
|---------------|--|--|------------|---|---|---|---|---|--------|---|---|-------------|
|               |  |  | 7          | 6 | 5 | 4 | 3 | 2 | 1      | 0 |   |             |
| 0x12          | Pixel Port Readback (S Bus MSBs)           | S[9:2] Readback.   | x          | x | x | x | x | x | x      | x | Read only   | 0xXX        |
| 0x13          | Pixel Port Readback (Y Bus MSBs)           | Y[9:2] Readback.   | x          | x | x | x | x | x | x      | x | Read only   | 0xXX        |
| 0x14          | Pixel Port Readback (C Bus MSBs)           | C[9:2] Readback.   | x          | x | x | x | x | x | x      | x | Read only   | 0xXX        |
| 0x15          | Pixel Port Readback (S, Y, and C Bus LSBs) | C[1:0] Readback.<br>Y[1:0] Readback.<br>S[1:0] Readback.<br>Reserved.              | 0          | 0 | x | x | x | x | x      | x | Read only   | 0xXX        |
| 0x16          | Control Port Readback                      | P_BLANK.<br>P_VSYNC.<br>P_HSYNC.<br>S_VSYNC.<br>S_HSYNC.<br>SFL/MISO.<br>Reserved. | 0          | 0 | x | x | x | x | x      | x | Read only   | 0xXX        |
| 0x17          | Software Reset                             | Reserved.  |            |   |   |   |   |   |        | 0 |   | 0x00        |
|               |  | Software Reset.  |            |   |   |   |   |   | 0<br>1 |   | Writing a 1 resets the device;<br>this is a self-clearing bit |             |
|               |  | Reserved.  | 0          | 0 | 0 | 0 | 0 | 0 |        |   |   |             |

# ADV7340/ADV7341

Table 18. Register 0x30

| SR7 to<br>SR0 | Register                 | Bit Description                           | Bit Number  |   |   |   |   |   |   |   | Register Setting  | Note                | Reset<br>Value |
|---------------|--------------------------|---|-------------|---|---|---|---|---|---|---|---|---------------------|----------------|
|               |                          |   | 7           | 6 | 5 | 4 | 3 | 2 | 1 | 0 |   |                     |                |
| 0x30          | ED/HD Mode<br>Register 1 | ED/HD Output<br>Standard.                 |             |   |   |   |   |   | 0 | 0 | EIA770.2 output.<br>EIA770.3 output.                    | ED<br>HD            | 0x00           |
|               |                          |   |             |   |   |   |   |   | 0 | 1 | EIA770.1 output.  |                     |                |
|               |                          |   |             |   |   |   |   |   | 1 | 0 | Output levels for full<br>input range.                  |                     |                |
|               |                          |   |             |   |   |   |   |   | 1 | 1 | Reserved.   |                     |                |
|               |                          | ED/HD Input<br>Synchronization<br>Format. |             |   |   |   |   | 0 |   |   | External HSYNC, VSYNC<br>and field inputs. <sup>1</sup> |                     |                |
|               |                          |   |             |   |   |   |   | 1 |   |   | Embedded EAV/SAV<br>codes.                              |                     |                |
|               |                          | ED/HD Input Mode.                         | 0           | 0 | 0 | 0 | 0 |   |   |   | SMPTE 293M,<br>ITU-BT.1358.                             | 525p @ 59.94 Hz     |                |
|               |                          |   | 0           | 0 | 0 | 0 | 1 |   |   |   | Nonstandard timing mode.                                |                     |                |
|               |                          |   | 0           | 0 | 0 | 1 | 0 |   |   |   | BTA-1004, ITU-BT.1362.                                  | 525p @ 59.94 Hz     |                |
|               |                          |   | 0           | 0 | 0 | 1 | 1 |   |   |   | ITU-BT.1358.  | 625p @ 50 Hz        |                |
|               |                          |   | 0           | 0 | 1 | 0 | 0 |   |   |   | ITU-BT.1362.  | 625p @ 50 Hz        |                |
|               |                          |   | 0           | 0 | 1 | 0 | 1 |   |   |   | SMPTE 296M-1,<br>SMPTE 274M-2.                          | 720p @ 60/59.94 Hz  |                |
|               |                          |   | 0           | 0 | 1 | 1 | 0 |   |   |   | SMPTE 296M-3.   | 720p @ 50 Hz        |                |
|               |                          |   | 0           | 0 | 1 | 1 | 1 |   |   |   | SMPTE 296M-4,<br>SMPTE 274M-5.                          | 720p @ 30/29.97 Hz  |                |
|               |                          |   | 0           | 1 | 0 | 0 | 0 |   |   |   | SMPTE 296M-6.   | 720p @ 25 Hz        |                |
|               |                          |   | 0           | 1 | 0 | 0 | 1 |   |   |   | SMPTE 296M-7,<br>SMPTE 296M-8.                          | 720p @ 24/23.98 Hz  |                |
|               |                          |   | 0           | 1 | 0 | 1 | 0 |   |   |   | SMPTE 240M.   | 1035i @ 60/59.94 Hz |                |
|               |                          |   | 0           | 1 | 0 | 1 | 1 |   |   |   | Reserved.   |                     |                |
|               |                          |   | 0           | 1 | 1 | 0 | 0 |   |   |   | Reserved.   |                     |                |
|               |                          |   | 0           | 1 | 1 | 0 | 1 |   |   |   | SMPTE 274M-4,<br>SMPTE 274M-5.                          | 1080i @ 30/29.97 Hz |                |
|               |                          |   | 0           | 1 | 1 | 1 | 0 |   |   |   | SMPTE 274M-6.   | 1080i @ 25 Hz       |                |
|               |                          |   | 0           | 1 | 1 | 1 | 1 |   |   |   | SMPTE 274M-7,<br>SMPTE 274M-8.                          | 1080p @ 0/29.97 Hz  |                |
|               |                          |   | 1           | 0 | 0 | 0 | 0 |   |   |   | SMPTE 274M-9.   | 1080p @ 25 Hz       |                |
|               |                          |   | 1           | 0 | 0 | 0 | 1 |   |   |   | SMPTE 274M-10,<br>SMPTE 274M-11.                        | 1080p @ 4/23.98 Hz  |                |
|               |                          |   | 1           | 0 | 0 | 1 | 0 |   |   |   | ITU-R BT.709-5.   | 1080Psf @ 24 Hz     |                |
|               |                          |   | 10011–11111 |   |   |   |   |   |   |   | Reserved.   |                     |                |

<sup>1</sup> Synchronization can be controlled with a combination of either  $\overline{\text{HSYNC}}$  and  $\overline{\text{VSYNC}}$  inputs or  $\overline{\text{HSYNC}}$  and field inputs, depending on Subaddress 0x34, Bit 6.



Table 19. Register 0x31 to Register 0x33

| SR7 to<br>SR0                                       | Register                 | Bit Description   | Bit Number |                  |                       |                       |        |                       |                                |                       | Register Setting   | Reset<br>Value |
|---|--------------------------|---|------------|------------------|-----------------------|-----------------------|--------|-----------------------|--------------------------------|-----------------------|--|----------------|
|   |                          |   | 7          | 6                | 5                     | 4                     | 3      | 2                     | 1                              | 0                     |  |                |
| 0x31  | ED/HD Mode<br>Register 2 | ED/HD Pixel Data Valid.                                     |            |                  |                       |                       |        |                       |                                | 0<br>1                | Pixel data valid off.<br>Pixel data valid on.  | 0x00           |
|   |                          | Reserved.   |            |                  |                       |                       |        |                       | 0                              |                       |  |                |
|   |                          | ED/HD Test Pattern Enable.                                  |            |                  |                       |                       |        | 0<br>1                |                                |                       | ED/HD test pattern off.<br>ED/HD test pattern on.  |                |
|   |                          | ED/HD Test Pattern Hatch/Field.                             |            |                  |                       |                       | 0<br>1 |                       |                                |                       | Hatch.<br>Field/frame.   |                |
|   |                          | ED/HD VBI Open.   |            |                  |                       | 0<br>1                |        |                       |                                |                       | Disabled.<br>Enabled.  |                |
|   |                          | ED/HD Undershoot Limiter.                                   |            | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1      |                       |        |                       |                                |                       | Disabled.<br>–11 IRE.<br>–6 IRE.<br>–1.5 IRE.  |                |
|   |                          | ED/HD Sharpness Filter.                                     | 0<br>1     |                  |                       |                       |        |                       |                                |                       | Disabled.<br>Enabled.  |                |
| 0x32  | ED/HD Mode<br>Register 3 | ED/HD Y Delay with Respect to Falling<br>Edge of HSYNC.     |            |                  |                       |                       |        | 0<br>0<br>0<br>0<br>1 | 0<br>0<br>1<br>1<br>0          | 0<br>1<br>0<br>1<br>0 | 0 clock cycles.<br>1 clock cycle.<br>2 clock cycles.<br>3 clock cycles.<br>4 clock cycles. | 0x00           |
|   |                          | ED/HD Color Delay with Respect to<br>Falling Edge of HSYNC. |            |                  | 0<br>0<br>0<br>0<br>1 | 0<br>1<br>1<br>0<br>0 |        |                       |                                |                       | 0 clock cycles.<br>1 clock cycle.<br>2 clock cycles.<br>3 clock cycles.<br>4 clock cycles. |                |
|   |                          | ED/HD CGMS.   |            | 0<br>1           |                       |                       |        |                       |                                |                       | Disabled.<br>Enabled.  |                |
|   |                          | ED/HD CGMS CRC.   | 0<br>1     |                  |                       |                       |        |                       |                                |                       | Disabled.<br>Enabled.  |                |
|   |                          | ED/HD Cr/Cb Sequence.                                       |            |                  |                       |                       |        |                       |                                | 0<br>1                | Cb after falling edge of HSYNC.<br>Cr after falling edge of HSYNC.                         |                |
| Reserved.   |                          |   |            |                  |                       |                       | 0      |                       | 0 must be written to this bit. |                       |  |                |
| ED/HD Input Format.                                 |                          |   |            |                  |                       | 0<br>1                |        |                       | 8-bit input.<br>10-bit input.  |                       |  |                |
| Sinc Compensation Filter on DAC 1, DAC 2,<br>DAC 3. |                          |   |            |                  | 0<br>1                |                       |        |                       | Disabled.<br>Enabled.          |                       |  |                |
| Reserved.   |                          |   |            | 0                |                       |                       |        |                       | 0 must be written to this bit. |                       |  |                |
| ED/HD Chroma SSAF.                                  |                          |   | 0<br>1     |                  |                       |                       |        |                       | Disabled.<br>Enabled.          |                       |  |                |
| ED/HD Chroma Input.                                 |                          | 0<br>1  |            |                  |                       |                       |        |                       | 4:4:4.<br>4:2:2.               |                       |  |                |
|   |                          | ED/HD Double Buffering.                                     | 0<br>1     |                  |                       |                       |        |                       |                                | Disabled.<br>Enabled. |  |                |

# ADV7340/ADV7341

Table 20. Register 0x34 to Register 0x35

| SR7 to<br>SR0 | Register                 | Bit Description                            | Bit Number |        |        |        |        |        |        |        | Register Setting  | Reset<br>Value |
|---------------|--------------------------|--|------------|--------|--------|--------|--------|--------|--------|--------|---|----------------|
|               |                          |  | 7          | 6      | 5      | 4      | 3      | 2      | 1      | 0      |   |                |
| 0x34          | ED/HD Mode<br>Register 5 | ED/HD Timing Reset.                        |            |        |        |        |        |        |        | 0<br>1 | Internal ED/HD timing counters enabled.<br>Resets the internal ED/HD timing counters. | 0x48           |
|               |                          | ED/HD HSYNC Control. <sup>1</sup>          |            |        |        |        |        |        | 0<br>1 |        | HSYNC output control.   |                |
|               |                          | ED/HD VSYNC Control. <sup>1</sup>          |            |        |        |        |        | 0<br>1 |        |        | VSYNC output control.   |                |
|               |                          | ED/HD Blank Polarity.                      |            |        |        |        | 0<br>1 |        |        |        | P_BLANK active high.<br>P_BLANK active low.   |                |
|               |                          | ED Macrovision Enable.                     |            |        |        | 0<br>1 |        |        |        |        | Macrovision disabled.<br>Macrovision enabled.   |                |
|               |                          | Reserved.                                  |            |        | 0      |        |        |        |        |        | 0 must be written to this bit.  |                |
|               |                          | ED/HD VSYNC/Field Input.                   |            | 0<br>1 |        |        |        |        |        |        | 0 = field input.<br>1 = VSYNC input.  |                |
|               |                          | Horizontal/Vertical Counters. <sup>2</sup> | 0<br>1     |        |        |        |        |        |        |        | Update field/line counter.<br>Field/line counter free running.                        |                |
| 0x35          | ED/HD Mode<br>Register 6 | Reserved.                                  |            |        |        |        |        |        |        | 0      |   | 0x00           |
|               |                          | ED/HD RGB Input Enable.                    |            |        |        |        |        |        | 0<br>1 |        | Disabled.<br>Enabled.   |                |
|               |                          | ED/HD Sync on PrPb.                        |            |        |        |        |        | 0<br>1 |        |        | Disabled.<br>Enabled.   |                |
|               |                          | ED/HD Color DAC Swap.                      |            |        |        |        | 0<br>1 |        |        |        | DAC 2 = Pb, DAC 3 = Pr.<br>DAC 2 = Pr, DAC 3 = Pb.                                    |                |
|               |                          | ED/HD Gamma Correction<br>Curve Select.    |            |        |        | 0<br>1 |        |        |        |        | Gamma Correction Curve A.<br>Gamma Correction Curve B.                                |                |
|               |                          | ED/HD Gamma Correction<br>Enable.          |            |        | 0<br>1 |        |        |        |        |        | Disabled.<br>Enabled.   |                |
|               |                          | ED/HD Adaptive Filter Mode.                |            | 0<br>1 |        |        |        |        |        |        | Mode A.<br>Mode B.  |                |
|               |                          | ED/HD Adaptive Filter Enable.              | 0<br>1     |        |        |        |        |        |        |        | Disabled.<br>Enabled.   |                |

<sup>1</sup> Used in conjunction with ED/HD sync in Subaddress 0x02, Bit 7, set to 1.

<sup>2</sup> When set to 0, the horizontal/vertical counters automatically wrap around at the end of the line/field/frame of the selected standard. When set to 1, the horizontal/vertical counters are free running and wrap around when external sync signals indicate to do so.

Table 21. Register 0x36 to Register 0x43

| SR7 to SR0 | Register                    | Bit Description                                | Bit Number                          |                                     |                                     |                                     |                                     |                                     |                                     |                                     | Register Setting   | Reset Value |
|------------|-----------------------------|--|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|--|-------------|
|            |                             |  | 7                                   | 6                                   | 5                                   | 4                                   | 3                                   | 2                                   | 1                                   | 0                                   |  |             |
| 0x36       | ED/HD Y Level <sup>1</sup>  | ED/HD Test Pattern Y Level.                    | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | Y level value  | 0xA0        |
| 0x37       | ED/HD Cr Level <sup>1</sup> | ED/HD Test Pattern Cr Level.                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | Cr level value   | 0x80        |
| 0x38       | ED/HD Cb Level <sup>1</sup> | ED/HD Test Pattern Cb Level.                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | Cb level value   | 0x80        |
| 0x39       | ED/HD Mode Register 7       | Reserved.                                      |                                     |                                     |                                     | 0                                   | 0                                   | 0                                   | 0                                   | 0                                   |  | 0x00        |
|            |                             | ED/HD EIA/CEA-861B Synchronization Compliance. |                                     |                                     | 0<br>1                              |                                     |                                     |                                     |                                     |                                     | Disabled<br>Enabled  |             |
|            |                             | Reserved.                                      | 0                                   | 0                                   |                                     |                                     |                                     |                                     |                                     |                                     |  |             |
| 0x40       | ED/HD Sharpness Filter Gain | ED/HD Sharpness Filter Gain, Value A.          |                                     |                                     |                                     |                                     | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 1<br>0<br>...<br>1<br>0<br>...<br>1 | Gain A = 0<br>Gain A = +1<br>...<br>Gain A = +7<br>Gain A = -8<br>...<br>Gain A = -1 | 0x00        |
|            |                             | ED/HD Sharpness Filter Gain, Value B.          | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>1<br>...<br>1<br>0<br>...<br>1 |                                     |                                     |                                     |                                     | Gain B = 0<br>Gain B = +1<br>...<br>Gain B = +7<br>Gain B = -8<br>...<br>Gain B = -1 |             |
| 0x41       | ED/HD CGMS Data 0           | ED/HD CGMS Data Bits.                          | 0                                   | 0                                   | 0                                   | 0                                   | C19                                 | C18                                 | C17                                 | C16                                 | CGMS C19 to C16  | 0x00        |
| 0x42       | ED/HD CGMS Data 1           | ED/HD CGMS Data Bits.                          | C15                                 | C14                                 | C13                                 | C12                                 | C11                                 | C10                                 | C9                                  | C8                                  | CGMS C15 to C8   | 0x00        |
| 0x43       | ED/HD CGMS Data 2           | ED/HD CGMS Data Bits.                          | C7                                  | C6                                  | C5                                  | C4                                  | C3                                  | C2                                  | C1                                  | C0                                  | CGMS C7 to C0  | 0x00        |

<sup>1</sup> For use with ED/HD internal test patterns only (Subaddress 0x31, Bit 2 = 1).

Table 22. Register 0x44 to Register 0x57

| SR7 to SR0 | Register       | Bit Description                  | Bit Number |   |   |   |   |   |   |   | Register Setting | Reset Value |
|------------|----------------|----------------------------------|------------|---|---|---|---|---|---|---|------------------|-------------|
|            |                |                                  | 7          | 6 | 5 | 4 | 3 | 2 | 1 | 0 |                  |             |
| 0x44       | ED/HD Gamma A0 | ED/HD Gamma Curve A (Point 24).  | x          | x | x | x | x | x | x | x | A0               | 0x00        |
| 0x45       | ED/HD Gamma A1 | ED/HD Gamma Curve A (Point 32).  | x          | x | x | x | x | x | x | x | A1               | 0x00        |
| 0x46       | ED/HD Gamma A2 | ED/HD Gamma Curve A (Point 48).  | x          | x | x | x | x | x | x | x | A2               | 0x00        |
| 0x47       | ED/HD Gamma A3 | ED/HD Gamma Curve A (Point 64).  | x          | x | x | x | x | x | x | x | A3               | 0x00        |
| 0x48       | ED/HD Gamma A4 | ED/HD Gamma Curve A (Point 80).  | x          | x | x | x | x | x | x | x | A4               | 0x00        |
| 0x49       | ED/HD Gamma A5 | ED/HD Gamma Curve A (Point 96).  | x          | x | x | x | x | x | x | x | A5               | 0x00        |
| 0x4A       | ED/HD Gamma A6 | ED/HD Gamma Curve A (Point 128). | x          | x | x | x | x | x | x | x | A6               | 0x00        |
| 0x4B       | ED/HD Gamma A7 | ED/HD Gamma Curve A (Point 160). | x          | x | x | x | x | x | x | x | A7               | 0x00        |
| 0x4C       | ED/HD Gamma A8 | ED/HD Gamma Curve A (Point 192). | x          | x | x | x | x | x | x | x | A8               | 0x00        |
| 0x4D       | ED/HD Gamma A9 | ED/HD Gamma Curve A (Point 224). | x          | x | x | x | x | x | x | x | A9               | 0x00        |
| 0x4E       | ED/HD Gamma B0 | ED/HD Gamma Curve B (Point 24).  | x          | x | x | x | x | x | x | x | B0               | 0x00        |
| 0x4F       | ED/HD Gamma B1 | ED/HD Gamma Curve B (Point 32).  | x          | x | x | x | x | x | x | x | B1               | 0x00        |
| 0x50       | ED/HD Gamma B2 | ED/HD Gamma Curve B (Point 48).  | x          | x | x | x | x | x | x | x | B2               | 0x00        |
| 0x51       | ED/HD Gamma B3 | ED/HD Gamma Curve B (Point 64).  | x          | x | x | x | x | x | x | x | B3               | 0x00        |
| 0x52       | ED/HD Gamma B4 | ED/HD Gamma Curve B (Point 80).  | x          | x | x | x | x | x | x | x | B4               | 0x00        |
| 0x53       | ED/HD Gamma B5 | ED/HD Gamma Curve B (Point 96).  | x          | x | x | x | x | x | x | x | B5               | 0x00        |
| 0x54       | ED/HD Gamma B6 | ED/HD Gamma Curve B (Point 128). | x          | x | x | x | x | x | x | x | B6               | 0x00        |
| 0x55       | ED/HD Gamma B7 | ED/HD Gamma Curve B (Point 160). | x          | x | x | x | x | x | x | x | B7               | 0x00        |
| 0x56       | ED/HD Gamma B8 | ED/HD Gamma Curve B (Point 192). | x          | x | x | x | x | x | x | x | B8               | 0x00        |
| 0x57       | ED/HD Gamma B9 | ED/HD Gamma Curve B (Point 224). | x          | x | x | x | x | x | x | x | B9               | 0x00        |

# ADV7340/ADV7341

Table 23. Register 0x58 to Register 0x5D

| SR7 to<br>SR0 | Register                          | Bit Description                           | Bit Number                          |                                     |                                     |                                     |                                     |                                     |                                     |                                     | Register<br>Setting  | Reset<br>Value |
|---------------|-----------------------------------|---|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|-------------------------------------|--|----------------|
|               |                                   |   | 7                                   | 6                                   | 5                                   | 4                                   | 3                                   | 2                                   | 1                                   | 0                                   |  |                |
| 0x58          | ED/HD Adaptive Filter Gain 1      | ED/HD Adaptive Filter Gain 1,<br>Value A. |                                     |                                     |                                     |                                     | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>1<br>...<br>1<br>0<br>...<br>1 | Gain A = 0<br>Gain A = +1<br>...<br>Gain A = +7<br>Gain A = -8<br>...<br>Gain A = -1 | 0x00           |
|               |                                   | ED/HD Adaptive Filter Gain 1,<br>Value B. | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>1<br>...<br>1<br>0<br>...<br>1 |                                     |                                     |                                     |                                     | Gain B = 0<br>Gain B = +1<br>...<br>Gain B = +7<br>Gain B = -8<br>...<br>Gain B = -1 |                |
| 0x59          | ED/HD Adaptive Filter Gain 2      | ED/HD Adaptive Filter Gain 2,<br>Value A. |                                     |                                     |                                     |                                     | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>1<br>...<br>1<br>0<br>...<br>1 | Gain A = 0<br>Gain A = +1<br>...<br>Gain A = +7<br>Gain A = -8<br>...<br>Gain A = -1 | 0x00           |
|               |                                   | ED/HD Adaptive Filter Gain 2,<br>Value B. | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>1<br>...<br>1<br>0<br>...<br>1 |                                     |                                     |                                     |                                     | Gain B = 0<br>Gain B = +1<br>...<br>Gain B = +7<br>Gain B = -8<br>...<br>Gain B = -1 |                |
| 0x5A          | ED/HD Adaptive Filter Gain 3      | ED/HD Adaptive Filter Gain 3,<br>Value A. |                                     |                                     |                                     |                                     | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>1<br>...<br>1<br>0<br>...<br>1 | Gain A = 0<br>Gain A = +1<br>...<br>Gain A = +7<br>Gain A = -8<br>...<br>Gain A = -1 | 0x00           |
|               |                                   | ED/HD Adaptive Filter Gain 3,<br>Value B. | 0<br>0<br>...<br>0<br>1<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>0<br>...<br>1<br>0<br>...<br>1 | 0<br>1<br>...<br>1<br>0<br>...<br>1 |                                     |                                     |                                     |                                     | Gain B = 0<br>Gain B = +1<br>...<br>Gain B = +7<br>Gain B = -8<br>...<br>Gain B = -1 |                |
| 0x5B          | ED/HD Adaptive Filter Threshold A | ED/HD Adaptive Filter Threshold A.        | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | Threshold A  | 0x00           |
| 0x5C          | ED/HD Adaptive Filter Threshold B | ED/HD Adaptive Filter Threshold B.        | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | Threshold B  | 0x00           |
| 0x5D          | ED/HD Adaptive Filter Threshold C | ED/HD Adaptive Filter Threshold C.        | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | x                                   | Threshold C  | 0x00           |

Table 24. Register 0x5E to Register 0x6E

| SR7 to<br>SR0 | Register                         | Bit Description                   | Bit Number |      |      |      |      |      |        |        | Register<br>Setting | Reset<br>Value |
|---------------|----------------------------------|-----------------------------------|------------|------|------|------|------|------|--------|--------|---------------------|----------------|
|               |                                  |                                   | 7          | 6    | 5    | 4    | 3    | 2    | 1      | 0      |                     |                |
| 0x5E          | ED/HD CGMS Type B<br>Register 0  | ED/HD CGMS Type B<br>Enable.      |            |      |      |      |      |      |        | 0<br>1 | Disabled<br>Enabled | 0x00           |
|               |                                  | ED/HD CGMS Type B<br>CRC Enable.  |            |      |      |      |      |      | 0<br>1 |        | Disabled<br>Enabled |                |
|               |                                  | ED/HD CGMS Type B<br>Header Bits. | H5         | H4   | H3   | H2   | H1   | H0   |        |        | H5 to H0            |                |
| 0x5F          | ED/HD CGMS Type B<br>Register 1  | ED/HD CGMS Type B<br>Data Bits.   | P7         | P6   | P5   | P4   | P3   | P2   | P1     | P0     | P7 to P0            | 0x00           |
| 0x60          | ED/HD CGMS Type B<br>Register 2  | ED/HD CGMS Type B<br>Data Bits.   | P15        | P14  | P13  | P12  | P11  | P10  | P9     | P8     | P15 to P8           | 0x00           |
| 0x61          | ED/HD CGMS Type B<br>Register 3  | ED/HD CGMS Type B<br>Data Bits.   | P23        | P22  | P21  | P20  | P19  | P18  | P17    | P16    | P23 to P16          | 0x00           |
| 0x62          | ED/HD CGMS Type B<br>Register 4  | ED/HD CGMS Type B<br>Data Bits.   | P31        | P30  | P29  | P28  | P27  | P26  | P25    | P24    | P31 to P24          | 0x00           |
| 0x63          | ED/HD CGMS Type B<br>Register 5  | ED/HD CGMS Type B<br>Data Bits.   | P39        | P38  | P37  | P36  | P35  | P34  | P33    | P32    | P39 to P32          | 0x00           |
| 0x64          | ED/HD CGMS Type B<br>Register 6  | ED/HD CGMS Type B<br>Data Bits.   | P47        | P46  | P45  | P44  | P43  | P42  | P41    | P40    | P47 to P40          | 0x00           |
| 0x65          | ED/HD CGMS Type B<br>Register 7  | ED/HD CGMS Type B<br>Data Bits.   | P55        | P54  | P53  | P52  | P51  | P50  | P49    | P48    | P55 to P48          | 0x00           |
| 0x66          | ED/HD CGMS Type B<br>Register 8  | ED/HD CGMS Type B<br>Data Bits.   | P63        | P62  | P61  | P60  | P59  | P58  | P57    | P56    | P63 to P56          | 0x00           |
| 0x67          | ED/HD CGMS Type B<br>Register 9  | ED/HD CGMS Type B<br>Data Bits.   | P71        | P70  | P69  | P68  | P67  | P66  | P65    | P64    | P71 to P64          | 0x00           |
| 0x68          | ED/HD CGMS Type B<br>Register 10 | ED/HD CGMS Type B<br>Data Bits.   | P79        | P78  | P77  | P76  | P75  | P74  | P73    | P72    | P79 to P72          | 0x00           |
| 0x69          | ED/HD CGMS Type B<br>Register 11 | ED/HD CGMS Type B<br>Data Bits.   | P87        | P86  | P85  | P84  | P83  | P82  | P81    | P80    | P87 to P80          | 0x00           |
| 0x6A          | ED/HD CGMS Type B<br>Register 12 | ED/HD CGMS Type B<br>Data Bits.   | P95        | P94  | P93  | P92  | P91  | P90  | P89    | P88    | P95 to P88          | 0x00           |
| 0x6B          | ED/HD CGMS Type B<br>Register 13 | ED/HD CGMS Type B<br>Data Bits.   | P103       | P102 | P101 | P100 | P99  | P98  | P97    | P96    | P103 to P96         | 0x00           |
| 0x6C          | ED/HD CGMS Type B<br>Register 14 | ED/HD CGMS Type B<br>Data Bits.   | P111       | P110 | P109 | P108 | P107 | P106 | P105   | P104   | P111 to P104        | 0x00           |
| 0x6D          | ED/HD CGMS Type B<br>Register 15 | ED/HD CGMS Type B<br>Data Bits.   | P119       | P118 | P117 | P116 | P115 | P114 | P113   | P112   | P119 to P112        | 0x00           |
| 0x6E          | ED/HD CGMS Type B<br>Register 16 | ED/HD CGMS Type B<br>Data Bits.   | P127       | P126 | P125 | P124 | P123 | P122 | P121   | P120   | P127 to P120        | 0x00           |

# ADV7340/ADV7341

Table 25. Register 0x80 to Register 0x83

| SR7 to<br>SR0 | Register              | Bit Description                        | Bit Number |   |   |   |   |   |   |   | Register Setting  | Reset<br>Value |
|---------------|-----------------------|--|------------|---|---|---|---|---|---|---|---|----------------|
|               |                       |  | 7          | 6 | 5 | 4 | 3 | 2 | 1 | 0 |   |                |
| 0x80          | SD Mode<br>Register 1 | SD Standard.                           |            |   |   |   |   |   | 0 | 0 | NTSC.<br>PAL B/D/G/H/I.<br>PAL M.<br>PAL N.   | 0x10           |
|               |                       | SD Luma Filter.                        |            |   |   | 0 | 0 | 0 |   |   | LPF NTSC.<br>LPF PAL.<br>Notch NTSC.<br>Notch PAL.<br>SSAF luma.<br>Luma CIF.<br>Luma QCIF.<br>Reserved.  |                |
|               |                       | SD Chroma Filter.                      | 0          | 0 | 0 |   |   |   |   |   | 1.3 MHz.<br>0.65 MHz.<br>1.0 MHz.<br>2.0 MHz.<br>Reserved.<br>Chroma CIF.<br>Chroma QCIF.<br>3.0 MHz.   |                |
| 0x82          | SD Mode<br>Register 2 | SD PrPb SSAF.                          |            |   |   |   |   |   | 0 | 1 | Disabled.<br>Enabled.   | 0x0B           |
|               |                       | SD DAC Output 1.                       |            |   |   |   |   |   | 0 | 1 | Refer to Table 32 in the Output<br>Configuration section.   |                |
|               |                       | SD DAC Output 2.                       |            |   |   |   |   | 0 | 1 |   | Refer to Table 32 in the Output<br>Configuration section.   |                |
|               |                       | SD Pedestal.                           |            |   |   |   | 0 | 1 |   |   | Disabled.<br>Enabled.   |                |
|               |                       | SD Square Pixel Mode.                  |            |   |   | 0 | 1 |   |   |   | Disabled.<br>Enabled.   |                |
|               |                       | SD VCR FF/RW Sync.                     |            |   | 0 | 1 |   |   |   |   | Disabled.<br>Enabled.   |                |
|               |                       | SD Pixel Data Valid.                   |            | 0 | 1 |   |   |   |   |   | Disabled.<br>Enabled.   |                |
|               |                       | SD Active Video Edge<br>Control.       | 0          | 1 |   |   |   |   |   |   | Disabled.<br>Enabled.   |                |
| 0x83          | SD Mode<br>Register 3 | SD Pedestal on YPrPb<br>Output.        |            |   |   |   |   |   | 0 | 1 | No pedestal on YPrPb.<br>7.5 IRE pedestal on YPrPb.   | 0x04           |
|               |                       | SD Output Levels Y.                    |            |   |   |   |   |   | 0 | 1 | Y = 700 mV/300 mV.<br>Y = 714 mV/286 mV.  |                |
|               |                       | SD Output Levels PrPb.                 |            |   |   |   | 0 | 0 | 0 | 1 | 700 mV p-p (PAL), 1000 mV p-p (NTSC).<br>700 mV p-p.<br>1000 mV p-p.<br>648 mV p-p.   |                |
|               |                       | SD VBI Open.                           |            |   |   | 0 | 1 |   |   |   | Disabled.<br>Enabled.   |                |
|               |                       | SD Closed Captioning<br>Field Control. |            | 0 | 0 | 0 | 1 |   |   |   | Closed captioning disabled.<br>Closed captioning on odd field only.<br>Closed captioning on even field only.<br>Closed captioning on both fields. |                |
|               |                       | Reserved.                              | 0          |   |   |   |   |   |   |   | Reserved.   |                |

Table 26. Register 0x84 to Register 0x89

| SR7 to<br>SR0 | Register              | Bit Description   | Bit Number |        |        |        |        |                  |                  |                  | Register Setting   | Reset<br>Value |
|---------------|-----------------------|---|------------|--------|--------|--------|--------|------------------|------------------|------------------|--|----------------|
|               |                       |   | 7          | 6      | 5      | 4      | 3      | 2                | 1                | 0                |  |                |
| 0x84          | SD Mode<br>Register 4 | SD VSYNC-3H.  |            |        |        |        |        |                  |                  | 0<br>1           | Disabled.<br>VSYNC = 2.5 lines (PAL),<br>VSYNC = 3 lines (NTSC).   | 0x00           |
|               |                       | SD SFL/SCR/TR Mode Select.  |            |        |        |        |        | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 |                  | Disabled.<br>Subcarrier phase reset mode enabled.<br>Timing reset mode enabled.<br>SFL mode enabled.     |                |
|               |                       | SD Active Video Length.   |            |        |        |        | 0<br>1 |                  |                  |                  | 720 pixels.<br>710 (NTSC), 702 (PAL).  |                |
|               |                       | SD Chroma.  |            |        |        | 0<br>1 |        |                  |                  |                  | Chroma enabled.<br>Chroma disabled.  |                |
|               |                       | SD Burst.   |            |        | 0<br>1 |        |        |                  |                  |                  | Enabled.<br>Disabled.  |                |
|               |                       | SD Color Bars.  |            | 0<br>1 |        |        |        |                  |                  |                  | Disabled.<br>Enabled.  |                |
|               |                       | SD Luma/Chroma Swap.  | 0<br>1     |        |        |        |        |                  |                  |                  | DAC 2 = luma, DAC 3 = chroma.<br>DAC 2 = chroma, DAC 3 = luma.   |                |
| 0x86          | SD Mode<br>Register 5 | NTSC Color Subcarrier Adjust (Delay<br>from the falling edge of output<br>HSYNC pulse to start of color burst). |            |        |        |        |        |                  | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 | 5.17 $\mu$ s.<br>5.31 $\mu$ s.<br>5.59 $\mu$ s (must be set for Macrovision<br>compliance).<br>Reserved. | 0x02           |
|               |                       | Reserved.   |            |        |        |        |        | 0                |                  |                  |  |                |
|               |                       | SD EIA/CEA-861B Synchronization<br>Compliance.  |            |        |        |        | 0<br>1 |                  |                  |                  | Disabled.<br>Enabled.  |                |
|               |                       | Reserved.   |            |        | 0<br>0 |        |        |                  |                  |                  |  |                |
|               |                       | SD Horizontal/Vertical Counter<br>Mode. <sup>1</sup>  |            | 0<br>1 |        |        |        |                  |                  |                  | Update field/line counter.<br>Field/line counter free running.   |                |
|               |                       | SD RGB Color Swap.  | 0<br>1     |        |        |        |        |                  |                  |                  | Normal.<br>Color reversal enabled.   |                |
| 0x87          | SD Mode<br>Register 6 | SD PrPb Scale.  |            |        |        |        |        |                  |                  | 0<br>1           | Disabled.<br>Enabled.  | 0x00           |
|               |                       | SD Y Scale.   |            |        |        |        |        |                  | 0<br>1           |                  | Disabled.<br>Enabled.  |                |
|               |                       | SD Hue Adjust.  |            |        |        |        |        | 0<br>1           |                  |                  | Disabled.<br>Enabled.  |                |
|               |                       | SD Brightness.  |            |        |        |        | 0<br>1 |                  |                  |                  | Disabled.<br>Enabled.  |                |
|               |                       | SD Luma SSAF Gain.  |            |        |        | 0<br>1 |        |                  |                  |                  | Disabled.<br>Enabled.  |                |
|               |                       | SD Input Standard Auto Detect.  |            |        | 0<br>1 |        |        |                  |                  |                  | Disabled.<br>Enabled.  |                |
|               |                       | Reserved.   |            | 0      |        |        |        |                  |                  |                  | 0 must be written to this bit.   |                |
|               |                       | SD RGB Input Enable.  | 0<br>1     |        |        |        |        |                  |                  |                  | SD YCrCb input.<br>SD RGB input.   |                |

# ADV7340/ADV7341

| SR7 to<br>SR0 | Register              | Bit Description                    | Bit Number |   |   |   |   |   |   |   | Register Setting                 | Reset<br>Value |
|---------------|-----------------------|------------------------------------|------------|---|---|---|---|---|---|---|----------------------------------|----------------|
|               |                       |                                    | 7          | 6 | 5 | 4 | 3 | 2 | 1 | 0 |                                  |                |
| 0x88          | SD Mode<br>Register 7 | Reserved.                          |            |   |   |   |   |   |   | 0 |                                  | 0x00           |
|               |                       | SD Noninterlaced Mode.             |            |   |   |   |   |   | 0 |   | Disabled.                        |                |
|               |                       |                                    |            |   |   |   |   |   | 1 |   | Enabled.                         |                |
|               |                       | SD Double Buffering.               |            |   |   |   |   | 0 |   |   | Disabled.                        |                |
|               |                       |                                    |            |   |   |   |   | 1 |   |   | Enabled.                         |                |
|               |                       | SD Input Format.                   |            |   |   | 0 | 0 |   |   |   | 8-bit input.                     |                |
|               |                       |                                    |            |   |   | 0 | 1 |   |   |   | 16-bit input.                    |                |
| 0x89          | SD Mode<br>Register 8 |                                    |            |   |   | 1 | 0 |   |   |   | 10-bit input.                    |                |
|               |                       |                                    |            |   |   | 1 | 1 |   |   |   | 20-bit input.                    |                |
|               |                       | SD Digital Noise Reduction.        |            |   | 0 |   |   |   |   |   | Disabled.                        |                |
|               |                       |                                    |            |   | 1 |   |   |   |   |   | Enabled.                         |                |
|               |                       | SD Gamma Correction Enable.        |            | 0 |   |   |   |   |   |   | Disabled.                        |                |
|               |                       |                                    |            | 1 |   |   |   |   |   |   | Enabled.                         |                |
|               |                       | SD Gamma Correction Curve Select.  | 0          |   |   |   |   |   |   |   | Gamma Correction Curve A.        |                |
| 0x89          | SD Mode<br>Register 8 |                                    | 1          |   |   |   |   |   |   |   | Gamma Correction Curve B.        |                |
|               |                       | SD Undershoot Limiter.             |            |   |   |   |   |   | 0 | 0 | Disabled.                        | 0x00           |
|               |                       |                                    |            |   |   |   |   |   | 0 | 1 | –11 IRE.                         |                |
|               |                       |                                    |            |   |   |   |   |   | 1 | 0 | –6 IRE.                          |                |
|               |                       |                                    |            |   |   |   |   |   | 1 | 1 | –1.5 IRE.                        |                |
|               |                       | Reserved.                          |            |   |   |   |   | 0 |   |   | 0 must be written to this bit.   |                |
| 0x89          | SD Mode<br>Register 8 | SD Black Burst Output on DAC Luma. |            |   |   |   | 0 |   |   |   | Disabled.                        |                |
|               |                       |                                    |            |   |   |   | 1 |   |   |   | Enabled.                         |                |
|               |                       | SD Chroma Delay.                   |            |   | 0 | 0 |   |   |   |   | Disabled.                        |                |
|               |                       |                                    |            |   | 0 | 1 |   |   |   |   | 4 clock cycles.                  |                |
| 0x89          | SD Mode<br>Register 8 |                                    |            |   | 1 | 0 |   |   |   |   | 8 clock cycles.                  |                |
|               |                       |                                    |            |   | 1 | 1 |   |   |   |   | Reserved.                        |                |
|               |                       | Reserved.                          | 0          | 0 |   |   |   |   |   |   | 0 must be written to these bits. |                |

<sup>1</sup> When set to 0, the horizontal/vertical counters automatically wrap around at the end of the line/field/frame of the selected standard. When set to 1, the horizontal/vertical counters are free running and wrap around when external sync signals indicate to do so.



Table 27. Register 0x8A to Register 0x98

| SR7 to<br>SR0 | Register  | Bit Description                                       | Bit Number       |                  |                  |                  |                  |                  |                  |                  | Register Setting  | Reset<br>Value |
|---------------|---|---|------------------|------------------|------------------|------------------|------------------|------------------|------------------|------------------|---|----------------|
|               |   |   | 7                | 6                | 5                | 4                | 3                | 2                | 1                | 0                |   |                |
| 0x8A          | SD Timing Register 0  | SD Slave/Master Mode.                                 |                  |                  |                  |                  |                  |                  |                  | 0<br>1           | Slave mode.<br>Master mode.   | 0x08           |
|               |   | SD Timing Mode.                                       |                  |                  |                  |                  |                  | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 |                  | Mode 0.<br>Mode 1.<br>Mode 2.<br>Mode 3.  |                |
|               |   | Reserved.   |                  |                  |                  |                  | 1                |                  |                  |                  |   |                |
|               |   | SD Luma Delay.  |                  |                  | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 |                  |                  |                  |                  | No delay.<br>2 clock cycles.<br>4 clock cycles.<br>6 clock cycles.  |                |
|               |   | SD Minimum Luma Value.                                |                  | 0<br>1           |                  |                  |                  |                  |                  |                  | −40 IRE.<br>−7.5 IRE.   |                |
|               |   | SD Timing Reset.                                      | x                |                  |                  |                  |                  |                  |                  |                  | A low-high-low transition<br>resets the internal SD timing<br>counters.                                     |                |
| 0x8B          | SD Timing Register 1<br>(Note: Applicable in<br>master modes only,<br>that is, Subaddress<br>0x8A, Bit 0 = 1) | SD HSYNC Width.                                       |                  |                  |                  |                  |                  |                  | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 | $t_a$ = 1 clock cycle.<br>$t_a$ = 4 clock cycles.<br>$t_a$ = 16 clock cycles.<br>$t_a$ = 128 clock cycles.  | 0x00           |
|               |   | SD HSYNC to VSYNC Delay.                              |                  |                  |                  |                  | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 |                  |                  | $t_b$ = 0 clock cycles.<br>$t_b$ = 4 clock cycles.<br>$t_b$ = 8 clock cycles.<br>$t_b$ = 18 clock cycles.   |                |
|               |   | SD HSYNC to VSYNC Rising<br>Edge Delay (Mode 1 Only). |                  |                  | x<br>x           | 0<br>1           |                  |                  |                  |                  | $t_c$ = $t_b$ .<br>$t_c$ = $t_b$ + 32 $\mu$ s.  |                |
|               |   | SD VSYNC Width (Mode 2<br>Only).                      |                  |                  | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 |                  |                  |                  |                  | 1 clock cycle.<br>4 clock cycles.<br>16 clock cycles.<br>128 clock cycles.                                  |                |
|               |   | SD HSYNC to Pixel Data<br>Adjust.                     | 0<br>0<br>1<br>1 | 0<br>1<br>0<br>1 |                  |                  |                  |                  |                  |                  | 0 clock cycles.<br>1 clock cycle.<br>2 clock cycles.<br>3 clock cycles.                                     |                |
| 0x8C          | SD F <sub>SC</sub> Register 0 <sup>1</sup>  | Subcarrier Frequency Bits[7:0].                       | x                | x                | x                | x                | x                | x                | x                | x                | Subcarrier Frequency Bits[7:0].   | 0x1F           |
| 0x8D          | SD F <sub>SC</sub> Register 1 <sup>1</sup>  | Subcarrier Frequency Bits[15:8].                      | x                | x                | x                | x                | x                | x                | x                | x                | Subcarrier Frequency Bits[15:8].  | 0x7C           |
| 0x8E          | SD F <sub>SC</sub> Register 2 <sup>1</sup>  | Subcarrier Frequency<br>Bits[23:16].                  | x                | x                | x                | x                | x                | x                | x                | x                | Subcarrier Frequency<br>Bits[23:16].  | 0xF0           |
| 0x8F          | SD F <sub>SC</sub> Register 3 <sup>1</sup>  | Subcarrier Frequency<br>Bits[31:24].                  | x                | x                | x                | x                | x                | x                | x                | x                | Subcarrier Frequency<br>Bits[31:24].  | 0x21           |
| 0x90          | SD F <sub>SC</sub> Phase  | Subcarrier Phase Bits[9:2].                           | x                | x                | x                | x                | x                | x                | x                | x                | Subcarrier Phase Bits[9:2].   | 0x00           |
| 0x91          | SD Closed Captioning  | Extended Data on Even Fields.                         | x                | x                | x                | x                | x                | x                | x                | x                | Extended Data Bits[7:0].  | 0x00           |
| 0x92          | SD Closed Captioning  | Extended Data on Even Fields.                         | x                | x                | x                | x                | x                | x                | x                | x                | Extended Data Bits[15:8].   | 0x00           |
| 0x93          | SD Closed Captioning  | Data on Odd Fields.                                   | x                | x                | x                | x                | x                | x                | x                | x                | Data Bits[7:0].   | 0x00           |
| 0x94          | SD Closed Captioning  | Data on Odd Fields.                                   | x                | x                | x                | x                | x                | x                | x                | x                | Data Bits[15:8].  | 0x00           |
| 0x95          | SD Pedestal Register 0  | Pedestal on Odd Fields.                               | 17               | 16               | 15               | 14               | 13               | 12               | 11               | 10               | Setting any of these bits to 1<br>disables pedestal on the line<br>number indicated by the bit<br>settings. | 0x00           |
| 0x96          | SD Pedestal Register 1  | Pedestal on Odd Fields.                               | 25               | 24               | 23               | 22               | 21               | 20               | 19               | 18               |   | 0x00           |
| 0x97          | SD Pedestal Register 2  | Pedestal on Even Fields.                              | 17               | 16               | 15               | 14               | 13               | 12               | 11               | 10               |   | 0x00           |
| 0x98          | SD Pedestal Register 3  | Pedestal on Even Fields.                              | 25               | 24               | 23               | 22               | 21               | 20               | 19               | 18               |   | 0x00           |

<sup>1</sup> SD subcarrier frequency registers default to NTSC subcarrier frequency values.

# ADV7340/ADV7341

Table 28. Register 0x99 to Register 0xA5

| SR7 to<br>SR0 | Register                 | Bit Description   | Bit Number |        |        |        |                           |                           |                           |                           | Register Setting                                   | Reset<br>Value      |
|---------------|--------------------------|---|------------|--------|--------|--------|---------------------------|---------------------------|---------------------------|---------------------------|--|---------------------|
|               |                          |   | 7          | 6      | 5      | 4      | 3                         | 2                         | 1                         | 0                         |  |                     |
| 0x99          | SD CGMS/WSS 0            | SD CGMS Data.   |            |        |        |        | x                         | x                         | x                         | x                         | CGMS Data Bits[C19:C16]                            | 0x00                |
|               |                          | SD CGMS CRC.  |            |        |        | 0<br>1 |                           |                           |                           |                           | Disabled<br>Enabled                                |                     |
|               |                          | SD CGMS on Odd Fields.  |            |        | 0<br>1 |        |                           |                           |                           |                           | Disabled<br>Enabled                                |                     |
|               |                          | SD CGMS on Even Fields.   |            | 0<br>1 |        |        |                           |                           |                           |                           | Disabled<br>Enabled                                |                     |
|               |                          | SD WSS.   | 0<br>1     |        |        |        |                           |                           |                           |                           | Disabled<br>Enabled                                |                     |
| 0x9A          | SD CGMS/WSS 1            | SD CGMS/WSS Data.   |            |        | x      | x      | x                         | x                         | x                         | x                         | CGMS Data Bits[C13:C8] or<br>WSS Data Bits[W13:W8] | 0x00                |
|               |                          | SD CGMS Data.   | x          | x      |        |        |                           |                           |                           |                           | CGMS Data Bits[C15:C14]                            |                     |
| 0x9B          | SD CGMS/WSS 2            | SD CGMS/WSS Data.   | x          | x      | x      | x      | x                         | x                         | x                         | x                         | CGMS Data Bits[C7:C0] or<br>WSS Data Bits[W7:W0]   | 0x00                |
| 0x9C          | SD Scale LSB<br>Register | LSBs for SD Y Scale Value.  |            |        |        |        |                           |                           | x                         | x                         | SD Y Scale Bits[1:0]                               | 0x00                |
|               |                          | LSBs for SD Cb Scale Value.   |            |        |        |        | x                         | x                         |                           |                           | SD Cb Scale Bits[1:0]                              |                     |
|               |                          | LSBs for SD Cr Scale Value.   |            |        | x      | x      |                           |                           |                           |                           | SD Cr Scale Bits[1:0]                              |                     |
|               |                          | LSBs for SD F <sub>SC</sub> Phase.  | x          | x      |        |        |                           |                           |                           |                           | Subcarrier Phase Bits[1:0]                         |                     |
| 0x9D          | SD Y Scale Register      | SD Y Scale Value.   | x          | x      | x      | x      | x                         | x                         | x                         | x                         | SD Y Scale Bits[9:2]                               | 0x00                |
| 0x9E          | SD Cb Scale<br>Register  | SD Cb Scale Value.  | x          | x      | x      | x      | x                         | x                         | x                         | x                         | SD Cb Scale Bits[9:2]                              | 0x00                |
| 0x9F          | SD Cr Scale Register     | SD Cr Scale Value.  | x          | x      | x      | x      | x                         | x                         | x                         | x                         | SD Cr Scale Bits[9:2]                              | 0x00                |
| 0xA0          | SD Hue Register          | SD Hue Adjust Value.  | x          | x      | x      | x      | x                         | x                         | x                         | x                         | SD Hue Adjust Bits[7:0]                            | 0x00                |
| 0xA1          | SD Brightness/WSS        | SD Brightness Value.  |            | x      | x      | x      | x                         | x                         | x                         | x                         | SD Brightness Bits[6:0]                            | 0x00                |
|               |                          | SD Blank WSS Data.  | 0<br>1     |        |        |        |                           |                           |                           |                           |  | Disabled<br>Enabled |
| 0xA2          | SD Luma SSAF             | SD Luma SSAF Gain/Attenuation.<br>Note: Only applicable if<br>Register 0x87, Bit 4 = 1. |            |        |        |        | 0<br>...<br>0<br>...<br>1 | 0<br>...<br>1<br>...<br>1 | 0<br>...<br>1<br>...<br>0 | 0<br>...<br>0<br>...<br>0 | −4 dB<br>...<br>0 dB<br>...<br>+4 dB               | 0x00                |
|               |                          |   |            |        |        |        |                           |                           |                           |                           |  |                     |
|               |                          |   |            |        |        |        |                           |                           |                           |                           |  |                     |
|               |                          | Reserved.   | 0          | 0      | 0      | 0      |                           |                           |                           |                           |  |                     |

| SR7 to<br>SR0 | Register | Bit Description  | Bit Number |     |     |     |     |     |     |     | Register Setting   | Reset<br>Value |
|---------------|----------|--|------------|-----|-----|-----|-----|-----|-----|-----|--------------------|----------------|
|               |          |  | 7          | 6   | 5   | 4   | 3   | 2   | 1   | 0   |                    |                |
| 0xA3          | SD DNR 0 | Coring Gain Border.<br>Note: In DNR mode, the values<br>in brackets apply. |            |     |     |     | 0   | 0   | 0   | 0   | No gain            | 0x00           |
|               |          |  |            |     |     |     | 0   | 0   | 0   | 1   | +1/16 [−1/8]       |                |
|               |          |  |            |     |     |     | 0   | 0   | 1   | 0   | +2/16 [−2/8]       |                |
|               |          |  |            |     |     |     | 0   | 0   | 1   | 1   | +3/16 [−3/8]       |                |
|               |          |  |            |     |     |     | 0   | 1   | 0   | 0   | +4/16 [−4/8]       |                |
|               |          |  |            |     |     |     | 0   | 1   | 0   | 1   | +5/16 [−5/8]       |                |
|               |          |  |            |     |     |     | 0   | 1   | 1   | 0   | +6/16 [−6/8]       |                |
|               |          |  |            |     |     |     | 0   | 1   | 1   | 1   | +7/16 [−7/8]       |                |
|               |          |  |            |     |     |     | 1   | 0   | 0   | 0   | +8/16 [−1]         |                |
|               |          | Coring Gain Data.<br>Note: In DNR mode, the values<br>in brackets apply.   | 0          | 0   | 0   | 0   |     |     |     |     | No gain            |                |
|               |          |  | 0          | 0   | 0   | 1   |     |     |     |     | +1/16 [−1/8]       |                |
|               |          |  | 0          | 0   | 1   | 0   |     |     |     |     | +2/16 [−2/8]       |                |
|               |          |  | 0          | 0   | 1   | 1   |     |     |     |     | +3/16 [−3/8]       |                |
|               |          |  | 0          | 1   | 0   | 0   |     |     |     |     | +4/16 [−4/8]       |                |
|               |          |  | 0          | 1   | 0   | 1   |     |     |     |     | +5/16 [−5/8]       |                |
|               |          |  | 0          | 1   | 1   | 0   |     |     |     |     | +6/16 [−6/8]       |                |
|               |          |  | 0          | 1   | 1   | 1   |     |     |     |     | +7/16 [−7/8]       |                |
|               |          |  | 1          | 0   | 0   | 0   |     |     |     |     | +8/16 [−1]         |                |
| 0xA4          | SD DNR 1 | DNR Threshold.   |            |     | 0   | 0   | 0   | 0   | 0   | 0   | 0                  | 0x00           |
|               |          |  |            |     | 0   | 0   | 0   | 0   | 0   | 1   | 1                  |                |
|               |          |  |            |     | ... | ... | ... | ... | ... | ... | ...                |                |
|               |          |  |            |     | 1   | 1   | 1   | 1   | 1   | 0   | 62                 |                |
|               |          |  |            |     | 1   | 1   | 1   | 1   | 1   | 1   | 63                 |                |
|               |          | Border Area.   |            | 0   |     |     |     |     |     |     | 2 pixels           |                |
|               |          |  |            | 1   |     |     |     |     |     |     | 4 pixels           |                |
|               |          | Block Size Control.  | 0          |     |     |     |     |     |     |     | 8 pixels           |                |
|               |          |  | 1          |     |     |     |     |     |     |     | 16 pixels          |                |
| 0xA5          | SD DNR 2 | DNR Input Select.  |            |     |     |     |     | 0   | 0   | 1   | Filter A           | 0x00           |
|               |          |  |            |     |     |     |     | 0   | 1   | 0   | Filter B           |                |
|               |          |  |            |     |     |     |     | 0   | 1   | 1   | Filter C           |                |
|               |          |  |            |     |     |     |     | 1   | 0   | 0   | Filter D           |                |
|               |          | DNR Mode.  |            |     |     |     | 0   |     |     |     | DNR mode           |                |
|               |          |  |            |     |     |     | 1   |     |     |     | DNR sharpness mode |                |
|               |          | DNR Block Offset.  | 0          | 0   | 0   | 0   |     |     |     |     | 0 pixel offset     |                |
|               |          |  | 0          | 0   | 0   | 1   |     |     |     |     | 1 pixel offset     |                |
|               |          |  | ...        | ... | ... | ... |     |     |     |     | ...                |                |
|               |          |  | 1          | 1   | 1   | 0   |     |     |     |     | 14 pixel offset    |                |
|               |          |  | 1          | 1   | 1   | 1   |     |     |     |     | 15 pixel offset    |                |

# ADV7340/ADV7341

Table 29. Register 0xA6 to Register 0xBB

| SR7 to<br>SR0 | Register             | Bit Description               | Bit Number |   |   |   |   |   |   |   | Register<br>Setting | Reset<br>Value |
|---------------|----------------------|-------------------------------|------------|---|---|---|---|---|---|---|---------------------|----------------|
|               |                      |                               | 7          | 6 | 5 | 4 | 3 | 2 | 1 | 0 |                     |                |
| 0xA6          | SD Gamma A0          | SD Gamma Curve A (Point 24).  | x          | x | x | x | x | x | x | x | A0                  | 0x00           |
| 0xA7          | SD Gamma A1          | SD Gamma Curve A (Point 32).  | x          | x | x | x | x | x | x | x | A1                  | 0x00           |
| 0xA8          | SD Gamma A2          | SD Gamma Curve A (Point 48).  | x          | x | x | x | x | x | x | x | A2                  | 0x00           |
| 0xA9          | SD Gamma A3          | SD Gamma Curve A (Point 64).  | x          | x | x | x | x | x | x | x | A3                  | 0x00           |
| 0xAA          | SD Gamma A4          | SD Gamma Curve A (Point 80).  | x          | x | x | x | x | x | x | x | A4                  | 0x00           |
| 0xAB          | SD Gamma A5          | SD Gamma Curve A (Point 96).  | x          | x | x | x | x | x | x | x | A5                  | 0x00           |
| 0xAC          | SD Gamma A6          | SD Gamma Curve A (Point 128). | x          | x | x | x | x | x | x | x | A6                  | 0x00           |
| 0xAD          | SD Gamma A7          | SD Gamma Curve A (Point 160). | x          | x | x | x | x | x | x | x | A7                  | 0x00           |
| 0xAE          | SD Gamma A8          | SD Gamma Curve A (Point 192). | x          | x | x | x | x | x | x | x | A8                  | 0x00           |
| 0xAF          | SD Gamma A9          | SD Gamma Curve A (Point 224). | x          | x | x | x | x | x | x | x | A9                  | 0x00           |
| 0xB0          | SD Gamma B0          | SD Gamma Curve B (Point 24).  | x          | x | x | x | x | x | x | x | B0                  | 0x00           |
| 0xB1          | SD Gamma B1          | SD Gamma Curve B (Point 32).  | x          | x | x | x | x | x | x | x | B1                  | 0x00           |
| 0xB2          | SD Gamma B2          | SD Gamma Curve B (Point 48).  | x          | x | x | x | x | x | x | x | B2                  | 0x00           |
| 0xB3          | SD Gamma B3          | SD Gamma Curve B (Point 64).  | x          | x | x | x | x | x | x | x | B3                  | 0x00           |
| 0xB4          | SD Gamma B4          | SD Gamma Curve B (Point 80).  | x          | x | x | x | x | x | x | x | B4                  | 0x00           |
| 0xB5          | SD Gamma B5          | SD Gamma Curve B (Point 96).  | x          | x | x | x | x | x | x | x | B5                  | 0x00           |
| 0xB6          | SD Gamma B6          | SD Gamma Curve B (Point 128). | x          | x | x | x | x | x | x | x | B6                  | 0x00           |
| 0xB7          | SD Gamma B7          | SD Gamma Curve B (Point 160). | x          | x | x | x | x | x | x | x | B7                  | 0x00           |
| 0xB8          | SD Gamma B8          | SD Gamma Curve B (Point 192). | x          | x | x | x | x | x | x | x | B8                  | 0x00           |
| 0xB9          | SD Gamma B9          | SD Gamma Curve B (Point 224). | x          | x | x | x | x | x | x | x | B9                  | 0x00           |
| 0xBA          | SD Brightness Detect | SD Brightness Value.          | x          | x | x | x | x | x | x | x | Read only.          | 0xXX           |
| 0xBB          | Field Count Register | Field Count.                  |            |   |   |   |   | x | x | x | Read only.          | 0x0X           |
|               |                      | Reserved.                     |            |   | 0 | 0 | 0 |   |   |   | Reserved.           |                |
|               |                      | Revision Code.                | 0          | 0 |   |   |   |   |   |   | Read only.          |                |

Table 30. Register 0xE0 to Register 0xF1

| SR7 to<br>SR0 | Register <sup>1</sup> | Bit Description  | Bit Number |   |   |   |   |   |   |   | Register Setting     | Reset<br>Value |
|---------------|-----------------------|------------------|------------|---|---|---|---|---|---|---|----------------------|----------------|
|               |                       |                  | 7          | 6 | 5 | 4 | 3 | 2 | 1 | 0 |                      |                |
| 0xE0          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE1          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE2          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE3          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE4          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE5          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE6          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE7          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE8          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xE9          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xEA          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xEB          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xEC          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xED          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xEE          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xEF          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xF0          | Macrovision           | MV Control Bits. | x          | x | x | x | x | x | x | x |                      | 0x00           |
| 0xF1          | Macrovision           | MV Control Bit.  | 0          | 0 | 0 | 0 | 0 | 0 | 0 | x | Bits[7:1] must be 0. | 0x00           |

<sup>1</sup> Macrovision registers are available on the ADV7340 only.

## INPUT CONFIGURATION

The ADV7340/ADV7341 support a number of different input modes. The desired input mode is selected using Subaddress 0x01, Bits[6:4]. The ADV7340/ADV7341 default to standard definition only (SD only) upon power-up. Table 31 provides an overview of all possible input configurations. Each input mode is described in detail in the following sections.

### STANDARD DEFINITION ONLY

#### Subaddress 0x01, Bits[6:4] = 000

Standard definition (SD) YCrCb data can be input in 4:2:2 format. Standard definition (SD) RGB data can be input in 4:4:4 format.

A 27 MHz clock signal must be provided on the **CLKIN\_A** pin. Input synchronization signals are provided on the **S\_HSYNC** and **S\_VSYNC** pins.

#### 8-/10-Bit 4:2:2 YCrCb Mode

##### Subaddress 0x87, Bit 7 = 0; Subaddress 0x88, Bit 3 = 0

In 8-/10-bit 4:2:2 YCrCb input mode, the interleaved pixel data is input on Pin S9 to Pin S2/S0 (or Pin Y9 to Pin Y2/Y0, depending on Subaddress 0x01, Bit 7), with S0/Y0 being the LSB in 10-bit input mode. ITU-R BT.601/656 input standard is supported.

#### 16-/20-Bit 4:2:2 YCrCb Mode

##### Subaddress 0x87, Bit 7 = 0; Subaddress 0x88, Bit 3 = 1


In 16-/20-bit 4:2:2 YCrCb input mode, the Y pixel data is input on Pin S9 to Pin S2/S0 (or Pin Y9 to Pin Y2/Y0, depending on Subaddress 0x01, Bit 7), with S0/Y0 being the LSB in 20-bit input mode.

The CrCb pixel data is input on Pin Y9 to Pin Y2/Y0 (or Pin C9 to Pin C2/C0, depending on Subaddress 0x01, Bit 7), with Y0/C0 being the LSB in 20-bit input mode.

#### 24-/30-Bit 4:4:4 RGB Mode

##### Subaddress 0x87, Bit 7 = 1

In 24-/30-bit 4:4:4 RGB input mode, the red pixel data is input on Pin S9 to Pin S2/S0, the green pixel data is input on Pin Y9 to Pin Y2/Y0, and the blue pixel data is input on Pin C9 to Pin C2/C0. S0, Y0, and C0 are the respective bus LSBs in 30-bit input mode.



\*SELECTED BY SUBADDRESS 0x01, BIT 7.

Figure 51. SD Only Example Application

Table 31. Input Configuration

| Input Mode <sup>1</sup> |   | S                                    |   |   |   |   |   |   |   |   |   | Y             |   |   |   |   |   |   |   |   |   | C            |   |   |   |   |   |   |   |   |   |
|-------------------------|---|--------------------------------------|---|---|---|---|---|---|---|---|---|---------------|---|---|---|---|---|---|---|---|---|--------------|---|---|---|---|---|---|---|---|---|
|                         |   | 9                                    | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 | 9             | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 | 9            | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |
| 000                     | SD Only                                       | Y/C/S Bus Swap (0x01[7]) = 0         |   |   |   |   |   |   |   |   |   |               |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         | 8-/10-Bit YCrCb <sup>2,3</sup>                | YCrCb                                |   |   |   |   |   |   |   |   |   |               |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         | 16-/20-Bit YCrCb <sup>2,3,4</sup>             | Y                                    |   |   |   |   |   |   |   |   |   | CrCb          |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         |   | Y/C/S Bus Swap (0x01[7]) = 1         |   |   |   |   |   |   |   |   |   |               |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         | 8-/10-Bit YCrCb <sup>2,3</sup>                |                                      |   |   |   |   |   |   |   |   |   | YCrCb         |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         | 16-/20-Bit YCrCb <sup>2,3,4</sup>             |                                      |   |   |   |   |   |   |   |   |   | Y             |   |   |   |   |   |   |   |   |   | CrCb         |   |   |   |   |   |   |   |   |   |
|                         |   | SD RGB Input Enable (0x87[7]) = 1    |   |   |   |   |   |   |   |   |   |               |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         | 24-/30-Bit RGB <sup>4</sup>                   | R                                    |   |   |   |   |   |   |   |   |   | G             |   |   |   |   |   |   |   |   |   | B            |   |   |   |   |   |   |   |   |   |
| 001                     | ED/HD-SDR Only <sup>3,5,6,7</sup>             | ED/HD RGB Input Enable (0x35[1]) = 0 |   |   |   |   |   |   |   |   |   |               |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         | 16-/20-Bit YCrCb                              |                                      |   |   |   |   |   |   |   |   |   | Y             |   |   |   |   |   |   |   |   |   | CrCb         |   |   |   |   |   |   |   |   |   |
|                         | 24-/30-Bit YCrCb                              | Cr                                   |   |   |   |   |   |   |   |   |   | Y             |   |   |   |   |   |   |   |   |   | Cb           |   |   |   |   |   |   |   |   |   |
|                         |   | ED/HD RGB Input Enable (0x35[1]) = 1 |   |   |   |   |   |   |   |   |   |               |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
|                         | 24-/30-Bit RGB <sup>4</sup>                   | R                                    |   |   |   |   |   |   |   |   |   | G             |   |   |   |   |   |   |   |   |   | B            |   |   |   |   |   |   |   |   |   |
| 010                     | ED/HD-DDR Only (8-/10-Bit) <sup>3,6,7</sup>   |                                      |   |   |   |   |   |   |   |   |   | YCrCb         |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
| 011                     | SD, ED/HD-SDR (24-/30-Bit) <sup>3,6,7,8</sup> | YCrCb (SD)                           |   |   |   |   |   |   |   |   |   | Y (ED/HD)     |   |   |   |   |   |   |   |   |   | CrCb (ED/HD) |   |   |   |   |   |   |   |   |   |
| 100                     | SD, ED/HD-DDR (16-/20-Bit) <sup>3,6,7,8</sup> | YCrCb (SD)                           |   |   |   |   |   |   |   |   |   | YCrCb (ED/HD) |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |
| 111                     | ED Only (54 MHz) (8-/10-Bit) <sup>3,6,7</sup> |                                      |   |   |   |   |   |   |   |   |   | YCrCb         |   |   |   |   |   |   |   |   |   |              |   |   |   |   |   |   |   |   |   |

<sup>1</sup> The input mode is determined by Subaddress 0x01, Bits[6:4].

<sup>2</sup> In SD only (YCrCb) mode, the format of the input data is determined by Subaddress 0x88, Bits[4:3]. See Table 26 for more information.

<sup>3</sup> For 8-/16-/24-bit inputs, only the eight most significant bits (MSBs) of each applicable input bus are used.

<sup>4</sup> External synchronization signals must be used in this input mode. Embedded EAV/SAV timing codes are not supported.

<sup>5</sup> In ED/HD-SDR only (YCrCb) mode, the format of the input data is determined by Subaddress 0x33, Bit 6. See Table 19 for more information.

<sup>6</sup> ED = enhanced definition = 525p and 625p.

<sup>7</sup> The bus width of the ED/HD input data is determined by Subaddress 0x33, Bit 2 (0 = 8-bit, 1 = 10-bit). See Table 19 for more information.

<sup>8</sup> The bus width of the SD input data is determined by Subaddress 0x88, Bit 4 (0 = 8-bit, 1 = 10-bit). See Table 26 for more information.

# ADV7340/ADV7341

## ENHANCED DEFINITION/HIGH DEFINITION ONLY

### Subaddress 0x01, Bits[6:4] = 001 or 010

Enhanced definition (ED) or high definition (HD) YCrCb data can be input in either 4:2:2 or 4:4:4 formats. If desired, dual data rate (DDR) pixel data inputs can be employed (4:2:2 format only).

Enhanced definition (ED) or high definition (HD) RGB data can be input in 4:4:4 format (single data rate only).

The clock signal must be provided on the CLKIN\_A pin. Input synchronization signals are provided on the P\_HSYNC, P\_VSYNC and P\_BLANK pins.

### 16-/20-Bit 4:2:2 YCrCb Mode (SDR)

#### Subaddress 0x35, Bit 1 = 0; Subaddress 0x33, Bit 6 = 1

In 16-/20-bit 4:2:2 YCrCb input mode, the Y pixel data is input on Pin Y9 to Pin Y2/Y0, with Y0 being the LSB in 20-bit input mode.

The CrCb pixel data is input on Pin C9 to Pin C2/C0, with C0 being the LSB in 20-bit input mode.


### 8-/10-Bit 4:2:2 YCrCb Mode (DDR)

#### Subaddress 0x35, Bit 1 = 0; Subaddress 0x33, Bit 6 = 1

In 8-/10-bit DDR 4:2:2 YCrCb input mode, the Y pixel data is input on Pin Y9 to Pin Y2/Y0 upon either the rising or falling edge of CLKIN\_A. Y0 is the LSB in 10-bit input mode.


The CrCb pixel data is also input on Pin Y9 to Pin Y2/Y0 upon the opposite edge of CLKIN\_A. Y0 is the LSB in 10-bit input mode.

Whether the Y data is clocked in upon the rising or falling edge of CLKIN\_A is determined by Subaddress 0x01, Bits[2:1] (see Figure 52 and Figure 53).



NOTES  
1. SUBADDRESS 0x01 [2:1] SHOULD BE SET TO 00 IN THIS CASE.

Figure 52. ED/HD-DDR Input Sequence (EAV/SAV)—Option A



NOTES  
1. SUBADDRESS 0x01 [2:1] SHOULD BE SET TO 11 IN THIS CASE.

Figure 53. ED/HD-DDR Input Sequence (EAV/SAV)—Option B

### 24-/30-Bit 4:4:4 YCrCb Mode

#### Subaddress 0x35, Bit 1 = 0; Subaddress 0x33, Bit 6 = 0

In 24-/30-bit 4:4:4 YCrCb input mode, the Y pixel data is input on Pin Y9 to Pin Y2/Y0, with Y0 being the LSB in 30-bit input mode.

The Cr pixel data is input on Pin S9 to Pin S2/S0, with S0 being the LSB in 30-bit input mode.

The Cb pixel data is input on Pin C9 to Pin C2/C0, with C0 being the LSB in 30-bit input mode.

### 24-/30-Bit 4:4:4 RGB Mode

#### Subaddress 0x35, Bit 1 = 1

In 24-/30-bit 4:4:4 RGB input mode, the red pixel data is input on Pin S9 to Pin S2/S0, the green pixel data is input on Pin Y9 to Pin Y2/Y0, and the blue pixel data is input on Pin C9 to Pin C2/C0. S0, Y0, and C0 are the respective bus LSBs in 30-bit input mode.




Figure 54. ED/HD Only Example Application

## SIMULTANEOUS STANDARD DEFINITION AND ENHANCED DEFINITION/HIGH DEFINITION

### Subaddress 0x01, Bits[6:4] = 011 or 100

The ADV7340/ADV7341 are able to simultaneously process SD 4:2:2 YCrCb data and ED/HD 4:2:2 YCrCb data. The 27 MHz SD clock signal must be provided on the CLKIN\_A pin. The ED/HD clock signal must be provided on the CLKIN\_B pin. SD input synchronization signals are provided on the S\_HSYNC and S\_VSYNC pins. ED/HD input synchronization signals are provided on the P\_HSYNC, P\_VSYNC and P\_BLANK pins.

### SD 8-/10-Bit 4:2:2 YCrCb and ED/HD-SDR 16-/20-Bit 4:2:2 YCrCb

The SD 8-/10-bit 4:2:2 YCrCb pixel data is input on Pin S9 to Pin S2/S0, with S0 being the LSB in 10-bit input mode.

The ED/HD 16-/20-bit 4:2:2 Y pixel data is input on Pin Y9 to Pin Y2/Y0, with Y0 being the LSB in 20-bit input mode.

The ED/HD 16-/20-bit 4:2:2 CrCb pixel data is input on Pin C9 to Pin C2/C0, with C0 being the LSB in 20-bit input mode.

### SD 8-/10-Bit 4:2:2 YCrCb and ED/HD-DDR 8-/10-Bit 4:2:2 YCrCb

The SD 8-/10-bit 4:2:2 YCrCb pixel data is input on Pin S9 to Pin S2/S0, with S0 being the LSB in 10-bit input mode.

The ED/HD-DDR 8-/10-bit 4:2:2 Y pixel data is input on Pin Y9 to Pin Y2/Y0 upon the rising or falling edge of CLKIN\_B. Y0 is the LSB in 10-bit input mode.

The ED/HD-DDR 8-/10-bit 4:2:2 CrCb pixel data is also input on Pin Y9 to Pin Y2/Y0 upon the opposite edge of CLKIN\_B. Y0 is the LSB in 10-bit input mode.

Whether the ED/HD Y data is clocked in upon the rising or falling edge of CLKIN\_B is determined by Subaddress 0x01, Bits[2:1] (See the input sequence shown in Figure 52 and Figure 53).




Figure 55. Simultaneous SD and ED Example Application




Figure 56. Simultaneous SD and HD Example Application

## ENHANCED DEFINITION ONLY (AT 54 MHz)

### Subaddress 0x01, Bits[6:4] = 111

Enhanced definition (ED) YCrCb data can be input in an interleaved 4:2:2 format on an 8-/10-bit bus at a rate of 54 MHz.

A 54 MHz clock signal must be provided on the CLKIN\_A pin. Input synchronization signals are provided on the P\_HSYNC, P\_VSYNC, and P\_BLANK pins.

The interleaved pixel data is input on Pin Y9 to Pin Y2/Y0, with Y0 being the LSB in 10-bit input mode.




Figure 57. ED Only (at 54 MHz) Input Sequence (EAV/SAV)




Figure 58. ED Only (at 54 MHz) Example Application

# ADV7340/ADV7341

## OUTPUT CONFIGURATION

The ADV7340/ADV7341 support a number of different output configurations. Table 32 to Table 35 list all possible output configurations.

Table 32. SD Only Output Configurations

| RGB/YPrPb Output Select <sup>1</sup> (0x02, Bit 5) | SD DAC Output 2 (0x82, Bit 2) | SD DAC Output 1 (0x82, Bit 1) | SD Luma/Chroma Swap (0x84, Bit 7) | DAC 1 | DAC 2  | DAC 3  | DAC 4 | DAC 5  | DAC 6  |
|--|-------------------------------|-------------------------------|-----------------------------------|-------|--------|--------|-------|--------|--------|
| 0  | 0                             | 0                             | 0                                 | G     | B      | R      | CVBS  | Luma   | Chroma |
| 0  | 0                             | 0                             | 1                                 | G     | B      | R      | CVBS  | Chroma | Luma   |
| 0  | 0                             | 1                             | 0                                 | CVBS  | Luma   | Chroma | G     | B      | R      |
| 0  | 0                             | 1                             | 1                                 | CVBS  | Chroma | Luma   | G     | B      | R      |
| 0  | 1                             | 0                             | 0                                 | CVBS  | B      | R      | G     | Luma   | Chroma |
| 0  | 1                             | 0                             | 1                                 | CVBS  | B      | R      | G     | Chroma | Luma   |
| 0  | 1                             | 1                             | 0                                 | G     | Luma   | Chroma | CVBS  | B      | R      |
| 0  | 1                             | 1                             | 1                                 | G     | Chroma | Luma   | CVBS  | B      | R      |
| 1  | 0                             | 0                             | 0                                 | Y     | Pb     | Pr     | CVBS  | Luma   | Chroma |
| 1  | 0                             | 0                             | 1                                 | Y     | Pb     | Pr     | CVBS  | Chroma | Luma   |
| 1  | 0                             | 1                             | 0                                 | CVBS  | Luma   | Chroma | Y     | Pb     | Pr     |
| 1  | 0                             | 1                             | 1                                 | CVBS  | Chroma | Luma   | Y     | Pb     | Pr     |
| 1  | 1                             | 0                             | 0                                 | CVBS  | Pb     | Pr     | Y     | Luma   | Chroma |
| 1  | 1                             | 0                             | 1                                 | CVBS  | Pb     | Pr     | Y     | Chroma | Luma   |
| 1  | 1                             | 1                             | 0                                 | Y     | Luma   | Chroma | CVBS  | Pb     | Pr     |
| 1  | 1                             | 1                             | 1                                 | Y     | Chroma | Luma   | CVBS  | Pb     | Pr     |

<sup>1</sup> If SD RGB output is selected, a color reversal is possible using Subaddress 0x86, Bit 7.

Table 33. ED/HD Only Output Configurations

| RGB/YPrPb Output Select (0x02, Bit 5) | ED/HD Color DAC Swap (0x35, Bit 3) | DAC 1 | DAC 2 | DAC 3 | DAC 4 | DAC 5 | DAC 6 |
|---------------------------------------|------------------------------------|-------|-------|-------|-------|-------|-------|
| 0                                     | 0                                  | G     | B     | R     | N/A   | N/A   | N/A   |
| 0                                     | 1                                  | G     | R     | B     | N/A   | N/A   | N/A   |
| 1                                     | 0                                  | Y     | Pb    | Pr    | N/A   | N/A   | N/A   |
| 1                                     | 1                                  | Y     | Pr    | Pb    | N/A   | N/A   | N/A   |

Table 34. Simultaneous SD and ED/HD Output Configurations

| RGB/YPrPb Output Select (0x02, Bit 5) | ED/HD Color DAC Swap (0x35, Bit 3) | SD Luma/Chroma Swap (0x84, Bit 7) | DAC 1 (ED/HD) | DAC 2 (ED/HD) | DAC 3 (ED/HD) | DAC 4 (SD) | DAC 5 (SD) | DAC 6 (SD) |
|---------------------------------------|------------------------------------|-----------------------------------|---------------|---------------|---------------|------------|------------|------------|
| 0                                     | 0                                  | 0                                 | G             | B             | R             | CVBS       | Luma       | Chroma     |
| 0                                     | 0                                  | 1                                 | G             | B             | R             | CVBS       | Chroma     | Luma       |
| 0                                     | 1                                  | 0                                 | G             | R             | B             | CVBS       | Luma       | Chroma     |
| 0                                     | 1                                  | 1                                 | G             | R             | B             | CVBS       | Chroma     | Luma       |
| 1                                     | 0                                  | 0                                 | Y             | Pb            | Pr            | CVBS       | Luma       | Chroma     |
| 1                                     | 0                                  | 1                                 | Y             | Pb            | Pr            | CVBS       | Chroma     | Luma       |
| 1                                     | 1                                  | 0                                 | Y             | Pr            | Pb            | CVBS       | Luma       | Chroma     |
| 1                                     | 1                                  | 1                                 | Y             | Pr            | Pb            | CVBS       | Chroma     | Luma       |

Table 35. ED Only (at 54 MHz) Output Configurations

| RGB/YPrPb Output Select (0x02, Bit 5) | ED/HD Color DAC Swap (0x35, Bit 3) | DAC 1 | DAC 2 | DAC 3 | DAC 4 | DAC 5 | DAC 6 |
|---------------------------------------|------------------------------------|-------|-------|-------|-------|-------|-------|
| 0                                     | 0                                  | G     | B     | R     | N/A   | N/A   | N/A   |
| 0                                     | 1                                  | G     | R     | B     | N/A   | N/A   | N/A   |
| 1                                     | 0                                  | Y     | Pb    | Pr    | N/A   | N/A   | N/A   |
| 1                                     | 1                                  | Y     | Pr    | Pb    | N/A   | N/A   | N/A   |



## FEATURES

### OUTPUT OVERSAMPLING

The ADV7340/ADV7341 include two on-chip phase locked loops (PLLs) that allow for oversampling of SD, ED, and HD video data. Table 36 shows the various oversampling rates supported in the ADV7340/ADV7341.

#### SD Only, ED Only, and HD Only Modes

PLL 1 is used in SD only, ED only, and HD only modes. PLL 2 is unused in these modes. PLL 1 is disabled by default and can be enabled using Subaddress 0x00, Bit 1 = 0.

#### SD and ED/HD Simultaneous Modes

Both PLL 1 and PLL 2 are used in simultaneous modes. The use of two PLLs allows for independent oversampling of SD and ED/HD video. PLL 1 is used to oversample SD video data, and PLL 2 is used to oversample ED/HD video data. In simultaneous modes, PLL 2 is always enabled. PLL 1 is disabled by default and can be enabled using Subaddress 0x00, Bit 1 = 0.

### ED/HD NONSTANDARD TIMING MODE

#### Subaddress 0x30, Bits[7:3] = 00001

For any ED/HD input data that does not conform to the standards available in the ED/HD input mode table (Subaddress 0x30, Bits[7:3]), the ED/HD nonstandard timing mode can be used to interface to the ADV7340/ADV7341.

ED/HD nonstandard timing mode can be enabled by setting Subaddress 0x30, Bits[7:3] to 00001.

A clock signal must be provided on the CLKIN\_A pin. P\_HSYNC and P\_VSYNC must be toggled by the user to generate the appropriate horizontal and vertical synchronization pulses on the analog output from the encoder. Figure 59 illustrates the various output levels that can be generated. Table 37 lists the transitions required to generate these output levels.

Embedded EAV/SAV timing codes are not supported in ED/HD nonstandard timing mode.

The user must ensure that appropriate pixel data is applied to the encoder where the blanking level is expected at the output.

Macrovision (ADV7340 only) and output oversampling are not available in ED/HD nonstandard timing mode.




Figure 59. ED/HD Nonstandard Timing Mode Output Levels

Table 36. Output Oversampling Modes and Rates

| Input Mode<br>Subaddress 0x01 [6:4] |                     | PLL and Oversampling Control<br>Subaddress 0x00, Bit 1 | Oversampling Mode and Rate |
|-------------------------------------|---------------------|--|----------------------------|
| 000                                 | SD only             | 1  | SD (2x)                    |
| 000                                 | SD only             | 0  | SD (16x)                   |
| 001/010                             | ED only             | 1  | ED (1x)                    |
| 001/010                             | ED only             | 0  | ED (8x)                    |
| 001/010                             | HD only             | 1  | HD (1x)                    |
| 001/010                             | HD only             | 0  | HD (4x)                    |
| 011/100                             | SD and ED           | 1  | SD (2x) and ED (8x)        |
| 011/100                             | SD and ED           | 0  | SD (16x) and ED (8x)       |
| 011/100                             | SD and HD           | 1  | SD (2x) and HD (4x)        |
| 011/100                             | SD and HD           | 0  | SD (16x) and HD (4x)       |
| 111                                 | ED only (at 54 MHz) | 1  | ED only (at 54 MHz) (1x)   |
| 111                                 | ED only (at 54 MHz) | 0  | ED only (at 54 MHz) (8x)   |

Table 37. ED/HD Nonstandard Timing Mode Synchronization Signal Generation

| Output Level Transition <sup>1</sup> | P_HSYNC | P_VSYNC                 |
|--------------------------------------|---------|-------------------------|
| b → c                                | 1 → 0   | 1 → 0 or 0 <sup>2</sup> |
| c → a                                | 0       | 0 → 1                   |
| a → b                                | 0 → 1   | 1                       |
| c → b                                | 0 → 1   | 0                       |

<sup>1</sup> a = tri-level synchronization pulse level; b = blanking level/active video level; c = synchronization pulse level.

<sup>2</sup> If P\_VSYNC = 1, it should transition to 0. If P\_VSYNC = 0, it should remain at 0. If tri-level synchronization pulse generation is not required, P\_VSYNC should always be 0.

# ADV7340/ADV7341

## ED/HD TIMING RESET

### Subaddress 0x34, Bit 0

An ED/HD timing reset is achieved by toggling the ED/HD timing reset control bit (Subaddress 0x34, Bit 0) from 0 to 1. In this state, the horizontal and vertical counters remain reset. When this bit is set back to 0, the internal counters resume counting. This timing reset applies to the ED/HD timing counters only.

## SD SUBCARRIER FREQUENCY LOCK, SUBCARRIER PHASE RESET, AND TIMING RESET

### Subaddress 0x84, Bits[2:1]

Together with the SFL/MISO pin and SD Mode Register 4 (Subaddress 0x84, Bits[2:1]), the ADV7340/ADV7341 can be used in timing reset mode, subcarrier phase reset mode, or SFL mode.

### Timing Reset (TR) Mode

In this mode (Subaddress 0x84, Bits[2:1] = 10), a timing reset is achieved in a low-to-high transition on the SFL/MISO pin (Pin 48). In this state, the horizontal and vertical counters remain reset.

Upon releasing this pin (set to low), the internal counters resume counting, starting with Field 1, and the subcarrier phase is reset. The minimum time the pin must be held high is one clock cycle; otherwise, this reset signal might not be recognized. This timing reset applies to the SD timing counters only.

### Subcarrier Phase Reset (SCR) Mode

In this mode (Subaddress 0x84, Bits[2:1] = 01), a low-to-high transition on the SFL/MISO pin (Pin 48) resets the subcarrier phase to 0 on the field following the subcarrier phase reset. This reset signal must be held high for a minimum of one clock cycle.

Because the field counter is not reset, it is recommended that the reset signal be applied in Field 7 (PAL) or Field 3 (NTSC). The reset of the phase then occurs on the next field, that is, Field 1, lined up correctly with the internal counters. The field count register at Subaddress 0xBB can be used to identify the number of the active field.

### Subcarrier Frequency Lock (SFL) Mode

In this mode (Subaddress 0x84, Bits[2:1] = 11), the ADV7340/ADV7341 can be used to lock to an external video source. The SFL mode allows the ADV7340/ADV7341 to automatically alter the subcarrier frequency to compensate for line length variations. When the part is connected to a device such as an [ADV7403](#) video decoder (see Figure 62) that outputs a digital data stream in the SFL format, the part automatically changes to the compensated subcarrier frequency on a line-by-line basis. This digital data stream is 67 bits wide, and the subcarrier is contained in Bit 0 to Bit 21. Each bit is two clock cycles long.




Figure 60. SD Timing Reset Timing Diagram (Subaddress 0x84, Bits[2:1] = 10)





Figure 61. SD Subcarrier Phase Reset Timing Diagram (Subaddress 0x84, Bits[2:1] = 01)



<sup>1</sup>FOR EXAMPLE, VCR OR CABLE.

<sup>2</sup>F<sub>SC</sub> PLL INCREMENT IS 22 BITS LONG. VALUE LOADED INTO ADV7340/ADV7341 F<sub>SC</sub> DDS REGISTER IS

F<sub>SC</sub> PLL INCREMENTS BITS 21:0 PLUS BITS 0:9 OF SUBCARRIER FREQUENCY REGISTERS.

<sup>3</sup>SEQUENCE BIT

PAL: 0 = LINE NORMAL, 1 = LINE INVERTED

NTSC: 0 = NO CHANGE

<sup>4</sup>RESET ADV7340/ADV7341 DDS.

<sup>5</sup>SELECTED BY SUBADDRESS 0x01, BIT 7.

Figure 62. SD Subcarrier Frequency Lock Timing and Connections Diagram (Subaddress 0x84, Bits[2:1] = 11)

08398-063

## SD VCR FF/RW SYNC

### Subaddress 0x82, Bit 5

In DVD record applications where the encoder is used with a decoder, the VCR FF/RW sync control bit can be used for non-standard input video, that is, in fast forward or rewind modes.

In fast forward mode, the sync information at the start of a new field in the incoming video usually occurs before the correct number of lines/fields is reached. In rewind mode, this sync signal usually occurs after the total number of lines/fields is reached. Conventionally, this means that the output video has corrupted field signals because one signal is generated by the incoming video and another is generated when the internal line/field counters reach the end of a field.

When the VCR FF/RW sync control is enabled (Subaddress 0x82, Bit 5), the line/field counters are updated according to the incoming VSYNC signal and when the analog output matches the incoming VSYNC signal.

This control is available in all slave-timing modes except Slave Mode 0.

## VERTICAL BLANKING INTERVAL

### Subaddress 0x31, Bit 4; Subaddress 0x83, Bit 4

The ADV7340/ADV7341 are able to accept input data that contains VBI data (such as CGMS, WSS, VITS) in SD, ED, and HD modes.

If VBI is disabled (Subaddress 0x31, Bit 4 for ED/HD; Subaddress 0x83, Bit 4 for SD), VBI data is not present at the output and the entire VBI is blanked. These control bits are valid in all master and slave timing modes.

For the SMPTE 293M (525p) standard, VBI data can be inserted on Line 13 to Line 42 of each frame, or on Line 6 to Line 43 for the ITU-R BT.1358 (625p) standard.

VBI data can be present on Line 10 to Line 20 for NTSC and on Line 7 to Line 22 for PAL.

In SD Timing Mode 0 (slave option), if VBI is enabled, the blanking bit in the EAV/SAV code is overwritten. It is possible to use VBI in this timing mode as well.

If CGMS is enabled and VBI is disabled, the CGMS data is nevertheless available at the output.

## SD SUBCARRIER FREQUENCY REGISTERS

### Subaddress 0x8C to Subaddress 0x8F

Four 8-bit registers are used to set up the subcarrier frequency. The value of these registers is calculated using:

$$\text{Subcarrier Frequency Register} = \frac{\text{Number of subcarrier periods in one video line}}{\text{Number of 27 MHz clk cycles in one video line}} \times 2^{32}$$

where the sum is rounded to the nearest integer.

For example, in NTSC mode:

$$\text{Subcarrier Register Value} = \left( \frac{227.5}{1716} \right) \times 2^{32} = 569408543$$

where:

Subcarrier Register Value = 569408543d = 0x21F07C1F

SD F<sub>SC</sub> Register 0: 0x1F

SD F<sub>SC</sub> Register 1: 0x7C

SD F<sub>SC</sub> Register 2: 0xF0

SD F<sub>SC</sub> Register 3: 0x21

# ADV7340/ADV7341

## Programming the $F_{SC}$

The subcarrier frequency register value is divided into four  $F_{SC}$  registers, as shown in the previous example. The four subcarrier frequency registers must be updated sequentially, starting with Subcarrier Frequency Register 0 and ending with Subcarrier Frequency Register 3. The subcarrier frequency updates only after the last subcarrier frequency register byte has been received by the ADV7340/ADV7341.

## Typical $F_{SC}$ Values

Table 38 outlines the values that should be written to the subcarrier frequency registers for NTSC and PAL B/D/G/H/I.

Table 38. Typical  $F_{SC}$  Values

| Subaddress | Description | NTSC | PAL B/D/G/H/I |
|------------|-------------|------|---------------|
| 0x8C       | $F_{SC0}$   | 0x1F | 0xCB          |
| 0x8D       | $F_{SC1}$   | 0x7C | 0x8A          |
| 0x8E       | $F_{SC2}$   | 0xF0 | 0x09          |
| 0x8F       | $F_{SC3}$   | 0x21 | 0x2A          |

## SD NONINTERLACED MODE

### Subaddress 0x88, Bit 1

The ADV7340/ADV7341 support a SD noninterlaced mode. Using this mode, progressive inputs at twice the frame rate of NTSC and PAL (240p/59.94 Hz and 288p/50 Hz, respectively)

can be input into the A ADV7340/ADV7341. The SD noninterlaced mode can be enabled using Subaddress 0x88, Bit 1.

A 27 MHz clock signal must be provided on the CLKIN\_A pin. Embedded EAV/SAV timing codes or external horizontal and vertical synchronization signals provided on the  $\overline{S\_HSYNC}$  and  $\overline{S\_VSYNC}$  pins can be used to synchronize the input pixel data.

All input configurations, output configurations and features available in NTSC and PAL modes are available in SD noninterlaced mode.

For 240p/59.94 Hz input, the ADV7340/ADV7341 should be configured for NTSC operation and Subaddress 0x88, Bit 1 should be set to 1.

For 288p/50 Hz input, the ADV7340/ADV7341 should be configured for PAL operation and Subaddress 0x88, Bit 1 should be set to 1.

## SD SQUARE PIXEL MODE

### Subaddress 0x82, Bit 4

The ADV7340/ADV7341 can be used to operate in square pixel mode (Subaddress 0x82, Bit 4). For NTSC operation, an input clock of 24.5454 MHz is required. Alternatively, for PAL operation, an input clock of 29.5 MHz is required. The internal timing logic adjusts accordingly for square pixel mode operation. In square pixel mode, the timing diagrams shown in Figure 63 and Figure 64 apply.




Figure 63. Square Pixel Mode EAV/SAV Embedded Timing




Figure 64. Square Pixel Mode Active Pixel Timing

## FILTERS

Table 39 shows an overview of the programmable filters available on the ADV7340/ADV7341.

**Table 39. Selectable Filters**

| Filter                         | Subaddress |
|--------------------------------|------------|
| SD Luma LPF NTSC               | 0x80       |
| SD Luma LPF PAL                | 0x80       |
| SD Luma Notch NTSC             | 0x80       |
| SD Luma Notch PAL              | 0x80       |
| SD Luma SSAF                   | 0x80       |
| SD Luma CIF                    | 0x80       |
| SD Luma QCIF                   | 0x80       |
| SD Chroma 0.65 MHz             | 0x80       |
| SD Chroma 1.0 MHz              | 0x80       |
| SD Chroma 1.3 MHz              | 0x80       |
| SD Chroma 2.0 MHz              | 0x80       |
| SD Chroma 3.0 MHz              | 0x80       |
| SD Chroma CIF                  | 0x80       |
| SD Chroma QCIF                 | 0x80       |
| SD PrPb SSAF                   | 0x82       |
| ED/HD Chroma Input             | 0x33       |
| ED/HD Sinc Compensation Filter | 0x33       |
| ED/HD Chroma SSAF              | 0x33       |

### SD Internal Filter Response

#### Subaddress 0x80, Bits[7:2]; Subaddress 0x82, Bit 0

The Y filter supports several different frequency responses, including two low-pass responses, two notch responses, an extended (SSAF) response with or without gain boost attenuation, a CIF response, and a QCIF response. The PrPb filter supports several different frequency responses, including six low-pass responses, a CIF response, and a QCIF response, as shown in Figure 39 and Figure 40.

If SD SSAF gain is enabled (Subaddress 0x87, Bit 4), there are 13 response options in the  $-4$  dB to  $+4$  dB range. The desired response can be programmed using Subaddress 0xA2. The variation of frequency responses is shown in Figure 36 to Figure 38.

In addition to the chroma filters listed in Table 39, the ADV7340/ADV7341 contain an SSAF filter specifically designed for the color difference component outputs, Pr and Pb. This filter has a cutoff frequency of  $\sim 2.7$  MHz and a gain of  $-40$  dB at 3.8 MHz (see Figure 65). This filter can be controlled with Subaddress 0x82, Bit 0.




Figure 65. PrPb SSAF Filter

If this filter is disabled, one of the chroma filters shown in Table 40 can be selected and used for the CVBS or luma/chroma signal.

**Table 40. Internal Filter Specifications**

| Filter          | Pass-Band Ripple (dB) <sup>1</sup> | 3 dB Bandwidth (MHz) <sup>2</sup> |
|-----------------|------------------------------------|-----------------------------------|
| Luma LPF NTSC   | 0.16                               | 4.24                              |
| Luma LPF PAL    | 0.1                                | 4.81                              |
| Luma Notch NTSC | 0.09                               | 2.3/4.9/6.6                       |
| Luma Notch PAL  | 0.1                                | 3.1/5.6/6.4                       |
| Luma SSAF       | 0.04                               | 6.45                              |
| Luma CIF        | 0.127                              | 3.02                              |
| Luma QCIF       | Monotonic                          | 1.5                               |
| Chroma 0.65 MHz | Monotonic                          | 0.65                              |
| Chroma 1.0 MHz  | Monotonic                          | 1                                 |
| Chroma 1.3 MHz  | 0.09                               | 1.395                             |
| Chroma 2.0 MHz  | 0.048                              | 2.2                               |
| Chroma 3.0 MHz  | Monotonic                          | 3.2                               |
| Chroma CIF      | Monotonic                          | 0.65                              |
| Chroma QCIF     | Monotonic                          | 0.5                               |

<sup>1</sup> Pass-band ripple is the maximum fluctuation from the 0 dB response in the pass band, measured in dB. The pass band is defined to have 0 Hz to  $f_c$  (Hz) frequency limits for a low-pass filter, and 0 Hz to  $f_1$  (Hz), and  $f_2$  (Hz) to infinity for a notch filter, where  $f_c$ ,  $f_1$ , and  $f_2$  are the  $-3$  dB points.

<sup>2</sup> 3 dB bandwidth refers to the  $-3$  dB cutoff frequency.

### ED/HD Sinc Compensation Filter Response

#### Subaddress 0x33, Bit 3

The ADV7340/ADV7341 include a filter designed to counter the effect of sinc roll-off in DAC 1, DAC 2, and DAC 3 while operating in ED/HD mode. This filter is enabled by default. It can be disabled using Subaddress 0x33, Bit 3. The benefit of the filter is illustrated in Figure 66 and Figure 67.

# ADV7340/ADV7341




Figure 66. ED/HD Sinc Compensation Filter Enabled




Figure 67. ED/HD Sinc Compensation Filter Disabled

## ED/HD TEST PATTERN COLOR CONTROLS

### Subaddress 0x36 to Subaddress 0x38

Three 8-bit registers at Subaddress 0x36 to Subaddress 0x38 are used to program the output color of the internal ED/HD test pattern generator (Subaddress 0x31, Bit 2 = 1), whether it be the lines of the cross hatch pattern or the uniform field test pattern. They are not functional as color controls for external pixel data input.

The values for the luma (Y) and the color difference (Cr and Cb) signals used to obtain white, black, and saturated primary and complementary colors conform to the ITU-R BT.601-4 standard.

Table 41 shows sample color values that can be programmed into the color registers when the output standard selection is set to EIA 770.2/EIA770.3 (Subaddress 0x30, Bits[1:0] = 00).

Table 41. Sample Color Values for EIA 770.2/EIA770.3 ED/HD Output Standard Selection

| Sample Color | Y Value    | Cr Value   | Cb Value   |
|--------------|------------|------------|------------|
| White        | 235 (0xEB) | 128 (0x80) | 128 (0x80) |
| Black        | 16 (0x10)  | 128 (0x80) | 128 (0x80) |
| Red          | 81 (0x51)  | 240 (0xF0) | 90 (0x5A)  |
| Green        | 145 (0x91) | 34 (0x22)  | 54 (0x36)  |
| Blue         | 41 (0x29)  | 110 (0x6E) | 240 (0xF0) |
| Yellow       | 210 (0xD2) | 146 (0x92) | 16 (0x10)  |
| Cyan         | 170 (0xAA) | 16 (0x10)  | 166 (0xA6) |
| Magenta      | 106 (0x6A) | 222 (0xDE) | 202 (0xCA) |

## COLOR SPACE CONVERSION MATRIX

### Subaddress 0x03 to Subaddress 0x09

The internal color space conversion (CSC) matrix automatically performs all color space conversions based on the input mode programmed in the mode select register (Subaddress 0x01, Bits[6:4]). Table 42 and Table 43 show the options available in this matrix.

An SD color space conversion from RGB-in to YPrPb-out is possible. An ED/HD color space conversion from RGB-in to YPrPb-out is not possible.

Table 42. SD Color Space Conversion Options

| Input | Output <sup>1</sup> | YPrPb/RGB Out (Reg. 0x02, Bit 5) | RGB In/YCrCb In (Reg. 0x87, Bit 7) |
|-------|---------------------|----------------------------------|------------------------------------|
| YCrCb | YPrPb               | 1                                | 0                                  |
| YCrCb | RGB                 | 0                                | 0                                  |
| RGB   | YPrPb               | 1                                | 1                                  |
| RGB   | RGB                 | 0                                | 1                                  |

<sup>1</sup> CVBS/YC outputs are available for all CSC combinations.

Table 43. ED/HD Color Space Conversion Options

| Input | Output | YPrPb/RGB Out (Reg. 0x02, Bit 5) | RGB In/YCrCb In (Reg. 0x35, Bit 1) |
|-------|--------|----------------------------------|------------------------------------|
| YCrCb | YPrPb  | 1                                | 0                                  |
| YCrCb | RGB    | 0                                | 0                                  |
| RGB   | RGB    | 0                                | 1                                  |

### ED/HD Manual CSC Matrix Adjust Feature

The ED/HD manual CSC matrix adjust feature provides custom coefficient manipulation for color space conversions and is used in ED and HD modes only. The ED/HD manual CSC matrix adjust feature can be enabled using Subaddress 0x02, Bit 3.

Normally, there is no need to enable this feature because the CSC matrix automatically performs the color space conversion based on the input mode chosen (ED or HD) and the input and output color spaces selected (see Table 43). For this reason, the ED/HD manual CSC matrix adjust feature is disabled by default.

If RGB output is selected, the ED/HD CSC matrix scalar uses the following equations:

$$R = GY \times Y + RV \times Pr$$

$$G = GY \times Y - (GU \times Pb) - (GV \times Pr)$$

$$B = GY \times Y + BU \times Pb$$

Note that subtractions are implemented in hardware.

If YPrPb output is selected, the following equations are used:

$$Y = GY \times Y$$

$$Pr = RV \times Pr$$

$$Pb = BU \times Pb$$

where:

$GY$  = Subaddress 0x05, Bits[7:0] and Subaddress 0x03, Bits[1:0].

$GU$  = Subaddress 0x06, Bits[7:0] and Subaddress 0x04, Bits[7:6].

$GV$  = Subaddress 0x07, Bits[7:0] and Subaddress 0x04, Bits[5:4].

$BU$  = Subaddress 0x08, Bits[7:0] and Subaddress 0x04, Bits[3:2].

$RV$  = Subaddress 0x09, Bits[7:0] and Subaddress 0x04, Bits[1:0].

Upon power-up, the CSC matrix is programmed with the default values shown in Table 44.

**Table 44. ED/HD Manual CSC Matrix Default Values**

| Subaddress | Default |
|------------|---------|
| 0x03       | 0x03    |
| 0x04       | 0xF0    |
| 0x05       | 0x4E    |
| 0x06       | 0x0E    |
| 0x07       | 0x24    |
| 0x08       | 0x92    |
| 0x09       | 0x7C    |

When the ED/HD manual CSC matrix adjust feature is enabled, the default coefficient values in Subaddress 0x03 to Subaddress 0x09 are correct for the HD color space only. The color components are converted according to the following 1080i and 720p standards (SMPTE 274M, SMPTE 296M):

$$R = Y + 1.575Pr$$

$$G = Y - 0.468Pr - 0.187Pb$$

$$B = Y + 1.855Pb$$

The conversion coefficients should be multiplied by 315 before being written to the ED/HD CSC matrix registers. This is reflected in the default values for  $GY = 0x13B$ ,  $GU = 0x03B$ ,  $GV = 0x093$ ,  $BU = 0x248$ , and  $RV = 0x1F0$ .

If the ED/HD manual CSC matrix adjust feature is enabled and another input standard (such as ED) is used, the scale values for

$GY$ ,  $GU$ ,  $GV$ ,  $BU$ , and  $RV$  must be adjusted according to this input standard color space. The user should consider that the color component conversion could use different scale values.

For example, SMPTE 293M uses the following conversion:

$$R = Y + 1.402Pr$$

$$G = Y - 0.714Pr - 0.344Pb$$

$$B = Y + 1.773Pb$$

The programmable CSC matrix is used for external ED/HD pixel data and is not functional when internal test patterns are enabled.

### Programming the CSC Matrix

If custom manipulation of the ED/HD CSC matrix coefficients is required for a YCrCb-to-RGB color space conversion, use the following procedure:

1. Enable the ED/HD manual CSC matrix adjust feature (Subaddress 0x02, Bit 3).
2. Set the output to RGB (Subaddress 0x02, Bit 5).
3. Disable sync on PrPb (Subaddress 0x35, Bit 2).
4. Enable sync on RGB (optional) (Subaddress 0x02, Bit 4).

The  $GY$  value controls the green signal output level, the  $BU$  value controls the blue signal output level, and the  $RV$  value controls the red signal output level.

## SD LUMA AND COLOR CONTROL

### Subaddress 0x9C to Subaddress 0x9F

SD Y Scale, SD Cb Scale, and SD Cr Scale are three 10-bit control registers that scale the SD Y, Cb, and Cr output levels.

Each of these registers represents the value required to scale the Cb or Cr level from 0.0 to 2.0 times its initial value and the Y level from 0.0 to 1.5 times its initial level. The value of these 10 bits is calculated using the following equation:

$$Y, Cb, \text{ or } Cr \text{ Scale Value} = \text{Scale Factor} \times 512$$

For example, if  $\text{Scale Factor} = 1.3$

$$Y, Cb, \text{ or } Cr \text{ Scale Value} = 1.3 \times 512 = 665.6$$

$$Y, Cb, \text{ or } Cr \text{ Scale Value} = 666 \text{ (rounded to the nearest integer)}$$

$$Y, Cb, \text{ or } Cr \text{ Scale Value} = 1010 \ 0110 \ 10b$$

Subaddress 0x9C, SD Scale LSB Register = 0x2A

Subaddress 0x9D, SD Y Scale Register = 0xA6

Subaddress 0x9E, SD Cb Scale Register = 0xA6

Subaddress 0x9F, SD Cr Scale Register = 0xA6

Note that this feature affects all interlaced output signals, that is, CVBS, Y/C, YPrPb, and RGB.

# ADV7340/ADV7341

## SD HUE ADJUST CONTROL

### Subaddress 0xA0

When enabled, the SD hue adjust control register (Subaddress 0xA0) is used to adjust the hue on the SD composite and chroma outputs. This feature can be enabled using Subaddress 0x87, Bit 2.

Subaddress 0xA0 contains the bits required to vary the hue of the video data, that is, the variance in phase of the subcarrier during active video with respect to the phase of the subcarrier during the color burst. The ADV7340/ADV7341 provide a range of  $\pm 22.5^\circ$  in increments of  $0.17578125^\circ$ . For normal operation (zero adjustment), this register is set to 0x80. Values 0xFF and 0x00 represent the upper and lower limits, respectively, of the attainable adjustment in NTSC mode. Values 0xFF and 0x01 represent the upper and lower limits, respectively, of the attainable adjustment in PAL mode.

The hue adjust value is calculated using the following equation:

$$\text{Hue Adjust } (^\circ) = 0.17578125^\circ (HCR_d - 128)$$

where  $HCR_d$  is the hue adjust control register (decimal)

For example, to adjust the hue by  $+4^\circ$ , write 0x97 to the hue adjust control register.

$$\left( \frac{4}{0.17578125} \right) + 128 \approx 151d = 0x97$$

where the sum is rounded to the nearest integer.

To adjust the hue by  $-4^\circ$ , write 0x69 to the hue adjust control register.

$$\left( \frac{-4}{0.17578125} \right) + 128 \approx 105d = 0x69$$

where the sum is rounded to the nearest integer.

## SD BRIGHTNESS DETECT

### Subaddress 0xBA

The ADV7340/ADV7341 allow monitoring of the brightness level of the incoming video data. The SD brightness detect register (Subaddress 0xBA) is a read-only register.

## SD BRIGHTNESS CONTROL

### Subaddress 0xA1, Bits[6:0]

When this feature is enabled, the SD brightness/WSS control register (Subaddress 0xA1) is used to control brightness by adding a programmable setup level onto the scaled Y data. This feature can be enabled using Subaddress 0x87, Bit 3.

For NTSC with pedestal, the setup can vary from 0 IRE to 22.5 IRE. For NTSC without pedestal and for PAL, the setup can vary from  $-7.5$  IRE to  $+15$  IRE.

The SD brightness control register is an 8-bit register. The seven LSBs of this 8-bit register are used to control the brightness level, which can be a positive or negative value.

For example, to add  $+20$  IRE brightness level to an NTSC signal with pedestal, write 0x28 to Subaddress 0xA1.

$$0 \times (\text{SD Brightness Value}) =$$

$$0 \times (\text{IRE Value} \times 2.015631) =$$

$$0 \times (20 \times 2.015631) = 0 \times (40.31262) \approx 0x28$$

To add  $-7$  IRE brightness level to a PAL signal, write 0x72 to Subaddress 0xA1.

$$0 \times (\text{SD Brightness Value}) =$$

$$0 \times (\text{IRE Value} \times 2.075631) =$$

$$0 \times (7 \times 2.015631) = 0x(14.109417) \approx 0001110b$$

$$0001110b \text{ into twos complement} = 1110010b = 0x72$$

Table 45. Sample Brightness Control Values<sup>1</sup>

| Setup Level (NTSC) with Pedestal | Setup Level (NTSC) Without Pedestal | Setup Level (PAL) | Brightness Control Value |
|----------------------------------|-------------------------------------|-------------------|--------------------------|
| 22.5 IRE                         | 15 IRE                              | 15 IRE            | 0x1E                     |
| 15 IRE                           | 7.5 IRE                             | 7.5 IRE           | 0x0F                     |
| 7.5 IRE                          | 0 IRE                               | 0 IRE             | 0x00                     |
| 0 IRE                            | $-7.5$ IRE                          | $-7.5$ IRE        | 0x71                     |

<sup>1</sup> Values in the range of 0x3F to 0x44 could result in an invalid output signal.

## SD INPUT STANDARD AUTO DETECTION

### Subaddress 0x87, Bit 5

The ADV7340/ADV7341 include an SD input standard auto-detect feature. This SD feature can be enabled by setting Subaddress 0x87, Bit 5 to 1.

When enabled, the ADV7340/ADV7341 can automatically identify an NTSC or PAL B/D/G/H/I input stream. The ADV7340/ADV7341 automatically update the subcarrier frequency registers with the appropriate value for the identified standard. The ADV7340/ADV7341 are also configured to correctly encode the identified standard.

The SD standard bits (Subaddress 0x80, Bits[1:0]) and the subcarrier frequency registers are not updated to reflect the identified standard. All registers retain their default or user-defined values.




Figure 68. Examples of Brightness Control Values



## DOUBLE BUFFERING

### **Subaddress 0x33, Bit 7 for ED/HD, Subaddress 0x88, Bit 2 for SD**

Double-buffered registers are updated once per field. Double buffering improves overall performance because modifications to register settings are not made during active video, but take effect prior to the start of the active video on the next field.

Double buffering can be activated on the following ED/HD registers using Subaddress 0x33, Bit 7: ED/HD Gamma A and Gamma B curves, and ED/HD CGMS registers.

Double buffering can be activated on the following SD registers using Subaddress 0x88, Bit 2: SD Gamma A and Gamma B curves, SD Y scale, SD Cr scale, SD Cb scale, SD brightness, SD closed captioning, and SD Macrovision Bits[5:0] (Subaddress 0xE0, Bits[5:0]).

## PROGRAMMABLE DAC GAIN CONTROL


### **Subaddress 0x0A to Subaddress 0x0B**

It is possible to adjust the DAC output signal gain up or down from its absolute level. This is illustrated in Figure 69.

DAC 4 to DAC 6 are controlled by Register 0x0A.

DAC 1 to DAC 3 are controlled by Register 0x0B.

#### CASE A



#### CASE B




Figure 69. Programmable DAC Gain—Positive and Negative Gain

In Case A of Figure 69, the video output signal is gained. The absolute level of the sync tip and blanking level both increase with respect to the reference video output signal. The overall gain of the signal is increased from the reference signal.

In Case B of Figure 69, the video output signal is reduced. The absolute level of the sync tip and blanking level both decrease

with respect to the reference video output signal. The overall gain of the signal is reduced from the reference signal.

The range of this feature is specified for  $\pm 7.5\%$  of the nominal output from the DACs. For example, if the output current of the DAC is 4.33 mA, the DAC gain control feature can change this output current from 4.008 mA ( $-7.5\%$ ) to 4.658 mA ( $+7.5\%$ ).

The reset value of the control registers is 0x00, that is, nominal DAC current is output. Table 46 is an example of how the output current of the DACs varies for a nominal 4.33 mA output current.

Table 46. DAC Gain Control

| Reg. 0x0A or Reg. 0x0B | DAC Current (mA) | % Gain   | Note                 |
|------------------------|------------------|----------|----------------------|
| 0100 0000 (0x40)       | 4.658            | 7.5000%  | Reset value, nominal |
| 0011 1111 (0x3F)       | 4.653            | 7.3820%  |                      |
| 0011 1110 (0x3E)       | 4.648            | 7.3640%  |                      |
| ...                    | ...              | ...      |                      |
| ...                    | ...              | ...      |                      |
| 0000 0010 (0x02)       | 4.43             | 0.0360%  |                      |
| 0000 0001 (0x01)       | 4.38             | 0.0180%  |                      |
| 0000 0000 (0x00)       | 4.33             | 0.0000%  |                      |
| 1111 1111 (0xFF)       | 4.25             | -0.0180% |                      |
| 1111 1110 (0xFE)       | 4.23             | -0.0360% |                      |
| ...                    | ...              | ...      |                      |
| ...                    | ...              | ...      |                      |
| 1100 0010 (0xC2)       | 4.018            | -7.3640% |                      |
| 1100 0001 (0xC1)       | 4.013            | -7.3820% |                      |
| 1100 0000 (0xC0)       | 4.008            | -7.5000% |                      |

## GAMMA CORRECTION

### **Subaddress 0x44 to Subaddress 0x57 for ED/HD, Subaddress 0xA6 to Subaddress 0xB9 for SD**

Generally, gamma correction is applied to compensate for the nonlinear relationship between signal input and output brightness level (as perceived on a CRT). It can also be applied wherever nonlinear processing is used.

Gamma correction uses the function

$$Signal_{OUT} = (Signal_{IN})^{\gamma}$$

where  $\gamma$  is the gamma correction factor.

Gamma correction is available for SD and ED/HD video. For both variations, there are 20, 8-bit registers. They are used to program the Gamma Correction Curve A and Gamma Correction Curve B.

ED/HD gamma correction is enabled using Subaddress 0x35, Bit 5. ED/HD Gamma Correction Curve A is programmed at Subaddress 0x44 to Subaddress 0x4D, and ED/HD Gamma Correction Curve B is programmed at Subaddress 0x4E to Subaddress 0x57.

## ADV7340/ADV7341

SD gamma correction is enabled using Subaddress 0x88, Bit 6. SD Gamma Correction Curve A is programmed at Subaddress 0xA6 to Subaddress 0xAF, and SD Gamma Correction Curve B is programmed at Subaddress 0xB0 to Subaddress 0xB9.

Gamma correction is performed on the luma data only. The user can choose one of two correction curves, Curve A or Curve B. Only one of these curves can be used at a time. For ED/HD gamma correction, curve selection is controlled using Subaddress 0x35, Bit 4. For SD gamma correction, curve selection is controlled using Subaddress 0x88, Bit 7.

The shape of the gamma correction curve is controlled by defining the curve response at 10 different locations along the curve. By altering the response at these locations, the shape of the gamma correction curve can be modified. Between these points, linear interpolation is used to generate intermediate values. Considering the curve has a total length of 256 points, the 10 programmable locations are at points 24, 32, 48, 64, 80, 96, 128, 160, 192, and 224. Locations 0, 16, 240, and 255 are fixed and cannot be changed.

From curve locations 16 to 240, the values at the programmable locations and, therefore, the response of the gamma correction curve should be calculated to produce the following result:

$$X_{DESIRED} = (X_{INPUT})^{\gamma}$$

where:

$X_{DESIRED}$  is the desired gamma corrected output.

$X_{INPUT}$  is the linear input signal.

$\gamma$  is the gamma correction factor.

To program the gamma correction registers, calculate the 10 programmable curve values using the following formula:

$$\gamma_n = \left( \left( \frac{n-16}{240-16} \right)^{\gamma} \times (240-16) \right) + 16$$

where:

$\gamma_n$  is the value to be written into the gamma correction register for point  $n$  on the gamma correction curve.

$n = 24, 32, 48, 64, 80, 96, 128, 160, 192, \text{ or } 224$ .

$\gamma$  is the gamma correction factor.

For example, setting  $\gamma = 0.5$  for all programmable curve data points results in the following  $\gamma_n$  values:

$$\gamma_{24} = [(8/224)^{0.5} \times 224] + 16 = 58$$

$$\gamma_{32} = [(16/224)^{0.5} \times 224] + 16 = 76$$

$$\gamma_{48} = [(32/224)^{0.5} \times 224] + 16 = 101$$

$$\gamma_{64} = [(48/224)^{0.5} \times 224] + 16 = 120$$

$$\gamma_{80} = [(64/224)^{0.5} \times 224] + 16 = 136$$

$$\gamma_{96} = [(80/224)^{0.5} \times 224] + 16 = 150$$

$$\gamma_{128} = [(112/224)^{0.5} \times 224] + 16 = 174$$

$$\gamma_{160} = [(144/224)^{0.5} \times 224] + 16 = 195$$

$$\gamma_{192} = [(176/224)^{0.5} \times 224] + 16 = 214$$

$$\gamma_{224} = [(208/224)^{0.5} \times 224] + 16 = 232$$

where the sum of each equation is rounded to the nearest integer.

The gamma curves in Figure 70 and Figure 71 are examples only; any user-defined curve in the range from 16 to 240 is acceptable.




Figure 70. Signal Input (Ramp) and Signal Output for Gamma 0.5




Figure 71. Signal Input (Ramp) and Selectable Output Curves

## ED/HD SHARPNESS FILTER AND ADAPTIVE FILTER CONTROLS

### Subaddress 0x40, Subaddress 0x58 to Subaddress 0x5D

There are three filter modes available on the ADV7340/ADV7341: a sharpness filter mode and two adaptive filter modes.

#### ED/HD Sharpness Filter Mode

To enhance or attenuate the Y signal in the frequency ranges shown in Figure 72, the ED/HD sharpness filter must be enabled (Subaddress 0x31, Bit 7) and the ED/HD adaptive filter must be disabled (Subaddress 0x35, Bit 7).

To select one of the 256 individual responses, the corresponding gain values, which range from  $-8$  to  $+7$  for each filter, must be programmed into the ED/HD sharpness filter gain register at Subaddress 0x40.

#### ED/HD Adaptive Filter Mode

The ED/HD Adaptive Filter Threshold A, B, and C registers, the ED/HD Adaptive Filter Gain 1, 2, and 3 registers, and the ED/HD sharpness filter gain register are used in adaptive filter mode. To activate the adaptive filter control, the ED/HD sharpness filter and the ED/HD adaptive filter must be enabled (Subaddress 0x31, Bit 7, and Subaddress 0x35, Bit 7, respectively).

The derivative of the incoming signal is compared to the three programmable threshold values: ED/HD Adaptive Filter Threshold A, B, and C (Subaddress 0x5B, Subaddress 0x5C, and Subaddress 0x5D, respectively). The recommended threshold range is 16 to 235, although any value in the range of 0 to 255 can be used.

The edges can then be attenuated with the settings in the ED/HD Adaptive Filter Gain 1, 2, and 3 registers (Subaddress 0x58, Subaddress 0x59, and Subaddress 0x5A, respectively), and the ED/HD sharpness filter gain register (Subaddress 0x40).

There are two adaptive filter modes available. The mode is selected using the ED/HD adaptive filter mode control (Subaddress 0x35, Bit 6):

- Mode A is used when the ED/HD adaptive filter mode control is set to 0. In this case, Filter B (LPF) is used in the adaptive filter block. In addition, only the programmed values for Gain B in the ED/HD sharpness filter gain register and ED/HD Adaptive Filter Gain 1, 2, and 3 registers are applied when needed. The Gain A values are fixed and cannot be changed.
- Mode B is used when ED/HD adaptive filter mode control is set to 1. In this mode, a cascade of Filter A and Filter B is used. Both settings for Gain A and Gain B in the ED/HD sharpness filter gain register and ED/HD Adaptive Filter Gain 1, 2, and 3 registers become active when needed.




Figure 72. ED/HD Sharpness and Adaptive Filter Control Block

# ADV7340/ADV7341




Figure 73. ED/HD Sharpness Filter Control with Different Gain Settings for ED/HD Sharpness Filter Gain Values

## ED/HD SHARPNESS FILTER AND ADAPTIVE FILTER APPLICATION EXAMPLES

### Sharpness Filter Application

The ED/HD sharpness filter can be used to enhance or attenuate the Y video output signal. The register settings in Table 47 were used to achieve the results shown in Figure 73. Input data was generated by an external signal source.

Table 47. ED/HD Sharpness Control

| Subaddress | Register Setting | Reference <sup>1</sup> |
|------------|------------------|------------------------|
| 0x00       | 0xFC             |                        |
| 0x01       | 0x10             |                        |
| 0x02       | 0x20             |                        |
| 0x30       | 0x00             |                        |
| 0x31       | 0x81             |                        |
| 0x40       | 0x00             | a                      |
| 0x40       | 0x08             | b                      |
| 0x40       | 0x04             | c                      |
| 0x40       | 0x40             | d                      |
| 0x40       | 0x80             | e                      |
| 0x40       | 0x22             | f                      |

<sup>1</sup> See Figure 73.




Figure 74. Input Signal to ED/HD Adaptive Filter

### Adaptive Filter Control Application

The register settings in Table 48 are used to obtain the results shown in Figure 75, that is, to remove the ringing on the input Y signal, as shown in Figure 74. Input data is generated by an external signal source.

Table 48. Register Settings for Figure 75

| Subaddress | Register Setting |
|------------|------------------|
| 0x00       | 0xFC             |
| 0x01       | 0x38             |
| 0x02       | 0x20             |
| 0x30       | 0x00             |
| 0x31       | 0x81             |
| 0x35       | 0x80             |
| 0x40       | 0x00             |
| 0x58       | 0xAC             |
| 0x59       | 0x9A             |
| 0x5A       | 0x88             |
| 0x5B       | 0x28             |
| 0x5C       | 0x3F             |
| 0x5D       | 0x64             |




Figure 75. Output Signal from ED/HD Adaptive Filter (Mode A)

When changing the adaptive filter mode to Mode B (Subaddress 0x35, Bit 6), the output shown in Figure 76 can be obtained.




Figure 76. Output Signal from ED/HD Adaptive Filter (Mode B)

## SD DIGITAL NOISE REDUCTION

### Subaddress 0xA3 to Subaddress 0xA5

Digital noise reduction (DNR) is applied to the Y data only. A filter block selects the high frequency, low amplitude components of the incoming signal (DNR input select). The absolute value of the filter output is compared to a programmable threshold value (DNR threshold control). There are two DNR modes available: DNR mode and DNR sharpness mode.

In DNR mode, if the absolute value of the filter output is smaller than the threshold, it is assumed to be noise. A programmable amount (coring gain border, coring gain data) of this noise signal is subtracted from the original signal. In DNR sharpness mode, if the absolute value of the filter output is less than the programmed threshold, it is assumed to be noise. Otherwise, if the level exceeds the threshold, now identified as a valid signal, a fraction of the signal (coring gain border, coring gain data) is added to the original signal to boost high frequency components and sharpen the video image.

In MPEG systems, it is common to process the video information in blocks of 8 pixels × 8 pixels for MPEG2 systems, or 16 pixels × 16 pixels for MPEG1 systems (block size control). DNR can be applied to the resulting block transition areas that are known to contain noise. Generally, the block transition area contains two pixels. It is possible to define this area to contain four pixels (border area).

It is also possible to compensate for variable block positioning or differences in YCrCb pixel timing with the use of the DNR block offset.

The digital noise reduction registers are three 8-bit registers. They are used to control the DNR processing.




Figure 77. SD DNR Block Diagram

### Coring Gain Border—Subaddress 0xA3, Bits[3:0]

These four bits are assigned to the gain factor applied to border areas. In DNR mode, the range of gain values is 0 to 1 in increments of 1/8. This factor is applied to the DNR filter output that lies below the set threshold range. The result is then subtracted from the original signal.


In DNR sharpness mode, the range of gain values is 0 to 0.5 in increments of 1/16. This factor is applied to the DNR filter output that lies above the threshold range. The result is added to the original signal.

### Coring Gain Data—Subaddress 0xA3, Bits[7:4]

These four bits are assigned to the gain factor applied to the luma data inside the MPEG pixel block. In DNR mode, the range of gain values is 0 to 1 in increments of 1/8. This factor is applied to the DNR filter output that lies below the set threshold range. The result is then subtracted from the original signal.

In DNR sharpness mode, the range of gain values is 0 to 0.5 in increments of 1/16. This factor is applied to the DNR filter output that lies above the threshold range. The result is added to the original signal.

# ADV7340/ADV7341




## DNR Threshold—Subaddress 0xA4, Bits[5:0]

These six bits are used to define the threshold value in the range of 0 to 63. The range is an absolute value.

## Border Area—Subaddress 0xA4, Bit 6

When this bit is set to Logic 1, the block transition area can be defined to consist of four pixels. If this bit is set to Logic 0, the border transition area consists of two pixels, where one pixel refers to two clock cycles at 27 MHz.




## Block Size Control—Subaddress 0xA4, Bit 7

This bit is used to select the size of the data blocks to be processed. Setting the block size control function to Logic 1 defines a 16 pixel  $\times$  16 pixel data block, and Logic 0 defines an 8 pixel  $\times$  8 pixel data block, where one pixel refers to two clock cycles at 27 MHz.

## DNR Input Select Control—Subaddress 0xA5, Bits[2:0]

Three bits are assigned to select the filter, which is applied to the incoming Y data. The signal that lies in the pass band of the selected filter is the signal that is DNR processed. Figure 80 shows the filter responses selectable with this control.



## DNR Mode Control—Subaddress 0xA5, Bit 4

This bit controls the DNR mode selected. Logic 0 selects DNR mode; Logic 1 selects DNR sharpness mode.

DNR works on the principle of defining low amplitude, high frequency signals as probable noise and subtracting this noise from the original signal.

In DNR mode, it is possible to subtract a fraction of the signal that lies below the set threshold, assumed to be noise, from the original signal. The threshold is set in DNR Register 1.

When DNR sharpness mode is enabled, it is possible to add a fraction of the signal that lies above the set threshold to the original signal, because this data is assumed to be valid data and not noise. The overall effect is that the signal is boosted (similar to using the extended SSAF filter).

## DNR Block Offset Control—Subaddress 0xA5, Bits[7:4]

Four bits are assigned to this control, which allows a shift of the data block of 15 pixels maximum. Consider the coring gain positions fixed. The block offset shifts the data in steps of one pixel such that the border coring gain factors can be applied at the same position regardless of variations in input timing of the data.

## SD ACTIVE VIDEO EDGE CONTROL

### Subaddress 0x82, Bit 7

The ADV7340/ADV7341 are able to control fast rising and falling signals at the start and end of active video in order to minimize ringing.

When the active video edge control feature is enabled (Subaddress 0x82, Bit 7 = 1), the first three pixels and the last three pixels of the active video on the luma channel are scaled so that maximum transitions on these pixels are not possible.

At the start of active video, the first three pixels are multiplied by 1/8, 1/2, and 7/8, respectively. Approaching the end of active video, the last three pixels are multiplied by 7/8, 1/2, and 1/8, respectively. All other active video pixels pass through unprocessed.




Figure 81. Example of Active Video Edge Functionality




Figure 82. Example of Video Output with Subaddress 0x82, Bit 7 = 0




Figure 83. Example of Video Output with Subaddress 0x82, Bit 7 = 1

# ADV7340/ADV7341

## EXTERNAL HORIZONTAL AND VERTICAL SYNCHRONIZATION CONTROL

For synchronization purposes, the ADV7340/ADV7341 are able to accept either time codes embedded in the input pixel data or external synchronization signals provided on the  $\overline{S\_HSYNC}$ ,  $\overline{S\_VSYNC}$ ,  $\overline{P\_HSYNC}$ ,  $\overline{P\_VSYNC}$ , and  $\overline{P\_BLANK}$  pins (see Table 49). It is also possible to output synchronization signals on the  $\overline{S\_HSYNC}$  and  $\overline{S\_VSYNC}$  pins (see Table 50 to Table 52).

**Table 49. Timing Synchronization Signal Input Options**

| Signal                      | Pin                   | Condition   |
|-----------------------------|-----------------------|---|
| SD $\overline{HSYNC}$ In    | $\overline{S\_HSYNC}$ | SD Slave Timing Mode 1, 2, or 3 selected (Subaddress 0x8A[2:0]). <sup>1</sup> |
| SD $\overline{VSYNC}$ In    | $\overline{S\_VSYNC}$ | SD Slave Timing Mode 1, 2, or 3 selected (Subaddress 0x8A[2:0]). <sup>1</sup> |
| ED/HD $\overline{HSYNC}$ In | $\overline{P\_HSYNC}$ | ED/HD Timing Sync. Inputs enabled (Subaddress 0x30, Bit 2 = 0).               |
| ED/HD $\overline{VSYNC}$ In | $\overline{P\_VSYNC}$ | ED/HD Timing Sync. Inputs enabled (Subaddress 0x30, Bit 2 = 0).               |
| ED/HD $\overline{BLANK}$ In | $\overline{P\_BLANK}$ |   |

<sup>1</sup>SD and ED/HD timing sync. Outputs must also be disabled (Subaddress 0x02[7:6] = 00).

**Table 50. Timing Synchronization Signal Output Options**

| Signal                       | Pin                   | Condition  |
|------------------------------|-----------------------|--|
| SD $\overline{HSYNC}$ Out    | $\overline{S\_HSYNC}$ | SD Timing Sync. Outputs enabled (Subaddress 0x02, Bit 6 = 1). <sup>1</sup> |
| SD $\overline{VSYNC}$ Out    | $\overline{S\_VSYNC}$ | SD Timing Sync. Outputs enabled (Subaddress 0x02, Bit 6 = 1). <sup>1</sup> |
| ED/HD $\overline{HSYNC}$ Out | $\overline{S\_HSYNC}$ | ED/HD Timing Sync. Outputs enabled (Subaddress 0x02, Bit 7 = 1).           |
| ED/HD $\overline{VSYNC}$ Out | $\overline{S\_VSYNC}$ | ED/HD Timing Sync. Outputs enabled (Subaddress 0x02, Bit 7 = 1).           |

<sup>1</sup>ED/HD timing sync. Outputs must also be disabled (Subaddress 0x02, Bit 7 = 0).

**Table 51.  $\overline{HSYNC}$  Output Control<sup>1</sup>**

| ED/HD Input Sync Format (0x30, Bit 2) | ED/HD $\overline{HSYNC}$ Control (0x34, Bit 1) | ED/HD Sync Output Enable (0x02, Bit 7) | SD Sync Output Enable (0x02, Bit 6) | Signal on $\overline{S\_HSYNC}$ Pin                             | Duration                              |
|---------------------------------------|--|--|-------------------------------------|---|---------------------------------------|
| x                                     | x  | 0                                      | 0                                   | Tristate.   | –                                     |
| x                                     | x  | 0                                      | 1                                   | Pipelined SD $\overline{HSYNC}$ .                               | See Appendix 5—SD Timing.             |
| 0                                     | 0  | 1                                      | x                                   | Pipelined ED/HD $\overline{HSYNC}$ .                            | As per $\overline{HSYNC}$ timing.     |
| 1                                     | 0  | 1                                      | x                                   | Pipelined ED/HD $\overline{HSYNC}$ based on AV Code H bit.      | Same as line blanking interval.       |
| x                                     | 1  | 1                                      | x                                   | Pipelined ED/HD $\overline{HSYNC}$ based on horizontal counter. | Same as embedded $\overline{HSYNC}$ . |

<sup>1</sup> In all ED/HD standards where there is a  $\overline{HSYNC}$  output, the start of the  $\overline{HSYNC}$  pulse is aligned with the falling edge of the embedded  $\overline{HSYNC}$  in the output video.

**Table 52.  $\overline{VSYNC}$  Output Control<sup>1</sup>**

| ED/HD Input Sync Format (0x30, Bit 2) | ED/HD $\overline{VSYNC}$ Control (0x34, Bit 2) | ED/HD Sync Output Enable (0x02, Bit 7) | SD Sync Output Enable (0x02, Bit 6) | Video Standard                  | Signal on $\overline{S\_VSYNC}$ Pin                           | Duration  |
|---------------------------------------|--|--|-------------------------------------|---------------------------------|---|---|
| x                                     | X  | 0                                      | 0                                   | x                               | Tristate.   | –   |
| x                                     | X  | 0                                      | 1                                   | Interlaced                      | Pipelined SD $\overline{VSYNC}$ /Field.                       | See Appendix 5—SD Timing.                         |
| 0                                     | 0  | 1                                      | x                                   | x                               | Pipelined ED/HD $\overline{VSYNC}$ or field signal.           | As per $\overline{VSYNC}$ or field signal timing. |
| 1                                     | 0  | 1                                      | x                                   | All HD interlaced standards     | Pipelined field signal based on AV Code F bit.                | Field.  |
| 1                                     | 0  | 1                                      | x                                   | All ED/HD progressive standards | Pipelined $\overline{VSYNC}$ based on AV Code V bit.          | Vertical blanking interval.                       |
| x                                     | 1  | 1                                      | x                                   | All ED/HD standards except 525p | Pipelined ED/HD $\overline{VSYNC}$ based on vertical counter. | Aligned with serration lines.                     |
| x                                     | 1  | 1                                      | x                                   | 525p                            | Pipelined ED/HD $\overline{VSYNC}$ based on vertical counter. | Vertical blanking interval.                       |

<sup>1</sup> In all ED/HD standards where there is a  $\overline{VSYNC}$  output, the start of the  $\overline{VSYNC}$  pulse is aligned with the falling edge of the embedded  $\overline{VSYNC}$  in the output video.



## LOW POWER MODE

### Subaddress 0x0D, Bits[2:0]

For power sensitive applications, the ADV7340/ADV7341 support an Analog Devices, Inc. proprietary low power mode of operation on DAC 1, DAC 2, and DAC 3. To utilize this low power mode, these DACs must be operating in full-drive mode ( $R_{SET} = 510\ \Omega$ ,  $R_L = 37.5\ \Omega$ ). Low power mode is not available in low drive mode ( $R_{SET} = 4.12\ k\Omega$ ,  $R_L = 300\ \Omega$ ). Low power mode can be independently enabled or disabled on DAC 1, DAC 2, and DAC 3 using Subaddress 0x0D, Bits[2:0]. Low power mode is disabled by default on each DAC.

In low power mode, DAC current consumption is content dependent. On a typical video stream, it can be reduced by as much as 40%. For applications requiring the highest possible video performance, low power mode should be disabled.

## CABLE DETECTION

### Subaddress 0x10

The ADV7340/ADV7341 include an Analog Devices, Inc. proprietary cable detection feature.

The cable detection feature is available on DAC 1 and DAC 2, while operating in full-drive mode ( $R_{SET1} = 510\ \Omega$ ,  $R_{L1} = 37.5\ \Omega$ , assuming a connected cable). The feature is not available in low drive mode ( $R_{SET} = 4.12\ k\Omega$ ,  $R_L = 300\ \Omega$ ). For a DAC to be monitored, the DAC must be powered up in Subaddress 0x00.

The cable detection feature can be used with all SD, ED, and HD video standards. It is available for all output configurations, that is, CVBS, YC, YPrPb, and RGB output configurations.

For CVBS/YC output configurations, both DAC 1 and DAC 2 are monitored, that is, the CVBS and YC luma outputs are monitored. For YPrPb and RGB output configurations, only DAC 1 is monitored, that is, the luma or green output is monitored.

Once per frame, the ADV7340/ADV7341 monitor DAC 1 and/or DAC 2, updating Subaddress 0x10, Bit 0 and Bit 1, respectively. If a cable is detected on one of the DACs, the relevant bit is set to 0. If not, the bit is set to 1.

## DAC AUTO POWER-DOWN

### Subaddress 0x10, Bit 4

For power sensitive applications, a DAC auto power-down feature can be enabled using Subaddress 0x10, Bit 4. This feature is only available when the cable detection feature is enabled.

With this feature enabled, the cable detection circuitry monitors DAC 1 and/or DAC 2 once per frame. If they are unconnected, some or all of the DACs automatically power down. Which DAC or DACs are powered down depends on the selected output configuration.

For CVBS/YC output configurations, if DAC 1 is unconnected, only DAC 1 powers down. If DAC 2 is unconnected, DAC 2 and DAC 3 power down.

For YPrPb and RGB output configurations, if DAC 1 is unconnected, all three DACs power down. DAC 2 is not monitored for YPrPb and RGB output configurations.

Once per frame, DAC 1 and/or DAC 2 are monitored. If a cable is detected, the appropriate DAC or DACs remain powered up for the duration of the frame. If no cable is detected, the appropriate DAC or DACs power down until the next frame when the process is repeated.

## PIXEL AND CONTROL PORT READBACK

### Subaddress 0x12 to Subaddress 0x16

The ADV7340/ADV7341 support the readback of most digital inputs via the I<sup>2</sup>C/SPI MPU port. This feature is useful for board-level connectivity testing with upstream devices.

The pixel port (S[9:0], Y[9:0], and C[9:0]), the control port (S\_HSYNC, S\_VSYNC, P\_HSYNC, P\_VSYNC and P\_BLANK), and the SFL/MISO pin are available for readback via the MPU port. The readback registers are located at Subaddress 0x12 to Subaddress 0x16.

When using this feature, a clock signal should be applied to the CLKIN\_A pin in order to register the levels applied to the input pins.

## RESET MECHANISM

### Subaddress 0x17, Bit 1

The ADV7340/ADV7341 have a software reset accessible via the I<sup>2</sup>C/SPI MPU port. A software reset is activated by writing a 1 to Subaddress 0x17, Bit 1. This resets all registers to their default values. This bit is self-clearing, that is, after a 1 has been written to the bit, the bit automatically returns to 0.

When operating in SPI mode, a software reset does not cause the device to revert to I<sup>2</sup>C mode. For this to occur, the ADV7340/ADV7341 need to be powered down.

The ADV7340/ADV7341 include a power-on reset (POR) circuit to ensure correct operation after power-up.

# ADV7340/ADV7341

## PRINTED CIRCUIT BOARD LAYOUT AND DESIGN

### DAC CONFIGURATIONS

The ADV7340/ADV7341 contain six DACs. All six DACs can be configured to operate in low drive mode. Low drive mode is defined as 4.33 mA full-scale current into a 300  $\Omega$  load,  $R_L$ .

DAC 1, DAC 2, and DAC 3 can also be configured to operate in full-drive mode. Full-drive mode is defined as 34.7 mA full-scale current into a 37.5  $\Omega$  load,  $R_L$ . Full-drive is the recommended mode of operation for DAC 1, DAC 2, and DAC 3.

The ADV7340/ADV7341 contain two  $R_{SET}$  pins. A resistor connected between the  $R_{SET1}$  pin and AGND is used to control the full-scale output current and, therefore, the DAC output voltage levels of DAC 1, DAC 2, and DAC 3. For low drive operation,  $R_{SET1}$  must have a value of 4.12 k $\Omega$ , and  $R_L$  must have a value of 300  $\Omega$ . For full-drive operation,  $R_{SET1}$  must have a value of 510  $\Omega$ , and  $R_L$  must have a value of 37.5  $\Omega$ .

A resistor connected between the  $R_{SET2}$  pin and AGND is used to control the full-scale output current and, therefore, the DAC output voltage levels of DAC 4, DAC 5, and DAC 6.  $R_{SET2}$  must have a value of 4.12 k $\Omega$ , and  $R_L$  must have a value of 300  $\Omega$  (that is, low drive operation only).

The resistors connected to the  $R_{SET1}$  and  $R_{SET2}$  pins should have a 1% tolerance.

The ADV7340/ADV7341 contain two compensation pins, COMP1 and COMP2. A 2.2 nF compensation capacitor should be connected from each of these pins to  $V_{AA}$ .

### VOLTAGE REFERENCE

The ADV7340/ADV7341 contain an on-chip voltage reference that can be used as a board-level voltage reference via the  $V_{REF}$  pin. Alternatively, the ADV7340/ADV7341 can be used with an external voltage reference by connecting the reference source to the  $V_{REF}$  pin. For optimal performance, an external voltage reference such as the AD1580 should be used with the ADV7340/ADV7341. If an external voltage reference is not used, a 0.1  $\mu$ F capacitor should be connected from the  $V_{REF}$  pin to  $V_{AA}$ .

### VIDEO OUTPUT BUFFER AND OPTIONAL OUTPUT FILTER

An output buffer is necessary on any DAC that operates in low drive mode ( $R_{SET} = 4.12$  k $\Omega$ ,  $R_L = 300$   $\Omega$ ). Analog Devices, Inc. produces a range of op amps suitable for this application, for example, the AD8061. For more information about line driver buffering circuits, see the relevant op amp data sheet.

An optional reconstruction (anti-imaging) low-pass filter (LPF) may be required on the ADV7340/ADV7341 DAC outputs if the part is connected to a device that requires this filtering.

The filter specifications vary with the application. The use of 16 $\times$  (SD), 8 $\times$  (ED), or 4 $\times$  (HD) oversampling can remove the requirement for a reconstruction filter altogether.

For applications requiring an output buffer and reconstruction filter, the ADA4430-1, ADA4411-3, and ADA4410-6 integrated video filter buffers should be considered.

Table 53. ADV7340/ADV7341 Output Rates

| Input Mode (0x01, Bits[6:4]) | PLL Control (0x00, Bit 1) | Output Rate (MHz) |       |
|------------------------------|---------------------------|-------------------|-------|
| SD Only                      | Off                       | 27                | (2x)  |
|                              | On                        | 216               | (16x) |
| ED Only                      | Off                       | 27                | (1x)  |
|                              | On                        | 216               | (8x)  |
| HD Only                      | Off                       | 74.25             | (1x)  |
|                              | On                        | 297               | (4x)  |

Table 54. Output Filter Requirements

| Application | Oversampling | Cutoff Frequency (MHz) | Attenuation -50 dB @ (MHz) |
|-------------|--------------|------------------------|----------------------------|
| SD          | 2 $\times$   | >6.5                   | 20.5                       |
| SD          | 16 $\times$  | >6.5                   | 209.5                      |
| ED          | 1 $\times$   | >12.5                  | 14.5                       |
| ED          | 8 $\times$   | >12.5                  | 203.5                      |
| HD          | 1 $\times$   | >30                    | 44.25                      |
| HD          | 4 $\times$   | >30                    | 267                        |




Figure 84. Example of Output Filter for SD, 16 $\times$  Oversampling




Figure 85. Example of Output Filter for ED, 8 $\times$  Oversampling




Figure 86. Example of Output Filter for HD, 4 $\times$  Oversampling




Figure 87. Output Filter Plot for SD, 16x Oversampling




Figure 88. Output Filter Plot for ED, 8x Oversampling




Figure 89. Output Filter Plot for HD, 4x Oversampling

## PRINTED CIRCUIT BOARD (PCB) LAYOUT

The ADV7340/ADV7341 are highly integrated circuits containing both precision analog and high speed digital circuitry. They have been designed to minimize interference effects on the integrity of the analog circuitry by the high speed digital circuitry. It is imperative that these same design and layout techniques be applied to the system-level design so that optimal performance is achieved.

The layout should be optimized for lowest noise on the ADV7340/ADV7341 power and ground planes by shielding the digital inputs and providing good power supply decoupling.

It is recommended to use a 4-layer printed circuit board with ground and power planes separating the signal trace layer and the solder side layer.

## Component Placement

Component placement should be carefully considered to separate noisy circuits, such as clock signals and high speed digital circuitry from analog circuitry.

The external loop filter components and components connected to the COMP,  $V_{REF}$ , and  $R_{SET}$  pins should be placed as close as possible to and on the same side of the PCB as the ADV7340/ADV7341. Adding vias to the PCB to get the components closer to the ADV7340/ADV7341 is not recommended.

It is recommended that the ADV7340/ADV7341 be placed as close as possible to the output connector, with the DAC output traces as short as possible.

The termination resistors on the DAC output traces should be placed as close as possible to and on the same side of the PCB as the ADV7340/ADV7341. The termination resistors should overlay the PCB ground plane.

External filter and buffer components connected to the DAC outputs should be placed as close as possible to the ADV7340/ADV7341 to minimize the possibility of noise pickup from neighboring circuitry, and to minimize the effect of trace capacitance on output bandwidth. This is particularly important when operating in low drive mode ( $R_{SET} = 4.12 \text{ k}\Omega$ ,  $R_L = 300 \Omega$ ).

## Power Supplies

It is recommended that a separate regulated supply be provided for each power domain ( $V_{AA}$ ,  $V_{DD}$ ,  $V_{DD\_IO}$ , and  $PV_{DD}$ ). For optimal performance, linear regulators rather than switch mode regulators should be used. If switch mode regulators must be used, care must be taken with regard to the quality of the output voltage in terms of ripple and noise. This is particularly true for the  $V_{AA}$  and  $PV_{DD}$  power domains. Each power supply should be individually connected to the system power supply at a single point through a suitable filtering device, such as a ferrite bead.

## ADV7340/ADV7341

### **Power Supply Decoupling**

It is recommended that each power supply pin be decoupled with 10 nF and 0.1  $\mu$ F ceramic capacitors. The  $V_{AA}$ ,  $PV_{DD}$ ,  $V_{DD\_IO}$ , and both  $V_{DD}$  pins should be individually decoupled to ground. The decoupling capacitors should be placed as close as possible to the ADV7340/ADV7341 with the capacitor leads kept as short as possible to minimize lead inductance.

A 1  $\mu$ F tantalum capacitor is recommended across the  $V_{AA}$  supply in addition to the 10 nF and 0.1  $\mu$ F ceramic capacitors.

### **Power Supply Sequencing**

The ADV7340/ADV7341 are robust to all power supply sequencing combinations. Any particular sequence can be used.

### **Digital Signal Interconnect**

The digital signal traces should be isolated as much as possible from the analog outputs and other analog circuitry. Digital signal traces should not overlay the  $V_{AA}$  or  $PV_{DD}$  power planes.

Due to the high clock rates used, avoid long clock traces to the ADV7340/ADV7341 to minimize noise pickup.

Any pull-up termination resistors for the digital inputs should be connected to the  $V_{DD}$  power supply.

Any unused digital inputs should be tied to ground.

### **Analog Signal Interconnect**

DAC output traces should be treated as transmission lines with appropriate measures taken to ensure optimal performance (for example, impedance matched traces). The DAC output traces should be kept as short as possible. The termination resistors on the DAC output traces should be placed as close as possible to and on the same side of the PCB as the ADV7340/ADV7341.

To avoid crosstalk between the DAC outputs, it is recommended that as much space as possible be left between the traces connected to the DAC output pins. Adding ground traces between the DAC output traces is also recommended.

## TYPICAL APPLICATION CIRCUIT




Figure 90. ADV7340/ADV7341 Typical Application Circuit

## APPENDIX 1—COPY GENERATION MANAGEMENT SYSTEM

### SD CGMS

#### **Subaddress 0x99 to Subaddress 0x9B**

The ADV7340/ADV7341 support copy generation management system (CGMS) conforming to the EIAJ CPR-1204 and ARIB TR-B15 standards. CGMS data is transmitted on Line 20 of the odd fields and Line 283 of even fields. Subaddress 0x99, Bits[6:5] control whether CGMS data is output on odd or even fields or both.

SD CGMS data can only be transmitted when the ADV7340/ADV7341 are configured in NTSC mode. The CGMS data is 20 bits long. The CGMS data is preceded by a reference pulse of the same amplitude and duration as a CGMS bit (see Figure 91).

### ED CGMS

#### **Subaddress 0x41 to Subaddress 0x43**

#### **Subaddress 0x5E to Subaddress 0x6E**

#### **525p**

The ADV7340/ADV7341 support copy generation management system (CGMS) in 525p mode in accordance with EIAJ CPR-1204-1.

When ED CGMS is enabled (Subaddress 0x32, Bit 6 = 1), 525p CGMS data is inserted on Line 41. The 525p CGMS data registers are at Subaddress 0x41, Subaddress 0x42, and Subaddress 0x43.

The ADV7340/ADV7341 also support CGMS Type B packets in 525p mode in accordance with CEA-805-A.

When ED CGMS Type B is enabled (Subaddress 0x5E, Bit 0 = 1), 525p CGMS Type B data is inserted on Line 40. The 525p CGMS Type B data registers are at Subaddress 0x5E to Subaddress 0x6E.

#### **625p**

The ADV7340/ADV7341 support copy generation management system (CGMS) in 625p mode in accordance with IEC62375 (2004).

When ED CGMS is enabled (Subaddress 0x32, Bit 6 = 1), 625p CGMS data is inserted on Line 43. The 625p CGMS data registers are at Subaddress 0x42 and Subaddress 0x43.

### HD CGMS

#### **Subaddress 0x41 to Subaddress 0x43**

#### **Subaddress 0x5E to Subaddress 0x6E**

The ADV7340/ADV7341 support copy generation management system (CGMS) in HD mode (720p and 1080i) in accordance with EIAJ CPR-1204-2.

When HD CGMS is enabled (Subaddress 0x32, Bit 6 = 1), 720p CGMS data is applied to Line 24 of the luminance vertical blanking interval.

When HD CGMS is enabled (Subaddress 0x32, Bit 6 = 1), 1080i CGMS data is applied to Line 19 and Line 582 of the luminance vertical blanking interval.

The HD CGMS data registers are at Subaddress 0x41, Subaddress 0x42, and Subaddress 0x43.

The ADV7340/ADV7341 also support CGMS Type B packets in HD mode (720p and 1080i) in accordance with CEA-805-A.

When HD CGMS Type B is enabled (Subaddress 0x5E, Bit 0 = 1), 720p CGMS data is applied to Line 23 of the luminance vertical blanking interval.

When HD CGMS Type B is enabled (Subaddress 0x5E, Bit 0 = 1), 1080i CGMS data is applied to Line 18 and Line 581 of the luminance vertical blanking interval.

The HD CGMS Type B data registers are at Subaddress 0x5E to Subaddress 0x6E.





### CGMS CRC FUNCTIONALITY

If SD CGMS CRC (Subaddress 0x99, Bit 4) or ED/HD CGMS CRC (Subaddress 0x32, Bit 7) is enabled, the upper six CGMS data bits, C19 to C14, which comprise the 6-bit CRC check sequence, are automatically calculated on the ADV7340/ADV7341. This calculation is based on the lower 14 bits (C13 to C0) of the data in the CGMS data registers and the result is output with the remaining 14 bits to form the complete 20 bits of the CGMS data. The calculation of the CRC sequence is based on the polynomial  $x^6 + x + 1$  with a preset value of 111111.


If SD CGMS CRC or ED/HD CGMS CRC are disabled, all 20 bits (C19 to C0) are output directly from the CGMS registers (CRC must be calculated by the user manually).

If ED/HD CGMS Type B CRC (Subaddress 0x5E, Bit 1) is enabled, the upper six CGMS Type B data bits (P122 to P127) that comprise the 6-bit CRC check sequence are automatically calculated on the ADV7340/ADV7341. This calculation is based on the lower 128 bits (H0 to H5 and P0 to P121) of the data in the CGMS Type B data registers. The result is output with the remaining 128 bits to form the complete 134 bits of the CGMS Type B data. The calculation of the CRC sequence is based on the polynomial  $x^6 + x + 1$  with a preset value of 111111.


If ED/HD CGMS Type B CRC is disabled, all 134 bits (H0 to H5 and P0 to P127) are output directly from the CGMS Type B registers (CRC must be calculated by the user manually).



# ADV7340/ADV7341



06398-096




06398-097

## NOTES

1. PLEASE REFER TO THE CEA-805-A SPECIFICATION FOR TIMING INFORMATION.

Figure 96. Enhanced Definition (525p) CGMS Type B Waveform



06398-098

## NOTES

1. PLEASE REFER TO THE CEA-805-A SPECIFICATION FOR TIMING INFORMATION.

Figure 97. High Definition (720p and 1080i) CGMS Type B Waveform



## APPENDIX 2—SD WIDE SCREEN SIGNALING

### *Subaddress 0x99, Subaddress 0x9A, Subaddress 0x9B*

The ADV7340/ADV7341 support wide screen signaling (WSS) conforming to the ETSI 300 294 standard. WSS data is transmitted on Line 23. WSS data can be transmitted only when the device is configured in PAL mode. The WSS data is 14 bits long. The function of each of these bits is shown in Table 55.

The WSS data is preceded by a run-in sequence and a start code (see Figure 98). If SD WSS (Subaddress 0x99, Bit 7) is set to Logic 1, it enables the WSS data to be transmitted on Line 23. The latter portion of Line 23 (42.5 sec from the falling edge of HSYNC) is available for the insertion of video. It is possible to blank the WSS portion of Line 23 with Subaddress 0xA1, Bit 7.

**Table 55. Function of WSS**

| Bit Description                | Bit Number |    |    |    |   |   |   |   |   |   |   |   |   |   | Setting                            |
|--------------------------------|------------|----|----|----|---|---|---|---|---|---|---|---|---|---|------------------------------------|
|                                | 13         | 12 | 11 | 10 | 9 | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 |                                    |
| Aspect Ratio, Format, Position |            |    |    |    |   |   |   |   |   |   | 1 | 0 | 0 | 0 | 4:3, full format, N/A              |
|                                |            |    |    |    |   |   |   |   |   |   | 0 | 0 | 0 | 1 | 14:9, letterbox, center            |
|                                |            |    |    |    |   |   |   |   |   |   | 0 | 0 | 1 | 0 | 14:9, letterbox, top               |
|                                |            |    |    |    |   |   |   |   |   |   | 1 | 0 | 1 | 1 | 16:9, letterbox, center            |
|                                |            |    |    |    |   |   |   |   |   |   | 0 | 1 | 0 | 0 | 16:9, letterbox, top               |
|                                |            |    |    |    |   |   |   |   |   |   | 1 | 1 | 0 | 1 | >16:9, letterbox, center           |
|                                |            |    |    |    |   |   |   |   |   |   | 1 | 1 | 1 | 0 | 14:9, full format, center          |
|                                |            |    |    |    |   |   |   |   |   |   | 0 | 1 | 1 | 1 | 16:0, N/A, N/A                     |
| Mode                           |            |    |    |    |   |   |   |   |   | 0 |   |   |   |   | Camera mode                        |
|                                |            |    |    |    |   |   |   |   |   | 1 |   |   |   |   | Film mode                          |
| Color Encoding                 |            |    |    |    |   |   |   |   | 0 |   |   |   |   |   | Normal PAL                         |
|                                |            |    |    |    |   |   |   |   | 1 |   |   |   |   |   | Motion Adaptive ColorPlus          |
| Helper Signals                 |            |    |    |    |   |   |   | 0 |   |   |   |   |   |   | Not present                        |
|                                |            |    |    |    |   |   |   | 1 |   |   |   |   |   |   | Present                            |
| Reserved                       |            |    |    |    |   |   | 0 |   |   |   |   |   |   |   |                                    |
| Teletext Subtitles             |            |    |    |    |   | 0 |   |   |   |   |   |   |   |   | No                                 |
|                                |            |    |    |    |   | 1 |   |   |   |   |   |   |   |   | Yes                                |
| Open Subtitles                 |            |    |    | 0  | 0 |   |   |   |   |   |   |   |   |   | No                                 |
|                                |            |    |    | 0  | 1 |   |   |   |   |   |   |   |   |   | Subtitles in active image area     |
|                                |            |    |    | 1  | 0 |   |   |   |   |   |   |   |   |   | Subtitles out of active image area |
|                                |            |    |    | 1  | 1 |   |   |   |   |   |   |   |   |   | Reserved                           |
| Surround Sound                 |            |    | 0  |    |   |   |   |   |   |   |   |   |   |   | No                                 |
|                                |            |    | 1  |    |   |   |   |   |   |   |   |   |   |   | Yes                                |
| Copyright                      |            | 0  |    |    |   |   |   |   |   |   |   |   |   |   | No copyright asserted or unknown   |
|                                |            | 1  |    |    |   |   |   |   |   |   |   |   |   |   | Copyright asserted                 |
| Copy Protection                | 0          |    |    |    |   |   |   |   |   |   |   |   |   |   | Copying not restricted             |
|                                | 1          |    |    |    |   |   |   |   |   |   |   |   |   |   | Copying restricted                 |




Figure 98. WSS Waveform Diagram

## APPENDIX 3—SD CLOSED CAPTIONING

### Subaddress 0x91 to Subaddress 0x94

The ADV7340/ADV7341 support closed captioning conforming to the standard television synchronizing waveform for color transmission. Closed captioning is transmitted during the blanked active line time of Line 21 of the odd fields and Line 284 of the even fields.

Closed captioning consists of a 7-cycle sinusoidal burst that is frequency- and phase-locked to the caption data. After the clock run-in signal, the blanking level is held for two data bits and is followed by the Logic 1 start bit. Sixteen bits of data follow the start bit. These consist of two 8-bit bytes, seven data bits, and one odd parity bit. The data for these bytes is stored in the SD closed captioning registers (Subaddress 0x93 to Subaddress 0x94).

The ADV7340/ADV7341 also support the extended closed captioning operation, which is active during even fields and encoded on Scan Line 284. The data for this operation is stored in the SD closed captioning registers (Subaddress 0x91 to Subaddress 0x92).

The ADV7340/ADV7341 automatically generate all clock run-in signals and timing that support closed captioning on Line 21 and Line 284. All pixels inputs are ignored on Line 21 and Line 284 if closed captioning is enabled.

The FCC Code of Federal Regulations (CFR) 47 Section 15.119 and EIA-608 describe the closed captioning information for Line 21 and Line 284.

The ADV7340/ADV7341 use a single buffering method. This means that the closed captioning buffer is only 1-byte deep. Therefore, there is no frame delay in outputting the closed captioning data, unlike other 2-byte deep buffering systems. The data must be loaded one line before it is output on Line 21 and Line 284. A typical implementation of this method is to use VSYNC to interrupt a microprocessor, which in turn loads the new data (2 bytes) in every field. If no new data is required for transmission, 0s must be inserted in both data registers; this is called nulling. It is also important to load control codes, all of which are double bytes, on Line 21. Otherwise, a TV does not recognize them. If there is a message such as “Hello World” that has an odd number of characters, it is important to add a blank character at the end to make sure that the end-of-caption, 2-byte control code lands in the same field.




Figure 99. SD Closed Captioning Waveform, NTSC

06398-100

## APPENDIX 4—INTERNAL TEST PATTERN GENERATION

### SD TEST PATTERNS

The ADV7340/ADV7341 are able to generate SD color bar and black bar test patterns.

The register settings in Table 56 are used to generate an SD NTSC 75% color bar test pattern. CVBS output is available on DAC 4, S-Video (Y/C) output is on DAC 5 and DAC 6, and YPrPb output is on DAC 1 to DAC 3. Upon power-up, the subcarrier frequency registers default to the appropriate values for NTSC. All other registers are set as normal/default.

**Table 56. SD NTSC Color Bar Test Pattern Register Writes**

| Subaddress | Setting |
|------------|---------|
| 0x00       | 0xFC    |
| 0x82       | 0xC9    |
| 0x84       | 0x40    |

To generate an SD NTSC black bar test pattern, the same settings shown in Table 56 should be used with an additional write of 0x24 to Subaddress 0x02.

For PAL output of either test pattern, the same settings are used, except that Subaddress 0x80 is programmed to 0x11 and the subcarrier frequency registers are programmed as shown in Table 57.

**Table 57. PAL F<sub>SC</sub> Register Writes**

| Subaddress | Description       | Setting |
|------------|-------------------|---------|
| 0x8C       | F <sub>SC</sub> 0 | 0xCB    |
| 0x8D       | F <sub>SC</sub> 1 | 0x8A    |
| 0x8E       | F <sub>SC</sub> 2 | 0x09    |
| 0x8F       | F <sub>SC</sub> 3 | 0x2A    |

Note that when programming the F<sub>SC</sub> registers, the user must write the values in the sequence F<sub>SC</sub>0, F<sub>SC</sub>1, F<sub>SC</sub>2, F<sub>SC</sub>3. The full F<sub>SC</sub> value to be written is accepted only after the F<sub>SC</sub>3 write is complete.

### ED/HD TEST PATTERNS

The ADV7340/ADV7341 are able to generate ED/HD color bar, black bar, and hatch test patterns.

The register settings in Table 58 are used to generate an ED 525p hatch test pattern. YPrPb output is available on DAC 1 to DAC 3. All other registers are set as normal/default.

**Table 58. ED 525p Hatch Test Pattern Register Writes**

| Subaddress | Setting |
|------------|---------|
| 0x00       | 0x1C    |
| 0x01       | 0x10    |
| 0x31       | 0x05    |

To generate an ED 525p black bar test pattern, the same settings as shown in Table 58 should be used with an additional write of 0x24 to Subaddress 0x02.

To generate an ED 525p flat field test pattern, the same settings shown in Table 58 should be used, except that 0x0D should be written to Subaddress 0x31.


The Y, Cr, and Cb levels for the hatch and flat field test patterns can be controlled using Subaddress 0x36, Subaddress 0x37, and Subaddress 0x38, respectively.

For ED/HD standards other than 525p, the same settings as shown in Table 58 (and subsequent comments) are used except that Subaddress 0x30, Bits[7:3] are updated as appropriate.

APPENDIX 5—SD TIMING


Mode 0 (CCIR-656)—Slave Option (Subaddress 0x8A = XXXXX000)

The ADV7340/ADV7341 are controlled by the SAV (start of active video) and EAV (end of active video) time codes embedded in the pixel data. All timing information is transmitted using a 4-byte synchronization pattern. A synchronization pattern is sent immediately before and after each line during active picture and retrace. If the S\_VSYNC and S\_HSYNC pins are not used, they should be tied high during this mode.



Mode 0 (CCIR-656)—Master Option (Subaddress 0x8A = XXXXX001)

The ADV7340/ADV7341 generate H and F signals required for the SAV and EAV time codes in the CCIR656 standard. The H bit is output on S\_HSYNC and the F bit is output on S\_VSYNC.






Figure 102. SD Master Mode 0, PAL




Figure 103. SD Master Mode 0, Data Transitions

## Mode 1—Slave Option (Subaddress 0x8A = XXXXX010)

In this mode, the ADV7340/ADV7341 accept horizontal sync and odd/even field signals. When  $\overline{\text{HSYNC}}$  is low, a transition of the field input indicates a new frame, that is, vertical retrace. The ADV7340/ADV7341 automatically blank all normally blank lines as per CCIR-624.  $\overline{\text{HSYNC}}$  and FIELD are input on the  $\overline{\text{S\_HSYNC}}$  and  $\overline{\text{S\_VSYNC}}$  pins, respectively.




Figure 104. SD Slave Mode 1, NTSC

# ADV7340/ADV7341




Figure 105. SD Slave Mode 1, PAL

## Mode 1—Master Option (Subaddress 0x8A = XXXXX011)

In this mode, the ADV7340/ADV7341 can generate horizontal sync and odd/even field signals. When  $\overline{\text{HSYNC}}$  is low, a transition of the field input indicates a new frame, that is, vertical retrace. The ADV7340/ADV7341 automatically blank all normally blank lines as per CCIR-624. Pixel data is latched on the rising clock edge following the timing signal transitions.  $\overline{\text{HSYNC}}$  and  $\overline{\text{FIELD}}$  are output on the  $\text{S\_HSYNC}$  and  $\text{S\_VSYNC}$  pins, respectively.




Figure 106. SD Timing Mode 1, Odd/Even Field Transitions (Master/Slave)

## Mode 2—Slave Option (Subaddress 0x8A = XXXXX100)

In this mode, the ADV7340/ADV7341 accept horizontal and vertical sync signals. A coincident low transition of both  $\overline{\text{HSYNC}}$  and  $\overline{\text{VSYNC}}$  inputs indicates the start of an odd field. A  $\overline{\text{VSYNC}}$  low transition when  $\overline{\text{HSYNC}}$  is high indicates the start of an even field. The ADV7340/ADV7341 automatically blank all normally blank lines as per CCIR-624.  $\overline{\text{HSYNC}}$  and  $\overline{\text{VSYNC}}$  are input on the  $\text{S\_HSYNC}$  and  $\text{S\_VSYNC}$  pins, respectively.



Figure 107. SD Slave Mode 2, NTSC



Figure 108. SD Slave Mode 2, PAL

**Mode 2—Master Option (Subaddress 0x8A = XXXXX 1 0 1)**

In this mode, the ADV7340/ADV7341 can generate horizontal and vertical sync signals. A coincident low transition of both  $\overline{\text{HSYNC}}$  and  $\overline{\text{VSYNC}}$  inputs indicates the start of an odd field.

A VSYNC low transition when HSYNC is high indicates the start of an even field. The ADV7340/ADV7341 automatically blank all normally blank lines as per CCIR-624. HSYNC and VSYNC are output on the S\_HSYNC and S\_VSYNC pins, respectively.



Figure 109. SD Timing Mode 2, Even-to-Odd Field Transition (Master/Slave)

# ADV7340/ADV7341




Figure 110. SD Timing Mode 2 Odd-to-Even Field Transition (Master/Slave)

## Mode 3—Master/Slave Option (Subaddress 0x8A = XXXXX 1 1 0 or XXXXX 1 1 1)

In this mode, the ADV7340/ADV7341 accept or generate horizontal sync and odd/even field signals. When  $\overline{\text{HSYNC}}$  is high, a transition of the field input indicates a new frame, that is, vertical retrace. The ADV7340/ADV7341 automatically blank all normally blank lines as per CCIR-624.  $\overline{\text{HSYNC}}$  and  $\overline{\text{VSYNC}}$  are output in master mode and input in slave mode on the  $\text{S\_VSYNC}$  and  $\text{S\_VSYNC}$  pins, respectively.




Figure 111. SD Timing Mode 3, NTSC




Figure 112. SD Timing Mode 3, PAL



## APPENDIX 6—HD TIMING




Figure 113. 1080i HSYNC and VSYNC Input Timing

06398-114

APPENDIX 7—VIDEO OUTPUT LEVELS

SD YPrPb OUTPUT LEVELS—SMPTE/EBU N10

Pattern: 100% Color Bars




Figure 114. Y Levels—NTSC

06398-115




Figure 117. Y Levels—PAL

06398-118




Figure 115. Pr Levels—NTSC

06398-116




Figure 118. Pr Levels—PAL

06398-119




Figure 116. Pb Levels—NTSC

06398-117




Figure 119. Pb Levels—PAL

06398-120

ED/HD YPrPb OUTPUT LEVELS




Figure 120. EIA-770.2 Standard Output Signals (525p/625p)




Figure 121. EIA-770.1 Standard Output Signals (525p/625p)




Figure 122. EIA-770.3 Standard Output Signals (1080i/720p)




Figure 123. Output Levels for Full Input Selection

# ADV7340/ADV7341

## SD/ED/HD RGB OUTPUT LEVELS

Pattern: 100%/75% Color Bars




Figure 124. SD/ED RGB Output Levels—RGB Sync Disabled




Figure 126. HD RGB Output Levels—RGB Sync Disabled




Figure 125. SD/ED RGB Output Levels—RGB Sync Enabled





Figure 127. HD RGB Output Levels—RGB Sync Enabled


## SD OUTPUT PLOTS



APL = 44.5% PRECISION MODE OFF  
525 LINE NTSC SYNCHRONOUS SYNC = A  
SLOW CLAMP TO 0.00V AT 6.72μs FRAMES SELECTED 1, 2

06398-129


Figure 128. NTSC Color Bars (75%)



NOISE REDUCTION: 0.00dB  
APL = 39.1% PRECISION MODE OFF  
625 LINE NTSC NO FILTERING SYNCHRONOUS SOUND-IN-SYNC OFF  
SLOW CLAMP TO 0.00 AT 6.72μs FRAMES SELECTED 1, 2, 3, 4

06398-132


Figure 131. PAL Color Bars (75%)



NOISE REDUCTION: 15.05dB  
APL = 44.3% PRECISION MODE OFF  
525 LINE NTSC NO FILTERING SYNCHRONOUS SYNC = SOURCE  
SLOW CLAMP TO 0.00V AT 6.72μs FRAMES SELECTED 1, 2

06398-130


Figure 129. NTSC Luma



APL NEEDS SYNC SOURCE. NO BUNCH SIGNAL  
625 LINE PAL NO FILTERING PRECISION MODE OFF  
SLOW CLAMP TO 0.00 AT 6.72μs SYNCHRONOUS SOUND-IN-SYNC OFF  
FRAMES SELECTED 1

06398-133


Figure 132. PAL Luma



NOISE REDUCTION: 15.05dB  
APL NEEDS SYNC SOURCE. PRECISION MODE OFF  
525 LINE NTSC NO FILTERING SYNCHRONOUS SYNC = B  
SLOW CLAMP TO 0.00 AT 6.72μs FRAMES SELECTED 1, 2

06398-131

Figure 130. NTSC Chroma



APL NEEDS SYNC SOURCE. NO BUNCH SIGNAL  
625 LINE PAL NO FILTERING PRECISION MODE OFF  
SLOW CLAMP TO 0.00 AT 6.72μs SYNCHRONOUS SOUND-IN-SYNC OFF  
FRAMES SELECTED 1

06398-134

Figure 133. PAL Chroma

APPENDIX 8—VIDEO STANDARDS




Figure 134. EAV/SAV Input Data Timing Diagram (SMPTE 274M)




Figure 135. EAV/SAV Input Data Timing Diagram (SMPTE 293M)




Figure 136. SMPTE 293M (525p)




Figure 137. ITU-R BT.1358 (625p)




Figure 138. SMPTE 296M (720p)





Figure 139. SMPTE 274M (1080i)

# ADV7340/ADV7341

## OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MS-026-BCD

Figure 140. 64-Lead Low Profile Quad Flat Package [LQFP]  
(ST-64-2)

Dimensions shown in millimeters

051706-A

## ORDERING GUIDE

| Model                        | Temperature Range | Macrovision <sup>1</sup><br>Antitaping | Package Description                          | Package Option |
|------------------------------|-------------------|--|--|----------------|
| ADV7340BSTZ <sup>2</sup>     | −40°C to +85°C    | Yes                                    | 64-Lead Low Profile Quad Flat Package [LQFP] | ST-64-2        |
| ADV7341BSTZ <sup>2</sup>     | −40°C to +85°C    | No                                     | 64-Lead Low Profile Quad Flat Package [LQFP] | ST-64-2        |
| EVAL-ADV7340EBZ <sup>2</sup> |                   | Yes                                    | ADV7340 Evaluation Platform                  |                |
| EVAL-ADV7341EBZ <sup>2</sup> |                   | No                                     | ADV7341 Evaluation Platform                  |                |

<sup>1</sup> Macrovision-enabled ICs require the buyer to be an approved licensee (authorized buyer) of ICs that are able to output Macrovision Rev 7.1.L1-compliant video.

<sup>2</sup> Z = Pb-free part.

Purchase of licensed I<sup>2</sup>C components of Analog Devices or one of its sublicensed Associated Companies conveys a license for the purchaser under the Philips I<sup>2</sup>C Patent Rights to use these components in an I<sup>2</sup>C system, provided that the system conforms to the I<sup>2</sup>C Standard Specification as defined by Philips.