PRELIMINARY



## DS1672 Low Voltage Serial Timekeeping Chip

## FEATURES

- 32-bit counter
- 2-wire serial interface
- Automatic power-fail detect and switch circuitry
- Power-fail reset output
- Low-voltage oscillator operation (1.3V min.)
- Trickle charge capability
- .

#### **ORDERING INFORMATION**

DS1672X-X

- 2 2.0V operation
- 3 3.0V operation
- 33 3.3V operation

blank 8-pin DIP S 8-pin SOIC U 8-pin μSOP

PIN AS	SIGN	MENT
--------	------	------

X1 🗌	1
X2 🗌	2
	3
GND	4

#### **PIN DESCRIPTION**

V<sub>CC</sub>, V<sub>BACKUP</sub> GND X1, X2 SCL SDA RST - Power Supply Inputs

V<sub>CC</sub>

RST

SCL

SDA

- Ground

8

7

6

5

- 32.768 kHz crystal pins
- Serial clock
- Serial data
- Reset output

### DESCRIPTION

The DS1672 incorporates a 32-bit counter and power monitoring functions. The 32-bit counter is designed to count seconds and can be used to derive time of day, week, month, month, and year by using a software algorithm. A precision temperature-compensated reference and comparator circuit monitors the status of  $V_{CC}$ . When an out-of-tolerance condition occurs, an internal power-fail signal is generated which forces the reset to the active state. When  $V_{CC}$  returns to an in-tolerance condition, the reset signal is kept in the active state for 250 ms to allow the power supply and processor to stabilize.

#### **OPERATION**

The block diagram in Figure 1 shows the main elements of the DS1672. As shown, communications to and from the DS1672 occur serially over a 2-wire bi-directional bus. The DS1672 operates as a slave device on the serial bus. Access is obtained by implementing a START condition and providing a device identification code followed by a register address. Subsequent registers can be accessed sequentially until a STOP condition is executed.





#### ADDRESS MAP

The counter is accessed by reading or writing the first 4 bytes of the DS1672 (00h - 03h). The control register and trickle charger are accessed by reading or writing the appropriate register bytes as illustrated in Figure 2. If the master continues to send or request more data after the address pointer has reached 05h, the address pointer will wrap around to location 00h.

#### DS1672 REGISTERS Figure 2

Address	<b>B7</b>	<b>B6</b>	B5	<b>B4</b>	B3	B2	<b>B1</b>	<b>B0</b>	Function
00h									Counter
									Byte 1
01h									Counter
									Byte 2
02h									Counter
									Byte 3
03h									Counter
									Byte 4
04h	EOSC								Control
05h	TCS	TCS	TCS	TCS	DS	DS	RS	RS	Trickle
									Charger

#### DATA RETENTION MODE

The device is fully accessible and data can be written and ready only when  $V_{CC}$  is greater than  $V_{PF}$ . However, when  $V_{CC}$  falls below  $V_{PF}$ , (point at which write protection occurs) the internal clock registers are blocked from any access. If  $V_{PF}$  is less than  $V_{BACKUP}$ , the device power is switched from  $V_{CC}$  to  $V_{BACKUP}$  when  $V_{CC}$  drops below  $V_{PF}$ . If  $V_{PF}$  is greater than  $V_{BACKUP}$ , the device power is switched from  $V_{CC}$  to  $V_{BACKUP}$  when  $V_{CC}$  drops below  $V_{BACKUP}$ . The registers are maintained from the  $V_{BACKUP}$  source until  $V_{CC}$  is returned to nominal levels.

## **OSCILLATOR CONTROL**

The  $\overline{\text{EOSC}}$  bit (bit 7 of the control register) controls the oscillator when in back-up mode. This bit when set to logic 0 will start the oscillator. When this bit is set to a logic 1, the oscillator is stopped and the DS1672 is placed into a low-power standby mode with a current drain of less than 200 nanoamps when in back-up mode. When the DS1672 is powered by V<sub>CC</sub>, the oscillator is always on regardless of the status of the  $\overline{\text{EOSC}}$  bit; however, the counter is incremented only when  $\overline{\text{EOSC}}$  is a logic 0.

## **CRYSTAL SELECTION**

A standard 32.768 kHz quartz crystal should be directly connected to the X1 and X2 oscillator pins. The crystal selected for use should have a specified load capacitance ( $C_L$ ) of 6 pF. For more information on crystal selection and crystal layout considerations, please consult Application Note 58, "Crystal Considerations with Dallas Real Time Clocks."

### MICROPROCESSOR MONITOR

A temperature-compensated comparator circuit monitors the level of  $V_{CC}$ . When  $V_{CC}$  falls to the powerfail trip point, the  $\overline{RST}$  signal (open drain) is pulled active. When  $V_{CC}$  returns to nominal levels, the  $\overline{RST}$ signal is kept in the active state for 250 ms (typically) to allow the power supply and microprocessor to stabilize. Note, however, that if the  $\overline{EOSC}$  bit is set to a logic 1 (to disable the oscillator during write protection), the reset signal will be kept in an active state for 250 ms plus the start-up time of the oscillator.

## **TRICKLE CHARGER**

The trickle charger is controlled by the trickle charge register. The simplified schematic of Figure 3 shows the basic components of the trickle charger. The trickle charge select (TCS) bit (bits 4-7) controls the selection of the trickle charger. In order to prevent accidental enabling, only a pattern on 1010 will enable the trickle charger. All other patterns will disable the trickle charger. The DS1672 powers up with the trickle charger disabled. The diode select (DS) bits (bits 2-3) select whether or not a diode is connected between  $V_{CC}$  and  $V_{BACKUP}$ . If DS is 01, no diode is selected or if DS is 10, a diode is selected. The RS bits (bits 0-1) select whether a resistor is connected between  $V_{CC}$  and  $V_{BACKUP}$  and what the value of the resistor is. The resistor selected by the resistor select (RS) bits and the diode selected by the diode select (DS) bits are as follows:

TCS	TCS	TCS	TCS	DS	DS	RS	RS	Function
Х	Х	Х	Х	0	0	Х	Х	Disabled
Х	Х	Х	Х	1	1	Х	Х	Disabled
Х	Х	Х	Х	Х	Х	0	0	Disabled
1	0	1	0	0	1	0	1	No diode, $100\Omega$ resistor
1	0	1	0	1	0	0	1	One diode, $100\Omega$ resistor
1	0	1	0	0	1	1	0	No diode, 2 k $\Omega$ resistor
1	0	1	0	1	0	1	0	One diode, $2 k\Omega$ resistor
1	0	1	0	0	1	1	1	No diode, 4 k $\Omega$ resistor
1	0	1	0	1	0	1	1	One diode, $4 k\Omega$ resistor

Diode and resistor selection is determined by the user according to the maximum current desired for battery or super cap charging. The maximum charging current can be calculated as illustrated in the following example. Assume that a system power supply of 3 volt is applied to  $V_{CC}$  and a super cap is connected to  $V_{BACKUP}$ . Also assume that the trickle charger has been enabled with a diode and resistor R2 between  $V_{CC}$  and  $V_{BACKUP}$ . The maximum current  $I_{max}$  would therefore be calculated as follows:

$$\begin{split} I_{max} &= (3.0V-diode~drop) \ / \ R2 \\ &\sim (3.0V-0.7V) \ / \ 2 \ k\Omega \\ &\sim 1.2 \ mA \end{split}$$

Obviously, as the super cap changes, the voltage drop between  $V_{CC}$  and  $V_{BACKUP}$  will decrease and therefore the charge current will decrease.



#### DS1672 PROGRAMMABLE TRICKLE CHARGER Figure 3

## 2-WIRE SERIAL DATA BUS

The DS1672 supports a bi-directional 2-wire bus and data transmission protocol. A device that sends data onto the bus is defined as a transmitter and a device receiving data as a receiver. The device that controls the message is called a "master." The devices that are controlled by the master are "slaves." The bus must be controlled by a master device which generates the serial clock (SCL), controls the bus access, and generates the START and STOP conditions. The DS1672 operates as a slave on the 2-wire bus. Connections to the bus are made via the open-drain I/O lines SDA and SCL.

The following bus protocol has been defined (see Figure 4).

Data transfer may be initiated only when the bus is not busy.

During data transfer, the data line must remain stable whenever the clock line is HIGH. Changes in the data line while the clock line is high will be interpreted as control signals.

Accordingly, the following bus conditions have been defined:

Bus not busy: Both data and clock lines remain HIGH.

**Start data transfer:** A change in the state of the data line from high to low, while the clock line is high, defines a START condition.

**Stop data transfer:** A change in the state of the data line from low to high, while the clock line is high, defines a STOP condition.

**Data valid:** The state of the data line represents valid data when, after a START condition, the data line is stable for the duration of the high period of the clock signal. The data on the line must be changed during the low period of the clock signal. There is one clock pulse per bit of data.

Each data transfer is initiated with a START condition and terminated with a STOP condition. The number of data bytes transferred between the START and the STOP conditions is not limited, and is determined by the master device. The information is transferred byte-wise and each receiver acknowledges with a ninth bit.

Acknowledge: Each receiving device, when addressed, is obliged to generate an acknowledge after the reception of each byte. The master device must generate an extra clock pulse which is associated with this acknowledge bit.

A device that acknowledges must pull down the SDA line during the acknowledge clock pulse in such a way that the SDA line is stable LOW during the HIGH period of the acknowledge related clock pulse. Of course, setup and hold times must be taken into account. A master must signal an end of data to the slave by not generating an acknowledge bit on the last byte that has been clocked out of the slave. In this case, the slave must leave the data line HIGH to enable the master to generate the STOP condition.



Figures 5 and 6 detail how data transfer is accomplished on the 2-wire bus. Depending upon the state of the  $R/\overline{w}$  bit, two types of data transfer are possible:

- 1. **Data transfer from a master transmitter to a slave receiver.** The first byte transmitted by the master is the slave address. Next follows a number of data bytes. The slave returns an acknowledge bit after each received byte.
- 2. **Data transfer from a slave transmitter to a master receiver.** The first byte (the slave address) is transmitted by the master. The slave then returns an acknowledge bit. Next follows a number of data bytes transmitted by the slave to the master. The master returns an acknowledge bit after all received bytes other than the last byte. At the end of the last received byte, a 'not acknowledge' is returned.

The master device generates all of the serial clock pulses and the START and STOP conditions. A transfer is ended with a STOP condition or with a repeated START condition. Since a repeated START condition is also the beginning of the next serial transfer, the bus will not be released.

The DS1672 may operate in the following two modes:

- 1. Slave receiver mode (DS1672 write mode): Serial data and clock are received through SDA and SCL. After each byte is received, an acknowledge bit is transmitted. START and STOP conditions are recognized as the beginning and end of a serial transfer. Address recognition is performed by hardware after reception of the slave address and direction bit. The address byte is the first byte received after the START condition is generated by the master. The address byte contains the 7-bit DS1672 address, which is 1101000, followed by the direction bit ( $R/\overline{w}$ ), which for a write is a 0. After receiving and decoding the address byte the DS1672 outputs an acknowledge on the SDA line. After the DS1672 acknowledges the slave address + write bit, the master transmits a register address to the DS1672. This will set the register pointer on the DS1672. The master will then begin transmitting each byte of data with the DS1672 acknowledging each byte received. The master will generate a STOP condition to terminate the data write.
- 2. Slave transmitter mode (DS1672 read mode): The first byte is received and handled as in the slave receiver mode. However, in this mode, the direction bit will indicate that the transfer direction is reversed. Serial data is transmitted on SDA by the DS1672 while the serial clock is input on SCL. START and STOP conditions are recognized as the beginning and end of a serial transfer. Address recognition is performed by hardware after reception of the slave address and direction bit. The address byte is the first byte received after the START condition is generated by the master. The address byte contains the 7-bit DS1672 address, which is 1101000, followed by the direction bit

 $(R/\overline{w})$ , which for a read is a 1. After receiving and decoding the address byte the DS1672 inputs an Acknowledge on the SDA line. The DS1672 then begins to transmit data starting with the register address pointed to by the register pointer. If the register pointer is not written to before the initiation of a read mode the first address that is read is the last one stored in the register pointer. The DS1672 must receive a not acknowledge to end a read.

## DATA WRITE – SLAVE RECEIVER MODE Figure 5



## DATA READ – SLAVE TRANSMITTER MODE Figure 6



## **ABSOLUTE MAXIMUM RATINGS\***

Voltage on Any Pin Relative to Ground Operating Temperature Storage Temperature Soldering Temperature -0.3V to +6.0V -40°C to +85°C -55°C to +125°C See J-STD-020A specification

\* This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operation sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods of time may affect reliability.

<b>RECOMMENDED DC OPERATING CONDITIONS</b> (-40°C to +8							
PARAMETER	SYMBOL	MIN	ТҮР	MAX	UNITS	NOTES	
Supply Voltage (DS1672-33)	V <sub>CC</sub>	2.97	3.3	3.63	V	1	
(DS1672-3)	V <sub>CC</sub>	2.7	3.0	3.3	V	1	
(DS1672-2)	V <sub>CC</sub>	1.8	2.0	2.2	V	1	
Logic 1	V <sub>IH</sub>	$0.7 V_{CC}$		$V_{CC} + 0.5$	V	1	
Logic 0	V <sub>IL</sub>	-0.5		$0.3V_{CC}$	V	1	
Backup Supply Voltage	VBACKUP	1.3		3.6	V	1	

### DC ELECTRICAL CHARACTERISTICS

DS1672-33		(-4	↓0°C to +	85°C; V <sub>CC</sub>	= 2.97 t	o 3.63V)
PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Active Supply Current	I <sub>CCA</sub>			2	mA	7
Standby Current	I <sub>CCS</sub>			500	μA	8
Power-Fail Voltage	$V_{PF}$	2.80	2.88	2.97	V	1

## **DC ELECTRICAL CHARACTERISTICS**

DS1672-3			(-40°C to	o +85°C; ∖	$V_{\rm CC} = 2.7$	′ to 3.3V)
PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Active Supply Current	I <sub>CCA</sub>			2	mA	7
Standby Current	I <sub>CCS</sub>			500	μA	9
Power-Fail Voltage	V <sub>PF</sub>	2.5	2.6	2.7	V	1

## DC ELECTRICAL CHARACTERISTICS

DS1672-2			(-40°C to	o +85°C; ∖	/ <sub>CC</sub> = 1.8	to 2.2V)
PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Active Supply Current	I <sub>CCA</sub>			2	mA	7
Standby Current	I <sub>CCS</sub>			500	μA	10
Power-Fail Voltage	V <sub>PF</sub>	1.6	1.7	1.8	V	1

#### DC ELECTRICAL CHARACTERISTICS

 $(-40^{\circ}C \text{ to } +85^{\circ}C; V_{CC} < V_{PF})$ 

					, ,	/0 11/
PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
Timekeeping Current	I <sub>OSC</sub>			1	μA	12
Backup Standby Current (Oscillator Off)	I <sub>BACKUP</sub>			200	nA	13

DS1672

AC ELECTRICAI	_ CHARA	CTERISTICS		(-40	°C to +	-85°C; V	$_{\rm CC}$ > $V_{\rm PF}$ )
PARAMETER	SYMBOL	CONDITION	MIN	TYP	MAX	UNITS	NOTES
SCL Clock	f <sub>SCL</sub>	Fast Mode	100		400	kHz	
Frequency		Standard Mode			100		
Bus Free Time	t <sub>BUF</sub>	Fast Mode	1.3			μs	
Between a STOP and START		Standard Mode	4.7				
Condition							
Hold Time	t <sub>HD:STA</sub>	Fast Mode	0.6			μs	2
(Repeated) START Condition		Standard Mode	4.0				
LOW Period of	t <sub>LOW</sub>	Fast Mode	1.3			μs	
SCL Clock		Standard Mode	4.7			•	
HIGH Period of	t <sub>HIGH</sub>	Fast Mode	0.6			μs	
SCL Clock		Standard Mode	4.0			-	
Set-up Time for a	t <sub>SU:STA</sub>	Fast Mode	0.6			μs	
Repeated START Condition		Standard Mode	4.7				
Data Hold Time	t <sub>HD:DAT</sub>	Fast Mode	0		0.9	μs	3, 4
		Standard Mode	0			-	
Data Set-up Time	t <sub>SU:DAT</sub>	Fast Mode	100			μs	11
		Standard Mode	250				
Rise Time of Both	t <sub>R</sub>	Fast Mode	$20 + 0.1C_B$		300	ns	5
SDA and SCL		Standard Mode			1000		
Signals							
Fall Time of Both	t <sub>F</sub>	Fast Mode	$20 + 0.1 C_B$		300	ns	5
SDA and SCL Signals		Standard Mode			300		
Set-up Time for	tsu.sto	Fast Mode	0.6			ЦS	
STOP Condition	-50.510	Standard Mode	4.0			pus	
Capacitive Load for each Bus Line	C <sub>B</sub>				400	pF	5
I/O Capacitance	C1/0			10		pF	
each Bus Line I/O Capacitance	C <sub>B</sub>			10	400	рг pF	3

## Timing Diagram Figure 7



## POWER-UP/DOWN TIMING Figure 8



POWER-UP DOWN CHARAC		(-40°C to +85°C)				
PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	NOTES
$V_{CC}$ Detect to $\overline{RST}$ ( $V_{CC}$ Falling)	t <sub>RPD</sub>			10	μs	
$V_{CC}$ Detect to $\overline{RST}$ ( $V_{CC}$ Rising)	t <sub>RPU</sub>		250		ms	6
$V_{CC}$ Fall Time; $V_{PF(MAX)}$ to $V_{PF(MIN)}$	t <sub>F</sub>	300			μs	
$V_{CC}$ Rise Time; $V_{PF(MIN)}$ to $V_{PF(MAX)}$	t <sub>R</sub>	0			μs	

#### WARNING:

Under no circumstances are negative undershoots, of any amplitude, allowed when device is in write protection.

#### NOTES:

- 1. All voltages are referenced to ground.
- 2. After this period, the first clock pulse is generated.
- 3. A device must internally provide a hold time of at least 300 ns for the SDA signal (referenced to the  $V_{IHMIN}$  of the SCL signal) in order to bridge the undefined region of the falling edge of SCL.
- 4. The maximum  $t_{HD:DAT}$  has only to be met if the device does not stretch the LOW period ( $t_{LOW}$ ) of the SCL signal.
- 5.  $C_B$  total capacitance of one bus line in pF.
- 6. If the  $\overline{\text{EOSC}}$  bit in the Control Register is set to logic 1,  $t_{\text{RPU}}$  is equal to 250 ms plus the start-up time of the crystal oscillator.
- 7. I<sub>CCA</sub> specified with SCL clocking at max frequency (400 kHz).
- 8.  $I_{CCS}$  specified with  $V_{CC} = 3.3V$  and SDA, SCL=3.3V.
- 9.  $I_{CCS}$  specified with  $V_{CC} = 3.0V$  and SDA, SCL=3.0V.
- 10.  $I_{CCS}$  specified with  $V_{CC} = 2.0V$  and SDA, SCL=2.0V.
- 11. A fast mode device can be used in a standard mode system, but the requirement  $t_{SU:DAT} >=$  to 250 ns must then be met. This will automatically be the case if the device does not stretch the LOW period of the SCL signal. If such a device does stretch the LOW period of the SCL signal, it must output the next data bit to the SDA line  $t_R \max + t_{SU:DAT} = 1000+250 = 1250$  ns before the SCL line is released.
- 12.  $I_{OSC}$  specified with  $V_{CC} = 0V$ ,  $V_{BACKUP} = 3.6V$  and oscillator enabled.
- 13.  $I_{BACKUP}$  specified with  $V_{CC} = 0V$ ,  $V_{BACKUP} = 3.6V$  and oscillator disabled.

#### DS1672

## 8-PIN DIP







PKG	8-PIN					
DIM	MIN	MAX				
A IN.	0.360	0.400				
MM	9.14	10.16				
B IN.	0.240	0.260				
MM	6.10	6.60				
C IN.	0.120	0.140				
MM	3.05	3.56				
D IN.	0.300	0.325				
MM	7.62	8.26				
E IN.	0.015	0.040				
MM	0.38	1.02				
F IN.	0.120	0.140				
MM	3.04	3.56				
G IN.	0.090	0.110				
MM	2.29	2.79				
H IN.	0.320	0.370				
MM	8.13	9.40				
J IN.	0.008	0.012				
MM	0.20	0.30				
K IN.	0.015	0.021				
MM	0.38	0.53				

#### DS1672

# 8-PIN SOIC (150-MIL)







DKC	8-PIN	
LVQ	(150-MIL)	
DIM	MIN	MAX
A IN.	0.188	0.196
MM	4.78	4.98
B IN.	0.150	0.158
MM	3.81	4.01
C IN.	0.048	0.062
MM	1.22	1.57
E IN.	0.004	0.010
MM	0.10	0.25
F IN.	0.053	0.069
MM	1.35	1.75
G IN.	0.050 BSC	
MM	1.27 BSC	
H IN.	0.230	0.244
MM	5.84	6.20
J IN.	0.007	0.011
MM	0.18	0.28
K IN.	0.012	0.020
MM	0.30	0.51
L IN.	0.016	0.050
MM	0.41	1.27
phi	$0^{\circ}$	8°