查询TPS3613-01供应商 捷多邦，专业PCB打样工厂，24小时加急出货

TPS3613-01
ADJUSTABLE BATTERY-BACKUP SUPERVISOR FOR RAM RETENTION

SLVS340B – DECEMBER 2000 – REVISED DECEMBER 2002

- Supply Current of 40 µA (Max)
- Battery Supply Current of 100 nA (Max)
- Supply Voltage Supervision Range:
  - Adjustable
  - Other Versions Available on Request
- Backup-Battery Voltage Can Exceed V_{DD}
- Power-On Reset Generator With Fixed 100-ms Reset Delay Time
- Active-High and Active-Low Reset Output
- Chip-Enable Gating . . . 3 ns (at V_{DD} = 5 V) Max Propagation Delay
- 10-Pin MSOP Package
- Temperature Range . . . –40°C to 85°C

typical applications

- Fax Machines
- Set-Top Boxes
- Advanced Voice Mail Systems
- Portable Battery Powered Equipment
- Computer Equipment
- Advanced Modems
- Automotive Systems
- Portable Long-Time Monitoring Equipment
- Point-of-Sale Equipment

MSOP (DGS) Package
(TOP VIEW)



ACTUAL SIZE
3,05 mm x 4,98 mm

description

The TPS3613-01 supervisory circuit monitors and controls processor activity by providing backup-battery switchover for data retention of CMOS RAM.

During power on, $\overline{RESET}$ is asserted when the supply voltage (V_{DD} or V_{BAT}) becomes higher than 1.1 V. Thereafter, the supply voltage supervisor monitors V_{DD} and keeps $\overline{RESET}$ output active as long as V_{DD} remains below the threshold voltage V_{IT}. An internal timer delays the return of the output to the inactive state (high) to ensure proper system reset. The delay time starts after V_{DD} has risen above the threshold voltage V_{IT}.

When the supply voltage drops below the threshold voltage V_{IT}, the output becomes active (low) again.

The TPS3613-01 is available in a 10-pin MSOP package and is characterized for operation over a temperature range of –40°C to 85°C.

typical operating circuit



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2002, Texas Instruments Incorporated

PACKAGE INFORMATION

T_A	DEVICE NAME	MARKING
–40°C to 85°C	TPS3613–01DGSR†	AFK

† The DGSR passive indicates tape and reel of 2500 parts.

ordering information application specific versions

TPS361 3 – 01 DGS R

- R — Reel
- DGS — Package
- 01 — Nominal Supply Voltage
- 3 — Functionality
- TPS361 — Family

DEVICE NAME	NOMINAL VOLTAGE‡, V_{NOM}
TPS3613–01 DGS	Adjustable

‡ For other threshold voltages, contact the local TI sales office for availability and lead-time.

FUNCTION TABLE

SENSE > V_{IT}	$V_{DD} > V_{BAT}$	$\overline{MR}$	$\overline{CEIN}$	V_{OUT}	$\overline{RESET}$	RESET	$\overline{CEOUT}$
0	0	0	0	V_{BAT}	0	1	DIS
0	0	0	1	V_{BAT}	0	1	DIS
0	0	1	0	V_{BAT}	0	1	DIS
0	0	1	1	V_{BAT}	0	1	DIS
0	1	0	0	V_{DD}	0	1	DIS
0	1	0	1	V_{DD}	0	1	DIS
0	1	1	0	V_{DD}	0	1	DIS
0	1	1	1	V_{DD}	0	1	DIS
1	0	0	0	V_{DD}	0	1	DIS
1	0	0	1	V_{DD}	0	1	DIS
1	0	1	0	V_{DD}	1	0	DIS
1	0	1	1	V_{DD}	1	0	EN
1	1	0	0	V_{DD}	0	1	DIS
1	1	0	1	V_{DD}	0	1	DIS
1	1	1	0	V_{DD}	1	0	DIS
1	1	1	1	V_{DD}	1	0	EN

functional schematic



timing diagram



Terminal Functions

TERMINAL		I/O	DESCRIPTION
NAME	NO.		
$\overline{CEIN}$	5	I	Chip-enable input
$\overline{CEOUT}$	6	O	Chip-enable output
GND	3	I	Ground
$\overline{MR}$	4	I	Manual reset input
RESET	7	O	Active-high reset output
$\overline{RESET}$	9	O	Active-low reset output
SENSE	8	I	Adjustable sense input
V_{BAT}	10	I	Backup-battery input
V_{DD}	2	I	Input supply voltage
V_{OUT}	1	O	Supply output

detailed description

backup-battery switchover

In case of a brownout or power failure, it may be necessary to preserve the contents of RAM. If a backup battery is installed at V_{BAT}, the device automatically switches the connected RAM to backup power when V_{DD} fails. In order to allow the backup battery (e.g., 3.6-V lithium cells) to have a higher voltage than V_{DD}, these supervisors do not connect V_{BAT} to V_{OUT} when V_{BAT} is greater than V_{DD}. V_{BAT} only connects to V_{OUT} (through a 15-Ω switch) when V_{DD} falls below V_{IT} and V_{BAT} is greater than V_{DD}. When V_{DD} recovers, switchover is deferred either until V_{DD} crosses V_{BAT}, or when V_{DD} rises above the reset threshold V_{IT}. V_{OUT} connects to V_{DD} through a 1-Ω (max) PMOS switch when V_{DD} crosses the reset threshold.

$V_{DD}>V_{BAT}$	$V_{DD}>V_{IT}$	V_{OUT}
1	1	V_{DD}
1	0	V_{DD}
0	1	V_{DD}
0	0	V_{BAT}



Figure 1. V_{DD} – V_{BAT} Switchover

detailed description (continued)

chip-enable signal gating

The internal gating of chip-enable (CE) signals prevents erroneous data from corrupting CMOS RAM during an under-voltage condition. The TPS3613 use a series transmission gate from $\overline{\text{CEIN}}$ to $\overline{\text{CEOUT}}$. During normal operation (reset not asserted), the CE transmission gate is enabled and passes all CE transitions. When reset is asserted, this path becomes disabled, preventing erroneous data from corrupting the CMOS RAM. The short CE propagation delay from $\overline{\text{CEIN}}$ to $\overline{\text{CEOUT}}$ enables the TPS3613 device to be used with most processors.

The CE transmission gate is disabled and $\overline{\text{CEIN}}$ is high impedance (disable mode) while reset is asserted. During a power-down sequence when V_{DD} crosses the reset threshold, the CE transmission gate is disabled and $\overline{\text{CEIN}}$ immediately becomes high impedance if the voltage at $\overline{\text{CEIN}}$ is high. If $\overline{\text{CEIN}}$ is low when reset is asserted, the CE transmission gate is disabled when $\overline{\text{CEIN}}$ goes high, or 15 µs after reset asserts, whichever occurs first. This allows the current write cycle to complete during power down. When the CE transmission gate is enabled, the impedance of $\overline{\text{CEIN}}$ appears as a resistor in series with the load at $\overline{\text{CEOUT}}$. The overall device propagation delay through the CE transmission gate depends on V_{OUT}, the source impedance of the drive connected to $\overline{\text{CEIN}}$, and the load at $\overline{\text{CEOUT}}$. To achieve minimum propagation delay, the capacitive load at $\overline{\text{CEOUT}}$ should be minimized, and a low-output-impedance driver is used.

In the disabled mode, the transmission gate is off and an active pullup connects $\overline{\text{CEOUT}}$ to V_{OUT}. This pullup turns off when the transmission gate is enabled.



Figure 2. Chip-Enable Timing

absolute maximum ratings over operating free-air temperature (unless otherwise noted)†

Supply voltage: V_{DD} (see Note1) . . . . . 7 V
$\overline{MR}$ and SENSE pins (see Note 1) . . . . . –0.3 V to (V_{DD} + 0.3 V)
Continuous output current at V_{OUT}: I_O . . . . . 400 mA
All other pins, I_O . . . . . ±10 mA
Continuous total power dissipation . . . . . See Dissipation Rating Table
Operating free-air temperature range, T_A . . . . . –40°C to 85°C
Storage temperature range, T_{stg} . . . . . –65°C to 150°C
Lead temperature soldering 1,6 mm (1/16 inch) from case for 10 seconds . . . . . 260°C

† Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTE 1: All voltage values are with respect to GND. For reliable operation the device must not be operated at 7 V for more than t=1000h continuously.

DISSIPATION RATING TABLE

PACKAGE	$T_A \leq 25°C$ POWER RATING	DERATING FACTOR ABOVE $T_A = 25°C$	$T_A = 70°C$ POWER RATING	$T_A = 85°C$ POWER RATING
DGS	424 mW	3.4 mW/°C	271 mW	220 mW

recommended operating conditions

	MIN	MAX	UNIT
Supply voltage, V_{DD}	1.65	5.5	V
Battery supply voltage, V_{BAT}	1.5	5.5	V
Input voltage, V_I	0	V_{DD} + 0.3	V
High-level input voltage, V_{IH}	0.7 x V_{DD}		V
Low-level input voltage, V_{IL}		0.3 x V_{DD}	V
Continuous output current at V_{OUT}, I_O		300	mA
Input transition rise and fall rate at $\overline{MR}$, $\Delta t/\Delta V$		100	ns/V
Slew rate at V_{DD} or V_{bat}		1	V/µs
Operating free-air temperature range, T_A	–40	85	°C

electrical characteristics over recommended operating conditions (unless otherwise noted)

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
V_{OH}	High-level output voltage	$\overline{\text{RESET}}$	V_{DD} = 1.8 V I_{OH} = –400 µA	V_{DD} – 0.2 V			V
			V_{DD} = 3.3 V, I_{OH} = –2 mA V_{DD} = 5 V, I_{OH} = –3 mA	V_{DD} – 0.4 V			
		RESET	V_{DD} = 1.8 V, I_{OH} = –20 µA	V_{DD} – 0.3 V			
			V_{DD} = 3.3 V, I_{OH} = –80 µA V_{DD} = 5 V, I_{OH} = –120 µA	V_{DD} – 0.4 V			
		$\overline{\text{CEOUT}}$	V_{OUT} = 1.8 V, I_{OH} = –1 mA	V_{OUT} – 0.2 V			
		Enable mode $\overline{\text{CEIN}}$ = V_{OUT}	V_{OUT} = 3.3 V, I_{OH} = –2 mA V_{OUT} = 5 V, I_{OH} = –5 mA	V_{OUT} – 0.3 V			
		$\overline{\text{CEOUT}}$ Disable mode	V_{OUT} = 3.3 V, I_{OH} = –0.5 mA	V_{OUT} – 0.4 V			
V_{OL}	Low-level output voltage	$\overline{\text{RESET}}$	V_{DD} = 1.8 V, I_{OL} = 400 µA			0.2	V
		RESET	V_{DD} = 3.3 V, I_{OL} = 2 mA V_{DD} = 5 V, I_{OL} = 3 mA			0.4	
		$\overline{\text{CEOUT}}$	V_{OUT} = 1.8 V, I_{OL} = 1.0 mA			0.2	
		Enable mode $\overline{\text{CEIN}}$ = 0 V	V_{OUT} = 3.3 V, I_{OL} = 2 mA V_{OUT} = 5 V, I_{OL} = 5 mA			0.3	
V_{res}	Power-up reset voltage (see Note 2)		V_{DD} > 1.1 V or V_{BAT} > 1.1 V, I_{OL} = 20 µA			0.4	V
V_{OUT}	Normal mode		I_O = 8.5 mA, V_{DD} = 1.8 V, V_{BAT} = 0 V	V_{DD} – 50 mV			V
			I_O = 125 mA, V_{DD} = 3.3 V, V_{BAT} = 0 V	V_{DD} – 150 mV			
			I_O = 200 mA, V_{DD} = 5 V, V_{BAT} = 0 V	V_{DD} – 200 mV			
	Battery-backup mode		I_O = 0.5 mA, V_{BAT} = 1.5 V, V_{DD} = 0 V	V_{BAT} – 20 mV			
			I_O = 7.5 mA, V_{BAT} = 3.3 V, V_{DD} = 0 V	V_{BAT} – 113 mV			
$R_{DS(on)}$	V_{DD} to V_{OUT} on-resistance		V_{DD} = 5 V		0.6	1	Ω
	V_{BAT} to V_{OUT} on-resistance		V_{BAT} = 3.3 V		8	15	
V_{IT}	Negative-going input threshold voltage (see Note 3)			1.13	1.15	1.17	V
V_{hys}	Hysteresis	Sense	1.1 V < V_{IT} < 1.65 V		12		mV
		V_{BSW} (see Note 4)	V_{DD} = 1.8 V		55		
I_{IH}	High-level input current	$\overline{\text{MR}}$	$\overline{\text{MR}}$ = 0.7 x V_{DD}, V_{DD} = 5 V	–33		–76	µA
I_{IL}	Low-level input current		$\overline{\text{MR}}$ = 0 V, V_{DD} = 5 V	–110		–255	
I_I	Input current	SENSE	V_{DD} = 1.15 V	–25		25	nA
I_{DD}	V_{DD} supply current		V_{OUT} = V_{DD}			40	µA
			V_{OUT} = V_{BAT}			40	
I_{BAT}	V_{BAT} supply current		V_{OUT} = V_{DD}	–0.1		0.1	µA
			V_{OUT} = V_{BAT}			0.5	
I_{lkg}	$\overline{\text{CEIN}}$ leakage current		Disable mode, V_I < V_{DD}			±1	µA
C_i	Input capacitance		V_I = 0 V to 5 V		5		pF

NOTES: 2. The lowest supply voltage at which $\overline{\text{RESET}}$ becomes active. $t_{r,(VDD)} \geq 15$ µs/V.
3. To ensure best stability of the threshold voltage, a bypass capacitor (ceramic, 0.1 µF) should be placed near to the supply terminals.
4. For V_{DD} < 1.6 V, V_{OUT} switches to V_{BAT} regardless of V_{BAT}

timing requirements at R_L = 1 MΩ, C_L = 50 pF, T_A = –40°C to 85°C

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
t_w	Pulse width	SENSE	$V_{IH} = V_{IT} + 0.2$ V, $V_{IL} = V_{IT} – 0.2$ V	6			µs

switching characteristics at R_L = 1 MΩ, C_L= 50 pF, T_A = –40°C to 85°C

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
t_d	Delay time		$V_{SENSE} \geq V_{IT} + 0.2$ V, $\overline{MR} \geq 0.7 \times V_{DD}$, See timing diagram	60	100	140	ms
t_{PLH}	Propagation (delay) time, low-to-high-level output	50% $\overline{RESET}$ to 50% $\overline{CEOUT}$	$V_{OUT} = V_{IT}$		15		µs
t_{PHL}	Propagation (delay) time, high-to-low-level output	50% $\overline{CEIN}$ to 50% $\overline{CEOUT}$, C_L = 50 pF only (see Note 5)	V_{DD} = 1.8 V		5	15	ns
			V_{DD} = 3.3 V		1.6	5	
			V_{DD} = 5 V		1	3	
		SENSE to $\overline{RESET}$	$V_{IL} = V_{IT} – 0.2$ V, $V_{IH} = V_{IT} + 0.2$ V		2	5	µs
		$\overline{MR}$ to $\overline{RESET}$	$V_{SENSE} \geq V_{IT} + 0.2$ V, $V_{IL} = 0.3 \times V_{DD}$, $V_{IH} = 0.7 \times V_{DD}$		0.1	1	µs
	Transition time	V_{DD} to V_{BAT}	$V_{IH} = V_{BAT} + 0.2$ V, $V_{IL} = V_{BAT} – 0.2$ V, $V_{BAT} < V_{IT}$			3	µs

NOTE 5: Assured by design

TYPICAL CHARACTERISTICS

Table of Graphs

			FIGURE
$r_{DS(on)}$	Static drain-source on-state resistance (V_{DD} to V_{OUT})	vs Output current	3
	Static drain-source on-state resistance (V_{BAT} to V_{OUT})	vs Output current	4
	Static drain-source on-state resistance ($\overline{CEIN}$ to $\overline{CEOUT}$)	vs Input voltage at $\overline{CEIN}$	5
I_{DD}	Supply current	vs Supply voltage	6
V_{IT}	Input threshold voltage at $\overline{RESET}$	vs Free-air temperature	7
V_{OH}	High-level output voltage at $\overline{RESET}$	vs High-level output current	8, 9
	High-level output voltage at $\overline{CEOUT}$		10, 11, 12, 13
V_{OL}	Low-level output voltage at $\overline{RESET}$	vs Low-level output current	14, 15
	Low-level output voltage at $\overline{CEOUT}$	vs Low-level output current	16, 17

STATIC DRAIN-SOURCE ON-STATE RESISTANCE (V_{DD} to V_{OUT}) vs OUTPUT CURRENT



Figure 3

STATIC DRAIN-SOURCE ON-STATE RESISTANCE (V_{BAT} to V_{OUT}) vs OUTPUT CURRENT



Figure 4

TYPICAL CHARACTERISTICS

STATIC DRAIN-SOURCE ON-STATE RESISTANCE ($\overline{CEIN}$ to $\overline{CEOUT}$) vs INPUT VOLTAGE AT $\overline{CEIN}$



Figure 5

SUPPLY CURRENT vs SUPPLY VOLTAGE



Figure 6

INPUT THRESHOLD VOLTAGE AT $\overline{RESET}$ vs FREE-AIR TEMPERATURE



Figure 7

TYPICAL CHARACTERISTICS

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{RESET}}$ vs HIGH-LEVEL OUTPUT CURRENT



Figure 8

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{RESET}}$ vs HIGH-LEVEL OUTPUT CURRENT



Figure 9

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$ vs HIGH-LEVEL OUTPUT CURRENT



Figure 10

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$ vs HIGH-LEVEL OUTPUT CURRENT



Figure 11

TYPICAL CHARACTERISTICS

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{CEOUT}$ vs HIGH-LEVEL OUTPUT CURRENT



Figure 12

HIGH-LEVEL OUTPUT VOLTAGE AT $\overline{CEOUT}$ vs HIGH-LEVEL OUTPUT CURRENT



Figure 13

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{RESET}$ vs LOW-LEVEL OUTPUT CURRENT



Figure 14

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{RESET}$ vs LOW-LEVEL OUTPUT CURRENT



Figure 15

TYPICAL CHARACTERISTICS

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$ vs LOW-LEVEL OUTPUT CURRENT



Figure 16

LOW-LEVEL OUTPUT VOLTAGE AT $\overline{\text{CEOUT}}$ vs LOW-LEVEL OUTPUT CURRENT



Figure 17

MECHANICAL DATA

DGS (S-PDSO-G10) **PLASTIC SMALL-OUTLINE PACKAGE**



NOTES: A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body dimensions do not include mold flash or protrusion.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third–party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Mailing Address:

Texas Instruments
Post Office Box 655303
Dallas, Texas 75265

Copyright © 2002, Texas Instruments Incorporated