



GM38C42, GM38C43, GM38C44, GM38C45 HIGH PERFORMANCE CURRENT MODE PWM CONTROLLERS

Power Management

Description

The GM38C4x are fixed frequency, high performance, current-mode PWM controllers. Gamma's BiCMOS devices are pin compatible with standard 384x bipolar devices but with several improvements.

Undervoltage lockout circuitry allows the '42 and '44 versions to start up at 14.5V and operate down to 9V, and the '43 and '45 versions start at 8.4V with operation down to 7.6V. All versions operate up to 16V.

When compared to bipolar 384x devices operating from a 15V supply, start-up current has been reduced to 50 μ A typical and operating current has been reduced to 4.0 mA typical. Decreased output rise and fall times drive larger MOSFETs, and rail-to-rail output capability increases efficiency, especially at lower supply voltages. The GM38C4x also features a trimmed oscillator discharge current and bandgap reference.

GM38C4x denotes 8-pin plastic DIP and SOP packages.

Application

Current-mode, off-line, switched-mode power supplies

Current-mode, dc-to-dc converters.

Step-down "buck" regulators

Features

- ◆ 40ns output rise and 30ns output fall times
- ◆ -40° to +85°C temp. range same as standard UC284x
- ◆ Low-power BiCMOS Process
- ◆ Very low start-up current (50 μ A typical)
- ◆ Low operating current (4mA typical)
- ◆ CMOS outputs with rail-to-rail swing
- ◆ ≥ 500 kHz current-mode operation
- ◆ Pin-for-pin compatible with UC3842/ 3843 / 3844/ 3845(A)
- ◆ Trimmed oscillator discharge current
- ◆ UVLO with hysteresis
- ◆ Low cross-conduction currents

Step-up "boost" regulators
Flyback, isolated regulators
Forward converters
Synchronous FET converters

GM38C42, GM38C43, GM38C44, GM38C45

◆ MARKING INFORMATION & PIN CONFIGURATIONS (TOP VIEW)



A = Assembly Location
 Y = Year
 W W = Work Week

◆ ORDERING INFORMATION

Ordering Number	Package	Shipping
GM38C42S8T	SO - 8	100 Units/ Tube
GM38C42S8R	SO - 8	2,500 Units/ Tape & Reel
GM38C42D8T	DIP-8	60 Units/ Tube
GM38C43S8T	SO - 8	100 Units/ Tube
GM38C43S8R	SO - 8	2,500 Units/ Tape & Reel
GM38C43D8T	DIP-8	60 Units/ Tube
GM38C44S8T	SO - 8	100 Units/ Tube
GM38C44S8R	SO - 8	2,500 Units/ Tape & Reel
GM38C44D8T	DIP-8	60 Units/ Tube
GM38C45S8T	SO - 8	100 Units/ Tube
GM38C45S8R	SO - 8	2,500 Units/ Tape & Reel
GM38C45D8T	DIP-8	60 Units/ Tube

* For detail Ordering Number identification, please see last page.

◆ ABSOLUTE MAXIMUM RATINGS

PARAMETER	SYMBOL	VALUE	UNIT
Zener Current Operation at $\geq 16V$ may require special precautions(Note6)	I_{DD}	30	mA
Supply Voltage(Note 6)	V_{DD}	18	V
Switch Supply Voltage	V_D	18	V
Current Sense Voltage	V_{ISNS}	- 0.3 to + 5.5	V
Feedback Voltage	V_{FB}	- 0.3 to + 5.5	V
Output Current	I_{OUT}	0.5	A
Storage Temperature	T_A	- 65 to + 150	$^{\circ}\text{C}$


◆ OPERATING RATINGS

PARAMETER	SYMBOL	VALUE	UNIT
Junction Temperature	T_J	150	$^{\circ}\text{C}$

◆ PACKAGE PIN DESCRIPTION

PIN LEAD	FUNCTION	FUNCTION
1	COMP	Compensation Connect external Compensation on network to modify the error amplifier output.
2	FB	Feedback (Input): Error amplifier input .Feedback is 2.5Vat desired output voltage.
3	I_{SNS}	Current Sense (Input): Current sense comparator input. Connect to current sensing resistor or current transformer.
4	R_T / C_T	Timing Resistor / Timing Capacitor: Connect external RC network to select switching frequency.
5	GND	Ground: Combined analog and power ground.
6	OUT	Power Output: Totem - pole output.
7	V_{DD}	Analog Supply (Input): Controller circuitry supply input. Return to analog ground (AGND).
8	V_{REF}	5V Reference (Output): Connect external RC network.

◆ BLOCK DIAGRAM



GM38C42, GM38C43, GM38C44, GM38C45

◆ ELECTRICAL CHARACTERISTICS

(T_A = -40°C to 85°C, Note 4, V_{DD} = 15V, C_T=3.3 nF, R_T=10k , unless otherwise noted)

CHARACTERISTICS	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Reference Section					
Output Voltage	T _A = 25°C, I _O = 1mA	4.9	5.0	5.1	V
Line Regulation	12V ≤ V _{DD} ≤ 16V, I _O = 5µA, (Note 6)		2	20	mV
Load Regulation	1 ≤ I _O ≤ 20mA		1	25	mV
Temp. Stability	(Note 1)		0.2		mV / °C
Total Output Variation	Line, Load, Temp., Note 1	4.82		5.18	V
Output Noise Voltage	10Hz ≤ f ≤ 10kHz, T _A = 25°C, (Note 1)		50		µV
Long Term Stability	T _A = 125°C, 1000hrs., (Note 1)		5	25	mV
Output Short Circuit		-30	-80	-180	mA
Oscillator Section					
Initial Accuracy	T _A = 25°C, (Note 5)	49	52	55	KHz
Voltage Stability	12 ≤ V _{DD} ≤ 16V, (Note 6)		0.2	1.0	%
Temp. Stability	T _{MIN} ≤ T _A ≤ T _{MAX} , (Note 1)		0.04		% / °C
Clock Ramp	T _A = 25°C, V _{RT/CT} = 2V,	7.7	8.4	9.0	
Reset Current	T _{MIN} ≤ T _A ≤ T _{MAX}	7.2	8.4	9.5	mA
Amplitude	V _{RT/CT} (Peak to Peak)		1.9		Vp-p
Error Amplifier Section					
Input Bias Current	V _{FB} = 5V		-0.1	-2	µA
Input Voltage	V _{COMP} = 2.5V	2.42	2.5	2.58	V
Open Loop Voltage Gain	2V ≤ V _O ≤ 4V	65			dB
Power Supply Rejection Ratio	12V ≤ V _{DD} ≤ 16V	60	70		dB
Output Sink Current	V _{FB} = 2.7V, V _{COMP} = 1.1V	2	14		mA
Output Source Current	V _{FB} = 2.3V, V _{COMP} = 5V	-0.5	-1		mA
High Output Voltage	V _{FB} = 2.3V, R _L = 15k to GND	5.0	6.8		V
Low Output Voltage	V _{FB} = 2.7V, R _L = 15k to V _{REF}		0.1	1.1	V
Unity Gain Bandwidth	(Note 1)	0.7	1.0		MHz
Current Sense Section					
Gain	Note 2 and 3	2.85	3.0	3.15	V / V
Maximum Threshold	V _{COMP} = 5V, (Note 2)	0.9	1.0	1.1	V
PSRR	12V ≤ V _{DD} ≤ 16V, (Note 2)		70		dB
Input Bias Current			-1.0	-2	µA
Delay to Output			120	250	ns

◆ ELECTRICAL CHARACTERISTICS

($T_A = -40^\circ\text{C}$ to 85°C , Note 4, $V_{DD} = 15\text{V}$, $C_T = 3.3\text{ nF}$, $R_T = 11\text{k}\Omega$, unless otherwise noted)

CHARACTERISTICS	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Output Section					
$R_{DS(ON)}$ High	$I_{SOURCE} = 200\text{mA}$		20		
	$I_{SINK} = 200\text{mA}$		11		
Rise Time	$T_A = 25^\circ\text{C}$, $C_L = 1\text{nF}$		40	80	ns
Fall Time	$T_A = 25^\circ\text{C}$, $C_L = 1\text{nF}$		30	60	ns
Undervoltage Lockout Section					
Start Threshold	GM3438C42, GM38C44	13.5	14.5	15.5	V
	GM3438C43, GM38C45	7.8	8.4	9.0	
Minimum Operating Voltage	GM3438C42, GM38C44	8	9	10	V
	GM3438C43, GM38C45	7.0	7.6	8.2	
PWM Section					
Maximum Duty Cycle	GM3438C42, GM38C43	94	96		%
	GM3438C44, GM38C45	46	50		
Minimum Duty Cycle				0	%
Total Standby Current					
Start - Up Current	$V_{DD} = 13\text{V}$ for GM38C42, GM38C44 $V_{DD} = 7.5\text{V}$ for GM38C43, GM38C45		50	200	μA
Operating Supply Current	$V_{FB} = V_{ISNS} = 0\text{V}$		4	6	mA
Zener Voltage	$I_{DD} = 25\text{ mA}$, Note 6	30	37		V

Note 1: These parameters, although guaranteed, are not 100% tested in production.

Note 2: Parameter measured at trip point of latch with $V_{EA} = 0$.

Note 3: Gain defined as:

$$A = \frac{V_{PIN1}}{V_{TH}(I_{SNS})} ; 0 \leq V_{TH}(I_{SNS}) \leq 0.8\text{V}$$

Note 4: Adjust V_{DD} above the start threshold before setting at 15V.

Note 5: Output frequency equals oscillator frequency for the GM38C42 and GM38C43. Output frequency for the GM38C44, and GM38C45 equals one half the oscillator frequency.

Note 6: On 8-pin version, 18V is maximum input on pin 7, as this is also the supply pin for the output stage.

GM38C42, GM38C43, GM38C44, GM38C45

◆ TYPICAL PERFORMANCE CHARACTERISTICS




Figure 1. Oscillator Frequency Configuration




Figure 2. GM38C42, GM38C43 Output Dead Time vs. Oscillator Frequency




Figure 3. Oscillator Discharge Current vs. Temperature




Figure 4. Current Sense Amplifier vs. Error Amplifier Output




Figure 5. Short - Circuit Reference Current vs. Temperature




Figure 6. GM38C4X Output Waveform

◆ Application Information

Familiarity with 384x converter designs is assumed.

The GM38C4x has been designed to be compatible with 384xA series controllers.

GM38C4x Advantages

Start-up Current

Start-up current has been reduced to an ultra-low 50 μ A(typical) permitting higher-valued, lower-wattage, start-up resistors (power controller during power supply start-up). The reduced resistor wattage reduces cost and printed circuit space.

Operating Current

Operating current has been reduced to 4mA compared to 11mA for a typical bipolar controller. The controller runs cooler and the V_{DD} hold-up capacitance required during start-up may be reduced.

Output Driver

Complementary internal P-and N-channel MOSFETs produce rail-to rail output voltages for better performance driving external power MOSFETs. The driver transistor's low on resistance and high peak current capability can drive gate capacitances of greater than 1000pF. The value of output capacitance which can be driven is determined only by the rise/fall time requirements. Within the restrictions of output capacity and controller power dissipation, maximum switching frequency can approach 500kHz.

Design Precautions

When operating near 20V, circuit transients can easily exceed the 20V absolute maximum rating, permanently damaging the controller's CMOS construction. To reduce transients, use a 0.1 μ F low-ESR capacitor to next to the controller's supply V_{DD} (or V_D for '-1' versions)and ground connections.

Film type capacitors, such as Wima MKS2, are recommended.

When designing high -frequency converters, avoid capacitive and inductive coupling of the switching waveform into high impedance circuitry such as the error amplifier, oscillator, and current sense amplifier. Avoid long printed-circuit traces and component leads. Locate oscillator and compensation circuitry neat the IC. Use high frequency decoupling capacitors on V_{REF} , and if necessary, on V_{DD} . Return high di/dt currents directly to their source and use large ground planes.

Buck Converter

Refer to Figure 7. When at least 26V is applied to the input, C5 is charged through R2 until the voltage V_{DD} is greater than 14.5V(the undervoltage lockout value of the GM38C42). Output switching begins when Q1 is turned on by the gate drive transformer T1, charging the output filter capacitor C3 through L1. D5 supplies a regulated +12V to V_{DD} once the circuit is running.

Current sense transformer CT1 provides current feedback to ISNS for current-mode operation and cycle-by-cycle current limiting. This is more efficient than a high- power sense resistor and provides the required ground-referenced level shift.


When Q1 turns off, current flow continues from ground through D1 and L1 until Q1 is turned on again.

The 100V Schottky diode D1 reduces the forward voltage drop in the main current path, resulting in higher efficiency than could be accomplished using an ultra-fast recovery diode. R1 and C2 suppress parasitic oscillations from D1.

Using a high-value inductance for L1 and a low-ESR capacitor for C3 permits small capacitance with minimum output ripple. This inductance value also improves circuit efficiency by reducing the flux swing in L1.

Magnetic components are carefully chosen for minimal loss at 500kHz.

GM38C42, GM38C43, GM38C44, GM38C45




* Locate near GM38C42 supply pins


Figure 7. 500kHz, 25W, Buck Converter

Test	Conditions	Results
Line Regulation	$V_{IN} = 26V$ to $80V$, $I_O = 2A$	0.5%
Load Regulation	$V_{IN} = 48V$, $I_O = 0.2A$ to $2A$	0.6%
Efficiency	$V_{IN} = 48V$, $I_O = 2A$	90%
Output Ripple	$V_{IN} = 48V$, $I_O = 2A$ (20MHz BW)	100mV

◆ SOP-8(SO-8) PACKAGE OUTLINE DIMENSIONS



◆ DIP-8 PACKAGE OUTLINE DIMENSIONS



◆ ORDERING NUMBER

