

**TOSHIBA**

**2SC4707**

TOSHIBA TRANSISTOR SILICON NPN EPITAXIAL TYPE

# 2SC4707

LOW FREQUENCY AMPLIFIER APPLICATIONS.

DRIVER STAGE AMPLIFIER APPLICATIONS.


SWITCHING APPLICATIONS.

- Excellent  $h_{FE}$  Linearity  
:  $h_{FE}(2) = 35$  (Min.), ( $V_{CE} = 2V$ ,  $I_C = 300mA$ )
- Complementary to 2SA1811

MAXIMUM RATINGS ( $T_a = 25^\circ C$ )

CHARACTERISTIC	SYMBOL	RATING	UNIT
Collector-Base Voltage	$V_{CBO}$	35	V
Collector-Emitter Voltage	$V_{CEO}$	30	V
Emitter-Base Voltage	$V_{EBO}$	5	V
Collector Current	$I_C$	500	mA
Base Current	$I_B$	100	mA
Collector Power Dissipation	$P_C$	800	mW
Junction Temperature	$T_j$	150	$^\circ C$
Storage Temperature Range	$T_{stg}$	-55~150	$^\circ C$

Unit in mm



JEDEC	TO-92MOD
EIAJ	—
TOSHIBA	2-5J1A

Weight : 0.36g

ELECTRICAL CHARACTERISTICS ( $T_a = 25^\circ C$ )

CHARACTERISTIC	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Collector Cut-off Current	$I_{CBO}$	$V_{CB} = 35V$ , $I_E = 0$	—	—	0.1	$\mu A$
Emitter Cut-off Current	$I_{EBO}$	$V_{EB} = 5V$ , $I_C = 0$	—	—	0.1	$\mu A$
DC Current Gain	$h_{FE}(1)$	$V_{CE} = 2V$ , $I_C = 100mA$	100	—	300	
	$h_{FE}(2)$	$V_{CE} = 2V$ , $I_C = 300mA$	35	—	—	
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C = 300mA$ , $I_B = 30mA$	—	0.2	0.5	V
Base-Emitter Voltage	$V_{BE}$	$V_{CE} = 2V$ , $I_C = 100mA$	—	0.8	1.0	V
Transition Frequency	$f_T$	$V_{CE} = 6V$ , $I_C = 20mA$	—	300	—	MHz
Collector Output Capacitance	$C_{ob}$	$V_{CB} = 6V$ , $I_E = 0$ , $f = 1MHz$	—	7	—	pF

961001FAA2

- TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.



