查询OPA705供应商 捷多邦，专业PCB打样工厂，24小时加急出货

Burr-Brown Products
from Texas Instruments

OPA705
OPA2705
OPA4705



SBOS182A – JUNE 2001

Low-Cost, CMOS, Rail-to-Rail, I/O OPERATIONAL AMPLIFIERS

FEATURES

- RAIL-TO-RAIL INPUT AND OUTPUT
- WIDE SUPPLY RANGE:
  Single Supply: 4V to 12V
  Dual Supplies: ±2 to ±6
- LOW QUIESCENT CURRENT: 160µA
- LIMITED RANGE CMRR: 96dB
- LOW OFFSET: 0.5mV
- HIGH SPEED: 1MHz, 0.6V/µs
- *Micro*SIZE PACKAGES:
  SOT23-5, MSOP-8, TSSOP-14
- LOW INPUT BIAS CURRENT: 1pA

APPLICATIONS

- AUTOMOTIVE APPLICATIONS:
  Audio, Sensor Applications, Security Systems
- PORTABLE EQUIPMENT
- ACTIVE FILTERS
- TRANSDUCER AMPLIFIER
- TEST EQUIPMENT
- DATA ACQUISITION

DESCRIPTION

The OPA705 series low-cost op amps are optimized for applications requiring rail-to-rail input and output swing. Single, dual, and quad versions are offered in a variety of packages. While the quiescent current is less than 200µA per amplifier, the OPA705 still offers excellent dynamic performance (1MHz GBW and 0.6V/µs SR) and unity-gain stability.

The OPA705 series is fully specified and guaranteed over the supply range of ±2V to ±6V. Input swing extends 300mV beyond the rail and the output swings to within 40mV of the rail.

The single version (OPA705) is available in the *Micro*SIZE SOT23-5 and in the standard SO-8 surface-mount packages. The dual version (OPA2705) is available in the MSOP-8, SO-8, and DIP-8 packages. The quad OPA4705 is available in the TSSOP-14 and SO-14 packages. All are specified for operation from –40°C to +85°C.



SOT23-5



SO-8, DIP-8



MSOP-8, SO-8, DIP-8



TSSOP-14, SO-14

Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include

Copyright © 2001, Texas Instruments Incorporated

ABSOLUTE MAXIMUM RATINGS[1]

Supply Voltage, V+ to V–	13.2V
Signal Input Terminals, Voltage[2]	(V–) –0.3V to (V+) +0.3V
Current[2]	10mA
Output Short-Circuit[3]	Continuous
Operating Temperature	–55°C to +125°C
Storage Temperature	–65°C to +150°C
Junction Temperature	+150°C
Lead Temperature (soldering, 10s)	+300°C

NOTES: (1) Stresses above these ratings may cause permanent damage. Exposure to absolute maximum conditions for extended periods may degrade device reliability. (2) Input terminals are diode-clamped to the power supply rails. Input signals that can swing more than 0.3V beyond the supply rails should be current-limited to 10mA or less. (3) Short-circuit to ground, one amplifier per package.

ELECTROSTATIC DISCHARGE SENSITIVITY

This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

PACKAGE/ORDERING INFORMATION

PRODUCT	DESCRIPTION	MINIMUM RECOMMENDED GAIN	PACKAGE	PACKAGE DRAWING NUMBER	PACKAGE MARKING	ORDERING NUMBER[1]	TRANSPORT MEDIA
OPA705NA	Single, GBW = 1MHz	1	SOT23-5	331	A05	OPA705NA/250	Tape and Reel
"	"	"	"	"	"	OPA705NA/3K	Tape and Reel
OPA705UA	Single, GBW = 1MHz	1	SO-8	182	OPA705UA	OPA705UA	Rails
"	"	"	"	"	"	OPA705UA/2K5	Tape and Reel
OPA705PA	Single, GBW = 1MHz	1	DIP-8	006	OPA705PA	OPA705PA	Rails
OPA2705EA	Dual, GBW = 1MHz	1	MSOP-8	337	B05	OPA2705EA/250	Tape and Reel
"	"	"	"	"	"	OPA2705EA/2K5	Tape and Reel
OPA2705UA	Dual, GBW = 1MHz	1	SO-8	182	OPA2705UA	OPA2705UA	Rails
"	"	"	"	"	"	OPA2705UA/2K5	Tape and Reel
OPA2705PA	Dual, GBW = 1MHz	1	DIP-8	006	OPA2705PA	OPA2705PA	Rails
OPA4705EA	Quad, GBW = 1MHz	1	TSSOP-14	357	OPA4705EA	OPA4705EA/250	Tape and Reel
"	"	"	"	"	"	OPA4705EA/2K5	Tape and Reel
OPA4705UA	Quad, GBW = 1MHz	1	SO-14	235	OPA4705UA	OPA4705UA	Rails
"	"	"	"	"	"	OPA4705UA/2K5	Tape and Reel

NOTE: (1) Models with a slash (/) are available only in Tape and Reel in the quantities indicated (e.g., /3K indicates 3000 devices per reel). Ordering 3000 pieces of “OPA705NA/3K” will get a single 3000-piece Tape and Reel.

ELECTRICAL CHARACTERISTICS: V_S = 4V to 12V

Boldface limits apply over the specified temperature range, **T_A = –40°C to +85°C**

At T_A = +25°C, R_L = 20kΩ connected to V_S/2 and V_{OUT} = V_S/2, unless otherwise noted.

PARAMETER		CONDITION	OPA705NA, UA, PA OPA2705EA, UA, PA OPA4705EA, UA MIN	TYP	MAX	UNITS
OFFSET VOLTAGE						
Input Offset Voltage	V_{OS}	V_S = ±5V, V_{CM} = 0V		±0.5	±5	mV
Drift	**dV_{OS}/dT**	**T_A = –40°C to +85°C**		**±4**		**µV/°C**
vs Power Supply	PSRR	V_S = ±2V to ±6V, V_{CM} = 0V		20	100	µV/V
Over Temperature		**V_S = ±2V to ±6V, V_{CM} = 0V**		**100**		**µV/V**
Channel Separation, dc		R_L = 20kΩ		1		µV/V
f = 1kHz				98		dB
INPUT VOLTAGE RANGE						
Common-Mode Voltage Range	V_{CM}		(V–) – 0.3		(V+) + 0.3	V
Common-Mode Rejection Ratio	CMRR	V_S = ±5V, (V–) – 0.3V < V_{CM} < (V+) + 0.3V	66	77		dB
over Temperature		**V_S = ±5V, (V–) < V_{CM} < (V+)**		**74**		**dB**
		V_S = ±5V, (V–) – 0.3V < V_{CM} < (V+) – 2V	66	96		dB
over Temperature		**V_S = ±5V, (V–) < V_{CM} < (V+) – 2V**		**93**		**dB**
INPUT BIAS CURRENT						
Input Bias Current	I_B	V_S = ±5V, V_{CM} = 0V		±1	±10	pA
Input Offset Current	I_{OS}	V_S = ±5V, V_{CM} = 0V		±0.5	±10	pA
INPUT IMPEDANCE						
Differential				$4 \cdot 10^9$ || 4		Ω || pF
Common-Mode				$5 \cdot 10^{12}$ || 4		Ω || pF
NOISE						
Input Voltage Noise, f = 0.1Hz to 10Hz		V_S = ±5V, V_{CM} = 0V		6		µVp-p
Input Voltage Noise Density, f = 1kHz	e_n	V_S = ±5V, V_{CM} = 0V		45		nV/√Hz
Current Noise Density, f = 1kHz	i_n	V_S = ±5V, V_{CM} = 0V		2.5		fA/√Hz
OPEN-LOOP GAIN						
Open-Loop Voltage Gain	A_{OL}	R_L = 100kΩ, (V–)+0.1V < V_O < (V+)–0.1V		120		dB
		R_L = 20kΩ, (V–)+0.075V < V_O < (V+)–0.075V	100	110		dB
over Temperature		**R_L = 20kΩ, (V–)+0.075V < V_O < (V+)–0.075V**		**106**		**dB**
		R_L = 5kΩ, (V–)+0.15V < V_O < (V+)–0.15V	100	110		dB
over Temperature		**R_L = 5kΩ, (V–)+0.15V < V_O < (V+)–0.15V**		**106**		**dB**
OUTPUT						
Voltage Output Swing from Rail		R_L = 100kΩ, A_{OL} > 80dB		40		mV
		R_L = 20kΩ, A_{OL} > 100dB			75	mV
		R_L = 5kΩ, A_{OL} > 100dB			150	mV
Output Current	I_{OUT}	|V_S – V_{OUT}| < 1V		±10		mA
Short-Circuit Current	I_{SC}			±40		mA
Capacitive Load Drive	C_{LOAD}		See Typical Performance Curves			
FREQUENCY RESPONSE		C_L = 100pF				
Gain-Bandwidth Product	GBW	G = +1		1		MHz
Slew Rate	SR	V_S = ±5V, G = +1		0.6		V/µs
Settling Time, 0.1%	t_S	V_S = ±5V, 5V Step, G = +1		15		µs
0.01%		V_S = ±5V, 5V Step, G = +1		20		µs
Overload Recovery Time		V_{IN} • Gain = V_S		3		µs
Total Harmonic Distortion + Noise	THD+N	V_S = ±5V, V_O = 3Vp-p, G = +1, f = 1kHz		0.02		%
POWER SUPPLY						
Specified Voltage Range, Single Supply	V_S		4		12	V
Specified Voltage Range, Dual Supplies	V_S		±2		±6	V
Operating Voltage Range				3.6 to 12		V
Quiescent Current (per amplifier)	I_Q	I_O = 0		160	250	µA
over Temperature				**200**		**µA**
TEMPERATURE RANGE						
Specified Range			–40		85	°C
Operating Range			–55		125	°C
Storage Range			–65		150	°C
Thermal Resistance	θ_{JA}					
SOT23-5 Surface-Mount				200		°C/W
MSOP-8 Surface-Mount				150		°C/W
TSSOP-14 Surface-Mount				100		°C/W
SO-8 Surface Mount				150		°C/W
SO-14 Surface Mount				100		°C/W
DIP-8				100		°C/W

TYPICAL CHARACTERISTICS

At T_A = +25°C, V_S = ±5V, and R_L = 20kΩ, unless otherwise noted.













TYPICAL CHARACTERISTICS (Cont.)

At T_A = +25°C, V_S = ±5V, and R_L = 20kΩ, unless otherwise noted.

COMMON-MODE REJECTION RATIO vs TEMPERATURE



OPEN-LOOP GAIN vs TEMPERATURE



INPUT BIAS (I_B) AND OFFSET (I_{OS}) CURRENT vs TEMPERATURE



QUIESCENT CURRENT vs TEMPERATURE



PSRR vs TEMPERATURE



TOTAL HARMONIC DISTORTION PLUS NOISE (Load = 5kΩ, BW = 8kHz, 1.0Vrms, G = +1)



TYPICAL CHARACTERISTICS (Cont.)

At T_A = +25°C, V_S = ±5V, and R_L = 20kΩ, unless otherwise noted.

INPUT BIAS CURRENT (I_B)
vs COMMON-MODE VOLTAGE (V_{CM})
TEMPERATURE = °25C



INPUT BIAS CURRENT (I_B)
vs COMMON-MODE VOLTAGE (V_{CM})
TEMPERATURE = 125°C



QUIESCENT CURRENT vs SUPPLY VOLTAGE



SHORT-CIRCUIT CURRENT
vs SUPPLY VOLTAGE



OUTPUT VOLTAGE SWING vs OUTPUT CURRENT



SMALL-SIGNAL OVERSHOOT (%)
vs CAPACITIVE LOAD AND GAIN



TYPICAL CHARACTERISTICS (Cont.)

At T_A = +25°C, V_S = ±5V, and R_L = 20kΩ, unless otherwise noted.

SETTLING TIME vs GAIN



V_{OS} PRODUCTION DISTRIBUTION



V_{OS} DRIFT PRODUCTION DISTRIBUTION



SMALL SIGNAL STEP RESPONSE
(G = +1V/V, R_L = 20kΩ, C_L = 100pF)



LARGE SIGNAL STEP RESPONSE
(G = +1V/V, R_L = 20kΩ, C_L = 100pF)



APPLICATIONS INFORMATION

OPA705 series op amps can operate on 160µA quiescent current from a single (or split) supply in the range of 4V to 12V (±2V to ±6V), making them highly versatile and easy to use. The OPA705 is unity-gain stable and offers 1MHz bandwidth and 0.6V/µs slew rate.

Rail-to-rail input and output swing helps maintain dynamic range, especially in low supply applications. Figure 1 shows the input and output waveforms for the OPA705 in unity-gain configuration. Operation is from a ±5V supply with a 100kΩ load connected to $V_S/2$. The input is a 10Vp-p sinusoid. Output voltage is approximately 10Vp-p.



FIGURE 1. Rail-to-Rail Input and Output.

Power-supply pins should be bypassed with 1000pF ceramic capacitors in parallel with 1µF tantalum capacitors.

OPERATING VOLTAGE

OPA705 series op amps are fully specified and guaranteed from +4V to +12V over a temperature range of –40ºC to +85ºC. Parameters that vary significantly with operating voltages or temperature are shown in the Typical Characteristics.

RAIL-TO-RAIL INPUT

The input common-mode voltage range of the OPA705 series extends 300mV beyond the supply rails at room temperature. This is achieved with a complementary input stage—an N-channel input differential pair in parallel with a P-channel differential pair, as shown in Figure 2. The N-channel pair is active for input voltages close to the positive rail, typically (V+) – 2.0V to 300mV above the positive supply, while the P-channel pair is on for inputs from 300mV below the negative supply to approximately (V+) – 1.5V. There is a small transition region, typically (V+) – 2.0V to (V+) – 1.5V, in which both pairs are on. This 500mV transition region can vary ±100mV with process variation. Thus, the transition region (both stages on) can range from (V+) – 2.1V to (V+) – 1.4V on the low end, up to (V+) – 1.9V to (V+) – 1.6V on the high end. Within the 500mV transition region PSRR, CMRR, offset voltage, and offset drift, and THD may vary compared to operation outside this region.



FIGURE 2. Simplified Schematic.

INPUT VOLTAGE

Device inputs are protected by ESD diodes that will conduct if the input voltages exceed the power supplies by more than approximately 300mV. Momentary voltages greater than 300mV beyond the power supply can be tolerated if the current is limited to 10mA. This is easily accomplished with an input resistor, as shown in Figure 3. Many input signals are inherently current-limited to less than 10mA; therefore, a limiting resistor is not always required. The OPA705 features no phase inversion when the inputs extend beyond supplies if the input current is limited, as seen in Figure 4.



FIGURE 3. Input Current Protection for Voltages Exceeding the Supply Voltage.



FIGURE 4. OPA705—No Phase Inversion with Inputs Greater than the Power-Supply Voltage.

RAIL-TO-RAIL OUTPUT

A class AB output stage with common-source transistors is used to achieve rail-to-rail output. This output stage is capable of driving 1kΩ loads connected to any point between V+ and ground. For light resistive loads (> 100kΩ), the output voltage can swing to 40mV from the supply rail. With moderate resistive loads (20kΩ), the output can swing to within 75mV from the supply rails while maintaining high open-loop gain (see the typical performance curve "Output Voltage Swing vs Output Current").

CAPACITIVE LOAD AND STABILITY

The OPA705 series op amps can drive up to 1000pF pure capacitive load. Increasing the gain enhances the amplifier's ability to drive greater capacitive loads (see the typical performance curve "Small Signal Overshoot vs Capacitive Load").

One method of improving capacitive load drive in the unity-gain configuration is to insert a 10Ω to 20Ω resistor inside the feedback loop, as shown in Figure 5. This reduces ringing with large capacitive loads while maintaining DC accuracy.



FIGURE 5. Series Resistor in Unity-Gain Buffer Configuration Improves Capacitive Load Drive.

APPLICATION CIRCUITS

The OPA705 series op amps are optimized for driving medium-speed sampling data converters. Figure 6 shows the OPA2705 in a dual-supply buffered reference configuration for the DAC7644. The DAC7644 is a 16-bit, low-power, quad-voltage output converter. Small size makes the combination ideal for automatic test equipment, data acquisition systems, and other low-power space-limited applications.



FIGURE 6. OPA705 as Dual Supply Configuration-Buffered References for the DAC7644.

IMPORTANT NOTICE

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgment, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Customers are responsible for their applications using TI components.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, license, warranty or endorsement thereof.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations and notices. Representation or reproduction of this information with alteration voids all warranties provided for an associated TI product or service, is an unfair and deceptive business practice, and TI is not responsible nor liable for any such use.

Resale of TI's products or services with *statements different from or beyond the parameters* stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service, is an unfair and deceptive business practice, and TI is not responsible nor liable for any such use.

Also see: Standard Terms and Conditions of Sale for Semiconductor Products. www.ti.com/sc/docs/stdterms.htm

Mailing Address:

Texas Instruments
Post Office Box 655303
Dallas, Texas 75265

Copyright © 2001, Texas Instruments Incorporated