

TOSHIBA

TC9304F-051

TOSHIBA CMOS DIGITAL INTEGRATED CIRCUIT SILICON MONOLITHIC

TC9304F-051

SINGLE CHIP DTS MICRO CONTROLLER (DTS-10)

TC9304F-051 is a single chip digital tuning system for car audio use. Having the capability corresponding to the requirement of the whole world with the abundant specification selecting jumpers, this system is provided with the functions for two bands or three bands, clock and tape.

FEATURES

Receiving band

| AREA | CODE | | BAND | RECEIVING BAND [Hz] | STEP [Hz] | FREF [Hz] | IF [Hz] |
|--------------|------|----|------|----------------------|--------------|-----------|-------------|
| | E0 | E1 | | | | | |
| Europe | 0 | 0 | FM | 87.50~108.00M | 50k | 25k | + 10.7M |
| | | | MW | 531~ 1602k | 9k | 9k | (*1) + 450k |
| | | | LW | 153 / 155~279 / 281k | (*2) 1k / 9k | 1k | |
| USA | 1 | 0 | FM | 87.5~ 107.9M | 200k | 25k | + 10.7M |
| | | | MW | 530~ 1710k | 10k | 10k | + 450k |
| Japan | 0 | 1 | FM | 76.1~ 89.9M | 100k | 25k | - 10.7M |
| | | | MW | 522~ 1629k | 9k | 9k | + 450k |
| South Africa | 1 | 1 | FM | 87.50~108.00M | 50k | 25k | - 10.7M |
| | | | MW | 531~ 1602k | 9k | 9k | + 450k |

(*1) MW and LW are operating as one band. LW stop frequency is can be selected.
 UP ...LW 279 / 281kHz ...→ MW 531kHz ...→ MW 1602kHz ...→ LW 153 / 155kHz...
 DOWN...MW 1602kHz ←... LW 153 / 155kHz ←... LW 279 / 281kHz ←... MW 531kHz...

(*2) LW manual tuning ; 153~281kHz
 LW auto tuning (Stop frequency 9N) ; 153~279kHz
 LW auto tuning (Stop frequency 9N + 2) ; 155~281kHz

Tuning function

- Manual UP/DOWN tuning
- Auto-search tuning (SEEK)
- Hold-search tuning (SCAN)
- Memory scan tuning
- LW stop frequency on SEEK/SCAN selector


980910EBA2

● TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.

● The products described in this document are subject to the foreign exchange and foreign trade laws.

● The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.

● The information contained herein is subject to change without notice.



○ Memory function

- Each band (FM1, FM2, MW/LW) : 6 stations, 3 bands×6 stations= 18 stations max.
But the receiving range of each band of FM1 and FM2 are the same.
- Auto-memory function
- Preset method can be chosen 1 key type or 6 keys type.

○ Others

- Clock function is optional.
- Clock display is optional at radio off mode.
- The abundant function switches and display for tape deck control.

