

No.4040

Monolithic Linear IC

LA7282,7282M

**VCR Audio Signal Recording/
Playback Processor**

Overview

The LA7282 and 7282M are small package LSIs containing all functions necessary to record and playback VTR audio signal.


Features

- Smaller package leaves large space for other components.
- Delete of In and Output electrolysis capacitor.
- Low capacitor (0.1 μ F) for the line amp inputs (PE IN and AUDIO IN)
- Non-Adjustment of PB Gain by less gain scatter

Package Dimensions


unit : mm

3067-DIP24S




unit : mm

3112-MFP24S



Pin Assignment



LA7282,7282M

Maximum Ratings at $T_a = 25^\circ\text{C}$

				unit
Maximum Supply Voltage	V_{CC} max		14	V
Pin 1 Input Voltage	V_{IN1}	$T_a = 65^\circ\text{C}, f = 80 \text{ kHz (sin)}, I_{LK} = 10 \mu\text{A}$	90 (± 45)	$\text{V}_{\text{p-p}}$
Pin 1 Input Current	I_{IN1}		± 1.5	mA
Allowable Power Dissipation	P_d max	$T_a \leq 65^\circ\text{C}$, when mounted on the recommended PCB	400	mW
Operating Temperature	T_{opr}		-10 to +65	$^\circ\text{C}$
Storage Temperature	T_{stg}		-55 to +125	$^\circ\text{C}$

Operating Conditions at $T_a = 25^\circ\text{C}$

				unit
Recommended Supply Voltage	V_{CC}		12.0	V
Operating Voltage Range	V_{CC} op		11.25 to 12.75	V

Operating Characteristics at $T_a = 25^\circ\text{C}$, $V_{CC} = 12 \text{ V}$, $f = 1 \text{ kHz}$, $\text{OdBv} = :1.0 \text{ Vrms}$

			min	typ	max	unit
Current Dissipation (EE)	I_{CCE}	Quiescent	8.0	12.0	17.0	mA
Current Dissipation (PB)	I_{CCP}	Quiescent	9.0	13.0	18.0	mA
Current Dissipation (REC)	I_{CCR}	Quiescent	7.0	10.0	14.0	mA
Overall Gain at PB Mode [Equalizing Amp]	$V_{G_{PB}}$	EQ IN-LINE OUT, $V_O = -5 \text{ dBv}$	59.0	59.5	60.0	dB
Open Loop Voltage Gain	$V_{G_{OE}}$	$V_O = -5 \text{ dBv}$	66.0	71.0		dB
Equivalent Input Noise Voltage	V_{NIE}	$R_g = 2.2 \text{ k}\Omega$, DIN Audio Filter		1.2	1.8	μVrms
Input Impedance [Line Amp]	Z_{INE}			130		$\text{k}\Omega$
Voltage Gain (PB IN)	$V_{G_{LP}}$	$V_O = -5 \text{ dBv}$	21.0	21.5	22.0	dB
Voltage Gain (EE,REC IN)	$V_{G_{LR}}$	$V_O = -5 \text{ dBv}$	21.0	21.5	22.0	dB
Total Harmonic Distortion	THD_L	$V_O = -5 \text{ dBv}$		0.3	0.5	%
Output Noise Voltage	V_{NOL}	DIN Audio Filter		-70.0	-64.0	dBv
Input Impedance (PB IN)	Z_{IN1}			120		$\text{k}\Omega$
Input Impedance (EE,REC IN)	Z_{IN2}			120		$\text{k}\Omega$
Maximum Output Voltage	V_{OML}	THD = 3%	1.5	2.1		Vrms
Output Voltage at ALC	V_{OA}	$V_{IN} = -28 \text{ dBv}$	-9.0	-8.0	-7.0	dBv
ALC Effect	ALC	$V_{IN} = -28 \text{ to } -8 \text{ dBv}$		1.5	3.0	dB
Total Harmonic Distortion at ALC	THD_A	$V_{IN} = -28 \text{ dBv}$		0.25	0.6	%
Muting Circuit						
Voltage Gain (open loop)	$V_{G_{OR}}$	$V_O = -5 \text{ dBv}$	47.0	52.0		dB
Voltage Gain (closed loop)	$V_{G_{CR}}$	$V_O = -5 \text{ dBv}$	12.5	13.0	13.5	dB
Total Harmonic Distortion	THD_R	$V_O = -5 \text{ dBv}$		0.1	0.3	%
Input Impedance	Z_{INR}			50		$\text{k}\Omega$
Maximum Output Voltage	V_{OMR}	THD = 3%	1.5	2.0		Vrms
On Voltage	V_{MON}	Pin 22, DC	3.8		6.0	V
Off Voltage	V_{MOFF}	Pin 22, DC	0		1.0	V
Mute Attenuation Level (PB,EE)	M_P, M_E		80.0	90.0		dB
Mute Attenuation Level (REC)	M_R		65.0	70.0		dB
PB/EE Selector Circuit						
PB Mode Hold Voltage	V_{PP}	Pin 23, DC	0		1.0	V
EE Mode Hold Voltage	V_{PE}	Pin 23, DC	3.3		6.0	V
REC/EE Selector Circuit						
REC Mode Hold Voltage	V_{RR}	Pin 24, DC	3.3		V_{CC}	V
EE Mode Hold Voltage	V_{RE}	Pin 24, DC	0		1.0	V

Continued on next page.


LA7282,7282M

			min	typ	max	unit
[Equalizer Selector Circuit]						
Switch On Voltage	V_{EON}	Pin 20, 21, DC	3.5		6.0	V
Switch Off Voltage	V_{EOFF}	Pin 20, 21, DC	0		0.8	V
[Head Selector Switch]						
Pin 1 On Resistance	R_{ON1}	$I_1 = \pm 1 \text{ mA}$		15	30	Ω
Pin 2 On Resistance	R_{ON2}	$I_2 = \pm 1 \text{ mA}$		5	10	Ω
Pin 1 Input Voltage	V_{IN1}	$T_a = 65^\circ\text{C}, f = 80 \text{ kHz (sin)}, I_{LK} = 10 \mu\text{A}$			± 45	V

- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of December, 1996. Specifications and information herein are subject to change without notice.


Block Diagram



Unit (resistance : Ω, capacitance : F)

LA7282,7282M

Test Circuit















Unit (resistance : Ω , capacitance : F)

<Switch Setting Table>

Parameter (Symbol)	SW1	SW2	SW3	SW4	SWS	V _M	V _P	V _R	Input	Measurement
I _{CCE}	2	1	1	2	1	GND	5V	GND	-	A
I _{CCP}	2	1	1	2	1	GND	GND	GND	-	A
I _{CCR}	2	1	1	2	1	GND	5V	5V	-	A
V _{G_{PB}}	1	1	1	2	1	GND	GND	GND	V _{IN1}	V _{O2}
V _{G_{OE}}	1	2	2	2	1	GND	GND	GND	V _{IN1}	V _{O1}
V _{NIE}	2	1	2	2	1	GND	GND	GND	-	V _{O1}
V _{G_{LP}, THD_L, V_{OML}}	2	1	2	2	1	GND	GND	GND	V _{IN2}	V _{O2}
V _{G_{LR}}	2	1	1	2	1	GND	5V	GND	V _{IN3}	V _{O2}
V _{NOL}	2	1	2	2	1	GND	5V	GND	-	V _{O2}
V _{OA, ALC, THD_A}	2	1	2	1	1	GND	5V	GND	V _{IN3}	V _{O2}
V _{G_{OR}}	2	1	2	2	2	GND	5V	GND	V _{IN4}	V _{O3}
V _{G_{CR}, THD_R, V_{OMR}}	2	1	2	2	1	GND	5V	GND	V _{IN4}	V _{O3}
M _P	1	1	1	2	1	5V	GND	GND	V _{IN1}	V _{O2}
M _R	2	1	1	2	1	5V	5V	GND	V _{IN4}	V _{O3}
M _E	2	1	2	2	1	5V	5V	GND	V _{IN2}	V _{O2}












LA7282,7282M

Pin Functions

Pin No.	Function	Terminal Circuit	Description
1	Head Switch 1 (High voltage)		EE, PB: on; REC: off On resistance: $10\ \Omega$, typ. With stand voltage during off: $\pm 45\ V$ ($f = 80\ kHz$)
2	EQ AMP Input and Head Switch 2		Input playback signal to the head. Input impedance: $130\ k\Omega$, typ. EE, REC: on; PB: off Switch on resistance: $5\ \Omega$, typ.
3	GND		An exclusive GND for pin 1 head switch 1, EQ AMP and playback EP switch
4	EP Switch 1		Sets the tape head resonant frequency. On resistance: $15\ \Omega$, typ. Input impedance: $120\ k\Omega$, typ. (playback EP mode)
5	EP Switch 2		Increases the voltage gain at higher frequencies by reducing negative feedback amount of the PB EQ AMP. On resistance: $15\ \Omega$, typ. Input impedance: $12\ k\Omega$, typ. (playback EP mode)
6	EQ AMP NFB		Input of negative feedback of the EQ AMP to establish desired equalizing characteristics.
7	GND		Common return for all circuits except for EQ AMP and head switch 1.
8	EQ AMP Output		
9	LINE AMP PB Input		Input PB signal to the EQ AMP. The input impedance of pin 9 is high ($120\ k\Omega$) and requires a small coupling capacitor of $0.1\ \mu F$.
10	ALC FILTER		Connecting this pin to GND through a capacitor enables detection. The RC time constant sets attack recovery time.
11	LINE AMP Audio Input		Input EE, REC signal. Select value of R_1 and R_2 so that the reference input is at the shoulder of the ALC.  The amp gain should be set for 21.5 dB. The input impedance of pin 11 is high ($120\ k\Omega$) and requires a small coupling capacitor of $0.1\ \mu F$.
12	ALC Detect Input		Accepts the output signal of LINE amp. The ALC level is determined by the voltage divider consisting of R_1 and R_2 . 
13	LINE AMP Output		Output impedance: $50\ \Omega$, typ.

Unit (resistance : Ω)

LA7282, 7282M

Pin No.	Function	Terminal Circuit	Description																								
14	REC AMP Input	 	<p>Input recording signal from LINE AMP.</p> <p>Input current is set by the divider consisting of R_1 and R_2.</p> <p>Pin 14 requires no coupling capacitor since REC AMP is to operate at zero level and as inverting amp.</p>																								
15	LP Switch		<p>Sets the high peaking point to the frequency suitable for LP.</p> <p>On resistance: $15\ \Omega$ typ.</p> <p>Input impedance: $60\ k\Omega$ typ.</p>																								
16	REC AMP NFB		<p>Connecting an L, C, R network to this pin causes a peaking frequency to rise.</p>																								
17	REC AMP Output		<p>Output impedance: $40\ \Omega$ typ.</p>																								
18	Ripple Filter		<p>Connecting a electrolytic capacitor across this pin and GND smoothes ripples.</p>																								
19	Supply Voltage (V_{CC})		<p>$V_{CC} = 15\ V$ max</p> <p>$V_{CC} = 11.25 - 12.75\ V$ typ.</p>																								
20	LP Control		<p>Applying $3.5\ V$ DC or more ($6.0\ V$ max.) to this pin turns on LP switch (pin 15). The switch turns off at $0.8\ V$ or below.</p>																								
21	EP Control		<p>Applying $3.5\ V$ DC or more ($6.0\ V$ max.) to this pin turns on EP switch (pin 4,5) and LP switch (pin 15). The switches turn off at $0.8\ V$ or below.</p>																								
22	MUTE Control		<p>Applying $3.8\ V$ DC or more ($6.0\ V$ max.) to this pin turns on mute circuit. The mute is disabled at $1.0\ V$ or below.</p> <p>[Control mode]</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th rowspan="2">Mode</th> <th colspan="2">MUTE r_{L_J}</th> <th colspan="2">MUTE r_{H_J}</th> </tr> <tr> <th>LINE AMP</th> <th>REC AMP</th> <th>LINE AMP</th> <th>REC AMP</th> </tr> </thead> <tbody> <tr> <td>PB Mode</td> <td>○</td> <td>✗</td> <td>✗</td> <td>✗</td> </tr> <tr> <td>EE Mode</td> <td>○</td> <td>○</td> <td>✗</td> <td>✗</td> </tr> <tr> <td>REC Mode</td> <td>○</td> <td>○</td> <td>○</td> <td>✗</td> </tr> </tbody> </table> <p>[O: Pass signal, x: Block signal]</p>	Mode	MUTE r_{L_J}		MUTE r_{H_J}		LINE AMP	REC AMP	LINE AMP	REC AMP	PB Mode	○	✗	✗	✗	EE Mode	○	○	✗	✗	REC Mode	○	○	○	✗
Mode	MUTE r_{L_J}		MUTE r_{H_J}																								
	LINE AMP	REC AMP	LINE AMP	REC AMP																							
PB Mode	○	✗	✗	✗																							
EE Mode	○	○	✗	✗																							
REC Mode	○	○	○	✗																							
23	PB Control		<p>Applying $3.3\ V$ DC or more ($6.0\ V$ max.) to this pin enters EE mode and $1.0\ V$ or below PB mode.</p>																								
24	REC Control		<p>Applying $3.0\ V$ DC or more (up to V_{CC}) to this pin enters REC mode and $1.0\ V$ or below EE mode.</p>																								

Unit (resistance : Ω)