

Ordering number : EN5520A

CMOS LSI

**SANYO****LC74785, LC74785M****On-Screen Display Controller LSI****Overview**


The LC74785 and LC74785M are on-chip EDS CMOS LSIs for on-screen display, a function that displays characters and patterns on a TV screen under microprocessor control. These LSIs support  $12 \times 18$  dot characters and can display 12 lines by 24 characters of text.

**Features**

- Display format: 24 characters by 12 rows (Up to 288 characters)
- Character format: 12 (horizontal)  $\times$  18 (vertical) dots
- Character sizes: Three sizes each in the horizontal and vertical directions
- Characters in font: 128
- Initial display positions: 64 horizontal positions and 64 vertical positions
- Blinking: Specifiable in character units
- Blinking types: Two periods supported: About 1.0 second and about 0.5 second
- Blanking: Over the whole font ( $12 \times 18$  dots)
- Background color
  - Background coloring: 8 colors (internal synchronization mode): 4fsc
  - Background coloring: 6 colors (internal synchronization mode): 2fsc
- Line background color
  - Can be set for 3 lines
  - Line background coloring: 8 colors (internal synchronization mode): 4fsc
  - Line background coloring: 6 colors (internal synchronization mode): 2fsc
- External control input: 8-bit serial input format
- On-chip sync separator circuit
- EDS support
- Video output
  - NTSC-format composite output
- Package
  - 24-pin plastic DIP (300 mil)
  - 24-pin plastic SOP (375 mil)


**Package Dimensions**

unit: mm

**3067-DIP24S**

SANYO: DIP24S


unit: mm

**3045B-MFP24**

SANYO: MFP24

## LC74785, LC74785M

### Pin Assignment



Top View

A06218

### Pin Functions

Pin No.	Pin	Function	Notes
1	Vss1	Ground	Ground connection (digital system ground)
2	Xtal IN		
3	Xtal OUT (MUTE)	Crystal oscillator (MUTE input)	These pins are used either to connect the crystal and capacitor used to form an external crystal oscillator used to generate the internal synchronizing signals, or to input an external clock signal (2fsc or 4fsc). As a mask option, the Xtalout pin can be set to function as the MUTE input pin. When this pin is set low, the video output is held at the pedestal level. (A pull-up resistor is built in and the input has hysteresis characteristics.)
4	CTRL1 (CHABLK)	Crystal oscillator input switching (CHABLK output)	Switches the mode between external clock input and crystal oscillator operation. A low level selects crystal oscillator operation and a high level selects external clock input. As a mask option, the CTRL1 input pin can be set to function as the CHABLK (character border) output. This is a 3-value output.
5	LN21	Data output	Line 21H pulse output (Even fields when MOD1 is low, both fields when MOD1 is high)
6	OSC IN		
7	OSC OUT	LC oscillator	Connections for the coil and capacitor that form the character output dot clock generation oscillator.
8	SYNC JDG	External synchronizing signal judgment output	Outputs the state of the external synchronizing signal presence/absence judgment. Outputs a high level when synchronizing signals are present. Outputs a field discrimination pulse (O/E pulse) when SEL2 is high.(HLFTON: Valid when 0) HLFTON: A signal in the range specified by LNA*, LNB*, and LNC* is output when HLFTON is high.) Outputs the dot clock (LC oscillator) when CS1 is high and RST is low. (This signal is not output on command resets.) Outputs the crystal oscillator clock when CS1 is low and RST is low. (This signal is not output on command resets.)
9	CS1	Enable input	Enable input pin for the OSD serial data input function. Serial data input is enabled when this pin is low. A pull-up resistor is built in. (The input has hysteresis characteristics.)
10	SCLK	Clock input	Input for the serial data input clock. A pull-up resistor is built in. (The input has hysteresis characteristics.)
11	SIN	Data input	Serial data input. A pull-up resistor is built in. (The input has hysteresis characteristics.)
12	VDD2	Power supply	Composite video signal level adjustment power supply (analog system power supply)
13	CVOUT	Video signal output	Composite video signal output
14	Vss2	Ground	Ground connection (analog system ground)

Continued on next page.

## LC74785, LC74785M

Continued from preceding page.

Pin No.	Pin	Function	Notes
15	CV <sub>IN</sub>	Video signal input	Composite video signal input
16	V <sub>DD1</sub>	Power supply	Power supply (+5 V: digital system power supply)
17	SYN <sub>IN</sub>	Sync separator circuit input	Video signal input for the built-in sync separator circuit
18	CDLR	Background color phase adjustment	Background color phase adjustment. Connect to ground through a resistor and a capacitor.
19	SEP <sub>OUT</sub>	Composite synchronizing signal output	Video signal output for the built-in sync separator circuit. Can be switched to function as an output for signal (high or ST. pulse) due to MOD0 by setting SEL0 high.
20	SEP <sub>IN</sub>	Vertical synchronizing signal input	Inputs the vertical synchronizing signal created by integrating the SEP <sub>OUT</sub> pin output signal. An integration circuit must be connected to the SEP <sub>OUT</sub> pin. This pin must be tied to V <sub>DD1</sub> if unused. This pin can be switched to function as the frame signal input mode by setting SEL1 high. (This is valid when CTL3 is set to 1.)
21	CS2	Enable input	EDS data output enable input. EDS data output is enabled when this pin is low. A pull-up resistor is built in. (The input has hysteresis characteristics.)
22	CPDT	Data output	EDS data output (This pin can be either an n-channel open-drain output or a CMOS output.)
23	RST	Reset input	System reset input A pull-up resistor is built in. (The input has hysteresis characteristics.)
24	V <sub>DD1</sub>	Power supply (+5 V)	Power supply (+5 V: digital system power supply)

Note: Both V<sub>DD1</sub> pins must be connected to the power supply.

## Specifications

### Absolute Maximum Ratings at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Supply voltage	V <sub>DD</sub>	V <sub>DD1</sub> and V <sub>DD2</sub>	V <sub>SS</sub> -0.3 to V <sub>SS</sub> +7.0	V
Input voltage	V <sub>IN</sub>	All input pins	V <sub>SS</sub> -0.3 to V <sub>DD</sub> +0.3	V
Output voltage	V <sub>OUT</sub>	LN21, CPDT, SEP <sub>OUT</sub> , and SYNC <sub>JDG</sub>	V <sub>SS</sub> -0.3 to V <sub>DD</sub> +0.3	V
Allowable power dissipation	Pd max	Ta = 25°C	350	mW
Operating temperature	Topr		-30 to +70	°C
Storage temperature	Tstg		-40 to +125	°C

### Allowable Operating Ranges at Ta = -30 to +70°C

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Supply voltage	V <sub>DD1</sub>	V <sub>DD1</sub>	4.5	5.0	5.5	V
	V <sub>DD2</sub>	V <sub>DD2</sub>	4.5	5.0	1.27V <sub>DD1</sub>	V
Input high-level voltage	V <sub>IH1</sub>	RST, CS1, CS2, SIN, SCLK, SEP <sub>IN</sub> , and MUTE	0.8V <sub>DD1</sub>		V <sub>DD1</sub> + 0.3	V
	V <sub>IH2</sub>	CTRL1	0.7V <sub>DD1</sub>		V <sub>DD1</sub> + 0.3	V
Input low-level voltage	V <sub>IL1</sub>	RST, CS1, CS2, SIN, SCLK, SEP <sub>IN</sub> , and MUTE	V <sub>SS</sub> - 0.3		0.2V <sub>DD1</sub>	V
	V <sub>IL2</sub>	CTRL1	V <sub>SS</sub> - 0.3		0.3V <sub>DD1</sub>	V
Pull-up resistance	R <sub>PU</sub>	Applies to pins set for the RST, CS1, CS2, SIN, SCLK, and MUTE pin options.	25	50	90	kΩ
Composite video signal input voltage	V <sub>IN1</sub>	CV <sub>IN</sub> ; V <sub>DD1</sub> = 5 V		2.0		V <sub>p-p</sub>
	V <sub>IN2</sub>	SYN <sub>IN</sub> ; V <sub>DD1</sub> = 5 V	1.5	2.0	2.5	V <sub>p-p</sub>
Input voltage	V <sub>IN3</sub>	Xtal <sub>IN</sub> (When external clock input is used) f <sub>in</sub> = 2 fsc or 4 fsc ; V <sub>DD1</sub> = 5 V	0.10		5.0	V <sub>p-p</sub>
Oscillator frequency	F <sub>Osc1</sub>	The Xtal <sub>IN</sub> and Xtal <sub>OUT</sub> oscillator pins (2 fsc: NTSC)		7.159		MHz
	F <sub>Osc1</sub>	The Xtal <sub>IN</sub> and Xtal <sub>OUT</sub> oscillator pins (4 fsc: NTSC)		14.318		MHz
	F <sub>Osc2</sub>	The OSC <sub>IN</sub> and OSC <sub>OUT</sub> oscillator pins (LC oscillator)	5		10	MHz

Note: When the Xtal<sub>IN</sub> pin is used in clock input mode, extreme care must be taken to prevent noise from entering the input signal.

## LC74785, LC74785M

### Electrical Characteristics at $T_a = -30$ to $+70^\circ\text{C}$ , $V_{DD1} = 5$ V unless otherwise specified.

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Input off leakage current	$I_{leak1}$	$CV_{IN}$			1	$\mu\text{A}$
Output off leakage current	$I_{leak2}$	$CV_{OUT}$			1	$\mu\text{A}$
Output high-level voltage	$V_{OH1}$	$LN21$ , $SYNC_{JDG}$ , $CPDT$ , and $SEP_{OUT}$ ; $V_{DD1} = 4.5$ V, $I_{OH} = -1.0$ mA	3.5			V
Output low-level voltage	$V_{OL1}$	$LN21$ , $SYNC_{JDG}$ , $CPDT$ , and $SEP_{OUT}$ ; $V_{DD1} = 4.5$ V, $I_{OL} = 1.0$ mA			1.0	V
Three-value output voltage	$V_O$	CHABLK; $V_{DD1} = 5.0$ V H M L	3.3		5.0	V
			1.8		2.3	V
			0		0.8	V
Input current	$I_{IH}$	$RST$ , $CS1$ , $\bar{CS2}$ , $SIN$ , $SCLK$ , $CTRL1$ , $SEP_{IN}$ , and $MUTE$ ; $V_{IN} = V_{DD1}$			1	$\mu\text{A}$
	$I_{IL}$	$CTRL1$ and $OSC_{IN}$ ; $V_{IN} = V_{SS1}$	-1			$\mu\text{A}$
Operating mode current drain	$I_{DD1}$	$V_{DD1}$ ; All outputs open, Xtal: 7.159 MHz, LC: 8 MHz			30	mA
	$I_{DD2}$	$V_{DD2}$ ; $V_{DD2} = 5$ V			20	mA
SYNC level	$V_{SN}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	0.70	0.82	0.94
			*2	0.89	1.01	1.13
			*3	1.18	1.30	1.42
Pedestal level	$V_{PD}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.32	1.44	1.56
			*2	1.52	1.64	1.76
			*3	1.81	1.93	2.05
Color burst low level	$V_{CBL}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	0.98	1.10	1.22
			*2	1.17	1.29	1.41
			*3	1.46	1.58	1.70
Color burst high level	$V_{CBH}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.63	1.75	1.87
			*2	1.83	1.95	2.07
			*3	2.11	2.23	2.35
Background color other than blue low level	$V_{RSL0}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.17	1.29	1.41
			*2	1.36	1.48	1.60
			*3	1.65	1.77	1.89
Background color other than blue high level	$V_{RSH0}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	2.33	2.45	2.57
			*2	2.52	2.64	2.76
			*3	2.81	2.93	3.05
Blue background color 1 low level	$V_{RSL1}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.08	1.20	1.32
			*2	1.27	1.39	1.51
			*3	1.56	1.68	1.80
Blue background color 2 low level	$V_{RSL2}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.49	1.61	1.83
			*2	1.68	1.80	1.92
			*3	1.97	2.09	2.21
Blue background color 1, 2 high level	$V_{RSH1}$ $V_{RSH2}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.97	2.09	2.21
			*2	2.17	2.29	2.41
			*3	2.46	2.58	2.70
Frame level 0	$V_{BK0}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.40	1.52	1.64
			*2	1.60	1.72	1.84
			*3	1.89	2.01	2.13
Frame level 1	$V_{BK1}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	1.97	2.09	2.21
			*2	2.17	2.29	2.41
			*3	2.46	2.58	2.70
Character level	$V_{CHA}$	$CV_{OUT}$ ; $V_{DD1} = 5.0$ V, $V_{DD2} = 5.0$ V	*1	2.55	2.67	2.79
			*2	2.75	2.87	2.99
			*3	3.04	3.16	3.28

- Note:
1. When the sync level is 0.8 V
  2. When the sync level is 1.0 V
  3. When the sync level is 1.3 V

## LC74785, LC74785M

### Timing Characteristics at $T_a = -30$ to $+70^\circ\text{C}$ , $V_{DD1} = 5 \pm 0.5 \text{ V}$


OSD write (See Figure 1.)

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Minimum input pulse width	$t_W(\text{SCLK})$	SCLK	200			ns
	$t_W(\text{CS1})$	$\overline{\text{CS1}}$ (The period when $\overline{\text{CS1}}$ is high)	1			$\mu\text{s}$
Data setup time	$t_{SU}(\text{CS1})$	$\overline{\text{CS1}}$	200			ns
	$t_{SU}(\text{SIN})$	SIN	200			ns
Data hold time	$t_h(\text{CS1})$	$\overline{\text{CS1}}$	2			$\mu\text{s}$
	$t_h(\text{SIN})$	SIN	200			ns
One word write time	$t_{word}$	The time to write 8 bits of data	4.2			$\mu\text{s}$
	$t_{wt}$	The RAM data write time	1			$\mu\text{s}$

EDS read (For the n-channel open-drain circuit, see Figure 2.)


Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Minimum input pulse width	$t_{CKCY}$	SCLK	2			$\mu\text{s}$
	$t_{CKL}$	SCLK	1			$\mu\text{s}$
Setup time	$t_{CKH}$	SCLK	1			$\mu\text{s}$
	$t_{ICK}$	SCLK	10			$\mu\text{s}$
Output delay time	$t_{CKO}$	CPDT			0.5	$\mu\text{s}$

Note: The CMOS output circuit follows the OSD timing.



**Figure 1 OSD Serial Data Input Timing**

A06219




Note: CPDT goes to the high-impedance state when  $\overline{\text{CS2}}$  is high.

A06220

**Figure 2 EDS Serial Output Test Conditions (For the n-channel open-drain circuit.)**

## LC74785, LC74785M




Note: The  $\overline{O/E}$  signal is output from the  $SYNC_{\text{D}\text{G}}$  pin when  $SEL2$  is high.  
 $LN21$  is output for even fields when  $MOD1$  is low and for both fields when  $MOD1$  is high.

A06221

Figure 3  $\overline{O/E}$  and  $LN21$  Output Timing

## LC74785, LC74785M




Note: When extracting closed caption character data when MOD1 is high (NTSC-TV), applications must determine whether the current field is odd or even by checking the signal level output from the SYNC<sub>IDG</sub> pin (with SEL2 set high) when a falling edge is detected on LN21.

A06222

Figure 4 Transferring caption data from the LC74785/M to the decoder LSI (microcontroller): Method 1 (Basic LC74785/M usage)

## LC74785, LC74785M

The timing of the transfer of caption data to the data output buffer is synchronized with the falling edge of the pulse output from LN21. Therefore, the software processing shown below is required if the decoder LSI (microcontroller) does not detect LN21 falling edges.



**Figure 5 Transferring caption data from the LC74785/M to the decoder LSI (microcontroller): Method 2  
(When it is not possible to allocate a port on the decoder LSI (microcontroller) to detect falling edges on LN21.)**


Since data is output to the output buffer once (during the even field) when MOD1 is low, the data transfer control operation from the decoder LSI (microcontroller) must be performed at least twice in a single frame (about 32 ms).

If a transfer control operation is performed twice in the same frame, the CPDT output on the second operation will be 16 bits of zero data. This allows the decoder LSI to determine that the data for the next frame has not been transferred yet.

Note: If CS2 remains low, the hardware will not be able to transfer the data to the output buffer. Therefore, the decoder LSI (microcontroller) must reset CS2 to high from low after it completes a data transfer control operation.  
Transfer method 2 cannot be used if MOD1 is high (NTSC-TV).

## LC74785, LC74785M

### System Block Diagram



A06224

## LC74785, LC74785M

---

### Display Control Commands

Display control commands have an 8-bit format and are transferred using the serial input function. Commands consist of a command identification code in the first byte and command data in the following bytes. The following commands are supported.

- 1 COMMAND0: Display memory (VRAM) write address setup command
- 2 COMMAND1: Display character data write command
- 3 COMMAND2: Vertical display start position and vertical character size setup command
- 4 COMMAND3: Horizontal display start position and horizontal character size setup command
- 5 COMMAND4: Display control setup command
- 6 COMMAND5: Display control setup command
- 7 COMMAND6: Synchronizing signal detection setup command
- 8 COMMAND7: Display control setup command
- 9 COMMAND8: Display control setup command
- 10 COMMAND9: Display control setup command
- 11 COMMAND10: Display control setup command

### Display Control Command Table

Command	First byte								Second byte							
	Command identification code				Data				Data							
	7	6	5	4	3	2	1	0	7	6	5	4	3	2	1	0
COMMAND0 Write address setup	1	0	0	0	V3	V2	V1	V0	0	0	0	H4	H3	H2	H1	H0
COMMAND1 Character write	1	0	0	1	0	0	0	0	at	c6	c5	c4	c3	c2	c1	c0
COMMAND2 Vertical character size and vertical display start position	1	0	1	0	VS 21	VS 20	VS 11	VS 10	0	FS	VP 5	VP 4	VP 3	VP 2	VP 1	VP 0
COMMAND3 Horizontal character size and horizontal display start position	1	0	1	1	HS 21	HS 20	HS 11	HS 10	0	LC	HP 5	HP 4	HP 3	HP 2	HP 1	HP 0
COMMAND4 Display control	1	1	0	0	TST MOD	RAM ERS	OSC STP	SYS RST	0	BLK 2	BLK 1	BLK 0	BK 1	BK 0	RV	DSP ON
COMMAND5 Display control	1	1	0	1	0	HLF TON	NON	INT	0	0	0	BCL	CB	PH	PH	PH
COMMAND6 Synchronizing signal detection	1	1	1	0	SEL 0	MOD 0	DIS LIN	MUT	0	RN 2	RN 1	RN 0	SN 3	SN 2	SN 1	SN 0
COMMAND7 Display control	1	1	1	1	0	0	SEL 1	CTL 3	0	0	0	VNP SEL	VSP SEL	MSK ERS	MSK SEL	EGL
COMMAND8 Display control	1	1	1	1	0	1	SEL 2	MOD 1	0	LNA 3	LNA 2	LNA 1	LNA 0	LPA 2	LPA 1	LPA 0
COMMAND9 Display control	1	1	1	1	1	0	LNB 3	MOD 2	0	LNB 3	LNB 2	LNB 1	LNB 0	LPB 2	LPB 1	LPB 0
COMMAND10 Display control	1	1	1	1	1	1	LNC 3	MOD 3	0	LNC 3	LNC 2	LNC 1	LNC 0	LPC 2	LPC 1	LPC 0

Once written, the command identification code in the first byte is stored until the next first byte is written. However, when the display character data write command (COMMAND1) is written, the LC74785/M locks into the display character data write mode, and another first byte cannot be written.

When the CS1 pin is set high, the LC74785/M is set to the COMMAND0 (display memory write address setup mode) state.

## LC74785, LC74785M

---

### COMMAND0 (Display memory write address setup command)

First byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	1	Command 0 identification code Sets the display memory write address.	
6	—	0		
5	—	0		
4	—	0		
3	V3	0		
		1		
2	V2	0		
		1		
1	V1	0		
		1		
0	V0	0	Display memory line address (0 to B hexadecimal)	
		1		

Second byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	0	Second byte identification code	
6	—	0		
5	—	0		
4	H4	0		
		1		
3	H3	0		
		1		
2	H2	0		
		1		
1	H1	0		
		1		
0	H0	0	Display memory column address (0 to 17 hexadecimal)	
		1		

Note: All registers are set to 0 when the LC74785/M is reset by the RST pin.

### COMMAND1 (Display character data write setup command)

First byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	1	Command 1 identification code Sets up display character data write mode.	When this command is input, the LC74785/M locks in the display character data write mode until the CS1 pin goes high.
6	—	0		
5	—	0		
4	—	1		
3	—	0		
2	—	0		
1	—	0		
0	—	0		

## LC74785, LC74785M

### Second byte

DA 0 to 7	Register	Contents				Notes
		State	Function			
7	at	0	Character attribute off			
		1	Character attribute on			
6	c6	0				
		1				
5	c5	0				
		1				
4	c4	0				
		1				
3	c3	0	Character code (00 to 7F hexadecimal)			
		1				
2	c2	0				
		1				
1	c1	0				
		1				
0	c0	0				
		1				


Note: All registers are set to 0 when the LC74785/M is reset by the  $\overline{\text{RST}}$  pin.

### COMMAND2 Vertical display start position and vertical character size setup command

#### First byte

DA 0 to 7	Register	Contents				Notes											
		State	Function														
7	—	1	Command 2 identification code Sets the vertical display start position and the vertical character size														
6	—	0															
5	—	1															
4	—	0															
3	VS21	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS21</td> <td>VS20</td> <td>0</td> <td>1</td> </tr> <tr> <td>0</td> <td></td> <td>1H/dot</td> <td>2H/dot</td> </tr> <tr> <td>1</td> <td></td> <td>3H/dot</td> <td>1H/dot</td> </tr> </table>	VS21	VS20	0	1	0		1H/dot	2H/dot	1		3H/dot	1H/dot	Second line vertical character size	
VS21	VS20	0	1														
0		1H/dot	2H/dot														
1		3H/dot	1H/dot														
		1															
2	VS20	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS11</td> <td>VS10</td> <td>0</td> <td>1</td> </tr> <tr> <td>0</td> <td></td> <td>1H/dot</td> <td>2H/dot</td> </tr> <tr> <td>1</td> <td></td> <td>3H/dot</td> <td>1H/dot</td> </tr> </table>			VS11	VS10	0	1	0		1H/dot	2H/dot	1		3H/dot	1H/dot
VS11	VS10	0	1														
0		1H/dot	2H/dot														
1		3H/dot	1H/dot														
		1															
1	VS11	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS11</td> <td>VS10</td> <td>0</td> <td>1</td> </tr> <tr> <td>0</td> <td></td> <td>1H/dot</td> <td>2H/dot</td> </tr> <tr> <td>1</td> <td></td> <td>3H/dot</td> <td>1H/dot</td> </tr> </table>	VS11	VS10	0	1	0		1H/dot	2H/dot	1		3H/dot	1H/dot	First line vertical character size	
VS11	VS10	0	1														
0		1H/dot	2H/dot														
1		3H/dot	1H/dot														
		1															
0	VS10	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS11</td> <td>VS10</td> <td>0</td> <td>1</td> </tr> <tr> <td>0</td> <td></td> <td>1H/dot</td> <td>2H/dot</td> </tr> <tr> <td>1</td> <td></td> <td>3H/dot</td> <td>1H/dot</td> </tr> </table>			VS11	VS10	0	1	0		1H/dot	2H/dot	1		3H/dot	1H/dot
VS11	VS10	0	1														
0		1H/dot	2H/dot														
1		3H/dot	1H/dot														
		1															

#### Second byte

DA 0 to 7	Register	Contents				Notes				
		State	Function							
7	—	0	Second byte identification bit							
6	FS	0	Crystal oscillator frequency: 2fsc							
		1	Crystal oscillator frequency: 4fsc							
5	VP5 (MSB)	0	If VS is the vertical display start position then: $VS = H \times (2 \sum_{n=0}^5 VP_n)$	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS</td> <td>HSYNC</td> </tr> <tr> <td>HS</td> <td>VSYNC</td> </tr> </table> <p>H: the horizontal synchronization pulse period</p> 	VS	HSYNC	HS	VSYNC	The vertical display start position is set by the 6 bits VP0 to VP5. The weight of bit 1 is 2H.	
VS	HSYNC									
HS	VSYNC									
		1								
4	VP4	0								
		1								
3	VP3	0								
		1								
2	VP2	0	If VS is the vertical display start position then: $VS = H \times (2 \sum_{n=0}^5 VP_n)$	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS</td> <td>HSYNC</td> </tr> <tr> <td>HS</td> <td>VSYNC</td> </tr> </table>	VS	HSYNC	HS	VSYNC	The vertical display start position is set by the 6 bits VP0 to VP5. The weight of bit 1 is 2H.	
VS	HSYNC									
HS	VSYNC									
		1								
1	VP1	0	If VS is the vertical display start position then: $VS = H \times (2 \sum_{n=0}^5 VP_n)$	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS</td> <td>HSYNC</td> </tr> <tr> <td>HS</td> <td>VSYNC</td> </tr> </table>	VS	HSYNC	HS	VSYNC	The vertical display start position is set by the 6 bits VP0 to VP5. The weight of bit 1 is 2H.	
VS	HSYNC									
HS	VSYNC									
		1								
0	VP0 (LSB)	0	If VS is the vertical display start position then: $VS = H \times (2 \sum_{n=0}^5 VP_n)$	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>VS</td> <td>HSYNC</td> </tr> <tr> <td>HS</td> <td>VSYNC</td> </tr> </table>	VS	HSYNC	HS	VSYNC	The vertical display start position is set by the 6 bits VP0 to VP5. The weight of bit 1 is 2H.	
VS	HSYNC									
HS	VSYNC									
		1								

Note: All registers are set to 0 when the LC74785/M is reset by the  $\overline{\text{RST}}$  pin.

## LC74785, LC74785M

---

COMMAND3 (Horizontal display start position and horizontal size setup command)

First byte

DA 0 to 7	Register	Contents			Notes							
		State	Function									
7	—	1										
6	—	0										
5	—	1	Command 3 identification code Sets the horizontal display start position and the horizontal character size.									
4	—	1										
3	HS21	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td style="padding: 2px;">HS21</td> <td style="padding: 2px;">HS20</td> <td style="padding: 2px;">0</td> <td style="padding: 2px;">1</td> </tr> <tr> <td style="padding: 2px;">0</td> <td style="padding: 2px;">1</td> <td style="padding: 2px;">1Tc/dot</td> <td style="padding: 2px;">2Tc/dot</td> </tr> </table>	HS21	HS20	0	1	0	1	1Tc/dot	2Tc/dot	Second line horizontal character size
HS21	HS20	0	1									
0	1	1Tc/dot	2Tc/dot									
		1										
2	HS20	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td style="padding: 2px;">HS21</td> <td style="padding: 2px;">HS20</td> <td style="padding: 2px;">0</td> <td style="padding: 2px;">1</td> </tr> <tr> <td style="padding: 2px;">0</td> <td style="padding: 2px;">1</td> <td style="padding: 2px;">3Tc/dot</td> <td style="padding: 2px;">1Tc/dot</td> </tr> </table>	HS21	HS20	0	1	0	1	3Tc/dot	1Tc/dot	Second line horizontal character size
HS21	HS20	0	1									
0	1	3Tc/dot	1Tc/dot									
		1										
1	HS11	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td style="padding: 2px;">HS11</td> <td style="padding: 2px;">HS10</td> <td style="padding: 2px;">0</td> <td style="padding: 2px;">1</td> </tr> <tr> <td style="padding: 2px;">0</td> <td style="padding: 2px;">1</td> <td style="padding: 2px;">1Tc/dot</td> <td style="padding: 2px;">2Tc/dot</td> </tr> </table>	HS11	HS10	0	1	0	1	1Tc/dot	2Tc/dot	First line horizontal character size
HS11	HS10	0	1									
0	1	1Tc/dot	2Tc/dot									
		1										
0	HS10	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td style="padding: 2px;">HS11</td> <td style="padding: 2px;">HS10</td> <td style="padding: 2px;">0</td> <td style="padding: 2px;">1</td> </tr> <tr> <td style="padding: 2px;">1</td> <td style="padding: 2px;">0</td> <td style="padding: 2px;">3Tc/dot</td> <td style="padding: 2px;">1Tc/dot</td> </tr> </table>	HS11	HS10	0	1	1	0	3Tc/dot	1Tc/dot	First line horizontal character size
HS11	HS10	0	1									
1	0	3Tc/dot	1Tc/dot									
		1										

Second byte

DA 0 to 7	Register	Contents			Notes	
		State	Function			
7	—	0	Second byte identification bit			
6	LC	0	Use the LC oscillator for the dot clock			
		1	Use the crystal oscillator for the dot clock			
5	HP5 (MSB)	0	If HS is the horizontal start position then: $HS = Tc \times \left( 2 \sum_{n=0}^5 HP_n \right)$	Selects the dot clock used for character display in the horizontal direction.  The horizontal display start position is set by the 6 bits HP0 to HP5. The weight of bit 1 is 2Tc.		
		1				
4	HP4	0				
		1				
3	HP3	0				
		1				
2	HP2	0	Tc: Period of the oscillator connected to OSCIN/OSCOUT in operating mode.	The horizontal display start position is set by the 6 bits HP0 to HP5. The weight of bit 1 is 2Tc.		
		1				
1	HP1	0				
		1				
0	HP0 (LSB)	0				
		1				

Note: All registers are set to 0 when the LC74785/M is reset by the  $\overline{RST}$  pin.

## LC74785, LC74785M

---

### COMMAND4 (Display control setup command)

First byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	1	Command 4 identification code Display control setup	
6	—	1		
5	—	0		
4	—	0		
3	TSTMOD	0	Normal operating mode	This bit must be set to 0.
		1	Test mode	
2	RAMERS	0	Erase display RAM. (Set the RAM data to 7F hexadecimal.)	Erasing RAM takes about 500 µs. (This operation must be executed in the DSPOFF state.)
		1		
1	OSCSTP	0	Do not stop the crystal and LC oscillators.	Valid in external synchronization mode when character display is off.
		1	Stop the crystal and LC oscillators.	
0	SYSRST	0	Reset all registers and turn display off.	The registers are reset when the CS1 pin is low, and the reset state is cleared when CS1 is set high.
		1		

Second byte

DA 0 to 7	Register	Contents		Notes												
		State	Function													
7	—	0	Second byte identification bit	Specifies the size for complete fill in												
6	BLK2	0	Character display area													
		1	Video display area													
5	BLK1	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>BLK1</td> <td>BLK0</td> <td>0</td> <td>1</td> </tr> <tr> <td>0</td> <td>Blanking off</td> <td>Character size</td> <td></td> </tr> <tr> <td>1</td> <td>Border size</td> <td>Full character size</td> <td></td> </tr> </table>		BLK1	BLK0	0	1	0	Blanking off	Character size		1	Border size	Full character size	
BLK1	BLK0	0	1													
0	Blanking off	Character size														
1	Border size	Full character size														
1																
4	BLK0	0	Changes the blanking size													
		1														
3	BK1	0	Blinking period: About 0.5 s	Switches the blinking period												
		1	Blinking period: About 1.0 s													
2	BK0	0	Blinking off	Blinking in reverse video mode switches the display between normal character display and reverse video display.												
		1	Blinking on													
1	RV	0	Reverse (character reversing) off													
		1	Reverse (character reversing) on													
0	DSPON	0	Character display off													
		1	Character display on													

Note: All registers are set to 0 when the LC74785/M is reset by the RST pin.

## LC74785, LC74785M

---

### COMMAND5 (Display control setup command)

#### First byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	HLFTON	—	1	Command 5 identification code Display control setup
6		—	1	
5		—	0	
4		—	1	
3		—	0	
2		0	External synchronizing signal judgment output signal	Switches the SYNCJDG (pin 8) output.
		1	A signal in the range specified by LNA*, LNB*, and LNC* is output.	
1	NON	0	Interlaced	Switches between interlaced and noninterlaced video.
		1	Noninterlaced	
0	INT	0	External synchronization	Switches between external and internal synchronization
		1	Internal synchronization	

#### Second byte

DA 0 to 7	Register	Contents		Notes																																				
		State	Function																																					
7	BCL	—	0	Second byte identification bit																																				
6		—	0																																					
5		—	0																																					
4		0	Background coloring on	Only valid in internal synchronization mode.																																				
		1	No background coloring (Only the background level is set)																																					
3		0	Color burst signal output.	Only valid when BCL is high.																																				
		1	Color burst signal output stopped.																																					
2	PH2	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <th>PH2</th> <th>PH1</th> <th>PH0</th> <th>Background color (phase)</th> </tr> <tr> <td>0</td> <td>0</td> <td>0</td> <td>Cyan *</td> </tr> <tr> <td>0</td> <td>0</td> <td>1</td> <td>Yellow *</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> <td>Red *</td> </tr> <tr> <td>0</td> <td>1</td> <td>1</td> <td>Blue *</td> </tr> <tr> <td>1</td> <td>0</td> <td>0</td> <td>Cyan - blue</td> </tr> <tr> <td>1</td> <td>0</td> <td>1</td> <td>Green *</td> </tr> <tr> <td>1</td> <td>1</td> <td>0</td> <td>Orange</td> </tr> <tr> <td>1</td> <td>1</td> <td>1</td> <td>Magenta *</td> </tr> </table>	PH2	PH1	PH0	Background color (phase)	0	0	0	Cyan *	0	0	1	Yellow *	0	1	0	Red *	0	1	1	Blue *	1	0	0	Cyan - blue	1	0	1	Green *	1	1	0	Orange	1	1	1	Magenta *	Background color specification
PH2	PH1	PH0	Background color (phase)																																					
0	0	0	Cyan *																																					
0	0	1	Yellow *																																					
0	1	0	Red *																																					
0	1	1	Blue *																																					
1	0	0	Cyan - blue																																					
1	0	1	Green *																																					
1	1	0	Orange																																					
1	1	1	Magenta *																																					
1	1																																							
0	0																																							
	1																																							

Note: All registers are set to 0 when the LC74785/M is reset by the RST pin.

## LC74785, LC74785M

---

### COMMAND6 (Synchronizing signal detection setup command)

First byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	1	Command 6 identification code Sets up synchronizing signal control.	
6		1		
5		1		
4		0		
3	SEL0	0	Sync separator signal	Switches the $SEPO_{OUT}$ (pin 19) output.
		1	Output signal set by MOD0	
2	MOD0	0	High-level output	Only valid when SEL0 is high.
		1	ST pulse signal	
1	DISLIN	0	12 lines	Switches the number of lines displayed.
		1	10 lines	
0	MUT	0	Normal output	$CV_{OUT}$ switching
		1	$CV_{IN}$ is cut and $CV_{OUT}$ is held at the pedestal level.	

Second byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	0	Second byte identification bit	
6		0		
5		1		
4		0		
3	RN2	0	External synchronizing signal detection control Signal absent → signal present transition detection	
		1		
5	RN1	0	Sets the sampling period in which SYNC can be detected continuously in the horizontal synchronizing signal period (1H).	
		1		
4	RN0	0	External synchronizing signal detection control Signal present → signal absent transition detection	
		1		
3	SN3	0	External synchronizing signal detection control Signal present → signal absent transition detection	
		1		
2	SN2	0	Sets the sampling period in which SYNC cannot be detected continuously in the horizontal synchronizing signal period (1H).	
		1		
1	SN1	0		
		1		
0	SN0	0		
		1		

Note: All registers are set to 0 when the LC74785/M is reset by the  $\overline{RST}$  pin.

## LC74785, LC74785M

---

### COMMAND7 (Display control setup command)

First byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	1		
6	—	1	Command 7 identification code	
5	—	1	Display control setup	
4	—	1		
3	—	0	Extended command 0 identification code	
2	—	0		
1	SEL1	0	Vertical synchronizing signal (external V separation) input	Switches the SEP <sub>IN</sub> (pin 20) input. Only valid when CTL3 is high.
		1	Frame signal input	
0	CTL3	0	Use internal V separation.	Switches V separation.
		1	Do not use internal V separation.	

Second byte

DA 0 to 7	Register	Contents		Notes
		State	Function	
7	—	0	Second byte identification bit	
6	—	0		
5	—	0		
4	VNPSEL	0	V falling edge detection	Switches the V acquisition polarity in external mode when internal V separation is used.
		1	V rising edge detection	
3	VSPSEL	0	VSEP: about 8.9 µs	Switches the internal V separation period.
		1	VSEP: about 17.8 µs	
2	MSKERS	0	Mask valid	Clears the HSYNC and VSYNC masks.
		1	Mask invalid	
1	MSKSEL	0	3H	Switches the VSYNC mask.
		1	20H	
0	EGL	0	Border level 0 only (VBK0)	Switches the border level. (Only valid when BLK0 is 0 and BLK1 is 1.)
		1	Two-stage border level (VBK0 and VBK1)	

Note: All registers are set to 0 when the LC74785/M is reset by the RST pin.

## LC74785, LC74785M

---

### COMMAND8 (Display control setup command)

First byte

DA 0 to 7	Register	Contents				Notes	
		State	Function				
7	—	1	Command 8 identification code Display control setup				
6	—	1					
5	—	1					
4	—	1					
3	—	0	Extended command 1 identification code				
2	—	1					
1	SEL2	0	External synchronizing signal judgment output signal			Switches the SYNCJDG (pin 8) output Valid when HLFTON is low.	
		1	O/E signal				
0	MOD1	0	Even field line 21 data extraction (VCR)			Switches line 21 data extraction.	
		1	Line 21 data extraction on both odd and even fields (NTSC-TV)				

Second byte

DA 0 to 7	Register	Contents				Notes	
		State	Function				
7	—	0	Second byte identification bit				
6	LNA3	0	LNA3	LNA2	LNA1	LNA0	Specified line
		1	0	0	0	0	Do not change the line background
	LNA2	0	0	0	1		Line 1
		1	0	0	1	0	Line 2
	LNA1	0	0	0	1	1	Line 3
		1	0	1	0	0	Line 4
	LNA0	0	0	1	0	1	Line 5
		1	0	1	1	0	Line 6
	LPA2	0	0	1	1	1	Line 7
		1	1	0	0	0	Line 8
	LPA1	0	1	0	0	1	Line 9
		1	1	0	1	0	Line 10
	LPA0	0	1	1	0	1	Line 11
		1	1	1	—	—	Line 12
2	LPA2	0	LPA2	LPA1	LPA0	Background color (phase)	
		1	0	0	0	Cyan	*
	LPA1	0	0	0	1	Yellow	*
		1	0	1	0	Red	*
	LPA0	0	0	1	1	Blue	*
		1	0	0	0	Cyan - blue	
	LPA0	0	1	0	1	Green	*
		1	1	0	0	Orange	
	LPA0	0	1	1	1	Magenta	*
		1	1	1	—	*: When 2 fsc is used.	

Note: All registers are set to 0 when the LC74785/M is reset by the RST pin.

## LC74785, LC74785M

---

### COMMAND9 (Display control setup command)

First byte

DA 0 to 7	Register	Contents				Notes	
		State	Function				
7	—	1	Command 9 identification code Display control setup				
6	—	1					
5	—	1					
4	—	1					
3	—	1					
2	—	0					
1	LNBSEL	0	Extended command 2 identification code				
		1	Normal line background color operation RV characters have the background color specified by PH* or the RV character background color is white.				
0	MOD2	0	LNBSEL: 1 setting specification				
		1	RV characters have the background color specified by PH*, characters are white.				

Second byte

DA 0 to 7	Register	Contents				Notes																																																											
		State	Function																																																														
7	—	0	Second byte identification bit																																																														
6	LNB3	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LNB3</th> <th>LNB2</th> <th>LNB1</th> <th>LNB0</th> <th>Specified line</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>0</td><td>Do not change the line background</td></tr> <tr><td>0</td><td>0</td><td>0</td><td>1</td><td>Line 1</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td><td>Line 2</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>1</td><td>Line 3</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>0</td><td>Line 4</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>1</td><td>Line 5</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>0</td><td>Line 6</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>1</td><td>Line 7</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>0</td><td>Line 8</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>1</td><td>Line 9</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>0</td><td>Line 10</td></tr> </tbody> </table>			LNB3	LNB2	LNB1	LNB0	Specified line	0	0	0	0	Do not change the line background	0	0	0	1	Line 1	0	0	1	0	Line 2	0	0	1	1	Line 3	0	1	0	0	Line 4	0	1	0	1	Line 5	0	1	1	0	Line 6	0	1	1	1	Line 7	1	0	0	0	Line 8	1	0	0	1	Line 9	1	0	1	0	Line 10
LNB3	LNB2	LNB1	LNB0	Specified line																																																													
0	0	0	0	Do not change the line background																																																													
0	0	0	1	Line 1																																																													
0	0	1	0	Line 2																																																													
0	0	1	1	Line 3																																																													
0	1	0	0	Line 4																																																													
0	1	0	1	Line 5																																																													
0	1	1	0	Line 6																																																													
0	1	1	1	Line 7																																																													
1	0	0	0	Line 8																																																													
1	0	0	1	Line 9																																																													
1	0	1	0	Line 10																																																													
1																																																																	
5	LNB2	0																																																															
		1																																																															
4	LNB1	0																																																															
		1																																																															
3	LNB0	0																																																															
		1																																																															
2	LPB2	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LPB2</th> <th>LPB1</th> <th>LPB0</th> <th>Background color (phase)</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>Cyan *</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>Yellow *</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>Red *</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>Blue *</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>Cyan - blue</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>Green *</td></tr> <tr><td>1</td><td>1</td><td>0</td><td>Orange</td></tr> <tr><td>1</td><td>1</td><td>1</td><td>Magenta *</td></tr> <tr><td colspan="4" style="text-align: center;">*: When 2 fsc is used.</td></tr> </tbody> </table>			LPB2	LPB1	LPB0	Background color (phase)	0	0	0	Cyan *	0	0	1	Yellow *	0	1	0	Red *	0	1	1	Blue *	1	0	0	Cyan - blue	1	0	1	Green *	1	1	0	Orange	1	1	1	Magenta *	*: When 2 fsc is used.																							
LPB2	LPB1	LPB0	Background color (phase)																																																														
0	0	0	Cyan *																																																														
0	0	1	Yellow *																																																														
0	1	0	Red *																																																														
0	1	1	Blue *																																																														
1	0	0	Cyan - blue																																																														
1	0	1	Green *																																																														
1	1	0	Orange																																																														
1	1	1	Magenta *																																																														
*: When 2 fsc is used.																																																																	
1																																																																	
1	LPB1	0																																																															
		1																																																															
0	LPB0	0																																																															
		1																																																															

Note: All registers are set to 0 when the LC74785/M is reset by the RST pin.

## LC74785, LC74785M

---

### COMMAND10 (Display control setup command)

First byte

DA 0 to 7	Register	Contents				Notes	
		State	Function				
7	—	1	Command 10 identification code Display control setup				
6	—	1					
5	—	1					
4	—	1					
3	—	1					
2	—	0					
1	LNCSEL	0	Extended command 2 identification code				
		1	Normal line background color operation RV characters have the background color specified by PH* or the RV character background color is white.				
0	MOD3	0	LNCSEL: 1 setting specification				
		1	RV characters have the background color specified by PH*, characters are white.				

Second byte

DA 0 to 7	Register	Contents				Notes																																																											
		State	Function																																																														
7	—	0	Second byte identification bit																																																														
6	LNC3	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LNC3</th> <th>LNC2</th> <th>LNC1</th> <th>LNC0</th> <th>Specified line</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>0</td><td>Do not change the line background</td></tr> <tr><td>0</td><td>0</td><td>0</td><td>1</td><td>Line 1</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td><td>Line 2</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>1</td><td>Line 3</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>0</td><td>Line 4</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>1</td><td>Line 5</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>0</td><td>Line 6</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>1</td><td>Line 7</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>0</td><td>Line 8</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>1</td><td>Line 9</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>0</td><td>Line 10</td></tr> </tbody> </table>			LNC3	LNC2	LNC1	LNC0	Specified line	0	0	0	0	Do not change the line background	0	0	0	1	Line 1	0	0	1	0	Line 2	0	0	1	1	Line 3	0	1	0	0	Line 4	0	1	0	1	Line 5	0	1	1	0	Line 6	0	1	1	1	Line 7	1	0	0	0	Line 8	1	0	0	1	Line 9	1	0	1	0	Line 10
LNC3	LNC2	LNC1	LNC0	Specified line																																																													
0	0	0	0	Do not change the line background																																																													
0	0	0	1	Line 1																																																													
0	0	1	0	Line 2																																																													
0	0	1	1	Line 3																																																													
0	1	0	0	Line 4																																																													
0	1	0	1	Line 5																																																													
0	1	1	0	Line 6																																																													
0	1	1	1	Line 7																																																													
1	0	0	0	Line 8																																																													
1	0	0	1	Line 9																																																													
1	0	1	0	Line 10																																																													
1																																																																	
5	LNC2	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LNC3</th> <th>LNC2</th> <th>LNC1</th> <th>LNC0</th> <th>Specified line</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>0</td><td>Do not change the line background</td></tr> <tr><td>0</td><td>0</td><td>0</td><td>1</td><td>Line 1</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td><td>Line 2</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>1</td><td>Line 3</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>0</td><td>Line 4</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>1</td><td>Line 5</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>0</td><td>Line 6</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>1</td><td>Line 7</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>0</td><td>Line 8</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>1</td><td>Line 9</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>0</td><td>Line 10</td></tr> </tbody> </table>			LNC3	LNC2	LNC1	LNC0	Specified line	0	0	0	0	Do not change the line background	0	0	0	1	Line 1	0	0	1	0	Line 2	0	0	1	1	Line 3	0	1	0	0	Line 4	0	1	0	1	Line 5	0	1	1	0	Line 6	0	1	1	1	Line 7	1	0	0	0	Line 8	1	0	0	1	Line 9	1	0	1	0	Line 10
LNC3	LNC2	LNC1	LNC0	Specified line																																																													
0	0	0	0	Do not change the line background																																																													
0	0	0	1	Line 1																																																													
0	0	1	0	Line 2																																																													
0	0	1	1	Line 3																																																													
0	1	0	0	Line 4																																																													
0	1	0	1	Line 5																																																													
0	1	1	0	Line 6																																																													
0	1	1	1	Line 7																																																													
1	0	0	0	Line 8																																																													
1	0	0	1	Line 9																																																													
1	0	1	0	Line 10																																																													
1																																																																	
4	LNC1	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LNC3</th> <th>LNC2</th> <th>LNC1</th> <th>LNC0</th> <th>Specified line</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>0</td><td>Do not change the line background</td></tr> <tr><td>0</td><td>0</td><td>0</td><td>1</td><td>Line 1</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td><td>Line 2</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>1</td><td>Line 3</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>0</td><td>Line 4</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>1</td><td>Line 5</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>0</td><td>Line 6</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>1</td><td>Line 7</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>0</td><td>Line 8</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>1</td><td>Line 9</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>0</td><td>Line 10</td></tr> </tbody> </table>			LNC3	LNC2	LNC1	LNC0	Specified line	0	0	0	0	Do not change the line background	0	0	0	1	Line 1	0	0	1	0	Line 2	0	0	1	1	Line 3	0	1	0	0	Line 4	0	1	0	1	Line 5	0	1	1	0	Line 6	0	1	1	1	Line 7	1	0	0	0	Line 8	1	0	0	1	Line 9	1	0	1	0	Line 10
LNC3	LNC2	LNC1	LNC0	Specified line																																																													
0	0	0	0	Do not change the line background																																																													
0	0	0	1	Line 1																																																													
0	0	1	0	Line 2																																																													
0	0	1	1	Line 3																																																													
0	1	0	0	Line 4																																																													
0	1	0	1	Line 5																																																													
0	1	1	0	Line 6																																																													
0	1	1	1	Line 7																																																													
1	0	0	0	Line 8																																																													
1	0	0	1	Line 9																																																													
1	0	1	0	Line 10																																																													
1																																																																	
3	LNC0	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LNC3</th> <th>LNC2</th> <th>LNC1</th> <th>LNC0</th> <th>Specified line</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>0</td><td>Do not change the line background</td></tr> <tr><td>0</td><td>0</td><td>0</td><td>1</td><td>Line 1</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>0</td><td>Line 2</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>1</td><td>Line 3</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>0</td><td>Line 4</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>1</td><td>Line 5</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>0</td><td>Line 6</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>1</td><td>Line 7</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>0</td><td>Line 8</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>1</td><td>Line 9</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>0</td><td>Line 10</td></tr> </tbody> </table>			LNC3	LNC2	LNC1	LNC0	Specified line	0	0	0	0	Do not change the line background	0	0	0	1	Line 1	0	0	1	0	Line 2	0	0	1	1	Line 3	0	1	0	0	Line 4	0	1	0	1	Line 5	0	1	1	0	Line 6	0	1	1	1	Line 7	1	0	0	0	Line 8	1	0	0	1	Line 9	1	0	1	0	Line 10
LNC3	LNC2	LNC1	LNC0	Specified line																																																													
0	0	0	0	Do not change the line background																																																													
0	0	0	1	Line 1																																																													
0	0	1	0	Line 2																																																													
0	0	1	1	Line 3																																																													
0	1	0	0	Line 4																																																													
0	1	0	1	Line 5																																																													
0	1	1	0	Line 6																																																													
0	1	1	1	Line 7																																																													
1	0	0	0	Line 8																																																													
1	0	0	1	Line 9																																																													
1	0	1	0	Line 10																																																													
1																																																																	
2	LPC2	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LPC2</th> <th>LPC1</th> <th>LPC0</th> <th>Background color (phase)</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>Cyan *</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>Yellow *</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>Red *</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>Blue *</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>Cyan - blue</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>Green *</td></tr> <tr><td>1</td><td>1</td><td>0</td><td>Orange</td></tr> <tr><td>1</td><td>1</td><td>1</td><td>Magenta *</td></tr> </tbody> </table>			LPC2	LPC1	LPC0	Background color (phase)	0	0	0	Cyan *	0	0	1	Yellow *	0	1	0	Red *	0	1	1	Blue *	1	0	0	Cyan - blue	1	0	1	Green *	1	1	0	Orange	1	1	1	Magenta *																								
LPC2	LPC1	LPC0	Background color (phase)																																																														
0	0	0	Cyan *																																																														
0	0	1	Yellow *																																																														
0	1	0	Red *																																																														
0	1	1	Blue *																																																														
1	0	0	Cyan - blue																																																														
1	0	1	Green *																																																														
1	1	0	Orange																																																														
1	1	1	Magenta *																																																														
1																																																																	
1	LPC1	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LPC2</th> <th>LPC1</th> <th>LPC0</th> <th>Background color (phase)</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>Cyan *</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>Yellow *</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>Red *</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>Blue *</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>Cyan - blue</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>Green *</td></tr> <tr><td>1</td><td>1</td><td>0</td><td>Orange</td></tr> <tr><td>1</td><td>1</td><td>1</td><td>Magenta *</td></tr> </tbody> </table>			LPC2	LPC1	LPC0	Background color (phase)	0	0	0	Cyan *	0	0	1	Yellow *	0	1	0	Red *	0	1	1	Blue *	1	0	0	Cyan - blue	1	0	1	Green *	1	1	0	Orange	1	1	1	Magenta *																								
LPC2	LPC1	LPC0	Background color (phase)																																																														
0	0	0	Cyan *																																																														
0	0	1	Yellow *																																																														
0	1	0	Red *																																																														
0	1	1	Blue *																																																														
1	0	0	Cyan - blue																																																														
1	0	1	Green *																																																														
1	1	0	Orange																																																														
1	1	1	Magenta *																																																														
1																																																																	
0	LPC0	0	<table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>LPC2</th> <th>LPC1</th> <th>LPC0</th> <th>Background color (phase)</th> </tr> </thead> <tbody> <tr><td>0</td><td>0</td><td>0</td><td>Cyan *</td></tr> <tr><td>0</td><td>0</td><td>1</td><td>Yellow *</td></tr> <tr><td>0</td><td>1</td><td>0</td><td>Red *</td></tr> <tr><td>0</td><td>1</td><td>1</td><td>Blue *</td></tr> <tr><td>1</td><td>0</td><td>0</td><td>Cyan - blue</td></tr> <tr><td>1</td><td>0</td><td>1</td><td>Green *</td></tr> <tr><td>1</td><td>1</td><td>0</td><td>Orange</td></tr> <tr><td>1</td><td>1</td><td>1</td><td>Magenta *</td></tr> </tbody> </table>			LPC2	LPC1	LPC0	Background color (phase)	0	0	0	Cyan *	0	0	1	Yellow *	0	1	0	Red *	0	1	1	Blue *	1	0	0	Cyan - blue	1	0	1	Green *	1	1	0	Orange	1	1	1	Magenta *																								
LPC2	LPC1	LPC0	Background color (phase)																																																														
0	0	0	Cyan *																																																														
0	0	1	Yellow *																																																														
0	1	0	Red *																																																														
0	1	1	Blue *																																																														
1	0	0	Cyan - blue																																																														
1	0	1	Green *																																																														
1	1	0	Orange																																																														
1	1	1	Magenta *																																																														
1																																																																	

Note: All registers are set to 0 when the LC74785/M is reset by the RST pin.

## LC74785, LC74785M

### Display Screen Structure


The display consists of 12 lines of 24 characters.

Up to 288 characters can be displayed.

The number of characters that can be displayed is reduced when enlarged characters are displayed.

Display memory addresses are specified as row (0 to 11 decimal) and column (0 to 23 decimal) addresses.

### Display Screen Structure (display memory addresses)




A06225

## LC74785, LC74785M

### Composite Video Signal Output Levels (internally generated levels)

CV<sub>OUT</sub> output level waveform ( $V_{DD2} = 5.00$  V)



A06226


Output level	Output voltage (1) [V]	Output voltage (2) [V]	Output voltage (3) [V]
V <sub>CHA</sub> : Character	2.67	2.87	3.16
V <sub>RSH0</sub> : High for background colors other than blue	2.45	2.64	2.93
V <sub>RSH1,2</sub> : High for blue background colors 1 and 2	2.09	2.29	2.58
V <sub>BK1</sub> :	Border 1	2.09	2.29
V <sub>CBH</sub> :	High for the color burst signal	1.75	1.95
V <sub>RSL2</sub> :	Low for blue background color 2	1.61	1.80
V <sub>BK0</sub> :	Border 0	1.52	1.72
V <sub>PD</sub> :	Pedestal level	1.44	1.64
V <sub>RSL0</sub> :	Low for background colors other than blue	1.29	1.48
V <sub>RSL1</sub> :	Low for blue background color 1	1.20	1.39
V <sub>CBL</sub> :	Low for the color burst signal	1.10	1.29
V <sub>SN</sub> :	Sync	0.82	1.01
			1.30

Note:  $V_{DD2} = 5.0$  V.

## LC74785, LC74785M


### Sample Application Circuit (When the LC74785/M is used in conjunction with a single-chip Y/C circuit.)

External system clock input




A06227

Crystal oscillator



A06228

External system clock input (when the pin 3 and 4 functions are modified by mask options)



A06229

Note: When a sync tip level of 1.3 V DC (CV<sub>IN</sub> input signal: sync tip = 1.3 V) is selected for the internal generated video signals by option settings, the electrolytic capacitor connected to SYN<sub>IN</sub> must be connected with the correct polarity.

When V<sub>DD1</sub> is 5.0 V, the SYN<sub>IN</sub> input video signal pedestal level is clamped at about 2.5 V DC.

## **LC74785, LC74785M**

---

- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
  - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
  - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of June, 1997. Specifications and information herein are subject to change without notice.