

**MOTOROLA
SEMICONDUCTOR
TECHNICAL DATA**

Designer's Data Sheet
Power Field Effect Transistor
P-Channel Enhancement-Mode
Silicon Gate

This TMOS Power FET is designed for medium voltage, high speed power switching applications such as switching regulators, converters, solenoid and relay drivers.


3

- Silicon Gate for Fast Switching Speeds — Switching Times Specified at 100°C
- Designer's Data — I_{DSS} , $V_{DS(on)}$, $V_{GS(th)}$ and SOA Specified at Elevated Temperature
- Rugged — SOA is Power Dissipation Limited
- Source-to-Drain Diode Characterized for Use With Inductive Loads



MTM20P10

TMOS POWER FET
20 AMPERES
 $R_{DS(on)} = 0.15 \text{ OHM}$
100 VOLTS



MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Drain-Source Voltage	V_{DSS}	100	Vdc
Drain-Gate Voltage ($R_{GS} = 1 \text{ M}\Omega$)	V_{DGR}	100	Vdc
Gate-Source Voltage Continuous Non-repetitive ($t_p \leq 50 \mu\text{s}$)	V_{GS} V_{GSM}	± 20 ± 40	Vdc Vpk
Drain Current Continuous Pulsed	I_D I_{DM}	20 80	Adc
Total Power Dissipation @ $T_C = 25^\circ\text{C}$ Derate above 25°C	P_D	125 1	Watts W/ $^\circ\text{C}$
Operating and Storage Temperature Range	T_J, T_{Stg}	-65 to 150	°C

THERMAL CHARACTERISTICS

Thermal Resistance Junction to Case Junction to Ambient	$R_{\theta JC}$ $R_{\theta JA}$	1 30	°C/W
Maximum Lead Temperature for Soldering Purposes, 1/8" from case for 5 seconds	T_L	300	°C

CASE 1-07
TO-204AA

Designer's Data for "Worst Case" Conditions — The Designer's Data Sheet permits the design of most circuits entirely from the information presented. SOA Limit curves — representing boundaries on device characteristics — are given to facilitate "worst case" design.

MTM20P10

MOTOROLA SC (XSTRS/R F) 6AF D ■ 6367254 0098599 450 ■ MOTB

3

ELECTRICAL CHARACTERISTICS ($T_C = 25^\circ\text{C}$ unless otherwise noted)

Characteristic	Symbol	Min	Max	Unit
----------------	--------	-----	-----	------

OFF CHARACTERISTICS

Drain-Source Breakdown Voltage ($V_{GS} = 0$, $I_D = 0.25 \text{ mA}$)	$V_{(BR)DSS}$	100	—	Vdc
Zero Gate Voltage Drain Current ($V_{DS} = \text{Rated } V_{DSS}$, $V_{GS} = 0$) ($V_{DS} = \text{Rated } V_{DSS}$, $V_{GS} = 0$, $T_J = 125^\circ\text{C}$)	I_{DSS}	—	10 100	$\mu\text{A}/\text{dc}$
Gate-Body Leakage Current, Forward ($V_{GSF} = 20 \text{ Vdc}$, $V_{DS} = 0$)	I_{GSSF}	—	100	nAdc
Gate-Body Leakage Current, Reverse ($V_{GSR} = 20 \text{ Vdc}$, $V_{DS} = 0$)	I_{GSSR}	—	100	nAdc

ON CHARACTERISTICS*

Gate Threshold Voltage ($V_{DS} = V_{GS}$, $I_D = 1 \text{ mA}$) $T_J = 100^\circ\text{C}$	$V_{GS(\text{th})}$	2 1.5	4.5 4	Vdc
Static Drain-Source On-Resistance ($V_{GS} = 10 \text{ Vdc}$, $I_D = 10 \text{ Adc}$)	$R_{DS(\text{on})}$	—	0.15	Ohm
Drain-Source On-Voltage ($V_{GS} = 10 \text{ V}$) ($I_D = 20 \text{ Adc}$) ($I_D = 10 \text{ Adc}$, $T_J = 100^\circ\text{C}$)	$V_{DS(\text{on})}$	— —	3.2 3	Vdc
Forward Transconductance ($V_{DS} = 10 \text{ V}$, $I_D = 10 \text{ A}$)	g_{FS}	5	—	mhos

DYNAMIC CHARACTERISTICS

Input Capacitance	$(V_{DS} = 25 \text{ V}, V_{GS} = 0,$ $f = 1 \text{ MHz})$ See Figure 10	C_{iss}	—	2000	pF
Output Capacitance		C_{oss}	—	950	
Reverse Transfer Capacitance		C_{rss}	—	400	

SWITCHING CHARACTERISTICS* ($T_J = 100^\circ\text{C}$)

Turn-On Delay Time	$(V_{DD} = 25 \text{ V}, I_D = 0.5 \text{ Rated } I_D$ $R_{gen} = 50 \text{ ohms}$ See Figures 12 and 13	$t_{d(on)}$	—	45	ns
Rise Time		t_r	—	200	
Turn-Off Delay Time		$t_{d(off)}$	—	150	
Fall Time		t_f	—	150	
Total Gate Charge	$(V_{DS} = 0.8 \text{ Rated } V_{DSS},$ $I_D = \text{Rated } I_D, V_{GS} = 10 \text{ V}$ See Figure 11	Q_g	52 (Typ)	75	nC
Gate-Source Charge		Q_{gs}	22 (Typ)	—	
Gate-Drain Charge		Q_{gd}	30 (Typ)	—	

SOURCE DRAIN DIODE CHARACTERISTICS*

Forward On-Voltage	$(I_S = \text{Rated } I_D$ $V_{GS} = 0)$	V_{SD}	2.8 (Typ)	4	Vdc
Forward Turn-On Time		t_{on}	100 (Typ)	—	ns
Reverse Recovery Time		t_{rr}	350 (Typ)	—	ns

*Pulse Test: Pulse Width $\leq 300 \mu\text{s}$, Duty Cycle $\leq 2.0\%$.

MTM20P10

MOTOROLA SC (XSTRS/R F)

68E D

■ 6367254 0098600 TT2 ■ MOT

TYPICAL ELECTRICAL CHARACTERISTICS




Figure 1. On-Region Characteristics




Figure 2. Gate-Threshold Voltage Variation
With Temperature




Figure 3. Transfer Characteristics




Figure 4. Breakdown Voltage Variation
With Temperature




Figure 5. On-Resistance versus Drain Current




Figure 6. On-Resistance Variation
With Temperature

SAFE OPERATING AREA INFORMATION




Figure 7. Maximum Rated Forward Biased Safe Operating Area




Figure 8. Maximum Rated Switching Safe Operating Area

FORWARD BIASED SAFE OPERATING AREA

The FBSOA curves define the maximum drain-to-source voltage and drain current that a device can safely handle when it is forward biased, or when it is on, or being turned on. Because these curves include the limitations of simultaneous high voltage and high current, up to the rating of the device, they are especially useful to designers of linear systems. The curves are based on a case temperature of 25°C and a maximum junction temperature of 150°C . Limitations for repetitive pulses at various case temperatures can be determined by using the thermal response curves. Motorola Application Note, AN569, "Transient Thermal Resistance-General Data and Its Use" provides detailed instructions.

SWITCHING SAFE OPERATING AREA

The switching safe operating area (SOA) of Figure 8 is the boundary that the load line may traverse without incurring damage to the MOSFET. The fundamental limits are the peak current, I_{DM} and the breakdown voltage, $V_{(BR)DSS}$. The switching SOA shown in Figure 8 is applicable for both turn-on and turn-off of the devices for switching times less than one microsecond.

The power averaged over a complete switching cycle must be less than:

$$\frac{T_J(\max) - T_C}{R_{\theta JC}}$$





Figure 9. Thermal Response

MTM20P10

MOTOROLA SC (XSTRS/R F)

68E D ■ 6367254 0098602 875 ■ MOT6



3

Figure 10. Capacitance Variation




Figure 11. Gate Charge versus Gate-To-Source Voltage




Figure 12. Switching Test Circuit

RESISTIVE SWITCHING




Figure 13. Switching Waveforms