



ELECTRONICS, INC.
44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089

NTE1006 Integrated Circuit FM Multiplex Stereo Demodulator

Description:

The NTE1006 is an integrated circuit in a 14-Lead DIP type package designed for use as an FM multiplex stereo demodulator. This device includes all the fundamental functions including a composite amp, doubler, decoder, separation controller, and lamp driver.

Features:

- Suitable for Low Level Input

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)


Maximum Supply Voltage (V_{1-7}, V_{6-7}), V_{CCmax}	20V
Lamp Driving Current, I_L	40mA
Allowable Power Dissipation ($T_A \leq +80^\circ\text{C}$), P_{Dmax}	370mW
Operating Temperature Range, T_{opr}	-20° to $+80^\circ\text{C}$
Storage Temperature Range, T_{stg}	-40° to $+125^\circ\text{C}$

Recommended Operating Condition: ($T_A = +25^\circ\text{C}$)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Recommended Supply Voltage	V_{CC}		4	-	12	V

Electrical Characteristics: ($T_A = +25^\circ\text{C}$, $V_{CC} = 6\text{V}$, $R_L = 3.3\text{k}\Omega$, Input = 100mV, $f = 1\text{kHz}$, L+R = 90%, Pilot = 10% unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Quiescent Current	I_{CCO}		-	7.0	10.5	mA
Input Resistance	r_i		-	20	-	k Ω
Channel Separation	Sep		30	45	-	dB
Total Harmonic Distortion (L+R)	THD		-	0.3	1.0	%
Lamp On Input Voltage	v_i		50	70	100	mV
Output Voltage	v_O		71	100	136	mV
Channel Balance			-	0.2	2.0	dB
SCA Rejection		L+R = 80%, Pilot = 10%, SCA = 10%	-	55	-	dB



Pin Connection Diagram

