



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE1387 Integrated Circuit Dual, Audio Power Amplifier, 2.4W/Ch

Features:


- Output Power: $P_{OUT} = 2.4W/Ch$ (Typ) at $V_{CC} = 14V$, $R_L = 8\Omega$, THD = 10%
- Wide Operating Supply Voltage Range: $V_{CC} = 5.5V$ to 20V
- Very Few External Components Required
- Built-In Turn-On “POP” Noise Muting Circuit
- Excellent Crosstalk: $CT = -60dB$ (Typ)

Absolute Maximum Ratings: ($T_A = +25^\circ C$ unless otherwise specified)

Operating Supply Voltage, V_{CC}	24V
Output Current (Peak), $I_{O(peak)}$	1.5A
Power Dissipation, P_D	12.5W
Operating Temperature Range, T_{opr}	-20° to +75°C
Storage Temperature Range, T_{stg}	-55° to +150°C

Electrical Characteristics: ($V_{CC} = 14V$, $R_L = 8\Omega$, $R_g = 600\Omega$, $f = 1kHz$, $T_A = +25^\circ C$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Quiescent Current	I_{CCQ}	$V_{CC} = 14V$	-	27	65	mA
		$V_{CC} = 20V$	-	3.3	-	
Output Power	P_{OUT}	THD = 10%	2.0	2.4	-	W
		$R_L = 4\Omega$, THD = 10%	-	4.0	-	
Voltage Gain	G_V		46	48	50	dB
Channel Voltage Gain Tatic	ΔG_V		-	0	1.5	dB
Total Harmonic Distortion	THD	$P_{OUT} = 500mW$	-	0.2	1.2	%
		$P_{OUT} = 1W$, $R_L = 4\Omega$	-	0.4	-	
Output Noise Voltage	V_{NO}	$R_g = 10k\Omega$	-	0.5	1.5	mV
Crosstalk	CT	$R_g = 0$, $P_{OUT} = 1.5W$	-	-60	-45	dB
Input Resistance	R_{IN}	$V_{OUT} = 1V_{rms}$	-	33	-	kΩ
Ripple Rejection	RR	$R_g = 0$, $f = 100Hz$	-	-50	-	dB



Pin Connection Diagram
(Front View)

