


UTC RXLD20

LINEAR INTEGRATED CIRCUIT

2.0A Output Type Low Power-Loss
Voltage Regulator

FEATURES


- *Low power-loss(Dropout voltage: 0.5V(max) at $I_o=2.0A$)
- *2.0A output type
- * Output voltage precision: $\pm 3.0\%$
- *Built-in ON/OFF control function
- *Built-in over current, overheat protection function, ASO protection circuit.
- *Lead forming type is also available.



APPLICATIONS

- *Power supplies for various electronic equipment such as AV, OA equipment.

INTERNAL CONNECTION DIAGRAM



Model Line-ups

	2.0A output
3.3V output	R33LD20
5.0V output	R05LD20
9.0V output	R09LD20
12.0V output	R12LD20

ABSOLUTE MAXIMUM RATINGS ($T_a=25^\circ C$)

PARAMETER	SYMBOL	RATING	UNIT
Input voltage ^(note 1)	V_{IN}	20	V
ON/OFF control terminal voltage ^(note1)	V_c	20	V
Output current	I_o	2.0	A
Power dissipation ^(note2)	P_{D1}	1.4	W
	P_{D2}	15	W
Junction temperature ^(note3)	T_j	150	°C
Operating temperature	T_{opr}	-20 ~ +80	°C
Storage temperature	T_{sta}	-40 ~ +150	°C
Soldering temperature	T_{sol}	260(For 10s)	°C

note1 : All are open except GND and applicable terminals.

UTC

UNISONIC TECHNOLOGIES CO., LTD.

1

QW-R102-015,A

UTC RXXLD20

LINEAR INTEGRATED CIRCUIT

note2 : P_{D1} :No heat sink; P_{D2} :With infinite heat sink

note3 : Overheat protection may operate at $125 \leq T_j \leq 150^\circ\text{C}$

UTC R33LD20 ELECTRICAL CHARACTERISTICS

(refer to the test circuits, unless otherwise specified, $T_a=25^\circ\text{C}$)

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Output voltage	V_o	$V_{in}=5\text{V}$, $I_o=1\text{A}$	3.201	3.3	3.399	V
Line regulation	ΔV_o	$V_{in}=4\sim10\text{V}$, $I_o=5\text{mA}$		0.1	2.5	%
Load regulation	ΔV_o	$V_{in}=5\text{V}$, $I_o=5\text{mA} \sim 2.0\text{A}$		0.1	2.0	%
Temperature coefficient of output voltage	$T_c V_o$	$T_j=0\sim125^\circ\text{C}$, $I_o=5\text{mA}$		± 0.02		%/°C
Ripple rejection	RR	Refer to Fig.2	45	55		dB
Dropout voltage	V_d	^(note4) , $I_o=2\text{A}$			0.5	V
ON-state voltage for control ^(note5)	$V_c(\text{ON})$	$V_{in}=5\text{V}$	2.0			V
ON-state current for control	$I_c(\text{ON})$	$V_c=2.7\text{V}$, $V_{in}=5\text{V}$			20	μA
OFF-state voltage for control	$V_c(\text{OFF})$	$V_{in}=5\text{V}$			0.8	V
OFF-state current for control	$I_c(\text{OFF})$	$V_c=0.4\text{V}$, $V_{in}=5\text{V}$			-0.4	mA
Quiescent current	I_q	$I_o=0\text{A}$, $V_{in}=5\text{V}$			10	mA

UTC R05LD20 ELECTRICAL CHARACTERISTICS

(refer to the test circuits, unless otherwise specified, $T_a=25^\circ\text{C}$)

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Output voltage	V_o	$V_{in}=7\text{V}$, $I_o=1\text{A}$	4.85	5.0	5.15	V
Line regulation	ΔV_o	$V_{in}=6\sim12\text{V}$, $I_o=5\text{mA}$		0.5	2.5	%
Load regulation	ΔV_o	$V_{in}=7\text{V}$, $I_o=5\text{mA} \sim 2.0\text{A}$		0.1	2.0	%
Temperature coefficient of output voltage	$T_c V_o$	$T_j=0\sim125^\circ\text{C}$, $I_o=5\text{mA}$		± 0.02		%/°C
Ripple rejection	RR	Refer to Fig.2	45	55		dB
Dropout voltage	V_d	^(note4) , $I_o=2\text{A}$			0.5	V
ON-state voltage for control ^(note5)	$V_c(\text{ON})$	$V_{in}=7\text{V}$	2.0			V
ON-state current for control	$I_c(\text{ON})$	$V_c=2.7\text{V}$, $V_{in}=7\text{V}$			20	μA
OFF-state voltage for control	$V_c(\text{OFF})$	$V_{in}=7\text{V}$			0.8	V
OFF-state current for control	$I_c(\text{OFF})$	$V_c=0.4\text{V}$, $V_{in}=7\text{V}$			-0.4	mA
Quiescent current	I_q	$I_o=0\text{A}$, $V_{in}=7\text{V}$			10	mA

UTC RXXLD20

LINEAR INTEGRATED CIRCUIT

UTC R09LD20 ELECTRICAL CHARACTERISTICS

(refer to the test circuits, unless otherwise specified, Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Output voltage	Vo	Vin=11V, Io=1A	8.73	9.0	9.27	V
Line regulation	ΔVo	Vin=10~16V, Io=5mA		0.5	2.5	%
Load regulation	ΔVo	Vin=11V, Io=5mA ~2.0A		0.1	2.0	%
Temperature coefficient of output voltage	TcVo	Tj=0~125°C, Io=5mA		±0.02		%/°C
Ripple rejection	RR	Refer to Fig.2	45	55		dB
Dropout voltage	Vd	^(note4) , Io=2A			0.5	V
ON-state voltage for control ^(note5)	Vc(ON)	Vin=11V	2.0			V
ON-state current for control	Ic(ON)	Vc=2.7V, Vin=11V			20	μA
OFF-state voltage for control	Vc(OFF)	Vin=11V			0.8	V
OFF-state current for control	Ic(OFF)	Vc=0.4V, Vin=11V			-0.4	mA
Quiescent current	Iq	Io=0A, Vin=11V			10	mA

UTC R12LD20 ELECTRICAL CHARACTERISTICS

(refer to the test circuits, unless otherwise specified, Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Output voltage	Vo	Vin=14V, Io=1A	11.64	12.0	12.36	V
Line regulation	ΔVo	Vin=13~19V, Io=5mA		0.5	2.5	%
Load regulation	ΔVo	Vin=14V, Io=5mA ~2.0A		0.1	2.0	%
Temperature coefficient of output voltage	TcVo	Tj=0~125°C, Io=5mA		±0.02		%/°C
Ripple rejection	RR	Refer to Fig.2	45	55		dB
Dropout voltage	Vd	^(note4) , Io=2A			0.5	V
ON-state voltage for control ^(note5)	Vc(ON)	Vin=14V	2.0			V
ON-state current for control	Ic(ON)	Vc=2.7V, Vin=14V			20	μA
OFF-state voltage for control	Vc(OFF)	Vin=14V			0.8	V
OFF-state current for control	Ic(OFF)	Vc=0.4V, Vin=14V			-0.4	mA
Quiescent current	Iq	Io=0A, Vin=14V			10	mA

note4 : Input voltage shall be the value when output voltage is 95% in comparison with the initial value.

note5 : TO-220B: In case of opening control terminal ⑤, output voltage turns on.

TO-220F-4: In case of opening control terminal ④, output voltage turns on.

UTC RXXLD20 LINEAR INTEGRATED CIRCUIT




Fig.1 Test Circuit






Fig.2 Test Circuit of Ripple Rejection

Fig.3 Power Dissipation vs.
Ambient Temperature



Note) Oblique line portion:Overheat protection may operate in this area.

Fig.4 Overcurrent Protection
Characteristics(Typical Value) (R33LD20)



UTC RXXLD20 LINEAR INTEGRATED CIRCUIT

Fig.5 Overcurrent Protection Characteristics (Typical Value)(R05LD20)




Fig.6 Overcurrent Protection Characteristics (Typical Value)(R09LD20)




Fig.7 Overcurrent Protection Characteristics (Typical Value)(R12LD20)




Fig.9 Output Voltage Deviation vs .Junction Temperature (R05LD20)




Fig.8 Output Voltage Deviation vs .Junction Temperature (R03LD20)





Fig.10 Output Voltage Deviation vs .Junction Temperature (R09LD20)



UTC RXXLD20 LINEAR INTEGRATED CIRCUIT

Fig.11 Output Voltage Deviation vs .Junction Temperature (R12LD20)




Fig.13 Output Voltage vs .Input Voltage (R05LD20)




Fig.15 Output Voltage vs .Input Voltage (R12LD20)




Fig.12 Output Voltage vs .Input Voltage (R33LD20)




Fig.14 Output Voltage vs .Input Voltage (R09LD20)





Fig.16 Circuit Operating Current vs .Input Voltage (R33LD20)



UTC RXXLD20

LINEAR INTEGRATED CIRCUIT

Fig.17 Circuit Operating Current vs .Input Voltage (R05LD20)




Fig.19 Circuit Operating Current vs .Input Voltage (R12LD20)




Fig.21 Quiescent Current vs .Junction Temperature




Fig.18 Circuit Operating Current vs .Input Voltage (R09LD20)




Fig.20 Dropout Voltage vs .Junction Temperature





Fig.22 Ripple Rejection vs .Input Ripple Frequency



[查询"R05LD20"供应商](#)

UTC RXXLD20 LINEAR INTEGRATED CIRCUIT

TYPICAL APPLICATION

