

FEATURES

- 16 × 16 high speed, nonblocking switch array
- Pinout and functionally equivalent to the **AD8114/AD8115**
- Complete solution
 - Buffered inputs
 - Programmable high impedance outputs
 - 16 output amplifiers, $G = +1$ (ADV3226), $G = +2$ (ADV3227)
 - Drives 150 Ω loads
- Operates on ± 5 V supplies
- Low power: 1.3 W
- Excellent ac performance
 - 3 dB bandwidth
 - 200 mV p-p: 820 MHz (ADV3226), 750 MHz (ADV3227)
 - 2 V p-p: 600 MHz (ADV3226), 750 MHz (ADV3227)
 - Slew rate: 2150 V/ μ s (ADV3226), 2950 V/ μ s (ADV3227)
- Serial or parallel programming of switch array
- 100-lead LFCSP (12 mm × 12 mm)

APPLICATIONS

- Routing of high speed signals including
 - Video (NTSC, PAL, S, SECAM, YUV, RGB)
 - Compressed video (MPEG, wavelet)
 - 3-level digital video (HDB3)
- Data communications
- Telecommunications

GENERAL DESCRIPTION

The ADV3226/ADV3227 are high speed 16 × 16 analog crosspoint switch matrices. They offer a -3 dB signal bandwidth greater than 750 MHz and channel switch times of less than 20 ns with 1% settling.

The ADV3226/ADV3227 include 16 independent output buffers that can be placed into a high impedance state for paralleling crosspoint outputs to prevent off channels from loading the output bus. The ADV3226 has a gain of +1 and the ADV3227 has a gain of +2. They both operate on voltage supplies of ± 5 V

FUNCTIONAL BLOCK DIAGRAM




Figure 1.

while consuming only 118 mA (ADV3226) and 133 mA (ADV3227) of idle current. Channel switching is performed via a serial digital control that can accommodate daisy chaining of several devices or via a parallel control to allow updating of an individual output without reprogramming the entire array.

The ADV3226/ADV3227 are available in the 100-lead LFCSP package over the extended industrial temperature range of -40°C to +85°C.

Rev. 0

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.
Tel: 781.329.4700
Fax: 781.461.3113
www.analog.com

©2010 Analog Devices, Inc. All rights reserved.



TABLE OF CONTENTS

Features	1	ESD Caution.....	7
Applications.....	1	Pin Configuration and Function Descriptions.....	8
General Description	1	Truth Table and Logic Diagram	10
Functional Block Diagram	1	Typical Performance Characteristics	11
Revision History	2	Circuit Diagrams	20
Specifications.....	3	Theory of Operation	21
Timing Characteristics (Serial)	5	Applications Information.....	21
Logic Levels	5	Power-On Reset	22
Timing Characteristics (Parallel)	6	Gain Selection	22
Absolute Maximum Ratings.....	7	Creating Larger Crosspoint Arrays	23
Thermal Resistance	7	Outline Dimensions	24
Power Dissipation.....	7	Ordering Guide	24

REVISION HISTORY

4/10—Revision 0: Initial Version

SPECIFICATIONS

$V_S = \pm 5\text{ V}$, $T_A = +25^\circ\text{C}$, $R_L = 150\ \Omega$, unless otherwise noted.

Table 1.

Parameter	Test Conditions/Comments	ADV3226			ADV3227			Unit
		Min	Typ	Max	Min	Typ	Max	
DYNAMIC PERFORMANCE								
–3 dB Bandwidth	200 mV p-p		820			750		MHz
	2 V p-p		600			750		MHz
Gain Flatness	0.1 dB, 2 V p-p		130			60		MHz
	0.5 dB, 2 V p-p, C _L = 2.2 pF		400			200		MHz
Propagation Delay	2 V p-p		0.6			0.6		ns
Settling Time	1%, 2 V step		3			3		ns
Slew Rate	2 V step, peak		2150			2950		V/μs
NOISE/DISTORTION PERFORMANCE								
Differential Gain Error	NTSC or PAL		0.04			0.02		%
Differential Phase Error	NTSC or PAL		0.01			0.01		Degrees
Crosstalk, All Hostile	f = 100 MHz		–45			–35		dB
	f = 5 MHz		–75			–60		dB
Off Isolation, Input to Output	f = 100 MHz, one channel		–80			–75		dB
IMD2	f = 100 MHz, R _L = 100 Ω					47		dBm
	f = 500 MHz, R _L = 100 Ω					22		dBm
IMD3	f = 100 MHz, R _L = 100 Ω					42		dBm
	f = 500 MHz, R _L = 100 Ω					14		dBm
Output 1 dB Compression Point	f = 100 MHz, R _L = 100 Ω					18		dBm
	f = 500 MHz, R _L = 100 Ω					9		dBm
Input Voltage Noise	0.01 MHz to 50 MHz		16			16		nV/√Hz
DC PERFORMANCE								
Gain Error			0.1	1.0		0.4	1.5	%
Gain Matching	Channel-to-channel			1.0			1.5	%
Gain Temperature Coefficient			0.8			16		ppm/°C
OUTPUT CHARACTERISTICS								
Output Resistance	DC, enabled		0.2			0.2		Ω
	DC, disabled		10			5		MΩ
Output Disabled Capacitance			2.7			2.7		pF
Output Leakage Current	Output disabled		1			1		μA
Output Voltage Range	No load		±3			±3		V
	R _L = 150 Ω		±2.8			±2.8		V
	Short-circuit current		55			55		mA
INPUT CHARACTERISTICS								
Input Offset Voltage	Worst case (all configurations)		±5			±5		mV
Input Offset Voltage Drift			8			8		μV/°C
Input Voltage Range	No load		±3			±1.5		V
	R _L = 150 Ω		±3			±1.5		V
Input Capacitance	Any switch configuration		2.1			2.1		pF
Input Resistance			2			2		MΩ
Input Bias Current	Any switch configuration		1			1		μA

ADV3226/ADV3227

[查询"ADV3226"供应商](#)

Parameter	Test Conditions/Comments	ADV3226			ADV3227			Unit
		Min	Typ	Max	Min	Typ	Max	
SWITCHING CHARACTERISTICS								
Enable/Disable Time	50% <u>UPDATE</u> to 1% settling	20			20			ns
Switching Time, 2 V Step	50% <u>UPDATE</u> to 1% settling	20			20			ns
Switching Transient (Glitch)		40			65			mV p-p
POWER SUPPLIES								
Supply Current	AVCC, outputs enabled, no load	110 130			125 140			mA
	AVCC, outputs disabled	25 35			25 35			mA
	AVEE, outputs enabled, no load	110 130			125 140			mA
	AVEE, outputs disabled	25 35			25 35			mA
	DVCC, outputs enabled, no load	8 10			8 10			mA
Supply Voltage Range		±4.5	±5	±5.5	±4.5	±5	±5.5	V
PSRR	DC to 50 kHz, AVCC, AVEE	>60			>60			dB
	f = 100 kHz, AVCC, AVEE	55			60			dB
	f = 10 MHz, AVCC	45			40			dB
	f = 10 MHz, AVEE	35			55			dB
	f = 100 kHz, DVCC	90			80			dB
OPERATING TEMPERATURE RANGE								
Temperature Range	Operating (still air)	−40 +85			−40 +85			°C
θJA	Operating (still air)	26			26			°C/W

TIMING CHARACTERISTICS (SERIAL)

Table 2.

Parameter	Symbol	Min	Typ	Max	Unit
Serial Data Setup Time	t_1	10			ns
CLK Pulse Width	t_2	10			ns
Serial Data Hold Time	t_3	10			ns
CLK Pulse Separation, Serial Mode	t_4	10			ns
CLK to UPDATE Delay	t_5	10			ns
UPDATE Pulse Width	t_6	10			ns
CLK to DATAOUT Valid, Serial Mode	t_7			50	ns
Propagation Delay, UPDATE to Switch On or Off			20		ns
Data Load Time, CLK = 5 MHz, Serial Mode			1.6		μ s
CLK, UPDATE Rise and Fall Times				50	ns
RESET Time			30		ns

Timing Diagram—Serial Mode




Figure 2. Timing Diagram, Serial Mode

LOGIC LEVELS

Table 3. Logic Levels

V_{IH}	V_{IL}	V_{OH}	V_{OL}	I_{IH}	I_{IL}	I_{IH}	I_{IL}	I_{OH}	I_{OL}
RESET, SER/PAR, CLK, DATAIN, CE, UPDATE	RESET, SER/PAR, CLK, DATAIN, CE, UPDATE	DATAOUT	DATAOUT	SER/PAR, CLK, DATAIN, CE, UPDATE	SER/PAR, CLK, DATAIN, CE, UPDATE	RESET	RESET	DATAOUT	DATAOUT
2.0 V min	0.8 V max	2.4 V min	0.4 V max	2 μ A max	2 μ A max	2 μ A max	300 μ A max	3 mA min	1 mA min

TIMING CHARACTERISTICS (PARALLEL)

Table 4.

Parameter	Symbol	Min	Typ	Max	Unit
Parallel Data Setup Time	t_{1d}	10			ns
Address Setup Time	t_{1a}	10			ns
CLK Pulse Width	t_2	10			ns
Parallel Data Hold Time	t_{3d}	10			ns
Address Hold Time	t_{3a}	10			ns
CLK Pulse Separation	t_4	20			ns
UPDATE Pulse Width	t_5	10			ns
CLK, UPDATE Rise and Fall Times				50	ns
RESET Time			30		ns

Timing Diagram—Parallel Mode




Figure 3. Timing Diagram, Parallel Mode

ABSOLUTE MAXIMUM RATINGS

Table 5.

Parameter	Rating
Analog Supply Voltage (AVCC – AVEE)	11 V
Digital Supply Voltage (DVCC – DGND)	6 V
Supply Potential Difference (AVCC – DVCC)	±0.5 V
Ground Potential Difference (AGND – DGND)	±0.5 V
Maximum Potential Difference (DVCC – AVEE)	6 V
Analog Input Voltage	$AVEE < V_{IN} < AVCC$
Digital Input Voltage	$DGND < D_{IN} < DVCC$
Exposed Paddle Voltage	$AVEE < V_{IN} < AVCC$
Output Voltage (Disabled Analog Output)	$AVEE < V_{OUT} < AVCC$
Output Short-Circuit	
Duration	Momentary
Current	Internally limited to 55 mA
Temperature	
Storage Temperature Range	–65°C to +125°C
Operating Temperature Range	–40°C to +85°C
Junction Temperature	150°C
Lead Temperature (Soldering, 10 sec)	300°C

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

THERMAL RESISTANCE

θ_{JA} is specified for the worst-case conditions, that is, a device soldered in a circuit board for surface-mount packages.

Table 6. Thermal Resistance

Package Type	θ_{JA}	θ_{JC}	θ_{JB}	ψ_{JT}	ψ_{JB}	Unit
100-Lead LFCSP	26	2.56	9.5	0.2	8.9	°C/W

POWER DISSIPATION

The ADV3226/ADV3227 operate with ± 5 V supplies and can drive loads down to 100 Ω , resulting in a wide range of possible power dissipations. For this reason, extra care must be taken when derating the operating conditions based on ambient temperature.

Packaged in the 100-lead LFCSP, the ADV3226/ADV3227 junction-to-ambient thermal impedance (θ_{JA}) is 26°C/W. For long-term reliability, the maximum allowed junction temperature of the die should not exceed 125°C; even temporarily exceeding this limit can cause a shift in parametric performance due to a change in stresses exerted on the die by the package. Exceeding a junction temperature of 150°C for an extended period can result in device failure. In Figure 4, the curve shows the range of allowed internal die power dissipation that meets these conditions over the –40°C to +85°C ambient temperature range. When using Figure 4, do not include the external load power in the maximum power calculation, but do include the load current dropped on the die output transistors.





Figure 4. Maximum Die Power Dissipation vs. Ambient Temperature

ESD CAUTION



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

PIN CONFIGURATION AND FUNCTION DESCRIPTIONS



- NOTES
- 1. NC = NO CONNECT.
 - 2. THE EXPOSED METAL PADDLE ON THE BOTTOM OF THE LFCSP PACKAGE MUST BE SOLDERED TO PCB GROUND FOR PROPER HEAT DISSIPATION AND ALSO FOR NOISE AND MECHANICAL STRENGTH BENEFITS.

09653-005

Figure 5. Pin Configuration

Table 7. Pin Function Descriptions

Pin No.	Mnemonic	Description	Pin No.	Mnemonic	Description
1	DVCC	Digital Positive Power Supply.	17	AGND	Analog Ground.
2	DGND	Digital Ground.	18	IN15	Input Number 15.
3	AGND	Analog Ground.	19	AGND	Analog Ground.
4	IN08	Input Number 8.	20	AVEE	Analog Negative Supply.
5	AGND	Analog Ground.	21	AVCC	Analog Positive Supply
6	IN09	Input Number 9.	22	AVCC	Analog Positive Supply.
7	AGND	Analog Ground.	23	OUT15	Output Number 15.
8	IN10	Input Number 10.	24	AVEE	Analog Negative Supply.
9	AGND	Analog Ground.	25	OUT14	Output Number 14.
10	IN11	Input Number 11.	26	AVCC	Analog Positive Supply.
11	AGND	Analog Ground.	27	OUT13	Output Number 13.
12	IN12	Input Number 12.	28	AVEE	Analog Negative Supply.
13	AGND	Analog Ground.	29	OUT12	Output Number 12.
14	IN13	Input Number 13.	30	AVCC	Analog Positive Supply.
15	AGND	Analog Ground.	31	OUT11	Output Number 11.
16	IN14	Input Number 14.	32	AVEE	Analog Negative Supply.

Pin No.	Mnemonic	Description
33	OUT10	Output Number 10.
34	AVCC	Analog Positive Supply.
35	OUT09	Output Number 9.
36	AVEE	Analog Negative Supply.
37	OUT08	Output Number 8.
38	AVCC	Analog Positive Supply.
39	OUT07	Output Number 7.
40	AVEE	Analog Negative Supply.
41	OUT06	Output Number 6.
42	AVCC	Analog Positive Supply.
43	OUT05	Output Number 5.
44	AVEE	Analog Negative Supply.
45	OUT04	Output Number 4.
46	AVCC	Analog Positive Supply.
47	OUT03	Output Number 3.
48	AVEE	Analog Negative Supply.
49	OUT02	Output Number 2.
50	AVCC	Analog Positive Supply.
51	OUT01	Output Number 1.
52	AVEE	Analog Negative Supply.
53	OUT00	Output Number 0.
54	AVCC	Analog Positive Supply.
55	AVCC	Analog Positive Supply.
56	AVEE	Analog Negative Supply.
57	AGND	Analog Ground.
58	IN00	Input Number 0.
59	AGND	Analog Ground.
60	IN01	Input Number 1.
61	AGND	Analog Ground.
62	IN02	Input Number 2.
63	AGND	Analog Ground.
64	IN03	Input Number 3.
65	AGND	Analog Ground.
66	IN04	Input Number 4.
67	AGND	Analog Ground.

Pin No.	Mnemonic	Description
68	IN05	Input Number 5.
69	AGND	Analog Ground.
70	IN06	Input Number 6.
71	AGND	Analog Ground.
72	IN07	Input Number 7.
73	AGND	Analog Ground.
74	DGND	Digital Ground.
75	DVCC	Digital Positive Power Supply.
76	D4	Parallel Data Input, Output Enable.
77	D3	Parallel Data Input.
78	D2	Parallel Data Input.
79	D1	Parallel Data Input.
80	D0	Parallel Data Input.
81	A3	Parallel Data Input.
82	A2	Parallel Data Input.
83	A1	Parallel Data Input.
84	A0	Parallel Data Input.
85 to 93	NC	No Connect.
94	$\overline{\text{SER/PAR}}$	Serial/Parallel Mode Select (Control Pin).
95	$\overline{\text{UPDATE}}$	Second Rank Write Strobe (Control Pin).
96	DATAIN	Serial Data In (Control Pin).
97	CLK	Serial Data Clock. Parallel 1st rank latch enable (control pin).
98	DATAOUT	Serial Data Out.
99	$\overline{\text{CE}}$	Chip Enable (Control Pin).
100	$\overline{\text{RESET}}$	Second Rank Reset (Control Pin).
N/A ¹	EP	Exposed Paddle. The exposed metal paddle on the bottom of the LFCSP package must be soldered to the PCB ground for proper heat dissipation and for noise and mechanical strength benefits.

¹ N/A means not applicable.

TRUTH TABLE AND LOGIC DIAGRAM

Table 8. Operation Truth Table¹

CE	UPDATE	CLK	DATAIN	DATAOUT	RESET	SER/PAR	Description
1	X	X	X	X	X	X	No change in logic.
0	X		Data _{in} ²	Data _{in-80}	X	0	The data on the serial DATAIN line is loaded into the serial register. The first bit clocked into the serial register appears at DATAOUT 80 clock cycles later.
0	X	0	D0...D4	N/A ³ in parallel mode ⁴	X	1	The data on the parallel data lines, D0 to D4, are loaded into the 80-bit serial shift register location addressed at A0 to A3.
0	0	X	X	X	1	X	Data in the 80-bit shift register transfers into the parallel latches that control the switch array. Latches are transparent.
X	X	X	X	X	0	X	Asynchronous operation. All outputs are disabled. Second rank latches are cleared. Remainder of logic is unchanged.

¹ X is don't care.
² Data_{in}: serial data.
³ N/A means not applicable.
⁴ DATAOUT remains active in parallel mode and always reflects the state of the MSB of the serial shift register.




Figure 6. Logic Diagram

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 7. ADV3226 Small Signal Frequency Response




Figure 10. ADV3227 Small Signal Frequency Response




Figure 8. ADV3226 Large Signal Frequency Response




Figure 11. ADV3227 Large Signal Frequency Response




Figure 9. ADV3226 Small Signal Frequency Response with Capacitive Loads




Figure 12. ADV3227 Small Signal Frequency Response, $R_L = 150\Omega$




Figure 13. ADV3226 Large Signal Frequency Response with Capacitive Loads




Figure 16. ADV3227 Large Signal Frequency Response with Capacitive Loads




Figure 14. ADV3226 Small Signal Pulse Response




Figure 17. ADV3227 Small Signal Pulse Response




Figure 15. ADV3226 Large Signal Pulse Response




Figure 18. ADV3227 Large Signal Pulse Response




Figure 19. ADV3226 Rising Edge Slew Rate




Figure 22. ADV3227 Rising Edge Slew Rate




Figure 20. ADV3226 Falling Edge Slew Rate




Figure 23. ADV3227 Falling Edge Slew Rate




Figure 21. ADV3226 Settling Time




Figure 24. ADV3227 Settling Time




Figure 25. ADV3226 Power Supply Rejection




Figure 28. ADV3227 Power Supply Rejection




Figure 26. ADV3226 Output Noise, 100 Ω Load




Figure 29. ADV3227 Output Noise, 100 Ω Load




Figure 27. ADV3226 Off Isolation




Figure 30. ADV3227 Off Isolation




Figure 31. ADV3226 Crosstalk, One Adjacent Channel, RTO




Figure 34. ADV3227 Crosstalk, One Adjacent Channel, RTO




Figure 32. ADV3226 Crosstalk, All Hostile, RTO




Figure 35. ADV3227 Crosstalk, All Hostile, RTO




Figure 33. ADV3226 Input Impedance




Figure 36. ADV3227 Input Impedance




Figure 37. ADV3226 Output Impedance, Disabled




Figure 40. ADV3227 Output Impedance, Disabled




Figure 38. ADV3226 Output Impedance, Enabled




Figure 41. ADV3227 Output Impedance, Enabled




Figure 39. ADV3226 Switching Time




Figure 42. ADV3227 Switching Time




Figure 43. ADV3226 Switching Glitch




Figure 46. ADV3227 Switching Glitch




Figure 44. ADV3226 Enable Time




Figure 47. ADV3227 Enable Time




Figure 45. ADV3226 Differential Gain Error




Figure 48. ADV3227 Differential Gain Error




Figure 49. ADV3226 Differential Phase Error




Figure 52. ADV3227 Differential Phase Error




Figure 50. ADV3226 Overdrive Recovery




Figure 53. ADV3227 Overdrive Recovery




Figure 51. ADV3227 1 dB Gain Compression, 100 Ω Load




Figure 54. ADV3227 Third-Order Intercept, 100 Ω Load




Figure 55. ADV3227 Second-Order Intercept, 100 Ω Load




Figure 57. ADV3227 Harmonic Distortion (Input Referred), 100 Ω Load




Figure 56. ADV3226 and ADV3227, Input V_{os} Distribution

CIRCUIT DIAGRAMS




Figure 58. Analog Input




Figure 61. Logic Input




Figure 59. Analog Output Enabled




Figure 62. Analog Output Disabled




Figure 60. ESD Map




Figure 63. Reset Input




Figure 64. Logic Output

THEORY OF OPERATION

The ADV3226 ($G = 1$) and ADV3227 ($G = 2$) are crosspoint arrays with 16 outputs, each of which can be connected to any one of 16 inputs. Organized by output row, 16 switchable input transconductance stages are connected to each output buffer to form 16-to-1 multiplexers. There are 16 of these multiplexers, each with its inputs wired in parallel, for a total array of 256 transconductance stages forming a multicast-capable crosspoint switch. Each input is buffered and is not loaded by the outputs, simplifying the construction of larger arrays using the ADV3226 or ADV3227 as a building block.

Decoding logic for each output selects one (or none) of the transconductance stages to drive the output stage. The enabled transconductance stage drives the output stage, and feedback forms a closed-loop amplifier. A mask programmable feedback network sets the closed-loop signal gain. For the ADV3226, this gain is 1, and for the ADV3227, this gain is 2.

The output stage of the ADV3226 or ADV3227 is designed for low differential gain and phase error when driving composite video signals. It also provides slew current for a fast pulse response when driving component video signals. Unlike many multiplexer designs, these requirements are balanced such that large signal bandwidth is very similar to small signal bandwidth. The design load is $150\ \Omega$, but provisions are made to drive loads as low as $100\ \Omega$ when on-chip power dissipation limits are not exceeded.

The outputs of the ADV3226/ADV3227 can be disabled to minimize on-chip power dissipation. When disabled, there is no feedback network loading the output. This high disabled output impedance allows multiple ICs to be bussed together without additional buffering. Care must be taken to reduce output capacitance, which results in more overshoot and frequency domain peaking.

A series of internal amplifiers drives internal nodes such that a wideband high impedance is presented at the disabled output, even while the output bus is under large signal swings. To keep these internal amplifiers in their linear range of operation when the outputs are disabled and driven externally, do not allow the voltage applied to them to exceed the valid output swing range for the ADV3226/ADV3227. If the disabled outputs are left floating, they may exhibit high enable glitches. If necessary, the disabled output can be kept from drifting out of range by applying an output load resistor to ground.

The connection of the ADV3226/ADV3227 is controlled by a flexible TTL-compatible logic interface. Either parallel or serial loading into a first rank of latches preprograms each output. A global update signal moves the programming data into the second rank of latches, simultaneously updating all outputs. In serial mode, a serial out pin allows devices to be daisy-chained together for single pin programming of multiple ICs. A power-on reset

pin is available to avoid bus conflicts by disabling all outputs. This power-on reset clears the second rank of latches but does not clear the first rank of latches. In serial mode, preprogramming individual inputs is not possible and the entire shift register needs to be flushed.

To easily interface to ground referenced video signals, the ADV3226/ADV3227 operate on split $\pm 5\text{ V}$ supplies. The logic inputs and output run on a single $+5\text{ V}$ supply, but the logic inputs switch at approximately 1.6 V for compatibility with a variety of logic families. The serial output buffer is a rail-to-rail output stage with 5 mA of drive capability.

APPLICATIONS INFORMATION

The ADV3226/ADV3227 have two options for changing the programming of the crosspoint matrix. In the first option, a serial word of 80 bits can be provided, which updates the entire matrix each time the 80-bit word is shifted into the part. The second option allows for changing the programming of a single output via a parallel interface. The serial option requires fewer signals but more time (clock cycles) for changing the programming, whereas the parallel programming technique requires more signals but can change a single output at a time and requires fewer clock cycles to complete the programming.

Serial Programming

The serial programming mode uses the $\overline{\text{CE}}$, CLK, DATAIN, $\overline{\text{UPDATE}}$, and SER/PAR pins. The first step is to assert a low on SER/PAR to enable the serial programming mode. $\overline{\text{CE}}$ for the chip must be low to allow data to be clocked into the device. The $\overline{\text{CE}}$ signal can be used to address an individual device when devices are connected in parallel.

The $\overline{\text{UPDATE}}$ signal should be high during the time that data is shifted into the serial port of the device. Although the data still shifts in when $\overline{\text{UPDATE}}$ is low, the transparent, asynchronous latches allow the shifting data to reach the matrix, which causes the matrix to try to update to every intermediate state as defined by the shifting data.

The data at DATAIN is clocked in at every falling edge of CLK. A total of 80 bits must be shifted in to complete the programming. For each of the 16 outputs, there are four bits (D0 to D3) that determine the source of its input. The MSB is shifted in first. A fifth bit (D4) precedes the four input select bits and determines the enabled state of the output. If D4 is low (output disabled), the four associated bits (D0 to D3) do not matter because no input switches to that output.

The most significant output address data is shifted in first, and the remaining addresses follow in sequence until the least significant output address data is shifted in. At this point, $\overline{\text{UPDATE}}$ can be taken low, which programs the device according to the

data that was just shifted in. The update registers are asynchronous, and when UPDATE is low (and CE is low), they are transparent.

If more than one ADV3226/ADV3227 device is to be serially programmed in a system, the DATAOUT signal from one device can be connected to the DATAIN of the next device to form a serial chain. Connect all of the CLK, CE, UPDATE, and SER/PAR pins in parallel and operate them as described previously in this section. The serial data is input to the DATAIN pin of the first device of the chain, and it ripples through to the last. Therefore, the data for the last device in the chain should come at the beginning of the programming sequence. The length of the programming sequence (80 bits) is multiplied by the number of devices in the chain.

Parallel Programming

When using the parallel programming mode, it is not necessary to reprogram the entire device when making changes to the matrix. Parallel programming allows the modification of a single output at a time. Because this takes only one CLK/UPDATE cycle, significant time savings can be realized by using parallel programming.

An important consideration in using parallel programming is that the RESET signal does not reset all registers in the ADV3226/ADV3227. When taken low, the RESET signal sets each output to the disabled state. This is helpful during power-up to ensure that two parallel outputs are not active at the same time.

After initial power-up, the internal registers in the device generally contain random data, even though the RESET signal was asserted. If parallel programming is used to program one output, that output is properly programmed, but the rest of the device has a random program state depending on the internal register content at power-up. Therefore, when using parallel programming, it is essential that all outputs be programmed to a desired state after power-up to ensure that the programming matrix is always in a known state. From this point, parallel programming can be used to modify either a single output or multiple outputs at one time.

Similarly, if both CE and UPDATE are taken low after initial power-up, the random power-up data in the shift register is programmed into the matrix. Therefore, to prevent programming the crosspoint into an unknown state, do not apply low logic levels to both CE and UPDATE after power is initially applied. To eliminate the possibility of programming the matrix to an unknown state, after initial power-up, program the full shift register one time to a desired state using either serial or parallel programming.

To change the programming of an output via parallel programming, take the SER/PAR and UPDATE pins high, and take the CE pin low. The CLK signal should be in the high state. Place the 4-bit address of the output to be programmed on A0 to A3.

The first four data bits (D0 to D3) contain the information that identifies the input that is programmed to the addressed output. The fifth data bit (D4) determines the enabled state of the output. If D4 is low (output disabled), the data on D0 to D3 does not matter.

After the address and data signals are established, they can be latched into the shift register by pulling the CLK signal low; however, the matrix is not programmed until the UPDATE signal is taken low. In this way, it is possible to latch in new data for several or all of the outputs first via successive negative transitions of CLK while UPDATE is held high and then have all the new data take effect when UPDATE goes low. Use this technique when programming the device for the first time after power-up when using parallel programming. In parallel mode, the CLK pin is level sensitive, whereas in serial mode, it is edge triggered.

POWER-ON RESET

When powering up the ADV3226/ADV3227, it is usually desirable to have the outputs come up in the disabled state. When taken low, the RESET pin causes all outputs to be in the disabled state. However, the RESET signal does not reset all registers in the ADV3226/ADV3227. This is important when operating in the parallel programming mode. Refer to the Parallel Programming section for information about programming internal registers after power-up. Serial programming programs the entire matrix each time; therefore, no special considerations apply.

Because the data in the shift register is random after power-up, it should not be used to program the matrix, or the matrix can enter unknown states. To prevent the matrix from entering unknown states, do not apply logic low signals to both CE and UPDATE initially after power-up. Instead, first load the shift register with the data and then take UPDATE low to program the device.

The RESET pin has a 20 kΩ pull-up resistor to DVCC that can be used to create a simple power-up reset circuit. A capacitor from RESET to ground holds the RESET pin low for a period during which the rest of the device stabilizes. The low condition causes all of the outputs to be disabled. The capacitor then charges through the pull-up resistor to the high state, thereby allowing full programming capability of the device.

GAIN SELECTION

The 16 × 16 crosspoints come in two versions, depending on the gain of the analog circuit path. The ADV3226 device is unity gain and can be used for analog logic switching and other applications where unity gain is desired. The ADV3226 outputs have very high impedance when their outputs are disabled.

The ADV3227 can be used for devices that drive a terminated cable with its outputs. This device has a built-in gain-of-2 that eliminates the need for a gain-of-2 buffer to drive a video line. Its

high output disabled impedance minimizes signal degradation when paralleling additional outputs.

CREATING LARGER CROSSPOINT ARRAYS

The ADV3226/ADV3227 are high density building blocks for creating crosspoint arrays of dimensions larger than 16×16 . Various features, such as output disable, chip enable, and gain-of-1 and gain-of-2 options, are useful for creating larger arrays. When required for customizing a crosspoint array size, they can be used with the [AD8108](#) and [AD8109](#), which are a pair of (unity-gain and gain-of-2) 8×8 video crosspoint switches, or with the [AD8110](#) and [AD8111](#), a pair of (unity-gain and gain-of-2) 16×8 video crosspoint switches.

The first consideration in constructing a larger crosspoint is to determine the minimum number of required devices that are required. The 16×16 architecture of the ADV3226/ADV3227 contains 256 points, which is a factor of 64 greater than a 4×1 crosspoint (or multiplexer). The benefits realized in PCB area used, power consumption, and design effort are readily apparent when compared to using multiples of these smaller 4×1 devices.

To obtain the minimum number of required points for a non-blocking crosspoint, multiply the number of inputs by the number of outputs. Nonblocking requires that the programming of a given input to one or more outputs does not restrict the availability of that input to be a source for any other outputs. Some nonblocking crosspoint architectures require more than this minimum. In addition, there are blocking architectures that can be constructed with fewer devices than this minimum. These systems have connectivity available on a statistical basis that is determined when designing the overall system.

The basic concept in constructing larger crosspoint arrays is to connect inputs in parallel in a horizontal direction and to wire-OR the outputs together in the vertical direction. The meaning of horizontal and vertical can best be understood by referring to Figure 65, which illustrates this concept for a 32×32 crosspoint array that uses four ADV3226 or ADV3227 devices.





Figure 65. A 32×32 Nonblocking Crosspoint Switch Array

Each input is uniquely assigned to each of the 32 inputs of the two devices and terminated appropriately. The outputs are wired-ORed together in pairs. Enable the output from only one wire-ORed pair at any given time. The device programming software must be properly written to prevent multiple connected outputs from being enabled at the same time.

For a complete 32×32 array in a single device, refer to the [AD8117](#) and [AD8118](#) for high bandwidth or the [ADV3200](#) and [ADV3201](#) for lower bandwidth. Also available are 32×16 arrays in a single package: [AD8104](#), [AD8105](#), [ADV3202](#), and [ADV3203](#).

OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MO-220-VRRE.

Figure 66. 100-Lead Lead Frame Chip Scale Package [LFCSP_VQ]
 12 mm × 12 mm Body, Very Thin Quad
 (CP-100-1)
 Dimensions shown in millimeters

06-11-2008-B

ORDERING GUIDE

Model ¹	Temperature Range	Package Description	Package Option
ADV3226ACPZ	−40°C to +85°C	100-Lead Lead Frame Chip Scale Package [LFCSP_VQ]	CP-100-1
ADV3227ACPZ	−40°C to +85°C	100-Lead Lead Frame Chip Scale Package [LFCSP_VQ]	CP-100-1
ADV3226-EVALZ		Evaluation Board	
ADV3227-EVALZ		Evaluation Board	

¹ Z = RoHS Compliant Part.