Order this document
by MRF641/D

查询"MRF641"供应商

The RF Line

NPN Silicon RF Power Transistor

MRF641

. . . designed for 12.5 Volt UHF large–signal amplifier applications in industrial and commercial FM equipment operating to 512 MHz.

- Specified 12.5 Volt, 470 MHz Characteristics —
  Output Power = 15 Watts
  Minimum Gain = 7.8 dB
  Efficiency = 55%
- Characterized with Series Equivalent Large–Signal Impedance Parameters
- Built–In Matching Network for Broadband Operation
- Tested for Load Mismatch Stress at all Phase Angles with 20:1 VSWR @ 16–Volt High Line and Overdrive
- Circuit board photomaster available upon request by contacting RF Tactical Marketing in Phoenix, AZ.

15 W, 470 MHz
CONTROLLED Q
RF POWER
TRANSISTOR
NPN SILICON



CASE 316–01, STYLE 1

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector–Emitter Voltage	V_{CEO}	16	Vdc
Collector–Base Voltage	V_{CBO}	36	Vdc
Emitter–Base Voltage	V_{EBO}	4.0	Vdc
Collector Current — Continuous	I_C	3.0	Adc
Total Device Dissipation @ T_C = 25°C Derate above 25°C	P_D	43.7 0.25	Watts W/°C
Storage Temperature Range	T_{stg}	–65 to +150	°C

THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Thermal Resistance, Junction to Case	$R_{\theta JC}$	4.0	°C/W

ELECTRICAL CHARACTERISTICS (T_C = 25°C unless otherwise noted.)

Characteristic	Symbol	Min	Typ	Max	Unit
OFF CHARACTERISTICS					
Collector–Emitter Breakdown Voltage (I_C = 20 mAdc, I_B = 0)	$V_{(BR)CEO}$	16	—	—	Vdc
Collector–Emitter Breakdown Voltage (I_C = 20 mAdc, V_{BE} = 0)	$V_{(BR)CES}$	36	—	—	Vdc
Emitter–Base Breakdown Voltage (I_E = 5.0 mAdc, I_C = 0)	$V_{(BR)EBO}$	4.0	—	—	Vdc
Collector Cutoff Current (V_{CE} = 15 Vdc, V_{BE} = 0, T_C = 25°C)	I_{CES}	—	—	5.0	mAdc

(continued)

© Motorola, Inc. 1994

ELECTRICAL CHARACTERISTICS — continued (T_C = 25°C unless otherwise noted.)

查询"MRF641"供应商

Characteristic	Symbol	Min	Typ	Max	Unit
ON CHARACTERISTICS					
DC Current Gain (I_C = 1.0 Adc, V_{CE} = 5.0 Vdc)	h_{FE}	30	70	150	—
DYNAMIC CHARACTERISTICS					
Output Capacitance (V_{CB} = 12.5 Vdc, I_E = 0, f = 1.0 MHz)	C_{ob}	—	40	60	pF
FUNCTIONAL TESTS					
Common–Emitter Amplifier Power Gain (V_{CC} = 12.5 Vdc, P_{out} = 15 W, f = 470 MHz)	G_{pe}	7.8	8.5	—	dB
Collector Efficiency (V_{CC} = 12.5 Vdc, P_{out} = 15 W, f = 470 MHz)	η	55	60	—	%
Output Mismatch Stress (V_{CC} = 16 Vdc, P_{in} = 3.0 W, f = 470 MHz, VSWR = 20:1, All Phase Angles)	ψ	No Degradation in Output Power			



PARTS

Z1 — 1.225″ x 0.187″ Microstrip
Z2 — 0.884″ x 0.187″ Microstrip
Z3 — Capacitor Block (Base)
Z4 — Collector Block
Z5 — 1.1″ x 0.187″ Microstrip
Z6 — 0.433″ x 0.187″ Microstrip
Z7 — 0.4″ x 0.187″ Microstrip

Dotted Area — Capacitor Assembly

C1, C2 — 0.8–10 pF Johanson
C3, C4 — 24 pF Chip Caps 100 mils ATC
C5, C6 — 22 pF Chip Caps 100 mils ATC
C12 — 220 pF Chip Cap 100 mils ATC
C7, C11 — 1.0 µF Tantalum 35 Vdc
C9, C10 — 680 pF Feedthrough Allen–Bradley
C13 — 200 pF UNELCO
C8 — 0.1 µF, 50 V Erie Red Cap
RFC1 — VK 200 — 104B Ferrite Choke
L1 — 4 Turns 0.2″ Dia. #16 AWG
L2 — 9 Turns 0.15″ Dia. #16 AWG

Bead — Ferroxcube 56–590–65–35EB

NOTES

*C5, C6, are mounted as close to the capacitor assembly as possible.
‡‡C3, C4 are mounted in the capacitor assembly.
Board — 62.5 mil Glass Teflon, ε_r = 2.55.

Figure 1. Test Circuit Schematic

查询"MRF641"供应商



Figure 2. Power Output versus Power Input



Figure 3. Power Output versus Frequency



Figure 4. Power Output versus Supply Voltage



Figure 5. Power Saturation Profile



Z_{OL}* = Conjugate of the load impedance into which the device output operates at a given power, η, and frequency.

Figure 6. Series Equivalent Input–Output Impedance

PACKAGE DIMENSIONS

查询"MRF641"供应商



NOTES:
1. FLANGE IS ISOLATED IN ALL STYLES.

DIM	INCHES MIN	INCHES MAX	MILLIMETERS MIN	MILLIMETERS MAX
A	24.38	25.14	0.960	0.990
B	12.45	12.95	0.490	0.510
C	5.97	7.62	0.235	0.300
D	5.33	5.58	0.210	0.220
E	2.16	3.04	0.085	0.120
F	5.08	5.33	0.200	0.210
H	18.29	18.54	0.720	0.730
J	0.10	0.15	0.004	0.006
K	10.29	11.17	0.405	0.440
L	3.81	4.06	0.150	0.160
N	3.81	4.31	0.150	0.170
Q	2.92	3.30	0.115	0.130
R	3.05	3.30	0.120	0.130
U	11.94	12.57	0.470	0.495

STYLE 1:
PIN 1. EMITTER
2. COLLECTOR
3. EMITTER
4. BASE

CASE 316–01
ISSUE D

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. “Typical” parameters can and do vary in different applications. All operating parameters, including “Typicals” must be validated for each customer application by customer’s technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and Ⓜ are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

Literature Distribution Centers:
USA: Motorola Literature Distribution; P.O. Box 20912; Phoenix, Arizona 85036.
EUROPE: Motorola Ltd.; European Literature Centre; 88 Tanners Drive, Blakelands, Milton Keynes, MK14 5BP, England.
JAPAN: Nippon Motorola Ltd.; 4-32-1, Nishi-Gotanda, Shinagawa-ku, Tokyo 141, Japan.
ASIA PACIFIC: Motorola Semiconductors H.K. Ltd.; Silicon Harbour Center, No. 2 Dai King Street, Tai Po Industrial Estate, Tai Po, N.T., Hong Kong.