

Pulse-Width Modulator Control System

GENERAL DESCRIPTION

The XR-2230 is a high-performance monolithic pulse width modulator control system. It contains all the necessary control blocks for designing switch mode power supplies, and other power control systems. Included in the 18-Pin dual-in-line package are two error amplifiers, a sawtooth generator, and the necessary control logic to drive two open-collector power transistors. Also included are protective features, such as adjustable dead-time control, thermal shutdown, soft-start control, and double-pulse protection circuitry.

The device provides two open-collector output transistors which are driven 180° out-of-phase, and are capable of sinking 30 mA. These outputs can be used to implement single-ended or push-pull switching regulation of either polarity in transformerless or transformer-coupled converters.

FEATURES

- Thermal Shutdown
- Adjustable Dead-time
- Dual Open-Collector
 - 30 mA Output Transistors
- Double-Pulse Protection Circuit
- Soft-Start Control
- High-Speed Remote Shut-Down Input
- Two High-Performance Error Amplifiers
 - with $\pm 5V$ Input Common-Mode Range


APPLICATIONS

- Switching Regulators
- Motor-Speed Controllers
- Pulse-Width Modulated Control Systems

ABSOLUTE MAXIMUM RATINGS

Positive Supply Voltage	-0.5 to +18V
Negative Supply Voltage	+0.5 to -18V
Input Voltage	-18 to +18V
Output Voltage	-0.5 to +18V
Power Dissipation ($T_A \leq 25^\circ C$)	400 mW
Operating Temperature	-10°C to +85°C
Storage Temperature	-55°C to +125°C

FUNCTIONAL BLOCK DIAGRAM



ORDERING INFORMATION

Part Number	Package	Operating Temperature
XR-2230CP	Plastic	0°C to +70°C

SYSTEM DESCRIPTION

The XR-2230 PWM circuit contains two high-performance error amplifiers with wide input common-mode range, and large voltage gains. Typically, one amplifier (Pins 16, 17, 18) is used for current sensing and the other (Pins 1, 2, 3) is used as an error amplifier to sense the output voltage. The XR-2230 requires a split supply between ± 8 volts and ± 15 volts, however, it can be operated from a single supply with proper external biasing on the ground pin and input pins of the error amplifiers. The output drivers capable of sinking 30 mA at a saturation voltage of about 0.3V can be used in a push-pull configuration, or can be paralleled for a single-ended configuration with a duty cycle between 0% to over 90%.

The XR-2230 features a self-protecting thermal-shutdown circuitry which turns off the output drivers when the junction temperature exceeds 130°C. The on-board regulator stabilizes the oscillator frequency to 0.1%/V for reliable performance.

XR-2230

ELECTRICAL CHARACTERISTICS

Test Conditions: $T_A = 25^\circ\text{C}$, $V_{CC} = +12\text{V}$, $V_{EE} = -12\text{V}$, $f_{OSC} = 20\text{ kHz}$, unless otherwise specified.

SYMBOL	PARAMETERS	MIN	TYP	MAX	UNIT	CONDITIONS
SUPPLY SECTION						
V _{CC}	Positive Supply Voltage	+10			V	
V _{EE}	Negative Supply Voltage			-10	V	
I _{CC}	Positive Supply Current	7.0	11.0	15.0	mA	
I _{EE}	Negative Supply Current	-2.0	-6.0	-2.0	mA	
OSCILLATOR SECTION						
f _{OSC}	Frequency Range	10		100	kHz	R _T = 30 kΩ, C _T = 4700 pF V _{CC} = +10V ≈ +15V V _{CC} = +18V, V _{EE} = -8V
	Initial Accuracy			15	%	
	Supply Voltage Stability		0.1		%/V	
	Low Supply Voltage	-20		+20	%	
	Temperature Stability		0.01		%/°C	
V _{OSC}	Sawtooth Peak Voltage	3.0	3.5	4.0	V	f _{OSC} = 20 kHz
δ	Duty Cycle Range	10		90	%	
VOLTAGE ERROR AMPLIFIER						
V _{OS}	Input Offset Voltage		2	10	mV	A _{VCL} = 40 dB V _{ICM} = ±4.5V
I _{BIAS}	Input Bias Current		- .5	-30	μA	
A _{VO}	Open-Loop Gain	60	90		dB	
f _{-3dB}	Closed-Loop Bandwidth		25		kHz	
CMMR	Common-Mode Rejection Ratio	60			dB	
V _{OM}	Output Voltage Swing	±5			V	R _L = 10 kΩ V _{CC} = +8V, V _{EE} = -8V A _{VCL} = 14 dB, R _F = 10 kΩ
SR	Slew Rate	2	4		V/μs	
	Input Voltage Range		±5		V	
CURRENT ERROR AMPLIFIER						
V _{OS}	Input Offset Voltage		4	20	mV	A _{VCL} = 40 dB V _{ICM} = ±4.5V
I _{BIAS}	Input Bias Current		-1.0	-60	μA	
A _{VO}	Open-Loop Gain	60	90		dB	
f _{-3dB}	Closed-Loop Bandwidth		25		kHz	
CMRR	Common-Mode Rejection Ratio	60	90		dB	
V _{OM}	Output Voltage Swing	±5 ±4			V V	R _L = 10 kΩ V _{CC} = +8V, V _{EE} = -8V A _{ACL} = 14 dB, R _F = 10 kΩ
SR	Slew Rate	4	8		V/μs	
	Input Voltage Range		±5		V	
MODULATOR SECTION						
t _d	Set Input Open Voltage	3.1	3.6	4.1	V	V _{CC} = +8V, V _{EE} = -8V
	(Pin 15)	2.8	3.3	4.3	V	
	Modin Input Open Voltage	3.1	3.6	4.1	V	
	(Pin 11)	2.8	3.3	4.3	V	
t _f	Inhibit Input Current (Pin 13)	-50	-10		μA	V _{CC} = +8V, V _{EE} = -8V
	Inhibit Propagation Delay		60		ns	
	Out1, Out2, Output Voltage			0.3	V	
	(Pins 9 and 10)			0.4	V	
	Low Supply Voltage			0.3	V	I _O = 30 mA, T _A = 25°C T _A = -10 ≈ +85°C I _O = 27 mA, T _A = 25°C
	Out1, Out2 Fall Time		30		ns	
	Modout Output Voltage			0.3	V	
	(Pin 12)			0.4	V	
	Under Low Supply Voltage			0.3	V	
	Oscillator Output Voltage			0.4	V	
(Pin 14)			0.6	V	I _O = 16 mA, T _A = 25°C T _A = -10 ≈ +85°C I _O = 24 mA, T _A = 25°C I _O = 3 mA, T _A = 25°C T _A = -10 ≈ +85°C	
Thermal Shutdown Temp.		130		°C		




Figure 1. Equivalent Schematic Diagram

PRINCIPLES OF OPERATION

The heart of the XR-2230 is the sawtooth generator. As seen in Figure 1, this sawtooth drives one input of each of the three system comparators. Comparators one and two have their other inputs tied to the outputs of the error amplifiers. These comparators will now produce, at their outputs, square waves which will have a duty cycle proportional to the voltage at the inputs to the error amplifiers, or pulse width information. The pulse width information is fed into the NOR gate and used to provide the reset information to the pulse-width modulation flip-flop (PWM). The PWM flip-flop information is fed in to the NAND gate with the external shutdown and PWM flip-flop set input. The information from the NAND gate drives an open-collector transistor to provide the pulse-width modulation output, Pin 12. The PWM output will be a square wave with a frequency set by the sawtooth generator, and a duty cycle equal to either comparator, one or two, whichever is shorter. If the external shutdown, Pin 13 is driven low, the PWM output will remain low or go to zero duty cycle. The set input of the PWM flip-flop, Pin 15, is normally connected to the buffered sawtooth generator output, Pin 14, so that a reset pulse is provided every cycle. Each output transistor is driven by a three input NAND gate. These inputs consist of:

1. Pulse width information from the PWM input, Pin 11, which is used to control the off time of the output transistors. The PWM input is normally tied to the

PWM output so that the output transistor's off time is a function of the error amplifier's input voltage.

2. Pulse-steering information from flip-flop two, which will determine which output transistor receives the PWM input signal. Flip-flop two will toggle once every cycle of the sawtooth generator's output, which will make the output transistor's toggle frequency one-half that of the sawtooth generator's.
3. Information from dead-time and thermal shutdown circuitry. The dead-time is an externally adjustable time between one output transistor turning off and the other turning on. This is used to protect external circuitry. This dead-time is controlled by an external voltage applied to Pin 6, which is internally compared with the sawtooth waveform. The thermal shutdown circuitry will drive the input to the NAND gate low, if the junction temperature exceeds 130°C. This will make both outputs low.

The circuit control blocks and functions operate as follows:

Error Amplifiers—These are high-gain op amps which are used to sense output conditions, voltage and current, and provide a dc voltage to comparators one and two. This will in turn adjust the PWM output duty cycle and ultimately that of the output transistors to correct for errors in the output voltage or overcurrent conditions. The amplifier's outputs are provided for tailoring the closed-

XR-2230

loop gain or frequency response of the system. Figure 2 shows the relationship between output duty cycle, Pins 11 and 12 connected, and the voltage at Pins 1 or 18. Amplifier two is approximately twice as fast as Amplifier one, and should, therefore, be used to sense output current.

External Shutdown, Pin 13—A low level signal applied to this pin will turn both outputs on. If not used, this input should be left open-circuited. The impedance at this node is approximately 1 MΩ.

Oscillator Output, Pin 14—This is an open-collector output which will be a square wave with a frequency set by the sawtooth generator. The duty cycle of this output will vary from 10 to 90%, and is a function of the dead-time setting. This pin is normally connected to Pin 15, set to provide reset pulses for the PWM flip-flop.

Set, Pin 15—This is the set input for the PWM flip-flop. A low-going signal at this pin will cause the flip-flop to be reset. The impedance at this pin is approximately 7.5 kΩ. This pin is normally connected to the oscillator output, Pin 14.

PWM Out, Pin 12—This is an open-collector output which provides a square wave with a duty cycle determined by the error amplifiers. This output is normally connected to PWM IN, Pin 11.

PWM In, Pin 11—This is the input which controls the duty cycle of the output transistors. A low level on this pin will drive both output transistors on. The impedance into this pin is approximately 7.4 kΩ.

Output Transistors, Pins 9 and 10—These pins provide the open-collector output transistors which are capable of sinking 30 mA, typically. They are alternately turned off, 180° out-of-phase, at a rate equal to one-half the frequency of the oscillator.




Figure 2. Modulation Duty Cycle vs Error Voltage

FADJ, Pin 7—A resistor, R_{ext} to $+V_{CC}$, and a capacitor, C_{ext} , to ground from this pin, set the frequency of the sawtooth and oscillator output, by the relationship:

$$F_{OSC} = \frac{2.68}{R_{ext} \times C_{ext}}$$

The sawtooth waveform a signal varying from zero volts to +5V, will be present at Pin 7. Normal values of R_{ext} will range from 1 kΩ to 100 kΩ. Figure 3 shows the oscillator period as a function of various R_{ext} and C_{ext} values.

The dead-time (minimum time from one output turning on to the other turning off) is controlled by the voltage applied to Pin 6.

Dead-time Control, Pin 6—Figure 4 shows output deadtime as a function of $V_{PIN 6}$. The maximum duty cycle of each output is also controlled by the dead-time, and may be determined by the following expression:

$$\text{Duty Cycle Max (\%)} = \left(1 - \frac{.35}{V_{PIN 6}}\right) \times 50\%$$

$$V_{PIN 6} < 3.5V$$

The impedance into this pin is approximately 10 kΩ.

APPLICATIONS INFORMATION

The soft-start function may be implemented as shown in Figure 7. This configuration will reduce the output duty cycle to zero, and gradually increase to its normal operating point, whenever power is applied to the circuit, or after an external shutdown command has been given. This is used to keep the magnetics in the circuit from saturating.




Figure 3. Oscillation Period vs R_{EXT} and C_{EXT}

The time for the duty cycle to start will be approximately equal to $R_1 \times C_1$.

A typical step-down switching regulator configuration is shown in Figure 8. Only one output transistor is used, so that the maximum duty cycle will be limited to 45%. If a larger duty cycle range is needed, the two outputs may be externally NOR'd as shown in Figure 9. This configuration will allow up to 90% duty cycles.

Figure 10 shows a detailed timing diagram of circuit operation.




Figure 4. Dead Time vs Dead Time Adjustment Voltage




Figure 5. Supply Current vs Supply Voltage




Figure 6. Output Saturation Voltage vs Load Current

RECOMMENDED OPERATING CONDITIONS

SYMBOL	PARAMETER	CONDITION	UNIT
V _{CC}	Positive Supply Voltage	+ 10 ~ + 15	V
V _{EE}	Negative Supply Voltage	- 10 ~ - 15	V
R _R	Minimum Feedback Resistance	10	kΩ
A _V	Minimum Voltage Gain	14 5	dB V/V

XR-2230




Figure 7. Soft Start Connection

5




Figure 8. +10V Step-Down Regulator




Figure 9. Outputs Nor'd for up to 90% Duty Cycle's




Figure 10. Timing Waveform Diagram

3422618 EXAR CORP

EXAR

91D 04225

D7-75-45-05

XR-1488/1489A



Quad Line Driver/Receiver

GENERAL DESCRIPTION

The XR-1488 is a monolithic quad line driver designed to interface data terminal equipment with data communications equipment in conformance with the specifications of EIA Standard No. RS232C. This extremely versatile integrated circuit can be used to perform a wide range of applications. Features such as output current limiting, independent positive and negative power supply driving elements, and compatibility with all DTL and TTL logic families greatly enhance the versatility of the circuit.

The XR-1489A is a monolithic quad line receiver designed to interface data terminal equipment with data communications equipment. The XR-1489A quad receiver along with its companion circuit, the XR-1488 quad driver, provide a complete interface system between DTL or TTL logic levels and the RS232C defined voltage and impedance levels.

FUNCTIONAL BLOCK DIAGRAMS



ABSOLUTE MAXIMUM RATINGS

Power Supply	
XR-1488	± 15 Vdc
XR-1489A	+ 10 Vdc
Power Dissipation	
Ceramic Package	1000 mW
Derate above +25°C	6.7 mW/°C
Plastic Package	650 mW/°C
Derate above +25°C	5 mW/°C

ORDERING INFORMATION

Part Number	Package	Operating Temperature
XR-1488N	Ceramic	0°C to +70°C
XR-1488P	Plastic	0°C to +70°C
XR-1489AN	Ceramic	0°C to +70°C
XR-1489AP	Plastic	0°C to +70°C

SYSTEM DESCRIPTION


The XR-1488 and XR-1489A are a matched set of quad line drivers and line receivers designed for interfacing between TTL/DTL and RS232C data communication lines.

The XR-1488 contains four independent split supply line drivers, each with a ± 10 mA current limited output. For RS232C applications, the slew rate can be reduced to the 30 V/ μ S limit by shunting the output to ground with a 410 pF capacitor. The XR-1489A contains four independent line receivers, designed for interfacing RS232C to TTL/DTL. Each receiver features independently programmable switching thresholds with hysteresis, and input protection to ± 30 V. The output can typically source 3 mA and sink 20 mA.

3422618 EXAR CORP
XR-494

91D 04470 D

T-58-11-31





91D 04475

DT-58-11-03

XR-1468/1568

Dual-Polarity Tracking Voltage Regulator

GENERAL DESCRIPTION

The XR-1468/1568 is a dual polarity tracking voltage regulator, internally trimmed for symmetrical positive and negative 15V outputs. Current output capability is 100 mA, and may be increased by adding external pass transistors. The device is intended for local "on-card" regulation, which eliminates the distribution problems associated with single point regulation.

The XR-1468CN and XR-1568N are guaranteed over the 0°C to 70°C commercial temperature range. The XR-1568M is rated over the full military temperature range of -55°C to +125°C.

FEATURES

- Internally Set for $\pm 15V$ Outputs
- ± 100 mA Peak Output Current
- Output Voltages Balanced Within 1% (XR-1568)
- 0.06% Line and Load Regulation
- Low Stand-By Current
- Output Externally Adjustable from ± 8 to ± 20 Volts
- Externally Adjustable Current Limiting
- Remote Sensing


APPLICATIONS

- Main Regulation in Small Instruments
- On-Card Regulation in Analog and Digital Systems
- Point-of-Load Precision Regulation

ABSOLUTE MAXIMUM RATINGS

Power Supply	± 30 Volts
Minimum Short-Circuit Resistance	4.0 Ohms
Load Current, Peak	± 100 mA
Power Dissipation	
Ceramic (N) Package	1.0 Watt
Derate Above +25°C	6.7 mW/°C
Operating Temperature	
XR-1568M	-55°C to +125°C
XR-1568/XR-1468C	0°C to +70°C
Storage Temperature	-65°C to +150°C

FUNCTIONAL BLOCK DIAGRAM



5

ORDERING INFORMATION

Part Number	Temperature	Output Offset	Package
XR-1568M	-55°C to +125°C	± 150 mV max	Ceramic
XR-1568N	0°C to +70°C	± 150 mV max	Ceramic
XR-1468CN	0°C to +70°C	± 300 mV max	Ceramic

SYSTEM DESCRIPTION

The XR-1468/1568 is a dual polarity tracking voltage regulator combining two separate regulators with a common reference element in a single monolithic circuit, thus providing a very close balance between the positive and negative output voltages. Outputs are internally set to ± 15 Volts but can be externally adjusted between ± 8.0 to ± 20 Volts with a single control. The circuit features ± 100 mA output current, with externally adjustable current limiting, and provision for remote voltage sensing.