

- Advanced, Integrated Speech Synthesizer for High-Quality Sound.
- Operates up to 12.32 MHz (Performs up to 12 MIPS)
- Single Chip Solution for up to 24 Minutes of Speech (Using 1.57 Mb of Onboard Program + Data ROM)
- Supports High-Quality Synthesis Algorithms Such as MELP, CELP, LPC, ADPCM, and Polyphonic Music
- Simultaneous Speech Plus Music Capabilities
- Very Low-Power Operation, Ideal for Hand-Held Devices.
- Low-Voltage Operation, Sustainable by Three Batteries
- Reduced Power Stand-By Modes, Less Than 10  $\mu$ A in Deep-Sleep Mode
- 640-Word RAM
- 32 I/O Pins Consisting of
  - 24 General Purpose Bit Configurable I/O
  - 8 Inputs With Programmable Pullup Resistor And a Dedicated Interrupt (Key-Scan)
- Direct Speaker Driver, 32  $\Omega$  (PDM)
- One-Bit Comparator With Edge-Detection Interrupt Service
- Resistor-Trimmed Oscillator or 32.768 kHz Crystal Reference Oscillator
- Serial Scan Port for In-Circuit Emulation and Diagnostics
- The MSP50C601 Is Sold in Die Form or 100-Pin PJM Package.
- An Emulator Device Is Available in a Ceramic Package for Development

### description

The MSP50C601 is a low-cost, mixed-signal processor that combines a speech synthesizer, general-purpose I/O, onboard ROM, and direct speaker drive in a single package. The computational unit utilizes a powerful new DSP which gives the MSP50C601 unprecedented speed and computational flexibility compared with previous devices of its type. The MSP50C601 supports a variety of speech and audio coding algorithms, providing a range of options for speech duration and sound quality.

The device consists of a micro-DSP core, embedded program, and data memory, and a self-contained clock generation system. General-purpose periphery is comprised of 32 bits of partially configurable I/O.

The core processor is a general-purpose 16-bit microcontroller with DSP capability. The basic core block includes computational unit (CU), data address unit, program address unit, two timers, eight level interrupt processor, and several system and control registers. The core processor gives the MSP50C601 break-point capability in emulation.

The processor is Harvard type for efficient DSP algorithm execution. It requires separate program and data memory blocks to permit simultaneous access. The ROM has a protection scheme to prevent third-party pirating. It is configured in 32K 17-bit words.

The total ROM space is divided into three areas: 1) The lower 2K words are reserved by Texas Instruments for a built-in self-test 2) The upper 30K words are for user program/data 3) An additional 1 Mb data ROM provides for up to 24 minutes of speech.

The data memory is internal static RAM. The RAM is configured in 640 17-bit words. All memories are designed to consume minimum power at a given system clock and algorithm acquisition frequency.

 Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

# MSP50C601 MIXED-SIGNAL PROCESSOR

SPSS029A – SEPTEMBER 2000 – REVISED FEBRUARY 2001


## description (continued)

A flexible clock generation system enables the software to control the clock over a wide frequency range. The implementation uses a phase-locked loop (PLL) circuit that drives the processor clock at a selectable frequency between the minimum and maximum achievable. Selectable frequencies for the processor clock are spaced apart in 65.536 kHz steps. The PLL clock-reference is also selectable; either a resistor-trimmed oscillator or a crystal-referenced oscillator may be used. Internal and external clock sources are controlled separately to provide different levels of power management.

The periphery consists of three 8-bit wide general-purpose I/O ports and one 8-bit wide dedicated input port. The bidirectional I/O can be configured under software control as either high-impedance inputs or as totem-pole outputs. They are controlled via addressable I/O registers. The input-only port has a programmable pullup option (70-k $\Omega$  minimum resistance) and a dedicated service interrupt. These features make the input port especially useful as a key-scan interface.

A simple one-bit comparator is also included in the periphery. The comparator is enabled by a control register, and its pin access is shared with two pins in one of the general-purpose I/O ports. Rounding out the MSP50C601 periphery is a built-in pulse-density-modulated DAC (digital-to-analog converter) with direct speaker-drive capability. The functional block diagram gives an overview of the MSP50C601 functionality.

## functional block diagram



**pin assignments**

| PJM PACKAGE<br>(TOP VIEW) |                  |
|---------------------------|------------------|
|                           | VSS3             |
| 1                         | 100              |
| 2                         | 99               |
| 3                         | PD0              |
| 4                         | 98               |
| DACM                      | PD1              |
| V <sub>DD3</sub>          | 97               |
| DACP                      | PD2              |
| V <sub>DD</sub>           | 96               |
| PF7                       | PD3              |
| PF6                       | 95               |
| PF5                       | PD4              |
| PF4                       | 94               |
| PF3                       | PD5              |
| PF2                       | 93               |
| PF1                       | PD6              |
| PF0                       | 92               |
| V <sub>SS</sub>           | PD7              |
| NC                        | 91               |
| NC                        | V <sub>DD2</sub> |
| NC                        | 90               |
| NC                        | 89               |
| NC                        | 88               |
| NC                        | 87               |
| NC                        | 86               |
| NC                        | 85               |
| NC                        | 84               |
| NC                        | 83               |
| NC                        | 82               |
| NC                        | 81               |
| 80                        | NC               |
| 79                        | NC               |
| 78                        | NC               |
| 77                        | NC               |
| 76                        | NC               |
| 75                        | NC               |
| 74                        | NC               |
| 73                        | NC               |
| 72                        | NC               |
| 71                        | NC               |
| 70                        | NC               |
| 69                        | NC               |
| 68                        | NC               |
| 67                        | NC               |
| 66                        | NC               |
| 65                        | NC               |
| 64                        | NC               |
| 63                        | NC               |
| 62                        | NC               |
| 61                        | NC               |
| 60                        | NC               |
| 59                        | NC               |
| 58                        | NC               |
| 57                        | NC               |
| 56                        | NC               |
| 55                        | NC               |
| 54                        | NC               |
| 53                        | NC               |
| 52                        | NC               |
| 51                        | NC               |
| 31                        | V <sub>DD</sub>  |
| 32                        | V <sub>DD1</sub> |
| 33                        | SCANOUT          |
| 34                        | TEST             |
| 35                        | SYNC             |
| 36                        | SYNCLK           |
| 37                        | SCANIN           |
| 38                        | RESET            |
| 39                        | PE7              |
| 40                        | PE6              |
| 41                        | PE5              |
| 42                        | PE4              |
| 43                        | PE3              |
| 44                        | PE2              |
| 45                        | PE1              |
| 46                        | PE0              |
| 47                        | PLL              |
| 48                        | OSCIN            |
| 49                        | OSCOUT           |
| 50                        | V <sub>SS</sub>  |

NC – No internal connection

# MSP50C601

## MIXED-SIGNAL PROCESSOR

SPSS029A – SEPTEMBER 2000 – REVISED FEBRUARY 2001

### Terminal Functions

| NAME  | PIN NO.              | PAD NO.                | I/O | DESCRIPTION                         |
|---|----------------------|------------------------|-----|-------------------------------------|
| <b>Input/Output Ports</b>   |                      |                        |     |                                     |
| PC0 – PC7   | 89 – 82              | 8 – 1                  | I/O | Port C general-purpose I/O (1 Byte) |
| PD0 – PD7   | 99 – 92              | 18 – 11                | I/O | Port D general-purpose I/O (1 Byte) |
| PE0 – PE7   | 46 – 39              | 48 – 41                | I/O | Port E general-purpose I/O (1 Byte) |
| PF0 – PF7   | 16 – 9               | 31 – 24                | I   | Port F key-scan input (1 Byte)      |
| Pins PD <sub>4</sub> and PD <sub>5</sub> may be dedicated to the comparator function, if the comparator enable bit is set.<br>Refer to Section 3.3, <i>Comparator</i> , for details.                |                      |                        |     |                                     |
| <b>Scan Port Control Signals</b>  |                      |                        |     |                                     |
| SCANIN  | 37                   | 39                     | I   | Scan port data input                |
| SCANOUT   | 33                   | 35                     | O   | Scan port data output               |
| SCANCLK   | 36                   | 38                     | I   | Scan port clock                     |
| SYNC  | 35                   | 37                     | I   | Scan port synchronization           |
| TEST  | 34                   | 36                     | I   | C601: test modes                    |
| The scan port pins must be bonded out on any MSP50C601 production board.<br>Consult the <i>Important Note regarding Scan Port Bond Out</i> , see Chapter 7 in the MSP50C614 User's Guide (SPSU014). |                      |                        |     |                                     |
| <b>Reference Oscillator Signals</b>   |                      |                        |     |                                     |
| OSCOUT  | 49                   | 51                     | O   | Resistor/crystal reference out      |
| OSCIN   | 48                   | 50                     | I   | Resistor/crystal reference in       |
| PLL   | 47                   | 49                     | O   | Phase-lock-loop filter              |
| <b>Digital-to-Analog Sound Output (DAC)</b>   |                      |                        |     |                                     |
| DACP  | 7                    | 22                     | O   | Digital-to-analog plus output (+)   |
| DACM  | 5                    | 20                     | O   | Digital-to-analog minus output (-)  |
| <b>Initialization</b>   |                      |                        |     |                                     |
| RESET   | 38                   | 40                     | I   | Initialization                      |
| <b>Power Signals</b>  |                      |                        |     |                                     |
| V <sub>SS</sub>   | 17, 50, 90,<br>100†  | 32, 52, 9,<br>19†      |     | Ground                              |
| V <sub>DD</sub>   | 6†, 8, 31,<br>32, 91 | 21†, 23,<br>33, 34, 10 |     | Processor power (+)                 |

† The V<sub>SS</sub> and V<sub>DD</sub> connections service the DAC circuitry. Their pins tend to sustain a higher current draw. A dedicated decoupling capacitor across these pins is therefore required.

**absolute maximum ratings over operating free-air temperature range (unless otherwise noted)<sup>†</sup>**

|  |                          |
|--|--------------------------|
| Supply voltage, $V_{DD}$ (see Note 1) .....    | –0.3 to 7 V              |
| Supply current, $I_{DD}$ (see Note 2) .....    | 35 mA                    |
| Input voltage range, $V_I$ (see Note 1) .....  | –0.3 to $V_{DD} + 0.3$ V |
| Output voltage range, $V_O$ (see Note 1) ..... | –0.3 to $V_{DD} + 0.3$ V |
| Storage temperature range, $T_A$ .....         | –30°C to 125°C           |

<sup>†</sup> Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTES: 1. Unless otherwise noted, all voltages are measured with respect to  $V_{SS}$ .

2. The total supply current includes the current out of all the I/O pins as well as the operating current of the device.


**recommended operating conditions**

|   |                      | MIN | MAX    | UNIT     |
|---|----------------------|-----|--------|----------|
| Supply voltage (with respect to $V_{SS}$ ), $V_{DD}$      |                      | 3   | 5.2    | V        |
| CPU clock rate (as programmed), $f_{(CPU)}$               |                      | 64  | 12,320 | kHz      |
| Load resistance between $DAC_P$ and $DAC_M$ , $R_{(DAC)}$ |                      | 32  |        | $\Omega$ |
| Operating free-air temperature, $T_A$                     | Device functionality | 0   | 70     | °C       |


**timing requirements**

|                 |  | MIN | MAX | UNIT   |
|-----------------|--|-----|-----|--------|
| $t_{(RESET)}$   | Reset low pulse width, while $V_{DD}$ is within specified limits                                 | 100 |     | ns     |
| $t_1^{(WIDTH)}$ | Pulse width required prior to a negative transition at pin...PD3, PD5, or PF0...PF7 <sup>‡</sup> | 2   |     | 1/FCPU |
| $t_2^{(WIDTH)}$ | Pulse width required prior to a positive transition at pin...PD2 or PD4 <sup>†</sup>             | 2   |     | 1/FCPU |

<sup>‡</sup> While these pins are being used as interrupt inputs.



**Figure 1. Initialization Timing Diagram**



**Figure 2. MSP50C601 External Interrupt Pin Pulse Width Requirements  $t_1^{(WIDTH)}$  and  $t_2^{(WIDTH)}$**

# MSP50C601

## MIXED-SIGNAL PROCESSOR

SPSS029A – SEPTEMBER 2000 – REVISED FEBRUARY 2001

### dc electrical characteristics, $T_A = 0^\circ\text{C} - 70^\circ\text{C}$

| PARAMETER                      |   | TEST CONDITIONS   |                          | MIN  | TYP <sup>§</sup> | MAX         | UNIT             |
|--------------------------------|---|---|--------------------------|------|------------------|-------------|------------------|
| RESET                          | Threshold changes                             | $V_{DD} = 3\text{ V}$   | Positive going threshold | 2.4  |                  |             | V                |
|                                |   |   | Negative going threshold | 1.8  |                  |             |                  |
|                                |   |   | Hysteresis               | 0.6  |                  |             |                  |
|                                |   | $V_{DD} = 5.2\text{ V}$   | Positive going threshold | 3.3  |                  |             | V                |
|                                |   |   | Negative going threshold | 2.9  |                  |             |                  |
|                                |   |   | Hysteresis               | 0.4  |                  |             |                  |
| $V_{IH}$                       | High-level input voltage                      | $V_{DD} = 3\text{ V}$   |                          | 2    | 3                |             | V                |
|                                |   | $V_{DD} = 4.5\text{ V}$   |                          | 3    | 4.5              |             |                  |
|                                |   | $V_{DD} = 5.2\text{ V}$   |                          | 3.5  | 5.2              |             |                  |
| $V_{IL}$                       | Low-level input voltage                       | $V_{DD} = 3\text{ V}$   |                          | 0    | 1                |             | V                |
|                                |   | $V_{DD} = 4.5\text{ V}$   |                          | 0    | 1.5              |             |                  |
|                                |   | $V_{DD} = 5.2\text{ V}$   |                          | 0    | 1.7              |             |                  |
| $I_{OH}^{\dagger}$             | High-level output current per pin of I/O port | $V_{DD} = 4.5\text{ V}$   | $V_{OH} = 4\text{ V}$    |      |                  | -2          | mA               |
| $I_{OL}^{\dagger}$             | Low-level output current per pin of I/O port  |   | $V_{OL} = 0.5\text{ V}$  |      |                  | 5           | mA               |
| $I_{OH}(\text{DAC})$           | High-level output DAC current                 |   | $V_{OH} = 4\text{ V}$    |      |                  | -10         | mA               |
| $I_{OL}(\text{DAC})$           | Low-level output DAC current                  |   | $V_{OL} = 0.5\text{ V}$  |      |                  | 20          | mA               |
| $I_{Ikg}$                      | Input leakage current                         | Excludes $\text{OSC}_{IN}$  |                          |      |                  | 1           | $\mu\text{A}$    |
| $I_{(\text{STANDBY})}$         | Standby current                               | RESET is low  |                          |      | 0.05             | 10          | $\mu\text{A}$    |
| $I_{DD}^{\dagger}$             | Operating current                             | $V_{DD} = 4.5\text{ V}$ , $\text{FCLOCK} = 12.32\text{ MHz}$  |                          |      | 15               |             | mA               |
| $I_{(\text{SLEEP-deep})}$      | Supply current                                | $V_{DD} = 4.5\text{ V}$ , DAC off, ARM set, OSC disabled  |                          | 0.05 | 10               |             | $\mu\text{A}$    |
| $I_{(\text{SLEEP-mid})}$       |   | $V_{DD} = 4.5\text{ V}$ , DAC off, ARM set, OSC enabled   |                          | 40   | 60               |             |                  |
| $I_{(\text{SLEEP-light})}$     |   | $V_{DD} = 4.5\text{ V}$ , DAC off, ARM clear, OSC enabled   |                          | 60   | 100              |             |                  |
| $V_{IO}$                       | Input offset voltage                          | $V_{DD} = 4.5\text{ V}$ , $V_{ref} = 1$ to $4.25\text{ V}$  |                          | 25   | 50               |             | $\text{mV}$      |
| $R_{(\text{PULLUP})}$          | F port pullup resistance                      | $V_{DD} = 5\text{ V}$   |                          | 70   | 150              |             | $\text{k}\Omega$ |
| $\Delta f_{(\text{RTO-trim})}$ | Trim deviation                                | $R_{RTO} = 470\text{ k}\Omega$ , $V_{DD} = 4.5\text{ V}$ , $T_A = 25^\circ\text{C}$ , $f_{RTO} = 8.192\text{ MHz}$ (PLL setting = 7 Ch) <sup>‡</sup>              |                          |      | $\pm 1\%$        | $\pm 3\%$   |                  |
| $\Delta f_{(\text{RTO-volt})}$ | Voltage deviation                             | $R_{RTO} = 470\text{ k}\Omega$ , $V_{DD} = 3.5$ to $5.2\text{ V}$ , $T_A = 25^\circ\text{C}$ , $f_{RTO} = 8.192\text{ MHz}$ (PLL setting = 7 Ch) <sup>‡</sup>     |                          |      |                  | $\pm 1.5\%$ |                  |
| $\Delta f_{(\text{RTO-temp})}$ | Temperature deviation                         | $R_{RTO} = 470\text{ k}\Omega$ , $V_{DD} = 4.5\text{ V}$ , $T_A = 0$ to $70^\circ\text{C}$ , $f_{RTO} = 8.192\text{ MHz}$ (PLL setting = 7 Ch) <sup>‡</sup>       |                          |      | $\pm 0.03$       |             | $^\circ\text{C}$ |
| $\Delta f_{(\text{RTO-res})}$  | Resistance deviation                          | $V_{DD} = 4.5\text{ V}$ , $T_A = 25^\circ\text{C}$ , $R_{OSC} = 470\text{ k}\Omega$ at $\pm 1\%$ , $f_{RTO} = 8.192\text{ MHz}$ (PLL setting = 7 Ch) <sup>‡</sup> |                          |      | $\pm 1\%$        |             |                  |

<sup>†</sup> Operating current assumes all inputs are tied to either  $V_{SS}$  or  $V_{DD}$  with no input currents due to programmed pullup resistors. The DAC output and other outputs are open circuited.

<sup>‡</sup> The best trim value is selected at nominal temperature and voltage but the deviation due to the trim error is ignored.

<sup>§</sup> Typical voltage and current measurement taken at  $25^\circ\text{C}$

<sup>¶</sup> Cannot exceed 15 mA total per internal  $V_{DD}$  pin. Port A, B share 1 internal  $V_{DD}$  pin; Port C, D share 1 internal  $V_{DD}$ .

**MSP50C601**  
**MIXED-SIGNAL PROCESSOR**

SPSS029A – SEPTEMBER 2000 – REVISED FEBRUARY 2001

---

**external component absolute values**

| PARAMETER |                          | TEST CONDITIONS                             | MIN  | MAX | UNIT             |
|-----------|--------------------------|---|------|-----|------------------|
| R(RTO)    | RTO external resistance  | $T_A = 25^\circ\text{C}$ ,<br>1% tolerance  | 470  |     | $\text{k}\Omega$ |
| C(PLL)    | PLL external capacitance | $T_A = 25^\circ\text{C}$ ,<br>10% tolerance | 3300 |     | $\text{pF}$      |


# **MSP50C601** **MIXED-SIGNAL PROCESSOR**

SPSS029A – SEPTEMBER 2000 – REVISED FEBRUARY 2001

## MECHANICAL DATA

## PJM (R-PQFP-G100)

## PLASTIC QUAD FLATPACK



NOTES: A. All linear dimensions are in millimeters.  
B. This drawing is subject to change without notice.  
C. Falls within JEDEC MS-022

## **IMPORTANT NOTICE**

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgment, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Customers are responsible for their applications using TI components.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, license, warranty or endorsement thereof.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations and notices. Representation or reproduction of this information with alteration voids all warranties provided for an associated TI product or service, is an unfair and deceptive business practice, and TI is not responsible nor liable for any such use.

Resale of TI's products or services with *statements different from or beyond the parameters* stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service, is an unfair and deceptive business practice, and TI is not responsible nor liable for any such use.

Also see: [Standard Terms and Conditions of Sale for Semiconductor Products](http://www.ti.com/sc/docs/stdterms.htm). [www.ti.com/sc/docs/stdterms.htm](http://www.ti.com/sc/docs/stdterms.htm)

### **Mailing Address:**

Texas Instruments  
Post Office Box 655303  
Dallas, Texas 75265