



BSS138

N-CHANNEL ENHANCEMENT MODE FIELD EFFECT TRANSISTOR

Features

- Low On-Resistance
- Low Gate Threshold Voltage
- Low Input Capacitance
- Fast Switching Speed
- Low Input/Output Leakage

Lead Free/RoHS Compliant (Note 3)

Qualified to AEC-Q101 Standards for High Reliability

Mechanical Data

Case: SOT-23

Case Material: Molded Plastic. UL Flammability Classification Rating 94V-0

Moisture Sensitivity: Level 1 per J-STD-020C

Terminals: Solderable per MIL-STD-202, Method 208


Lead Free Plating (Matte Tin Finish annealed over Alloy 42 leadframe).

Terminal Connections: See Diagram

Marking (See Page 2): K38

Ordering & Date Code Information: See Page 2

Weight: 0.008 grams (approximate)



SOT-23		
Dim	Min	Max
A	0.37	0.51
B	1.20	1.40
C	2.30	2.50
D	0.89	1.03
E	0.45	0.60
G	1.78	2.05
H	2.80	3.00
J	0.013	0.10
K	0.903	1.10
L	0.45	0.61
M	0.085	0.180
	0	8
All Dimensions in mm		

Maximum Ratings @ T_A = 25 C unless otherwise specified

Characteristic	Symbol	BSS138	Units
Drain-Source Voltage	V _{DSS}	50	V
Drain-Gate Voltage R _{GS} 20K	V _{DGR}	50	V
Gate-Source Voltage	V _{GSS}	20	V
Drain Current	I _D	200	mA
Power Dissipation (Note 1)	P _d	300	mW
Thermal Resistance, Junction to Ambient (Note 1)	R _{JA}	417	C/W
Operating and Storage Temperature Range	T _j , T _{STG}	-55 to +150	C

Electrical Characteristics @ T_A = 25 C unless otherwise specified

Characteristic	Symbol	Min	Typ	Max	Unit	Test Condition
OFF CHARACTERISTICS (Note 2)						
Drain-Source Breakdown Voltage	BV _{DSS}	50	75		V	V _{GS} = 0V, I _D = 250 A
Zero Gate Voltage Drain Current	I _{DSS}			0.5	μA	V _{DS} = 50V, V _{GS} = 0V
Gate-Body Leakage	I _{GSS}			100	nA	V _{GS} = 20V, V _{DS} = 0V
ON CHARACTERISTICS (Note 2)						
Gate Threshold Voltage	V _{GS(th)}	0.5	1.2	1.5	V	V _{DS} = V _{GS} , I _D = 250 A
Static Drain-Source On-Resistance	R _{DS(ON)}		1.4	3.5		V _{GS} = 10V, I _D = 0.22A
Forward Transconductance	g _{FS}	100			mS	V _{DS} = 25V, I _D = 0.2A, f = 1.0KHz
DYNAMIC CHARACTERISTICS						
Input Capacitance	C _{iss}			50	pF	V _{DS} = 10V, V _{GS} = 0V f = 1.0MHz
Output Capacitance	C _{oss}			25	pF	
Reverse Transfer Capacitance	C _{rss}			8.0	pF	
SWITCHING CHARACTERISTICS						
Turn-On Delay Time	t _{D(ON)}			20	ns	V _{DD} = 30V, I _D = 0.2A, R _{GEN} = 50
Turn-Off Delay Time	t _{D(OFF)}			20	ns	

Notes: 1. Device mounted on FR-5 PCB 1.0 x 0.75 x 0.062 inch pad layout as shown on Diodes, Inc. suggested pad layout AP02001, which can be found on our website at <http://www.diodes.com/datasheets/ap02001.pdf>.

2. Short duration test pulse used to minimize self-heating effect.

3. No purposefully added lead.




Ordering Information (Note 4)

Device	Packaging	Shipping
BSS138-7-F	SOT-23	3000/Tape & Reel

Notes: 4. For Packaging Details, go to our website at <http://www.diodes.com/datasheets/ap02007.pdf>.

Marking Information



K38 = Product Type Marking Code
 YM = Date Code Marking
 Y = Year ex: N = 2002
 M = Month ex: 9 = September

Date Code Key

Year	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009
Code	J	K	L	M	N	P	R	S	T	U	V	W

Month	Jan	Feb	March	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code	1	2	3	4	5	6	7	8	9	O	N	D




Fig. 1 Drain-Source Current vs. Drain-Source Voltage




Fig. 2 Transfer Characteristics




Fig. 3 Drain-Source On Resistance vs. Junction Temperature




Fig. 4 Gate Threshold Voltage vs. Junction Temperature




Fig. 5 Drain-Source On Resistance vs. Drain Current




Fig. 6 Drain-Source On Resistance vs. Drain Current




Fig. 7 Drain-Source On Resistance vs. Drain Current




Fig. 8 Drain-Source On Resistance vs. Drain Current




Fig. 9 Body Diode Current vs. Body Diode Voltage




Fig. 10 Capacitance vs. Drain Source Voltage

IMPORTANT NOTICE

Diodes, Inc. and its subsidiaries reserve the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes. Diodes, Inc. does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

LIFE SUPPORT

The products located on our website at www.diodes.com are not recommended for use in life support systems where a failure or malfunction of the component may directly threaten life or cause injury without the expressed written approval of Diodes Incorporated.