

# **BAW56DW**

### QUAD SURFACE MOUNT SWITCHING DIODE ARRAY

#### **Features**

Fast Switching Speed

Ultra-Small Surface Mount Package

For General Purpose Switching Applications

High Conductance

Two "BAW56" Circuits In One Package Lead Free/RoHS Compliant (Note 3)

Qualified to AEC-Q101 Standards for High Reliability

### **Mechanical Data**

Case: SOT-363

Case Material: Molded Plastic. UL Flammability

Classification Rating 94V-0


Moisture Sensitivity: Level 1 per J-STD-020C

Terminals: Solderable per MIL-STD-202, Method 208

Lead Free Plating (Matte Tin Finish annealed over Alloy 42 leadframe). Please see Ordering Information, Note 5, on

Page 2

Polarity: See Diagram
Marking: KJC (See Page 2)
Weight: 0.006 grams (approximate)



- E. L T. C.								
SOT-363								
Dim	Min	Max						
Α	0.10	0.30						
В	1.15	1.35						
С	2.00 2.20							
D	0.65 Nominal							
F	0.30	0.40						
Н	1.80	2.20						
J	177	0.10						
K	0.90 1.00							
L	0.25	0.40						
M	0.10	0.25						
	0	8°						
All Dimensions in mm								

### Maximum Ratings @ TA = 25 C unless otherwise specified

Characteristic	Symbol	Value	Unit	
Non-Repetitive Peak Reverse Voltage	V <sub>RM</sub>	100	V	
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V <sub>RRM</sub> V <sub>RWM</sub> V <sub>R</sub>	75	V	
RMS Reverse Voltage	V <sub>R(RMS)</sub>	53	V	
Forward Continuous Current (Note 1)	I <sub>FM</sub>	300	mA	
Average Rectified Output Current (Note 1)	Io	150	mA	
Non-Repetitive Peak Forward Surge Current @ t = 1.0 s @ t = 1.0s	I <sub>FSM</sub>	2.0 1.0	А	
Power Dissipation (Note 1)	P <sub>d</sub>	200	mW	
Thermal Resistance Junction to Ambient Air (Note 1)	R JA	625	C/W	
Operating and Storage Temperature Range	T <sub>j</sub> , T <sub>STG</sub>	-65 to +150	C C	


# Electrical Characteristics @ T<sub>A</sub> = 25 C unless otherwise specified


Characteristic	Symbol	Min	Max	Unit	Test Condition		
Reverse Breakdown Voltage (Note 2)	V <sub>(BR)R</sub>	75		V	I <sub>R</sub> = 2.5 A		
Forward Voltage	V <sub>F</sub>		0.715 0.855 1.0 1.25	V	IF = 1.0mA IF = 10mA IF = 50mA IF = 150mA		
Reverse Current (Note 2)	I <sub>R</sub>		2.5 50 30 25	A A A nA	$\begin{tabular}{lll} $V_R = 75V$ \\ $V_R = 75V$, $T_j = 150$ C \\ $V_R = 25V$, $T_j = 150$ C \\ $V_R = 20V$ \\ \end{tabular}$		
Total Capacitance	Ст		2.0	pF	V <sub>R</sub> = 0, f = 1.0MHz		
Reverse Recovery Time	t <sub>rr</sub>		4.0	ns	$I_F = I_R = 10 \text{mA},$ $I_{rr} = 0.1 \text{ x } I_R, R_L = 100$		

Device mounted on FR-4 PC board with recommended pad layout, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf.

. Short duration test pulse used to minimize self-heating effect.









V<sub>R</sub>, REVERSE VOLTAGE (V) Fig. 3 Typical Capacitance vs. Reverse Voltage

20



V<sub>R</sub>, INSTANTANEOUS REVERSE VOLTAGE (V) Fig. 2 Typical Reverse Characteristics



 $T_A$ , AMBIENT TEMPERATURE (°C) Fig. 4 Power Derating Curve

0

Ν

D

## Ordering Information (Note 4)

0


Device	Packaging	Shipping		
BAW56DW-7-F	SOT-363	3000/Tape & Reel		

4. For Packaging Details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.

30

40

# **Marking Information**



3

KJC = Product Type Marking Code YM = Date Code Marking Y = Year ex: N = 2002M = Month ex: 9 = September

Date Code Key

Code

Year	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012
Code	L	М	N	Р	R	S	Т	U	V	W	Х	Υ	Z
Month		Jan	Feb	March	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec



#### IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

#### LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.