

TOSHIBA Field Effect Transistor Silicon N Channel MOS Type (U-MOSIII)

## TPCS8209

Lithium Ion Battery Applications

Notebook PC Applications

Portable Equipment Applications

- Small footprint due to small and thin package
- Low drain-source ON resistance:  $R_{DS(ON)} = 19 \text{ m}\Omega$  (typ.)
- High forward transfer admittance:  $|Y_{fs}| = 9.2 \text{ S}$  (typ.)
- Low leakage current:  $I_{DSS} = 10 \text{ }\mu\text{A}$  (max) ( $V_{DS} = 20 \text{ V}$ )
- Enhancement mode:  $V_{th} = 0.5 \sim 1.2 \text{ V}$  ( $V_{DS} = 10 \text{ V}$ ,  $I_D = 200 \text{ }\mu\text{A}$ )

Absolute Maximum Ratings ( $T_a = 25^\circ\text{C}$ )


| Characteristics   |   | Symbol    | Rating         | Unit             |
|---|---|-----------|----------------|------------------|
| Drain-source voltage  |   | $V_{DSS}$ | 20             | V                |
| Drain-gate voltage ( $R_{GS} = 20 \text{ k}\Omega$ )                                  |   | $V_{DGR}$ | 20             | V                |
| Gate-source voltage   |   | $V_{GSS}$ | $\pm 12$       | V                |
| Drain current   | DC (Note 1)                                     | $I_D$     | 5              | A                |
|   | Pulse (Note 1)                                  | $I_{DP}$  | 20             |                  |
| Drain power dissipation ( $t = 10 \text{ s}$ ) (Note 2a)                              | Single-device operation (Note 3a)               | $P_D$ (1) | 1.1            | W                |
|   | Single-device value at dual operation (Note 3b) | $P_D$ (2) | 0.75           |                  |
| Drain power dissipation ( $t = 10 \text{ s}$ ) (Note 2b)                              | Single-device operation (Note 3a)               | $P_D$ (1) | 0.6            | W                |
|   | Single-device value at dual operation (Note 3b) | $P_D$ (2) | 0.35           |                  |
| Single pulse avalanche energy (Note 4)  |   | $E_{AS}$  | 32.5           | mJ               |
| Avalanche current   |   | $I_{AR}$  | 5              | A                |
| Repetitive avalanche energy<br>Single-device value at dual operation (Note 2a, 3b, 5) |   | $E_{AR}$  | 0.075          | mJ               |
| Channel temperature   |   | $T_{ch}$  | 150            | $^\circ\text{C}$ |
| Storage temperature range   |   | $T_{stg}$ | $-55 \sim 150$ | $^\circ\text{C}$ |

Note: (Note 1), (Note 2), (Note 3), (Note 4) and, (Note 5): See the next page.

Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings. Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook ("Handling Precautions"/Derating Concept and Methods) and individual reliability data (i.e. reliability test report and estimated failure rate, etc.).


This transistor is an electrostatic-sensitive device. Please handle with caution.

Unit: mm



Weight: 0.035 g (typ.)


## Circuit Configuration



## Thermal Characteristics

| Characteristics   |   | Symbol            | Max | Unit |
|---|---|-------------------|-----|------|
| Thermal resistance, channel to ambient<br>(t = 10 s)<br>(Note 2a) | Single-device operation<br>(Note 3a)                  | $R_{th(ch-a)}(1)$ | 114 | °C/W |
|   | Single-device value at<br>dual operation<br>(Note 3b) | $R_{th(ch-a)}(2)$ | 167 |      |
| Thermal resistance, channel to ambient<br>(t = 10 s)<br>(Note 2b) | Single-device operation<br>(Note 3a)                  | $R_{th(ch-a)}(1)$ | 208 | °C/W |
|   | Single-device value at<br>dual operation<br>(Note 3b) | $R_{th(ch-a)}(2)$ | 357 |      |


## Marking (Note 6)




Note 1: Ensure that the channel temperature does not exceed 150°C.

Note 2:

a) Device mounted on a glass-epoxy board (a)



b) Device mounted on a glass-epoxy board (b)



Note 3:


- The power dissipation and thermal resistance values are shown for a single device (During single-device operation, power is only applied to one device.).
- The power dissipation and thermal resistance values are shown for a single device (During dual operation, power is evenly applied to both devices.).

Note 4:  $V_{DD} = 16\text{ V}$ ,  $T_{ch} = 25^\circ\text{C}$  (initial),  $L = 1.0\text{ mH}$ ,  $R_G = 25\ \Omega$ ,  $I_{AR} = 5\text{ A}$


Note 5: Repetitive rating; pulse width limited by maximum channel temperature

Note 6: ○ on lower right of the marking indicates Pin 1.

※ Weekly code: (Three digits)















## Electrical Characteristics (Ta = 25°C)



| Characteristics                                 |               | Symbol                | Test Condition   | Min | Typ. | Max | Unit |
|---|---------------|-----------------------|--|-----|------|-----|------|
| Gate leakage current                            |               | I <sub>GSS</sub>      | V <sub>GS</sub> = ±10 V, V <sub>DS</sub> = 0 V   | —   | —    | ±10 | μA   |
| Drain cut-OFF current                           |               | I <sub>DSS</sub>      | V <sub>DS</sub> = 20 V, V <sub>GS</sub> = 0 V  | —   | —    | 10  | μA   |
| Drain-source breakdown voltage                  |               | V <sub>(BR)</sub> DSS | I <sub>D</sub> = 10 mA, V <sub>GS</sub> = 0 V  | 20  | —    | —   | V    |
|   |               | V <sub>(BR)</sub> DSX | I <sub>D</sub> = 10 mA, V <sub>GS</sub> = −12 V  | 8   | —    | —   |      |
| Gate threshold voltage                          |               | V <sub>th</sub>       | V <sub>DS</sub> = 10 V, I <sub>D</sub> = 200 μA  | 0.5 | —    | 1.2 | V    |
| Drain-source ON resistance                      |               | R <sub>DS</sub> (ON)  | V <sub>GS</sub> = 2.0 V, I <sub>D</sub> = 3.5 A  | —   | 34   | 60  | mΩ   |
|   |               |                       | V <sub>GS</sub> = 2.5 V, I <sub>D</sub> = 3.5 A  | —   | 26   | 40  |      |
|   |               |                       | V <sub>GS</sub> = 4.0 V, I <sub>D</sub> = 4.0 A  | —   | 19   | 30  |      |
| Forward transfer admittance                     |               | Y <sub>fs</sub>       | V <sub>DS</sub> = 10 V, I <sub>D</sub> = 2.5 A   | 4.6 | 9.2  | —   | S    |
| Input capacitance                               |               | C <sub>iss</sub>      | V <sub>DS</sub> = 10 V, V <sub>GS</sub> = 0 V, f = 1 MHz   | —   | 1280 | —   | pF   |
| Reverse transfer capacitance                    |               | C <sub>rss</sub>      |  | —   | 130  | —   |      |
| Output capacitance                              |               | C <sub>Oss</sub>      |  | —   | 150  | —   |      |
| Switching time                                  | Rise time     | t <sub>r</sub>        |  <p>V<sub>GS</sub> 5 V<br/>0 V</p> <p>I<sub>D</sub> = 2.5 A</p> <p>V<sub>OUT</sub></p> <p>4.7 kΩ</p> <p>4 Ω</p> <p>R<sub>L</sub> = 4 Ω</p> <p>V<sub>DD</sub> ≈ 10 V</p> <p>Duty ≤ 1%, t<sub>w</sub> = 10 μs</p> | —   | 4.5  | —   | ns   |
|   | Turn-ON time  | t <sub>on</sub>       |  | —   | 11   | —   |      |
|   | Fall time     | t <sub>f</sub>        |  | —   | 7.3  | —   |      |
|   | Turn-OFF time | t <sub>off</sub>      |  | —   | 33   | —   |      |
| Total gate charge (gate-source plus gate-drain) |               | Q <sub>g</sub>        | V <sub>DD</sub> ≈ 16 V, V <sub>GS</sub> = 5 V, I <sub>D</sub> = 5 A  | —   | 15   | —   | nC   |
| Gate-source charge 1                            |               | Q <sub>gs1</sub>      |  | —   | 3.3  | —   |      |
| Gate-drain (“miller”) charge                    |               | Q <sub>gd</sub>       |  | —   | 3.5  | —   |      |

## Source-Drain Ratings and Characteristics (Ta = 25°C)

| Characteristics         |                | Symbol    | Test Condition                               | Min | Typ. | Max  | Unit |
|-------------------------|----------------|-----------|--|-----|------|------|------|
| Drain reverse current   | Pulse (Note 1) | $I_{DRP}$ | —  | —   | —    | 20   | A    |
| Forward voltage (diode) |                | $V_{DSF}$ | $I_{DR} = 5 \text{ A}, V_{GS} = 0 \text{ V}$ | —   | —    | -1.2 | V    |







**RESTRICTIONS ON PRODUCT USE**

20070701-EN

- The information contained herein is subject to change without notice.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.  
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc.
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/or sale are prohibited under any applicable laws and regulations.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties.
- Please contact your sales representative for product-by-product details in this document regarding RoHS compatibility. Please use these products in this document in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances. Toshiba assumes no liability for damage or losses occurring as a result of noncompliance with applicable laws and regulations.