# **Fuseholders**

Special Types

# For ATO<sup>®</sup> Fuses In-Line Type

#### **SPECIFICATIONS:**

Electrical: Intended for use with 32 volts Autofuse® fuses rated to 20 or 30 amperes depending on wire size and terminal combinations.

Mounting: Capable of snap-mounting to panel from rear. Fuseholders interlock for multiple mounting.

Molded Parts: Black Thermoplastic (UL 94V2).

Terminals: Brass. Tin-plated. Snap-lock into body.

Ambient Temperature: -40°C to +85°C.

Wire: Stranded with PVC insulation, black #14 AWG for 155 300 Series and orange #10 AWG for 155 400 Series.

#### PATENTED

#### **ORDERING INFORMATION:**

Unassembled	Assembled with 8" Wire Loop, No Fuse	Assembled with 8" Wire Loop and Fuse	Fuse Amperage Rating
155 320U (Terminals designed for #14 AWG stranded wire and marked "14").	155 300 (#14 wire/ terminals rated to 20A).	155 303A 155 304A 155 305A 155 37.5A 155 310A 155 315A 155 320A	3 4 5 7.5 10 15 20
<b>155</b> 430U (Terminals designed for #10 AWG stranded wire and marked "10").	155 400 (#10 wire/ terminals rated to 30A).	<b>155</b> 425A <b>155</b> 430A	25 30

# For ATO<sup>®</sup> Fuses P.C. Board Mount Type

#### **SPECIFICATIONS:**

Electrical: Intended for use with 32 volts ATO® fuses rated to 15 amperes.

Molded Parts: Black Thermoplastic

Terminals: Copper Alloy, Tin Plated

Ambient Temperature: -40°C to +85°C.

**ORDERING INFORMATION:** 

Catalog Number: 04450715

# For MINI<sup>®</sup> Fuses In-Line Type — Easy Crimp Fuseholder

#### **SPECIFICATIONS:**


Terminals: Copper Alloy/Tin plated. Body: Black Thermoplastic.


### **Operating Temperature:** –40°C to +105°C.

Use standard crimping tool and crimp the matted area to secure wire. (Possible crimp tool - Ideal #30-428 [Toothed Die slot] or equivalent). **ORDERING INFORMATION:** 

Catalog Number	Description	
1 <b>53</b> 002	20A Max. Rating — Terminals will accept #16-22 AWG (1.0- .33 mm <sup>2</sup> ) stranded wire (use appropriate wire size based on fuse usage). For example — Use #16 AWG wire for 20A fuse.	
	<ul> <li>30A Max. Rating — Terminals will accept #10–14 AWG (5.0-20 mm²) stranded wire (use appropriate wire size based on tuse usage). For example — Use #10 AWG wire for 30A fuse.</li> </ul>	

Tool For Fuse Removal or Replacement; Part No. 097024.





ation on n



Typical Multiple Mounting (Fuseholders interlocked)

Recommended Panel Mounting Hole (.04" / .078" thick panel) (.415") , 10.54

专业PCB打样工厂,24-4-4-5-10-9出货工TCITUSE

