

查询7352供应商

捷多邦 专业

7352

FILTRAN

V.90

Modem Transformer

PCB打样工

, 24小时加急出货

The 7352 is designed for V.90 applications.






- Designed to reflect 600 ohms on PRI with 290 ohms on SEC.
- Low distortion, specifically designed for V.90 applications



MECHANICAL AND SCHEMATIC (All dimensions in inches)

SUGGESTED PAD LAYOUT


SCHEMATIC



ELECTRICAL SPECIFICATION @ 25°C

| Part Number | Turns Ratio<br>±2% | DCR @ 20°C<br>(Ω ±10%) |     | Frequency Response<br>(dB) | Return Loss<br>(dB min.) | Insertion Loss<br>(dB max.) | Total Harmonic Distortion<br>(dB max.) | Max D.C. Unbalance<br>(mA) | Hipot<br>(VAC) |
|-------------|--------------------|------------------------|-----|----------------------------|--------------------------|-----------------------------|--|----------------------------|----------------|
|             |                    | (PRI):(SEC)            | PRI |                            |                          |                             |  |                            |                |
| 7352        |                    | 14:1                   | 171 | ±0.10                      | 30                       | 3.5                         | -85                                    | 0                          | PRI-SEC        |

Longitudinal Balance 60 dB min 200 - 1000 Hz  
40 dB min 1000 - 4000 Hz



找PDF  
pdf.dzsc.com