

# POWER TRANSFORMER **CHASSIS MOUNT: OUICK-CONNECT WORLD SERIES TM**

# VPS20-1250

### Electrical Specifications (@25C)

- 1. Maximum Power: 25VA
- 2. Primary Series: 230VAC@50/60Hz; Parallel: 115VAC@50/60Hz
- 3. Secondary Series<sup>1</sup>: 20V CT@ 1.25A; Parallel<sup>2</sup>: 10.0V @ 2.5A
- 4. Voltage Regulation: 25% TYP @ full load to no load
- 5. Temperature Rise: 30C TYP (45C MAX allowed)
- 6. Insulation Resistance: 100MΩ
- 7. Recommended Fuse<sup>3</sup>

Series: Inherently limited. No fusing required.

Parallel: Littelfuse p/n 313 3HXP, 3A 250V, slow blow, 1/4 x 1 1/4 or, Cooper Bussmann p/n BKMDL-3, 3A 250V, 1/4 x 1 1/4

#### **Construction:**

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

#### Safetv:

These units are designed with 4000VAC isolation between the primary and secondary, and also, between each winding and the core.

#### Agency File:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose. File E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 CSA: File LR 221330. C22.2 NO. 66, General Purpose. TUV Certificate No.: R72103639, EN60950, Information Technology



#### Dimensions

A. Dimensions:						Unit: In inches		
н	W	D	А	В	С	Т	MW	ML
2-5/16	2-13/16	1-15/16	2	1-1/8	5/16	3/16	2-3/8	-

B. Mounting Hole Size: 3/16"

C. WT | bs. : 1.25

## Connections4:

Input: Series – 6 and 1, Jumper 5 to 2 Parallel - 6 and 1, Jumper 6 to 2 and 5 to 1 Output: Series - 12 and 7, Jumper 11 to 8 Parallel - 12 and 7, Jumper 12 to 8 and 11 to 7

RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

<sup>1</sup> Inherently limited. Class 2 not wet, Class 3 wet.


<sup>3</sup> Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.


Primary and secondary windings are designed to be connected in series or parallel. Winding are not intended to be used independently.


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757


460 Harley Knox Blvd. Perris. California 92571











Publish Date: December 4, 2013

<sup>&</sup>lt;sup>2</sup> Non-Inherently limited. Class 2.