

贴片三极管上的印字, 与真实名称的对照表.txt

印字	器件	厂商	类型	封装	器件用途及参数
-28	PDTA114WU	Phi	N	SOT323	npn dtr
-24	PDTC114TU	Phi	N	SOT323	npn dtr R1 10k
-23	PDTA114TU	Phi	N	SOT323	npn dtr R1 10k
-20	PDTC114WU	Phi	N	SOT323	npn dtr
-6	PMSS3906	Phi	N	SOT323	2N3906
-4	PMSS3904	Phi	N	SOT323	2N3904
0	2SC3603	Nec	CX	SOT173	Npn RF fT 7GHz
1	Gali-1 MC	AZ	SOT89	DC-8GHz	MMIC amp 12dB gain
1	2SC3587	Nec	CX	-	npn RF fT10GHz
1	BA277	Phi	I	SOD523	VHF Tuner band switch diode
2	BST82	Phi	M	-	n-ch mosfet 80V 175mA
2	MRF5711L	Mot	X	SOT143	npn RF MRF571
2	DTCC114T	Roh	N	-	50V 100mA npn sw + 10k base res
2	Gali-2 MC	AZ	SOT89	DC-8GHz	MMIC amp 16dB gain
2	BAT62-02W	Sie	I	SCD80	BAT16 schottky diode
2	2SC3604	Nec	CX	-	npn RF fT8GHz 12dB@2GHz
3	Gali-3 MC	AZ	SOT89	DC-3GHz	MMIC amp 22dB gain
3	DTC143TE	Roh	N	EMT3	npn dtr R1 4k7 50V 100mA
3	DTC143TUA	Roh	N	SC70	npn dtr R1 4k7 50V 100mA
3	DTC143TKA	Roh	N	SC59	npn dtr R1 4k7 50V 100mA
3	BAT60A	Sie	I	SOD323	10V 3A sw schottky
3	BAT62-02W	Sie	I	SCD80	-
4	DTC114TCA	Roh	N	SOT23	npn dtr R1 10k 50V 100mA
4	DTC114TE	Roh	N	EMT3	npn dtr R1 10k 50V 100mA
4	DTC114TUA	Roh	N	SC70	npn dtr R1 10k 50V 100mA
4	DTC114TKA	Roh	N	SC59	npn dtr R1 10k 50V 100mA
4	MRF5211L	Mot	X	SOT143	pnp RF MRF521
4	Gali-4 MC	AZ	SOT89	DC-4GHz	MMIC amp 17.5 dBm
4	BB664	Sie	I	SCD80	Varicap 42-2.5pF
5	SSTPAD5	Sil	J	-	PAD-5 5pA leakage diode
5	Gali-4 MC	AZ	SOT89	DC-4GHz	MMIC amp 18 dBm o/p
5	DTC124TE	Roh	N	EMT3	npn dtr R1 22k 50V 100mA
5	DTC124TUA	Roh	N	SC70	npn dtr R1 22k 50V 100mA
5	DTC124TKA	Roh	N	SC59	npn dtr R1 22k 50V 100mA
6	Gali-6 MC	AZ	SOT89	DC-4GHz	MMIC amp 115 dBm o/p
6	DTC144TE	Roh	N	EMT3	npn dtr R1 47k 50V 100mA
6	DTC144TUA	Roh	N	SC70	npn dtr R1 47k 50V 100mA
6	DTC144TKA	Roh	N	SC59	npn dtr R1 47k 50V 100mA
9	DTC115TUA	Roh	N	SC70	npn dtr R2 100k 50V 100mA
9	DTC115TKA	Roh	N	SC59	npn dtr R2 100k 50V 100mA
9	BC849	Mot	N	SOT23	BC 549B
10	SSTPAD10	Sil	J	-	PAD-10 10pA leakage diode
10	MRF9411L	Mot	X	SOT143	npn Rf 8GHz MRF941
11	SO2369R	SGS	R	SOT23R	2N2369
11	MRF9511L	Mot	X	SOT143	npn RF 8GHz MRF951
11	MUN5311DW1	Mot	DP	SOT363	npn/pnp dtr 10k+10k
11	PDTA114EU	Phi	N	SOT416	pnp dtr
12	MUN5312DW1	Mot	DP	SOT363	npn/pnp dtr 22k+22k
12	DTA123EUA	Rho	N	SC70	pnp dtr 2k2+2k2 50V 100ma
12	DTA123EKA	Rho	N	SC59	pnp dtr 2k2+2k2 res 50V 100ma
13	DTA143EUA	Rho	N	SC70	pnp dtr 4k7+4k7 50V 100ma
13	DTA143EKA	Rho	N	SC59	pnp dtr 4k7+4k7 50V 100ma
13	DTA143ECA	Rho	N	SOT23	pnp dtr 4k7+4k7 50V 100ma
13	MA4CS103A	M/A	C	SOT23	Schottky RF 20V 100mA
13	MUN5313DW1	Mot	DP	SOT363	npn/pnp dtr 47k+47k
14	BAT114-099R	Sie	DQ	-	Quad Schottky crossover ring
14	DTA114EUA	Roh	N	SC70	pnp dtr 10k + 10k
14	DTA114EKA	Roh	N	SC59	pnp dtr 10k + 10k
14	MUN5314DW1	Mot	DP	SOT363	npn/pnp dtr 10k R1
14	DTA114ECA	Roh	N	SOT23	pnp dtr 10k + 10k
15	DTA124EUA	Roh	N	SC70	pnp dtr 30V 50mA 22k+22k
15	DTA124EKA	Roh	N	SC59	pnp dtr 30V 50mA 22k+22k
15	DTA124ECA	Roh	N	SOT23	pnp dtr 30V 50mA 22k+22k
15	MUN5315DW1	Mot	DP	SOT363	npn/pnp dtr 10k R1
15	MMBT3960	Mot	N	-	2N3960
16	MUN5316DW1	Mot	DP	SOT363	npn/pnp dtr 4k7 R1
16	DTA144EUA	Roh	N	SC70	pnp dtr 30V 50mA 47k+47k
16	DTA144EKA	Roh	N	SC59	pnp dtr 30V 50mA 47k+47k
18	BFP181T	Tfk	X	-	npn Rf fT 7.8GHz 10V 20mA
18	PDTC143ZK	Phi	N	SOT346	npn dtr 4k7+47k
19	PDTA143ZK	Phi	N	SOT346	pnp dtr 4k7+47k
19	DTA115EUA	Rho	N	SC70	pnp dtr 100k+100k 50V 100ma
19	DTA115EKA	Rho	N	SC59	pnp dtr 100k+100k 50V 100ma
20	SSTPAD20	Sil	J	-	PAD-20 20pA leakage diode



贴片三极管上的印字，与真实名称的对照表.txt

20	MRF5811 Mot	X	SOT143	npn Rf fT 5GHz 0.2A
21	Gali-21 MC	AZ	SOT89	DC-8GHz MMIC amp 14 dB gain
22	MMBT4209	Nat	N	SOT23 pnp sw 850MHz 2N4209
22	DTC123EUA	Rho	N	SC70 npn dtr 2k2+2k2 50V 100ma
22	DTC123EKA	Rho	N	SC59 npn dtr 2k2+2k2 50V 100ma
23	MMBT3646	Nat	N	SOT23 npn sw 350MHz 2N3646
23	DTC143EUA	Roh	N	SC70 pnp dtr 50V 100mA 4k7+ 4k7
23	DTC143EKA	Roh	N	SC59 pnp dtr 50V 100mA 4k7+ 4k7
24	MMBD2101	Nat	C	SOT23 Si diode 100V 200mA
24	DTC114ECA	Roh	N	SOT23 npn dtr 50V 100mA 10k + 10k
24	DTC114EUA	Roh	N	SC70 npn dtr 50V 100mA 10k + 10k
24	DTC114EKA	Roh	N	SC59 npn dtr 50V 100mA 10k + 10k
24	2SC5006 Nec	N	-	npn RF fT 4.5GHz @3V 7mA
25	MMBD2102	Nat	K	SOT23 Si diode 100V 200mA
25	DTC124ECA	Roh	N	SOT23 npn dtr 50V 100mA 22k + 22k
25	DTC124EKA	Roh	N	SC59 npn dtr 50V 100mA 22k + 22k
25	DTC124EUA	Roh	N	SC70 npn dtr 50V 100mA 22k + 22k
26	MMBD2103	Nat	D	SOT23 dual MMBD1201
26	DTC144EKA	Roh	N	SC59 npn dtr 50V 30mA 47k + 47k
26	DTC144EUA	Roh	N	SC70 npn dtr 50V 30mA 47k + 47k
27	MMBD2104	Nat	B	SOT23 dual cc MMBD1201
28	BFP280T Tfk	W	-	npn RF fT 7GHz 8V 10mA
28	MMBD2105	Nat	A	SOT23 dual ca MMBD1201
29	MMBD1401	Nat	C	SOT23 Si diode 200V 100mA
29	DTC115EE	Roh	N	EMT3 npn dtr 100k +100k 50V 20mA
29	DTC115EUA	Roh	N	SC70 npn dtr 100k +100k 50V 20mA
29	DTC115EKA	Roh	N	SC59 npn dtr 100k +100k 50V 20mA
30	MUN5330DW1	Mot	DP	SOT363 npn/pnp dtr 1k0+1k0
31	MUN5331DW1	Mot	DP	SOT363 npn/pnp dtr 2k2+2k2
31	MMBD1402	Nat	K	SOT23 Si diode 200V 100mA
32	MUN5332DW1	Mot	DP	SOT363 npn/pnp dtr 4k7+4k7
32	MMBD1403	Nat	D	SOT23 dual Si diode 200V 100mA
32	BAT32 Sie	CS	-	18GHz zero-bias schottky
33	MUN5333DW1	Mot	DP	SOT363 npn/pnp dtr 4k7+47k
33	DTA143XE	Roh	N	EMT3 pnp dtr 4k7+10k 50V 100mA
33	DTA143XUA	Roh	N	SC70 pnp sw 4k7+10k bias res 50V 100mA
33	DTA143XKA	Roh	N	SC59 pnp sw 4k7+10k bias res 50V 100mA
33	MMBD1404	Nat	B	SOT23 dual cc Si diode 200V 100mA
33	Gali-33 MC	AZ	SOT89	DC-4GHz MMIC amp 19dB gain
34	MUN5334DW1	Mot	DP	SOT363 npn/pnp dtr 22k+47k
34	MMBD1405	Nat	A	SOT23 dual ca Si diode 200V 100mA
34	2SC5007 Nec	N	-	npn RF fT 7GHz @3V 7mA
35	MUN5335DW1	Mot	DP	SOT363 npn/pnp dtr 2k2+47k
35	DTA124XE	Roh	N	EMT3 pnp dtr 22k+47k 50V 50mA
35	DTA124XUA	Roh	N	SC70 pnp dtr 22k+47k 50V 50mA
35	DTA124XKA	Roh	N	SC59 pnp dtr 22k+47k 50V 50mA
41	BAT14-115S	Sie	CS	SOT173 40GHz schottky diode
41	BAT14-115R	Sie	CZ	SOT173 40GHz schottky ring quad
42	BAT14-025S	Sie	CS	SOT173 4GHz schottky diode
42	BAT14-025R	Sie	CZ	SOT173 4GHz schottky ring quad
43	BAS40 Sie	C	SOT23	schottky diode 40V 100mA
43	DTA143EE	Mot	N	SOT416 pnp dtr 4k7 + 4k7
43	DTC143XE	Roh	N	EMT3 npn dtr 4k7+10k 50V 100mA
43	DTC143XUA	Roh	N	SC70 npn dtr 4k7+10k 50V 100mA
43	DTC143XKA	Roh	N	SC59 npn dtr 4k7+10k 50V 100mA
44	BAS40-04	Sie	D	SOT23 dual series BAS40
44	BAS40-04W	Sie	D	SOT323 dual series BAS40
44	2SC5009 Nec	N	-	npn RF fT 12GHz @3V 5mA
45	BAS40-05	Sie	A	SOT23 dual ca BAS40
45	BAS40-05W	Sie	A	SOT323 dual ca BAS40
45	BAT14-055S	Sie	CS	SOT173 8GHz schottky diode
45	BAT14-055R	Sie	CZ	SOT173 8GHz schottky ring quad
45	DTC124XE	Roh	N	EMT3 npn dtr 22k+47k 50V 50mA
45	DTC124XUA	Roh	N	SC70 npn dtr 22k+47k 50V 50mA
45	DTC124XKA	Roh	N	SC59 npn dtr 22k+47k 50V 50mA
46	BAS40-06	Sie	B	SOT23 dual cc BAS40
46	BAS40-06W	Sie	B	SOT323 dual cc BAS40
46	MBT3946DW	Mot	DP	- 2N3904/2N3906 pair
47	BAS40-07	Sie	S	SOT143 dual BAS40
47	BAS40-07W	Sie	S	SOT343 dual BAS40
49	BAT14-095S	Sie	CS	SOT173 18GHz schottky diode
49	BAT14-095R	Sie	CZ	SOT173 18GHz schottky ring quad
50	SSTPAD50	Sil	J	- PAD-50 50pA leakage diode
51	BAT15-115S	Sie	CS	SOT173 40GHz schottky diode
51	BAT15-115R	Sie	CZ	SOT173 40GHz schottky ring quad



贴片三极管上的印字，与真实名称的对照表.txt

52	BAT15-025S	Sie	CS	SOT173	4GHz schottky diode
52	BAT15-025R	Sie	CZ	SOT173	4GHz schottky ring quad
52	Gali-52 MC	AZ	SOT89	DC-2GHz	MMIC amp 23 dB gain
52	BAS52-02V	Inf	I	SC79	Schottky diode 45V 750mA
52	DTA123YE	Roh	N	EMT3	pnp dtr 2k2 +10k 50V 100mA
52	DTA123YUA	Roh	N	SC70	pnp dtr 2k2 +10k 50V 100mA
52	DTA123YKA	Roh	N	SC59	pnp dtr 2k2 +10k 50V 100mA
54	DTA114YE	Roh	N	EMT3	pnp dtr 10k + 47k 50V 100mA
54	DTA114YUA	Roh	N	SC70	pnp dtr 10k + 47k 50V 100mA
54	DTA114YKA	Roh	N	SC59	pnp dtr 10k + 47k 50V 100mA
55	BAT15-055S	Sie	CS	SOT173	8GHz schottky diode
55	BAT15-055R	Sie	CZ	SOT173	8GHz schottky ring quad
55	Gali-55 MC	AZ	SOT89	DC-4GHz	MMIC amp 21 dB gain
57	BFQ57	Sie	CX	SOT173	npn 6.5GHz 16V/35mA
58	BFQ58	Sie	CX	SOT173	npn 6.5GHz 16V/30mA
59	BAT15-095S	Sie	CS	SOT173	18GHz schottky diode
59	BAT15-095R	Sie	CZ	SOT173	18GHz schottky ring quad
62	DTC123YE	Roh	N	EMT3	npn dtr 2k2 +10k 50V 100mA
62	DTC123YUA	Roh	N	SC70	npn dtr 2k2 +10k 50V 100mA
62	DTC123YKA	Roh	N	SC59	npn dtr 2k2 +10k 50V 100mA
64	DTC114YE	Roh	N	EMT3	npn dtr 10k + 47k 50V 100mA
64	DTC114YUA	Roh	N	SC70	npn dtr 10k + 47k 50V 100mA
64	DTC114YKA	Roh	N	SC59	npn dtr 10k + 47k 50V 100mA
67	BFP67	Tfk	X	-	npn Rf fT 7.5GHz 10V 50mA
69	DTA114YE	Mot	N	SOT416	pnp dtr 10k +47k
69	DTC115EE	Roh	N	EMT3	npn dtr 100k+100k 50V 20mA
69	DTC115EUA	Roh	N	SC70	npn dtr 100k+100k 50V 20mA
69	DTC115EKA	Roh	N	SC59	npn dtr 100k+100k 50V 20mA
70	BFQ70	Sie	CX	SOT173	npn fT 5.2GHz 15V 35mA
71	BFQ71	Sie	CX	SOT173	npn fT 5.2GHz 15V 30mA
72	BFQ72	Sie	CX	SOT173	npn fT 5.1GHz 15V 50mA
72	2N7002	Sil	M	SOT23	n-ch mosfet 60V 170mA
73	MA4CS101A	M/A	C	SOT23	schottky diode 70V 50mA
73	BFQ73	Sie	CX	SOT173	npn fT 4.9GHz 15V 75mA
73	2SC5004	Nec	N	-	npn RF 5GHz @5V 5mA
74	BFQ74	Sie	CX	SOT173	npn fT 6GHz 16V 35mA
74	MA4CS101B	M/A	D	SOT23	dual series MA4CS101A (73)
74	DTA114WE	Rho	N	EMT3	pnp dtr 10k + 4k7 50V 100mA
74	DTA114WUA	Rho	N	SC70	pnp dtr 10k + 4k7 50V 100mA
74	DTA114WKA	Rho	N	SC59	pnp dtr 10k + 4k7 50V 100mA
74	2SC5005	Nec	N	-	npn RF 5.5GHz @5V 5mA
75	BFQ75	Sie	CX	SOT173	pnp fT 5GHz 12V 50mA
76	BFQ76	Sie	CX	SOT173	pnp fT 5GHz 15V 30mA
76	DTA144WE	Rho	N	EMT3	pnp dtr 47k + 22k 50V 30mA
76	DTA144WUA	Rho	N	SC70	pnp dtr 47k + 22k 50V 30mA
76	DTA144WKA	Rho	N	SC59	pnp dtr 47k + 22k 50V 30mA
77	MA4CS101E	M/A	S	SOT143	dual MA4CS101A (73)
77	BFQ77	Sie	CX	SOT173	npn fT 7GHz 15V 20mA
78	MMBT4258	Nat	N	SOT23	pnp sw fT 700MHz
81	SO2369AR	SGS	R	SOT23R	2N2369A
81	ZMV831BV2	Zet	I	SOD523	28V hyperabrupt varicap 15pF @2V
82	2SC5009	Nec	N	-	npn RF fT 12GHz @ 3V 5mA
82	ZMV832BV2	Zet	I	SOD523	28V hyperabrupt varicap 22pF @2V
83	MMBT4400	Nat	N	-	npn 2N4400
83	2SC5010	Nec	N	-	npn RF fT 12GHz 3V 10mA
83	MA4CS102A	M/A	C	SOT23	schottky diode 8V 30mA
84	MA4CS102B	M/A	D	SOT23	dual ser schottky diode 8V 30mA
84	DTC114WE	Rho	N	EMT3	npn dtr 10k + 4k7 50V 100mA
84	DTC114WUA	Rho	N	SC70	npn dtr 10k + 4k7 50V 100mA
84	DTC114WKA	Rho	N	SC59	npn dtr 10k + 4k7 50V 100mA
85	MMBD1701	Nat	C	-	Fast Si diode 30V 50mA
85	MA4CS102A	M/A	B	SOT23	dual cc schottky diode 8V 30mA
86	MMBD1702	Nat	K	-	Fast Si diode 30V 50mA
86	DTC144WE	Rho	N	EMT3	npn dtr 47k + 22k 50V 30mA
86	DTC144WUA	Rho	N	SC70	npn dtr 47k + 22k 50V 30mA
86	DTC144WKA	Rho	N	SC59	npn dtr 47k + 22k 50V 30mA
87	MMBD1703	Nat	D	-	dual ser MMBD1701
87	MA4CS102A	M/A	S	SOT143	dual schottky diode 8V 30mA
88	MMBD1704	Nat	B	-	dual cc MMBD1701
89	MMBD1705	Nat	A	-	dual ca MMBD1701
91	ZV931V2	Zet	I	SOD523	4-13.5pF hyperabrupt varicap
91	DTA113TKA	Roh	N	SC59	pnp dtr R11k0 50V 100mA
92	ZV932V2	Zet	I	SOD523	5.5-17pF hyperabrupt varicap
93	ZV933V2	Zet	I	SOD523	12-42pF hyperabrupt varicap
93	DTA143TE	Roh	N	EMT3	pnp dtr R1 4k7 50V 100mA



贴片三极管上的印字，与真实名称的对照表.txt

93	DTA143TUA	Roh	N	SC70	pnp	dtr	R1	4k7	50V	100mA
93	DTA143TKA	Roh	N	SC59	pnp	dtr	R1	4k7	50V	100mA
94	DTA114TE	Roh	N	EMT3	pnp	dtr	R1	10k	50V	100mA
94	DTA114TUA	Roh	N	SC70	pnp	dtr	R1	10k	50V	100mA
94	DTA114TKA	Roh	N	SC59	pnp	dtr	R1	10k	50V	100mA
95	DTA124TE	Roh	N	EMT3	pnp	dtr	R1	22k	50V	100mA
95	DTA124TCA	Roh	N	SOT23	pnp	dtr	R1	22k	50V	100mA
95	DTA124TKA	Roh	N	SC59	pnp	dtr	R1	22k	50V	100mA
96	DTA144TE	Roh	N	EMT3	pnp	dtr	R1	47k	50V	100mA
96	DTA144TUA	Roh	N	SC70	pnp	dtr	R1	47k	50V	100mA
96	DTA144TKA	Roh	N	SC59	pnp	dtr	R1	47k	50V	100mA
99	DTA115TE	Roh	N	EMT3	pnp	dtr	R1	100k	50V	100mA
99	DTA115TUA	Roh	N	SC70	pnp	dtr	R1	100k	50V	100mA
99	DTA115TKA	Roh	N	SC59	pnp	dtr	R1	100k	50V	100mA
100	SSTPAD100	Sil	J	SOT23	PAD-100			100pA		leakage diode
101	PZM10NB1	Phi	C	SOT346	10V	0.3W				zener
102	PZM10NB2	Phi	C	SOT346	10V	0.3W				zener
103	PZM10NB3	Phi	C	SOT346	10V	0.3W				zener
111	PZM11NB1	Phi	C	SOT346	11V	0.3W				zener
111	DTA113ZUA	Roh	N	SC70	pnp	dtr	1k+10k	50V	100mA	
112	PZM11NB2	Phi	C	SOT346	11V	0.3W				zener
113	PZM11NB3	Phi	C	SOT346	11V	0.3W				zener
113	DTA143ZUA	Roh	N	SC70	pnp	dtr	4k7+47k	50V	100mA	
121	PZM12NB1	Phi	C	SOT346	12V	0.3W				zener
121	DTC113ZUA	Roh	N	SC70	npn	dtr	1k+10k	50V	100mA	
122	PZM12NB2	Phi	C	SOT346	12V	0.3W				zener
123	PZM12NB3	Phi	C	SOT346	12V	0.3W				zener
123	DTC143ZUA	Roh	N	SC70	npn	dtr	4k7+47k	50V	100mA	
131	PZM13NB1	Phi	C	SOT346	13V	0.3W				zener
132	PZM13NB2	Phi	C	SOT346	13V	0.3W				zener
132	DTA123JUA	Roh	N	SC70	pnp	dtr	2k2+47k	50V	100mA	
133	PZM13NB3	Phi	C	SOT346	13V	0.3W				zener
142	DTA123JUA	Roh	N	SC70	npn	dtr	2k2+47k	50V	100mA	
151	PZM15NB1	Phi	C	SOT346	15V	0.3W				zener
152	PZM15NB2	Phi	C	SOT346	15V	0.3W				zener
153	PZM15NB3	Phi	C	SOT346	15V	0.3W				zener
156	DTA144VUA	Roh	N	SC70	pnp	dtr	47k+10k	50V	100mA	
161	PZM16NB1	Phi	C	SOT346	16V	0.3W				zener
162	PZM16NB2	Phi	C	SOT346	16V	0.3W				zener
163	PZM16NB3	Phi	C	SOT346	16V	0.3W				zener
166	DTC144VUA	Roh	N	SC70	npn	dtr	47k+10k	50V	100mA	
179	FMMT5179	Zet	N	-				2N5179		
181	PZM18NB1	Phi	C	SOT346	18V	0.3W				zener
182	PZM18NB2	Phi	C	SOT346	18V	0.3W				zener
183	PZM18NB3	Phi	C	SOT346	18V	0.3W				zener
200	SSTPAD200	Sil	J	-	PAD-200			200pA		leakage diode
201	PZM20NB1	Phi	C	SOT346	20V	300mW				Zener
202	PZM20NB2	Phi	C	SOT346	20V	300mW				Zener
203	PZM20NB3	Phi	C	SOT346	20V	300mW				Zener
221	PZM22NB1	Phi	C	SOT346	22V	300mW				Zener
222	PZM22NB2	Phi	C	SOT346	22V	300mW				Zener
223	PZM22NB3	Phi	C	SOT346	22V	300mW				Zener
241	PZM24NB	Phi	C	SOT346	24V	300mW				Zener
242	PZM24NB	Phi	C	SOT346	24V	300mW				Zener
243	PZM20NB	Phi	C	SOT346	24V	300mW				Zener
271	PZM2.7NB1	Phi	C	SOT346	2.7V	300mW				Zener
272	PZM2.7NB2	Phi	C	SOT346	2.7V	300mW				Zener
301	FDV301N	Fch	M	SOT23	n-ch	'digital'	fet	25V	0.22A	
302	FDV302P	Fch	M	SOT23	p-ch	'digital'	fet	25V	0.13A	
303	FDV303N	Fch	M	SOT23	n-ch	'digital'	fet	25V	0.68A	
304	FDV304P	Fch	M	SOT23	p-ch	'digital'	fet	25V	0.46A	
331	NDS331N	Fch	M	SOT23	n-ch	mosfet		1.3A	20V	
331	PZM3.3NB1	Phi	C	SOT346	3.3V	300mW				zener
332	PZM3.3NB2	Phi	C	SOT346	3.3V	300mW				zener
332	NDS332N	Fch	M	SOT23	"p-ch	mosfet		0.4A, 1A	pk, 20V"	
335	NDS335N	Fch	M	SOT23	"n-ch	mosfet		70 mA, 1.7A	pk, 20V"	
336	NDS336N	Fch	M	SOT23	"p-ch	mosfet		0.27A, 1.2A	pk, 20V"	
337	NDS337N	Fch	M	SOT23	"n-ch	mosfet		50 mA, 2.5A	pk 20V"	
338	NDS338N	Fch	M	SOT23	"p-ch	mosfet		0.13A, 1.6A	pk 20V"	
340	FDV340P	Fch	M	SOT23	p-ch	mosfet		20V 70 mA		
351	NDS351N	Fch	M	SOT23	n-ch	mosfet		1.1A 30V		
352	NDS352N	Fch	M	SOT23	p-ch	mosfet		0.5A 20V		
355	NDS355N	Fch	M	SOT23	"n-ch	mosfet		0.1A, 1.6A	pk 30V"	
356	NDS356N	Fch	M	SOT23	"p-ch	mosfet		0.3A, 1.1A	pk 20V"	
357	NDS357N	Fch	M	SOT23	n-ch	mosfet		2.5A	pk 30V	



贴片三极管上的印字，与真实名称的对照表.txt

358	NDS358N Fch	M	SOT23	"p-ch mosfet 0.2A, 1.6A pk 30V"
358	FDN358N Fch	M	SOT23	p-ch mosfet 0.2A 1.6A pk 30V
360	FDN360P Fch	M	SOT23	"p-ch mosfet 80mA, 2a PK, 30V"
361	PZM3.6NB1	Phi	C	SOT346 3.6V 300mW Zener
362	PZM3.3NB2	Phi	C	SOT346 3.6V 300mW Zener
391	PZM3.9NB1	Phi	C	SOT346 3.9V 300mW Zener
392	PZM3.9NB2	Phi	C	SOT346 3.9V 300mW Zener
413	FMMT413 Zet	N	SOT23	npn avalanche 150v 0.1A
415	FMMT415 Zet	N	SOT23	npn avalanche 260v 0.1A
417	FMMT417 Zet	N	SOT23	npn avalanche 320v 0.1A
431	PZM4.3NB1	Phi	C	SOT346 4.3V 0.3W zener
432	PZM4.3NB2	Phi	C	SOT346 4.3V 0.3W zener
433	PZM4.3NB3	Phi	C	SOT346 4.3V 0.3W zener
449	FMMT449 Zet	N	SOT23	npn 50V 1A low Vce sat
451	FMMT451 Zet	N	SOT23	npn 60V 1A
455	FMMT455 Zet	N	SOT23	NPN 140V 1A
458	FMMT458 Zet	N	SOT23	npn 400V 0.4A
471	PZM4.7NB1	Phi	C	SOT346 4.7V 0.3W zener
472	PZM4.7NB2	Phi	C	SOT346 4.7V 0.3W zener
473	PZM4.7NB3	Phi	C	SOT346 4.7V 0.3W zener
491	FMMT491 Zet	N	SOT23	ZTX 450/451
493	FMMT493 Zet	N	SOT23	ZTX 453
494	FMMT494 Zet	N	SOT23	npn 120V 1A
495	FMMT495 Zet	N	SOT23	npn 170V 1A
497	FMMT497 Zet	N	SOT23	npn 300V 0.5A
500	SSTPAD500	Sil	J	PAD-500 500pA leakage diode
511	PZM5.1NB1	Phi	C	SOT346 5.1V 0.3W zener
512	PZM5.1NB2	Phi	C	SOT346 5.1V 0.3W zener
513	PZM5.1NB3	Phi	C	SOT346 5.1V 0.3W zener
558	FMMT558 Zet	N	SOT23	pnp 400V 0.15A
561	PZM5.1NB1	Phi	C	SOT346 5.6V 0.3W zener
562	PZM5.1NB2	Phi	C	SOT346 5.6V 0.3W zener
563	PZM5.1NB3	Phi	C	SOT346 5.6V 0.3W zener
589	FMMT589 Zet	N	SOT23	pnp 30V 1A
593	FMMT593 Zet	N	SOT23	ZTX 553
605	NDS0605 Fch	M	SOT23	P-ch mosfet 60V 180mA
605	NDS0605 Fch	M	-	p-ch sw mosfet 60V
610	NDS0610 Fch	M	-	p-ch sw mosfet 60V
614	FMMT614 Zet	N	SOT23	sw
617	FMMT617 Zet	N	SOT23	npn sw 15V 3A
618	FMMT618 Zet	N	SOT23	npn sw 20V 2.5A
619	FMMT619 Zet	N	SOT23	npn sw 50V 2A
621	PZM6.2NB1	Phi	C	SOT346 6.2V 0.3W zener
622	PZM6.2NB2	Phi	C	SOT346 6.2V 0.3W zener
623	PZM6.2NB3	Phi	C	SOT346 6.2V 0.3W zener
624	FMMT624 Zet	N	SOT23	-
625	FMMT625 Zet	N	SOT23	-
634	FMMT634 Zet	N	SOT23	100V 0.9A darlington npn
651	PZT651 Mot	N	SOT223	npn 60V 1A
681	PZM6.8NB1	Phi	C	SOT346 6.8V 0.3W zener
682	PZM6.8NB2	Phi	C	SOT346 6.8V 0.3W zener
683	PZM6.8NB1	Phi	C	SOT346 6.8V 0.3W zener
701	2N7001 Mot	M	SOT23	n-ch mosfet
702	2N7002 Mot	M	SOT23	n-ch mosfet 60V 0.11A
703	2N7003 Mot	M	SOT23	n-ch mosfet
712	NDS7002A	Nat	M	SOT23 n-ch mosfet 60V 0.28A
717	FMMT717 Zet	N	SOT23	pnp sw 0.625W 2.5A 12V
718	FMMT718 Zet	N	SOT23	pnp sw 0.625W 1.5A 20V
720	FMMT720 Zet	N	SOT23	pnp sw 0.625W 1.5A
722	FMMT722 Zet	N	SOT23	pnp sw
723	FMMT723 Zet	N	SOT23	pnp sw
730	FMMT730 Zet	N	SOT23	ZTX550/551
751	PZM7.5NB1	Phi	C	SOT346 7.5V 0.3W zener
752	PZM7.5NB2	Phi	C	SOT346 7.5V 0.3W zener
753	PZM7.5NB3	Phi	C	SOT346 7.5V 0.3W zener
821	PZM8.2NB1	Phi	C	SOT23 8.2V 0.3W zener
822	PZM8.2NB2	Phi	C	SOT23 8.2V 0.3W zener
822	S822T Tfk	X	-	npn RF fT 5.2GHz 6V 8mA
823	PZM8.2NB3	Phi	C	SOT23 8.2V 0.3W zener
852	S852T Tfk	N	SOT23	npn RF fT 5.2GHz 6V 8mA
887	S887T Tfk	W	SOT143	n-ch dg uhf mosfet
888	S888T Tfk	W	SOT142	n-ch dg uhf mosfet
911	PZM9.1NB1	Phi	C	SOT346 9.1V 0.3W zener
912	PZM9.1NB2	Phi	C	SOT346 9.1V 0.3W zener
913	PZM9.1NB3	Phi	C	SOT346 9.1V 0.3W zener



贴片三极管上的印字，与真实名称的对照表.txt

05F	TSDf1205R	Tfk	WQ	-	fT12GHz npn 4V 5mA
0A	MUN5111DW1	Mot	DO	SOT363	dual pnp dtr 10k+10k
0A	DTC125TUA	Roh	N	SC70	nnp dtr R2 100k 50V 100mA
0A	DTC125TKA	Roh	N	SC59	nnp dtr R2 100k 50V 100mA
0B	MUN5112DW1	Mot	DO	SOT363	dual pnp dtr 22k+22k
0C	MUN5113DW1	Mot	DO	SOT363	dual pnp dtr 47k+47k
0D	MUN5114DW1	Mot	DO	SOT363	dual pnp dtr 10k+47k
0E	MUN5115DW1	Mot	DO	SOT363	dual pnp dtr R1 10k
0F	MUN5116DW1	Mot	DO	SOT363	dual pnp dtr R1 4k7
0G	MUN5130DW1	Mot	DO	SOT363	dual pnp dtr 1k0+1k0
0H	MUN5131DW1	Mot	DO	SOT363	dual pnp dtr 2k2+2k2
0J	MUN5132DW1	Mot	DO	SOT363	dual pnp dtr 4k7+4k7
0K	MUN5133DW1	Mot	DO	SOT363	dual pnp dtr 4k7+47k
0L	MUN5134DW1	Mot	DO	SOT363	dual pnp dtr 22k+47k
0M	MUN5135DW1	Mot	DO	SOT363	dual pnp dtr 2k2+47k
1 (red)	BB669	Sie	I	SOD323	56-2.7 pF varicap
10A	PZM10NB2A	Phi	A	SOT346	dual ca 10V 0.3W zener
10V	PZM10NB	Phi	C	SOT346	10V 0.3W zener
10Y	BZV49-C10	Phi	0	SOT89	10V 1W zener
11A	PZM11NB2A	Phi	A	SOT346	dual ca 11V 0.3W zener
11A	MMBD1501A	Nat	C	SOT23	Si diode 200V 100mA
11V	PZM11NB	Phi	C	SOT346	11V 0.3W zener
11Y	BZV49-C11	Phi	0	SOT89	11V 1W zener
12A	MMBD1502A	Nat	K	SOT23	Si diode 200V 100mA
12A	PZM12NB2A	Phi	A	SOT346	dual ca 12V 0.3W zener
12E	ZC2812E	Zet	D	SOT23	dual series RF schottkyl5V 20mA
12V	PZM12NB	Phi	C	SOT346	12V 0.3W zener
12Y	BZV49-C12	Phi	0	SOT89	12V 1W zener
13A	MMBD1503A	Nat	D	SOT23	dual Si diode 200V 100mA
13A	PZM13NB2A	Phi	A	SOT346	dual ca 13V 0.3W zener
13E	ZC2813E	Zet	A	SOT23	dual ca RF schottkyl5V 20mA
13s	BAS125	Sie	C	SOT23	Schottky sw 24V 100mA
13s	BAS125W	Sie	C	SOT323	Schottky sw 24V 100mA
13t	BC846BPN	Phi	N	SOT363	BC546B
13V	PZM13NB	Phi	C	SOT346	13V 0.3W zener
13Y	BZV49-C13	Phi	0	SOT89	13V 1W zener
14A	MMBD1504A	Nat	B	-	dual cc Si diode 200V 100mA
14s	BAS125-04	Sie	D	SOT23	Dual series Schottky 25V 100mA
14s	BAS125-04W	Sie	D	SOT323	Dual series Schottky 25V 100mA
15A	MMBD1505A	Nat	A	-	dual ca Si diode 200V 100mA
15A	PZM15NB2A	Phi	A	SOT346	dual ca 15V 0.3W zener
15s	BAS125-05	Sie	B	SOT23	dual cc Schottky 25V 100mA
15s	BAS125-05W	Sie	B	SOT323	dual cc Schottky 25V 100mA
15V	PZM15NB	Phi	C	SOT346	15V 0.3W zener
15Y	BZV49-C15	Phi	0	SOT89	15V 1W zener
16s	BAS125-06	Sie	A	SOT23	dual ca Schottky 25V 100mA
16s	BAS125-06W	Sie	A	SOT323	dual ca Schottky 25V 100mA
16V	PZM16NB	Phi	C	SOT346	16V 0.3W zener
16Y	BZV49-C16	Phi	0	SOT89	16V 1W zener
17s	BAS125-07	Sie	S	SOT143	dual Schottky 25V 100mA
17s	BAS125-07W	Sie	S	SOT343	dual Schottky 25V 100mA
18V	PZM18NB	Phi	C	SOT346	18V 0.3W zener
18Y	BZV49-C18	Phi	0	SOT89	18V 1W zener
1A	BC846A	Phi	N	SOT23	BC546A
1A	BC846AT	Phi	N	SOT416	BC546A
1A	FMMT3904	Zet	N	SOT23	2N3904
1A	MMBT3904	Mot	N	SOT23	2N3904
1A	IRLML2402	IR	F	SOT23	n-ch mosfet 20V 0.9A
-1A	PMST3904	Phi	N	SOT323	2N3904
1A-	BC846AW	Phi	N	SOT323	BC546A
1AM	MMBT3904L	Mot	N	SOT23	2N3904
1Ap	BC846A	Phi	N	SOT23	BC546A
1At	BC846A	Phi	N	SOT23	BC546A
1At	BC846AW	Phi	N	SOT323	BC546A
1B	BC846B	Phi	N	SOT23	BC546B
1B	BC846BT	Phi	N	SOT416	BC546B
1B	FMMT2222	Zet	N	SOT23	2N2222
1B	MMBT2222	Mot	N	SOT23	2N2222
1B	IRLML2803	IR	F	SOT23	n-ch mosfet 30V 0.9A
-1B	PMST2222	Phi	N	SOT323	2N2222
1B-	BC846BW	Phi	N	SOT323	BC546B
1Bp	BC846B	Phi	N	SOT23	BC546B
1Bs	BC817UPN	Sie	N	SC74	-
1Bt	BC846B	Phi	N	SOT23	BC546B
1Bt	BC846BW	Phi	N	SOT323	BC546B



贴片三极管上的印字，与真实名称的对照表.txt

1C	FMMT-A20	Zet	N	SOT23	MPSA20
1C	MMBTA20L	Mot	N	SOT23	MPS3904
1C	IRLML6302	IR	F	SOT23	p-ch mosfet 20V 0.6A
1Cp	BAP50-05	Phi	B	SOT23	dual cc GP RF pin diode
1Cs	BC847S	Sie	-	SOT363	BC457
1D	MMBTA42	Mot	N	SOT23	MPSA42 300V npn
1D	IRLML5103	IR	F	SOT23	p-ch mosfet 30V 0.6A
1D-	BC846W	Phi	N	SOT323	BC456
1DN	2SC4083	Roh	N	-	nnp 11V 3.2GHz TV tuners
1Dp	BC846	Phi	N	SOT23	BC456
1DR	MSD1328R	Mot	N	SOT346	nnp gp 25V 500mA
1Ds	BC846U	Sie	N	SC74	BC456
1Ds	BC846U	Sie	-	SOT363	BC456
1Dt	BC846	Phi	N	SOT23	BC456
1Dt	BC846W	Phi	N	SOT323	BC456
1E	BC847A	Phi	N	SOT23	BC547A
1E	BC847AT	Phi	N	SOT416	BC547A
1E	FMMT-A43	Zet	N	-	MPSA43
1E	MMBTA43	Mot	N	SOT23	MPSA43 200V npn
1E-	BC847A	Phi	N	SOT323	BC547A
1EN	2SC4084	Roh	N	-	nnp 20V 2.0GHz TV tuners
1Ep	BC847A	Phi	N	SOT23	BC547A
1ER	BC847AR	Phi	R	SOT23R	BC547A
1Es	BC847A	Sie	N	SOT23	BC457
1Es	BC847AW	Sie	N	SOT323	BC457
1Et	BC847A	Phi	N	SOT23	BC547A
1Et	BC847A	Phi	N	SOT323	BC547A
1F	BC847B	Phi	N	SOT23	BC547B
1F	BC847BT	Phi	N	SOT416	BC547B
1F	MMBT5550	Mot	N	SOT23	2N5550 140V npn
1F-	BC847BW	Phi	N	SOT323	BC547B
1Fp	BC847B	Phi	N	SOT23	BC547B
1FR	BC847BR	Phi	R	SOT23R	BC547B
1Fs	BC847B	Sie	N	SOT23	BC547B
1Fs	BC847BT	Sie	N	SC75	BC547B
1Fs	BC847BW	Sie	N	SOT323	BC547B
1Ft	BC847B	Phi	N	SOT23	BC547B
1Ft	BC847BW	Phi	N	SOT323	BC547B
1FZ	FMBT5550	Zet	N	SOT23	2N5550 140V npn
1G	BC847C	Phi	N	SOT23	BC547C
1G	BC847CT	Phi	N	SOT416	BC547C
1G	FMMT-A06	Zet	N	SOT23	MPSA06
1G	MMBTA06	Mot	N	SOT23	MPSA06
1G-	BC847CW	Phi	N	SOT323	BC547C
1GM	MMBTA06	Mot	N	SOT23	MPSA06
1Gp	BC847C	Phi	N	SOT23	BC547C
1GR	BC847CR	Phi	R	SOT23R	BC547C
1Gs	BC847C	Sie	N	SOT23	BC547C
1Gs	BC847CW	Sie	N	SOT323	BC547C
1Gt	BC847CW	Phi	N	SOT323	BC547C
1GT	SOA06	SGS	N	SOT23	MPSA06
1H	FMMT-A05	Zet	N	-	MPSA05
1H	MMBTA05	Mot	N	SOT23	MPSA05
1H-	BC847W	Phi	N	SOT323	BC547
1Hp	BC847	Phi	N	SOT23	BC547
1Ht	BC847	Phi	N	SOT23	BC547
1Ht	BC847W	Phi	N	SOT323	BC547
1HT	SOA05	SGS	N	SOT23	MPSA05
1J	BC848A	Phi	N	SOT23	BC548A
1J	FMMT2369	Zet	N	SOT23	2N2369
1J	MMBT2369	Mot	N	SOT23	MPS2369
1JA	MMBT2369A	Mot	N	SOT23	MPS2369A
1Jp	BCV61A	Phi	VQ	SOT143	nnp current mirror hFe 180
1JR	BC848AR	Phi	R	SOT23R	BC548A
1Js	BC848A	Sie	N	SOT23	BC548A
1Js	BC848AW	Sie	N	SOT323	BC548A
1Js	BCV61A	Sie	VQ	SOT143	nnp current mirror hFe 180
1JZ	BC848A	Zet	N	SOT23	BC548A
1K	BC848B	ITT	N	SOT23	BC548B
1K	MMBT6428	Mot	N	SOT23	MPSA18 50V
1K	FMMT4400	Zet	N	SOT23	2N4400
1KM	MMBT6428L	Mot	N	SOT23	MPSA18 50V
1Kp	BC848B	Phi	N	SOT23	BC548B
1Kp	BCV61B	Phi	VQ	SOT143B	nnp current mirror hFe 290
1KR	BC848BR	Phi	R	SOT23R	BC548B



贴片三极管上的印字，与真实名称的对照表.txt

1Ks	BC848B	Sie	N	SOT23	BC548B
1Ks	BC848BW	Sie	N	SOT323	BC548B
1Ks	BCV61B	Sie	VQ	SOT143B	npn current mirror hFe 290
1KZ	FMMT4400		Zet	N	SOT23 2N4400
1L	BC848C	ITT	N	SOT23	BC548C
1L	MMBT6429		Mot	N	- MPSA18 45V
1L	FMMT4401		Zet	N	- 2N4401
1L	BCV61C	Sie	VQ	SOT143B	npn current mirror hFe 520
1Lp	BC848C	Phi	N	SOT23	BC548C
1Lp	BCV61C	Phi	VQ	SOT143B	npn current mirror hFe 520
1LR	BC848CR	Phi	R	SOT23R	BC548C
1Ls	BC848C	Sie	N	SOT23	BC548C
1Ls	BC848CW	Sie	N	SOT323	BC548C
1M	MMBT A13	Mot	N	SOT23	MPSA13 darlington
1M	FMMT-A13		Zet	N	SOT23 MPSA13
1Mp	BC848	Phi	N	SOT23	BC548
1Mp	BCV61	Phi	VQ	SOT143B	npn current mirror
1N	FMMT-A14		Zet	N	SOT23 MPSA14
1N	MMBT A14	Mot	N	SOT23	MPSA14 darlington
1N5	ZTX11N15DF		Zet	N	SOT23 npn 15V 3A low saturation V
1P	FMMT2222A		Zet	N	- 2N2222A
1P	MMBT2222A		Mot	N	SOT23 2N2222A
1P	BC847PN	Sie	DI	-	npn/npn separate pair gp AF
1Q	MMBT5088		Mot	N	SOT23 MPSA18 Vce 30V
1R	MMBT5089		Mot	N	SOT23 MPSA18 Vce 25V
1S	MMBT2369A		Nat	N	SOT23 2N2369A 500MHz sw npn
1S	MSC3130	Mot	H	SOT346	npn RF ft 1.4GHz 10V
1T	MMBT3960A		Mot	N	- 2N3960A
1U	MMBT2484L		Mot	N	SOT23 MPSA18
1V	MMBT6427		Mot	H	SOT23 2N6426/7 darlington npn
1V-	BF820W	Phi	N	SOT323	npn 300V 50mA BF420
1Vp	BF820	Phi	N	SOT23	npn 300V 50mA BF420
1Vt	BF820	Phi	N	SOT23	npn 300V 50mA BF420
1Vt	BF820W	Phi	N	SOT323	npn 300V 50mA BF420
1W	FMMT3903		Zet	N	SOT23 2N3903
1W -	BF822W	Phi	N	SOT323	npn 300V 50mA BF421
1W t	BF822W	Phi	N	SOT323	npn 300V 50mA BF421
1Wp	BF821	Phi	N	SOT23	npn 300V 50mA BF421
1Wt	BF821	Phi	N	SOT23	npn 300V 50mA BF421
1X	MMBT930L		Mot	N	SOT23 MPS3904
1Xp	BF822	Phi	N	SOT23	npn 250V 50mA BF422
1Xt	BF822	Phi	N	SOT23	npn 250V 50mA BF422
1Y	MMBT3903		Mot	N	SOT23 2N3903
1Yp	BF823	Phi	N	SOT23	npn 250V 50mA BF423
1Yt	BF823	Phi	N	SOT23	npn 250V 50mA BF423
1Z	BAS70-06		Zet	A	SOT23 dual RF CA schottky diode
1Z	MMBT6517		Mot	N	SOT23 2N6517 npn Vce 350V
2 (blue)	BAR64-03W		Sie	I	SOD323 pin diode
2 (white)	BB439		Sie	I	SOD323 29-5 pF varicap
20F	TSDF1220		Tfk	X	SOT143 ft 12GHz npn 6V 20mA
20V	PZM20NB	Phi	C	SOT346	20V 300mW zener
20Y	BZV49-C20		Phi	0	SOT89 20V 1W zener
22V	PZM22NB	Phi	C	SOT346	22V 300mW zener
22Y	BZV49-C22		Phi	0	SOT89 22V 1W zener
24V	PZM24NB	Phi	C	SOT346	24V 300mW Zener
24Y	BZV49-C24		Phi	0	SOT89 24V 1W zener
27V	PZM27NB	Phi	C	SOT346	27V 300mW Zener
27Y	BZV49-C27		Phi	0	SOT89 27V 1W zener
2A	MMBT3906L		Mot	N	SOT23 2N3906
2A	MMBT3906W		Mot	N	SOT323 2N3906
2A	FMMT3906		Zet	N	SOT23 2N3906
2A4	PZM2.4NB2A		Phi	A	SOT346 dual 2.4V cc Zener
2A7	PZM2.7NB2A		Phi	A	SOT346 dual 2.7V cc Zener
2B	BC849B	ITT	N	SOT23	BC549B
2B	FMMT2907		Zet	N	SOT23 2N2907
2B	MMBT2907		Mot	N	SOT23 MPS2907
2B-	BC849BW	Phi	N	SOT323	BC549B
2Bp	BC849B	Phi	N	SOT23	BC549B
2BR	BC849BR	Phi	R	SOT23R	BC549B
2Bs	BC849B	Sie	N	SOT23	BC549B
2Bs	BC849BW	Sie	N	SOT323	BC549B
2Bt	BC849BW	Phi	N	SOT323	BC549B
2BZ	FMMT2907		Zet	N	SOT23 2N2907
2C	BC849C	ITT	N	SOT23	BC549C
2C	MMBT A70	Mot	N	SOT23	MPSA70



贴片三极管上的印字，与真实名称的对照表.txt

2C-	BC849CW	Phi	N	SOT323	BC549C	
2Cp	BC849C	Phi	N	SOT23	BC549C	
2CR	BC849CR	Phi	R	SOT23R	BC549C	
2Cs	BC849C	Sie	N	SOT23	BC549C	
2Cs	BC849CW	Sie	N	SOT323	BC549C	
2Ct	BC849C	Phi	N	SOT23	BC549C	
2Ct	BC849CW	Phi	N	SOT323	BC549C	
2CZ	FMMTA70	Zet	N	SOT23	MPSA70	
2D	MMBTA92	Mot	N	SOT23	MPSA92	pnP Vce 300V
2E	MMBTA93	Mot	N	SOT23	MPSA93	pnP Vce 200V
2E	FMMT-A93	Zet	N	SOT23	MPSA93	
2F	BC850B	ITT	N	SOT23	BC550B	
2F	FMMT2907A	Zet	N	SOT23	2N2907A	
2F	MMBT2907A	Mot	N	SOT23	MPS2907A	
2F	MMBT2907AW	Mot	N	SOT323	MPS2907A	
2F-	BC850BW	Phi	N	SOT323	BC550B	
2Fp	BC850B	Phi	N	SOT23	BC550B	
2FR	BC850BR	Phi	R	SOT23R	BC550B	
2Fs	BC850B	Sie	N	SOT23	BC550B	
2Fs	BC850BW	Sie	N	SOT323	BC550B	
2Ft	BC850B	Phi	N	SOT23	BC550B	
2Ft	BC850BW	Phi	N	SOT323	BC550B	
2G	BC850C	ITT	N	SOT23	BC550C	
2G	FMMT-A56	Zet	N	SOT23	MPSA56	
2G	MMBTA56	Mot	N	SOT23	MPSA56	
2G-	BC850CW	Phi	N	SOT323	BC550C	
2GM	MMBTA56	Mot	N	SOT23	MPSA56	
2Gp	BC850C	Phi	N	SOT23	BC550C	
2GR	BC850CR	Phi	R	SOT23R	BC550C	
2Gs	BC850C	Sie	N	SOT23	BC550C	
2Gt	BC850C	Phi	N	SOT323	BC550C	
2Gt	BC850CW	Phi	N	SOT323	BC550C	
2GT	SOA56	SGS	N	SOT23	MPSA56	
2H	FMMT-A55	Zet	N	SOT23	MPSA55	
2H	MMBTA55	Mot	N	SOT23	MPSA55	
2HT	SOA55	SGS	N	SOT23	MPSA55	
2J	MMBT3640	Mot	N	SOT23	MPS3640	pnP sw
2K	FMMT4402	Zet	N	SOT23	2N4402	
2K	MMBT8598	Mot	N	-	2N4125	pnP 60V
2L	MMBT5401	Mot	N	SOT23	2N5401	pnP 150V
2L	FMMT4403	Zet	N	SOT23	2N4403	
2M	FMMT5087	Zet	N	SOT23	2N5087	
2M	MMBT404	Mot	N	SOT23	pnP-chopper	24V 150mA
2N	MMBT404A	Mot	N	SOT23	pnP-chopper	35V 150mA
2N0	ZXT11N20DF	Zet	N	SOT23	npN 20V 2.5A	low sat switch
2P	FMMT2222R	Zet	R	SOT23R	2N2222	
2P	MMBT5086	Mot	N	SOT23	2N5086	
2Q	MMBT5087	Mot	N	SOT23	2N5087	
2R	HSMS-8102	HP	Z	SOT23	10-14GHz	schottky mixer pair
2T	SO4403	SGS	N	SOT23	2N4403	
2T	MMBT4403	Mot	N	SOT23	2N4403	
2T	HT2	Zet	N	SOT23	pnP 80V	100mA
2U	MMBTA63	Mot	N	SOT23	MPSA63	darlington
2V	MMBTA64	Mot	N	SOT23	MPSA64	darlington
2V4	PZM2.4NB	Phi	C	SOT346	2.4V 300mW	Zener
2V7	PZM2.7NB	Phi	C	SOT346	2.7V 300mW	Zener
2W	FMMT3905	Zet	N	SOT23	2N3905	
2W	MMBT8599	Mot	N	-	2N4125	Vce 80V pnp
2X	SO4401	SGS	N	SOT23	2N4401	
2X	MMBT4401	Mot	N	SOT23	2N4401	
2Y4	BZV49-C2V4	Phi	0	SOT89	2.4V 1W	zener
2Y7	BZV49-C2V7	Phi	0	SOT89	2.7V 1W	zener
2Z	MMBT6520	Mot	N	SOT23	2N6520	pnP Vce 350V
2Z	BAS70-04	Zet	D	SOT23	dual series RF	schottky 70V 15mA
2Z5	BAS70-05	Zet	B	SOT23	dual cc RF	Schottky 70V 15mA
30V	PZM30NB1	Phi	C	SOT346	30V 300mW	zener
30Y	BZV49-C30	Phi	0	SOT89	30V 1W	zener
33V	PZM33NB1	Phi	C	SOT346	33 300mW	zener
33Y	BZV49-C33	Phi	0	SOT89	33V 1W	zener
36V	PZM36NB1	Phi	C	SOT346	36V 300mW	Zener
36Y	BZV49-C36	Phi	0	SOT89	36V 1W	zener
39V	PZM39NB1	Phi	C	SOT346	39V 300mW	Zener
39Y	BZV49-C39	Phi	0	SOT89	39V 1W	zener
3A	BC856A	ITT	N	SOT23	BC556A	
3A	BC856AT	Phi	N	SOT416	BC556A	



贴片三极管上的印字，与真实名称的对照表.txt

3A	MMBTH24	Mot	N	SOT23	VHF mixer npn fT 600MHz
3A-	BC856AW	Phi	N	SOT323	BC556A
3A0	PZM3. 0NB2A	Phi	C	SOT346	dual 3.0V Zener
3A3	PZM3. 3NB2A	Phi	C	SOT346	dual 3.3V Zener
3A6	PZM3. 6NB2A	Phi	C	SOT346	dual 3.6V Zener
3A9	PZM3. 9NB2A	Phi	C	SOT346	dual 3.9V Zener
3Ap	BC856A	Phi	N	SOT23	BC556A
3AR	BC856AR	Phi	R	SOT23R	BC556A
3As	BC856A	Sie	N	SOT23	BC556A
3At	BC856A	Phi	N	SOT23	BC556A
3At	BC856AW	Phi	N	SOT323	BC556A
3B	BC856B	ITT	N	SOT23	BC556B
3B	BC856BT	Phi	N	SOT416	BC556B
3B	FMMT918	Zet	N	SOT23	2N918
3B	MMBT918	Mot	N	SOT23	2N918
3B-	BC856BW	Phi	N	SOT323	BC556B
3Bp	BC856B	Phi	N	SOT23	BC556B
3BR	BC856BR	Phi	R	SOT23	BC556B
3Bs	BC856B	Sie	N	SOT23	BC556B
3Bt	BC856B	Phi	N	SOT23	BC556B
3Bt	BC856BW	Phi	N	SOT323	BC556B
3C	FMMTA20R	Zet	R	SOT23R	MPSA20
3C	BC857	Sie	DO	-	pnp separate pair gp AF
3D	BC856	Phi	N	SOT23	BC556 hfe 75 min
3D	MMBTH81L	Mot	N	SOT23	UHF pnp fT 600MHz
3D	BC856S	Sie	DO	-	pnp separate pair gp AF
3D-	BC856W	Phi	N	SOT323	BC556 hfe 75 min
3Dp	BC856	Phi	N	SOT23	BC556 hfe 75 min
3Dt	BC856	Phi	N	SOT23	BC556 hfe 75 min
3Dt	BC856W	Phi	N	SOT323	BC556 hfe 75 min
3E	BC857A	Phi	N	SOT23	BC557A
3E	BC857AT	Phi	N	SOT416	BC557A
3E	MMBTH10	Mot	N	SOT23	MPSH10 fT 650MHz
3E	FMMT-A42	Zet	N	SOT23	MPSA42
3E-	BC857A	Phi	N	SOT323	BC557A
3EM	MMBTH10L	Mot	N	SOT23	VHF amp 650MHz fT
3Ep	BC857A	Phi	N	SOT23	BC557A
3ER	BC857AR	Phi	R	SOT23R	BC557A
3Et	BC857A	Phi	N	SOT23	BC557A
3Et	BC857A	Phi	N	SOT323	BC557A
3EZ	FMMTH10	Zet	N	SOT23	nnp fT 650MHz
3F	BC857B	Phi	N	SOT23	BC557B
3F	BC857BT	Phi	N	SOT416	BC557B
3F-	BC857BW	Phi	N	SOT323	BC557B
3Fp	BC857B	Phi	N	SOT23	BC557B
3FR	BC857BR	Phi	R	SOT23R	BC557B
3Fs	BC857B	Sie	N	SOT23	BC557B
3Ft	BC857B	Phi	N	SOT23	BC557B
3Ft	BC857BW	Phi	N	SOT323	BC557B
3Ft	BC857BS	Phi	N	SOT363	BC557B
3G	BC857C	Phi	N	SOT23	BC557C
3G	BC857C	Phi	N	SOT23	BC557C
3G	MMBTH11	NS	N	SOT23	-
3G	MGSF3454X	Mot	DK	TSOP6	n-ch enh tmosfet 1.75A
3G-	BC857CW	Phi	N	SOT323	BC557C
3Gp	BC857C	Phi	N	SOT23	BC557C
3GR	BC857CR	Phi	R	SOT23R	BC557CR
3Gs	BC857C	Sie	N	SOT23	BC557C
3Gt	BC857C	Phi	N	SOT23	BC557C
3Gt	BC857CW	Phi	N	SOT323	BC557C
3H	MMBTH30	NS	N	SOT23	-
3H-	BC857CW	Phi	N	SOT323	BC557
3Hp	BC857C	Phi	N	SOT23	BC557
3Ht	BC857C	Phi	N	SOT23	BC557
3Ht	BC857CW	Phi	N	SOT323	BC557
3J	MMBTH69	Mot	N	SOT23	pnp UHF fT 2GHz
3J	BC858A	Phi	N	SOT23	BC558A
3Jp	BCV62A	Phi	VQ	SOT143	pnp current mirror hFe 180
3JR	BC858AR	Phi	R	SOT23R	BC558A
3Js	BC858A	Sie	N	SOT23	BC558A
3Js	BCV62A	Sie	VQ	SOT143	pnp current mirror hFe 180
3K	BC858B	Phi	N	SOT23	BC558B
3Kp	BCV62B	Phi	VQ	SOT143	nnp current mirror hFe 290
3KR	BC858BR	Phi	R	SOT23R	BC558B
3Ks	BCV62B	Sie	VQ	SOT143	nnp current mirror hFe 290



贴片三极管上的印字，与真实名称的对照表.txt

3L	BC858C	Phi	N	SOT23	BC558C
3Lp	BCV62C	Phi	VQ	SOT143	pnnp current mirror hFe 520
3LR	BC858CR	Phi	R	SOT23R	BC558C
3Ls	BCV62C	Sie	VQ	SOT143	pnnp current mirror hFe 520
3M	BC858	Phi	N	SOT23	BC558
3M	FMMT5087R		Zet	R	SOT23R 2N5087 BC322
3Mp	BCV62	Phi	VQ	SOT143	pnnp current mirror
3Ms	BCV62	Sie	VQ	SOT143	pnnp current mirror
3N	MMBT4402		Nat	N	SOT23 2N4402 pnp
3P	FMT2222AR		Zet	R	SOT23R 2N2222A
3R	MMBT5571		Nat	N	SOT23 pnp sw 850MHz
3S	MMBT5551		Nat	N	SOT23 npn 160V
3T	HT3	Zet	N	SOT23	npn 80V 100mA
3V0	PZM3.0NB	Phi	C	SOT346	3.0V 300mW Zener
3V3	PZM3.3NB	Phi	C	SOT346	3.3V 300mW Zener
3V6	PZM3.6NB	Phi	C	SOT346	3.6V 300mW Zener
3V9	PZM3.9NB	Phi	C	SOT346	3.9V 300mW Zener
3W	FMMT-A12		Zet	N	- MPSA12
3Y3	BZV49-C3V3	Phi	0	SOT89	3.3V 1W zener
3Y6	BZV49-C3V6	Phi	0	SOT89	3.6V 1W zener
3Y9	BZV49-C3V9	Phi	0	SOT89	3.9V 1W zener
4 (red)	BB57-03W		Sie	I	SOD323 Varicap
4 (white)	BAS140W		Sie	I	SOD323 40V 120mA sw schottky
4 (yellow)	BB644		Sie	I	SOD323 Varicap 42-2.5pF
41A	FMMT491A		Zet	N	SOT23 npn 40v 1A max
41D	BAT14-115D		Sie	CY	SOT173 40GHz schottky dual
42D	BAT14-025D		Sie	CY	SOT173 4GHz schottky dual
43V	PZM43NB	Phi	C	SOT346	43V 0.3W zener
43Y	BZV49-C43	Phi	0	SOT89	43V 1W zener
45D	BAT14-055D		Sie	CY	SOT173 8GHz schottky dual
47V	PZM47NB	Phi	C	SOT346	47V 0.3W zener
47Y	BZV49-C47	Phi	0	SOT89	47V 1W zener
49D	BAT14-095D		Sie	CY	SOT173 18GHz schottky dual
4A	MMBV109	Mot	C	SOT23	MV209 varicap
4A	FMMV109	Zet	C	SOT23	MV209 varicap
4A	HD3A	Zet	C	-	75V 100mA sw diode
4A	BC859A	ITT	N	SOT23	BC559A
4A3	PZM4.3NB2A	Phi	A	SOT346	dual ca 4.3V Zener
4A7	PZM4.7NB2A	Phi	A	SOT346	dual ca 4.7V Zener
4Ap	BC859A	Phi	N	SOT23	BC559A
4AR	BC859AR	Phi	R	SOT23R	BC559A
4As	BC859AW	Sie	N	SOT323	BC559A
4As	BC859A	Sie	N	SOT23	BC559A
4B	MMBV432	Mot	B	-	dual cc varicap 1.5-45pF
4B	BC859B	ITT	N	SOT23	BC559B
4B-	BC859BW	Phi	N	SOT323	BC559B
4Bp	BC859B	Phi	N	SOT23	BC559B
4BR	BC859BR	Phi	R	SOT23R	BC559B
4Bs	BC859B	Sie	N	SOT23	BC559B
4Bs	BC859BW	Sie	N	SOT323	BC559B
4Bt	BC859B	Phi	N	SOT23	BC559B
4Bt	BC859BW	Phi	N	SOT323	BC559B
4C	BC859C	ITT	N	SOT23	BC559C
4C	MMVB3102		Mot	C	SOT23 varicap 6-35pF
4C	BC859C	Phi	N	SOT23	BC559C
4C-	BC859CW	Phi	N	SOT323	BC559C
4Cp	BC859C	Phi	N	SOT23	BC559C
4CR	BC859CR	Phi	R	SOT23R	BC559C
4Cs	BC859C	Sie	N	SOT23	BC559C
4Cs	BC859CW	Sie	N	SOT323	BC559C
4Ct	BC859C	Phi	N	SOT23	BC559C
4Ct	BC859CW	Phi	N	SOT323	BC559C
4D	BC859B	Phi	N	SOT23	BC559B
4D	MMBV3401		Mot	C	SOT23 VHF pin diode
4D	HD3A	Zet	C	SOT23	sw diode 75V 100mA
4D-	BC859W	Phi	N	SOT323	BC559B
4Dt	BC859W	Phi	N	SOT323	BC559B
4E	BC860A	Phi	N	SOT23	BC560A
4E	FMMT-A92		Zet	N	SOT23 MPSA92
4E	MMBV105G		Mot	C	SOT23 MV105 varicap
4ER	BC860AR	Phi	R	SOT23R	BC560A
4F	MMBD353	Mot	Z	SOT23	dual MBD101
4F	BC860B	Phi	N	SOT23	BC560B
4F	Gali-4F	MC	AZ	SOT89	DC-4GHz MMIC amp 15 dBm o/p
4F-	BC860BW	Phi	N	SOT323	BC560B



贴片三极管上的印字，与真实名称的对照表.txt

4Fp	BC860B	Phi	N	SOT23	BC560B	
4FR	BC860BR	Phi	R	SOT23	BC560B	
4Fs	BC860B	Sie	N	SOT23	BC560B	
4Fs	BC860BW	Sie	N	SOT323	BC560B	
4Ft	BC860B	Phi	N	SOT23	BC560B	
4Ft	BC860BW	Phi	N	SOT323	BC560B	
4G	MMBV2101		Mot	C	SOT23	MV2101 varicap
4G	BC860C	Phi	N	SOT23	BC560C	
4G-	BC860CW	Phi	N	SOT323	BC560C	
4Gp	BC860C	Phi	N	SOT23	BC560C	
4GR	BC860CR	Phi	R	SOT23	BC560CR	
4Gs	BC860C	Sie	N	SOT23	BC560C	
4Gs	BC860CW	Sie	N	SOT323	BC560C	
4Gt	BC860C	Phi	N	SOT23	BC560C	
4Gt	BC860CW	Phi	N	SOT323	BC560C	
4H	MMBV2103		Mot	C	SOT23	MV2103 varicap
4H-	BC860W	Phi	N	SOT323	BC560	
4Hp	BC860	Phi	N	SOT23	BC560	
4Ht	BC860W	Phi	N	SOT323	BC560	
4J	FMMT38A	Zet	N	SOT23	BCX38A	
4J	MMBV2109		Mot	C	SOT23	MV2109 varicap
4K	BAP64-04		Phi	D	-	dual series 3GHz pin diode
4K	MMSB3000		Mot	I	SOD123	Si diode 30V 0.2A
4L	BAP50-04		Phi	D	-	dual series GP RF pin diode
4M	MMBD101	Mot	C	SOT23	MBD101	schottky diode
4Ms	BAT240A	Sie	EQ	SOT143		dual schottky 250V 0.4A
4R	MMBV3700		Mot	C	SOT23	200V vhf pin diode
4S	MMBD201	Mot	C	SOT23	MBD201	
4T	MMBD301	Mot	C	SOT23	MBD301	UHF schottky diode
4U	MMBV2105		Mot	C	SOT23	MV2105 varicap
4V	MMBV2106		Mot	C	SOT23	MV2106 varicap
4V	BCW65AR	Zet	R	SOT23R	npn 32V 0.8A	
4V3	PZM4.3NB		Phi	C	SOT346	4.3V 0.3W zener
4V7	PZM4.7NB		Phi	C	SOT346	4.7V 0.3W zener
4W	MMBV2107		Mot	C	SOT23	MV2107 varicap
4W	BCW67AR	Zet	R	SOT23R	pnv 32V 0.8A	
4X	MMBV2108		Mot	C	SOT23	MV2108 varicap
4Y	MMBV2102		Mot	C	SOT23	MV2102 varicap
4Y3	BZV49-C4V3		Phi	O	SOT89	4.3V 1W zener
4Y7	BZV49-C4V7		Phi	O	SOT89	4.7V 1W zener
4Z	MMBV2104		Mot	C	SOT23	MV2104 varicap
5 (red)	BBY57-03W		Sie	I	SOD323	varicap
5 (white)	BAT60B		Sie	I		10V 3A sw Schottky
51D	BAT15-115D		Sie	CY	SOT173	40GHz schottky dual
51V	PZM51NB	Phi	C	SOT346	51V 0.3W zener	
51Y	BZV49-C51		Phi	O	SOT89	51V 1W zener
52D	BAT15-025D		Sie	CY	SOT173	4GHz schottky dual
53s	BAT17	Sie	C	SOT23		schottky diode 4V 100mA
54s	BAT17-04		Sie	D	SOT23	dual series BAT17
54s	BAT17-04W		Sie	D	SOT323	dual series BAT17
55D	BAT15-055D		Sie	CY	SOT173	8GHz schottky dual
55s	BAT17-05		Sie	A	SOT23	dual ca BAT17
55s	BAT17-05W		Sie	A	SOT323	dual ca BAT17
56s	BAT17-06		Sie	B	SOT23	dual cc BAT17
56s	BAT17-06W		Sie	B	SOT323	dual cc BAT17
56V	PZM56NB	Phi	C	SOT346	56V 0.3W zener	
56Y	BZV49-C56		Phi	O	SOT89	56V 1W zener
57s	BAT17-07		Sie	S	SOT143	dual BAT17
59D	BAT15-095D		Sie	CY	SOT173	18GHz schottky dual
5A	BC807-16		Phi	N	SOT23	BC327-16
5A	BSS123	Mot	M	SOT23		n-ch tmosfet Vds 100V
5A	MMBD6050		Mot	C	SOT23	sw diode 70V 0.2A
5A	FMD6050		Zet	C	SOT23	sw diode 70V 100mA
5A-	BC807-16W		Phi	N	SOT323	BC327-16
5A1	PZM5.1NB2A		Phi	A	SOT346	dual ca 5.1V 0.3W zener
5A6	PZM5.6NB2A		Phi	A	SOT346	dual ca 5.6V 0.3W zener
5Ap	BC807-16		Phi	N	SOT23	BC327-16
5AR	BC807-16R		Phi	R	SOT23R	BC327-16
5As	BC807-16		Sie	N	SOT23	BC327-16
5As	BC807-16W		Sie	N	SOT323	BC327-16
5At	BC807-16		Phi	N	SOT23	BC327-16
5At	BC807-16W		Phi	N	SOT323	BC327-16
5B	MMBT4123		Mot	N	SOT23	2N4123
5B	BC807-25		SGS	N	SOT23	BC327-25
5B	MMBD6100		Mot	B	SOT23	cc dual diode 70V 0.2A



贴片三极管上的印字，与真实名称的对照表.txt

5B	FMMD6100	Zet	B	SOT23	cc dual diode 70V 0.2A
5B-	BC807-25W	Phi	N	SOT323	BC327-25
5BM	MMBD6100	Mot	B	SOT23	cc dual diode 70V 0.2A
5Bp	BC807-25	Phi	N	SOT23	BC327-25
5BR	BC807-25R	Phi	R	SOT23R	BC327-25
5Bs	BC807-25	Sie	N	SOT23	BC327-25
5Bs	BC807-25W	Sie	N	SOT323	BC327-25
5Bs	BC807-25U	Sie	N	SC74	BC327-25
5Bt	BC807-25	Phi	N	SOT23	BC327-25
5Bt	BC807-25W	Phi	N	SOT323	BC327-25
5C	BC807-40	SGS	N	SOT23	BC327-40
5C	MMBD7000	Mot	D	SOT23	2 ser diodes 100V 0.2A
5C	FMMD7000	Zet	D	SOT23	2 ser diodes 70V 200mA
5C-	BC807-40W	Phi	N	SOT323	BC327-40
5Cp	BC807-40	Phi	N	SOT23	BC327-40
5CR	BC807-40R	Phi	R	SOT23E	BC327-40
5Cs	BC807-40	Sie	N	SOT23	BC327-40
5Cs	BC807-40W	Sie	N	SOT323	BC327-40
5Ct	BC807-40	Phi	N	SOT23	BC327-40
5Ct	BC807-40W	Phi	N	SOT323	BC327-40
5D	FMMD914	Zet	C	SOT23	1N914
5D	MMBD914	Mot	C	SOT23	1N914
5D	MMSD914	Mot	I	SOD123	1N914
5D	HD2A	Zet	B		dual cc HD2 75V 100mA
5D-	BC807W	Phi	N	SOT323	BC327
5Dp	BC807	Phi	N	SOT23	BC327
5Dt	BC807	Phi	N	SOT23	BC327
5Dt	BC807W	Phi	N	SOT323	BC327
5E	BC808-16	Phi	N	SOT23	BC328-16
5E	FMMT-A43R	Zet	R	SOT23R	MPSA43
5E	BC808-16	Phi	N	SOT23	BC328-16
5ER	BC808-16R	Phi	R	SOT23R	BC328-16
5Es	BC808-16	Sie	N	SOT23	BC328-16
5Es	BC808-16W	Sie	N	SOT323	BC328-16
5F	BC808-25	Phi	N	SOT23	BC328-25
5F	MMBD501	Mot	C	SOT23	MBD501 hot carrier diode
5F	Gali-5F	MC	AZ	SOT89	DC-4GHz MMIC amp 20 dB gain
5FR	BC808-25R	Phi	R	SOT23R	BC328-25
5Fs	BC808-25	Sie	N	SOT23	BC328-25
5Fs	BC808-25W	Sie	N	SOT323	BC328-25
5G	BC808-40	Phi	N	SOT23	BC328-40
5G	MMBD353	Mot	D		dual series MBD101
5GR	BC808-40R	Phi	R	SOT23R	BC328-40
5Gs	BC808-40	Sie	N	SOT23	BC328-40
5Gs	BC808-40W	Sie	N	SOT323	BC328-40
5H	MMBD701	Mot	C	SOT23	MBD701 UHF schottky diode
5H	MMBD4148	Mot	C	SOT23	1N4148
5Hp	BC808	Phi	N	SOT23	BC328
5HZ	BC808	Zet	N	SOT23	BC328
5I	MMSD4148	Mot	C		1N4148
5J	FMMT38B	Zet	N		BCX38B
5K	MMBV809	Mot	C	SOT23	Hyperabrupt varicap
5Kp	BAP64-05	Phi	B		dual cc 3GHz RF pin diode
5L	MMBV609	Mot	B	SOT23	dual cc Hyperabrupt varicap
5N	MMBD452L	Mot	D	SOT23	series UHF schottky diodes
5P	FMMT2907AR	Zet	R	SOT23R	2N2907A
5T	BCW66GR	Sie	R	SOT23R	nnp 45V 0.8A 350mW
5V	BCW65BR	Zet	R	SOT23R	nnp 32V 0.8A
5V1	PZM5.1NB	Phi	C	SOT346	5.1V 0.3W zener
5V6	PZM5.6NB	Phi	C	SOT346	5.6V 0.3W zener
5W	BCW67BR	Zet	R	SOT23R	pnp 32V 0.8A
5Y1	BZV49-C5V1	Phi	0	SOT89	5.1V 1W zener
5Y6	BZV49-C5V6	Phi	0	SOT89	5.6V 1W zener
6 (red)	BBY56-03W	Sie	I	SOD323	varicap
60s	BAR60	Sie	QQ	SOT143	3 pin diodes
61A	MMBF4117	Nat	F	-	n-ch jfet ultra low i/p Ig
61A	MMBF4119	Nat	F	-	n-ch jfet ultra low i/p Ig
61C	MMBF4118	Nat	F	-	n-ch jfet ultra low i/p Ig
61J	MMBF4091	Nat	F	-	n-ch jfet sw/chopper
61K	MMBF4092	Nat	F	-	n-ch jfet sw/chopper
61L	MMBF4093	Nat	F	-	n-ch jfet sw/chopper
61M	MMBF4859	Nat	F	-	n-ch jfet sw/chopper
61N	MMBF5514	Nat	F	-	p-ch jfet sw/chopper
61P	MMBF5115	Nat	F	-	p-ch jfet sw/chopper
61Q	MMBF5516	Nat	F	-	p-ch jfet sw/chopper



贴片三极管上的印字，与真实名称的对照表.txt

61s	BAR61	Sie	PQ	SOT143	3 pin diodes pi atten
61S	MMBF5458	Nat	F	-	n-ch jfet gp 2N5458
61T	MMBF5459	Nat	F	-	n-ch jfet gp 2N5459
61U	MMBF5461	Nat	F	-	p-ch jfet gp 2N5461
61V	MMBF5462	Nat	F	-	p-ch jfet gp 2N5462
62P	MMBFJ201	Nat	F	-	n-ch jfet gp J201
62Q	MMBFJ202	Nat	F	-	n-ch jfet gp J202
62R	MMBFJ203	Nat	F	-	n-ch jfet gp J203
62S	MMBFJ270	Nat	F	-	p-ch jfet gp J270
62T	MMBFJ271	Nat	F	-	p-ch jfet gp J271
62V	PZM62NB1	Phi	C	SOT346	62V 0.3W zener
62Y	BZV49-C62	Phi	O	SOT89	62V 1W zener
63Q	MMBFJ304	Nat	F	-	n-ch jfet vhf J304
63s	BAT64	Sie	C	SOT23	Schottky 40V 250mA gp
63s	BAT64W	Sie	C	SOT323	Schottky 40V 250mA gp
64s	BAT64-04	Sie	D	SOT23	dual ser gp Schottky 40V 250mA
64s	BAT64-04W	Sie	D	SOT323	dual ser gp Schottky 40V 250mA
65s	BAT64-05	Sie	B	SOT23	dual cc gp Schottky 40V 250mA
65s	BAT64-05W	Sie	B	SOT323	dual cc gp Schottky 40V 250mA
66s	BAT64-06	Sie	A	SOT23	dual ca gp Schottky 40V 250mA
66s	BAT64-06W	Sie	A	SOT323	dual ca gp Schottky 40V 250mA
67R	BFP67R	Tfk	WQ	-	npn Rf ft 7.5GHz 10V 50mA
67s	BAT64-07	Sie	S	SOT143	dual gp Schottky 40V 250mA
67s	BAT64-07W	Sie	S	SOT343	dual gp Schottky 40V 250mA
68V	PZM68NB1	Phi	C	SOT346	68V 0.3W zener
68Y	BZV49-C68	Phi	O	SOT89	68V 1W zener
6A	MMBF4416	Mot	F	SOT23	2N4416 n-ch vhf jfet
6A	MUN2111	Mot	N	SOT23	pnp dtr with 10k+10k
6A	MUN5111	Mot	N	SOT323	pnp dtr with 10k+10k
6A	BC817-16	Phi	N	SOT23	BC337-16
6A-	BC817-16W	Phi	N	SOT323	BC337-16
6A2	PZM6.2NB2A	Phi	A	SOT346	dual ca 6.2V 0.3W zener
6A8	PZM6.8NB2A	Phi	A	SOT346	dual ca 6.8V 0.3W zener
6Ap	BC817-16W	Phi	N	SOT23	BC337-16
6AR	BC817-16R	Phi	R	SOT23	BC337-16
6As	BC817-16	Sie	N	SOT23	BC337-16
6As	BC817-16	Sie	N	SOT323	BC337-16
6At	BC817-16	Phi	N	SOT23	BC337-16
6At	BC817-16W	Phi	N	SOT323	BC337-16
6AZ	BC817-16	Zet	N	SOT23	BC337-16
6B	MMBF5484	Mot	F	SOT23	n-ch jfet 2N5484
6B	BC817-25	Phi	N	SOT23	BC337-25
6B	MUN2112	Mot	N	SOT23	pnp dtr 22k+22k
6B	MUN5112	Mot	N	SOT323	MUN2112
6B-	BC817-25W	Phi	N	SOT323	BC337-25
6Bp	BC817-25	Phi	N	SOT23	BC337-25
6BR	BC817-25R	Phi	R	SOT23R	BC337-25
6Bs	BC817-25	Sie	N	SOT23	BC337-25
6Bs	BC817-25W	Sie	N	SOT323	BC337-25
6Bt	BC817-25	Phi	N	SOT23	BC337-25
6Bt	BC817-25W	Phi	N	SOT323	BC337-25
6BZ	BC817-25	Zet	N	SOT23	BC337-25
6C	BC817-40	Phi	N	SOT23	BC337-40
6C	MMBFU310	Mot	F	SOT23	n-ch jfet U310
6C	MUN2113	Mot	N	SOT23	pnp dtr 47k+47k
6C	MUN5113	Mot	N	SOT323	MUN2113
6C-	BC817-40W	Phi	N	SOT323	BC337-40
6Cp	BC817-40	Phi	N	SOT23	BC337-40
6CR	BC817-40R	Phi	R	SOT23R	BC337-40
6Cs	BC817-40	Sie	N	SOT23	BC337-40
6Cs	BC817-40W	Sie	N	SOT323	BC337-40
6Ct	BC817-40	Phi	N	SOT23	BC337-40
6Ct	BC817-40W	Phi	N	SOT323	BC337-40
6CZ	BC817-40	Zet	N	SOT23	BC337-40
6D	MMBF5457	Mot	F	SOT23	2N5457 n-ch jfet
6D	MUN2114	Mot	N	SOT23	pnp dtr 10k+47k
6D	MUN5114	Mot	N	SOT323	MUN2114
6D-	BC817W	Phi	N	SOT323	BC337
6Dp	BC817	Phi	N	SOT23	BC337
6Dt	BC817	Phi	N	SOT23	BC337
6Dt	BC817W	Phi	N	SOT323	BC337
6DZ	BC817	Zet	N	SOT23	BC337
6E	FMMT-A93R	Zet	R	SOT23R	MPSA93
6E	MMBF5460	Mot	F	SOT23	p-ch jfet 2N5460
6E	BC818-16	Phi	N	SOT23	BC338-16



贴片三极管上的印字，与真实名称的对照表.txt

6E	MUN2115	Mot	N	SOT23	pnp dtr R1 10k
6E	MUN5115	Mot	N	SOT323	MUN2115
6ER	BC818-16R		Phi	R	SOT23 BC338-16
6Es	BC818-16		Sie	N	SOT23 BC338-16
6Es	BC818-16W		Sie	N	SOT323 BC338-16
6EZ	BC818-16		Zet	N	SOT23 BC338-16
6F	MMBF4860		Mot	F	SOT23 2N4860 n-ch jfet
6F	BC818-25		Phi	N	SOT23 BC338-25
6F	MUN2116	Mot	N	SOT23	pnp dtr R1 4k7
6F	MUN5116	Mot	N	SOT323	MUN2116
6F	Gali-6F	MC	AZ	SOT89	DC-4GHz MMIC amp 12 dB gain
6FR	BC818-25R		Phi	R	SOT23R BC338-25
6Fs	BC818-25		Sie	N	SOT23 BC338-25
6Fs	BC818-25W		Sie	N	SOT323 BC338-25
6FZ	BC818-25		Zet	N	SOT23 BC338-25
6G	BC818-40		Phi	N	SOT23 BC338-40
6G	MMBF4393		Mot	F	SOT23 n-ch jfet 2N4393
6G	MUN2130	Mot	N	SOT23	pnp dtr 1k0+1k0
6G	MUN5130	Mot	N	SOT323	"ial">MUN2130 "
6GR	BC818-40R		Phi	R	SOT23 BC338-40
6Gs	BC818-40		Sie	N	SOT23 BC338-40
6Gs	BC818-40W		Sie	N	SOT323 BC338-40
6GZ	BC818-40		Zet	N	SOT23 BC338-40
6H	MMBF5486		Mot	F	SOT23 n-ch jfet 2N5486
6H	MUN2131	Mot	N	SOT23	pnp dtr 2k2 +2k2
6H	MUN5131	Mot	N	SOT323	MUN2121
6Hp	BC818		Phi	N	SOT23 BC338
6HZ	BC818		Zet	N	SOT23 BC338
6J	MMBF4391		Mot	F	SOT23 n-ch jfet 2N4391
6J	MUN2132	Mot	N	SOT23	pnp dtr 4k7+ 4k7
6J	MUN5132	Mot	N	SOT323	MUN2132
6K	MMBF4932		Mot	F	SOT23 n-ch jfet 2N4932
6K	MUN2133	Mot	N	SOT23	pnp dtr 4k7+ 47k
6K	MUN5133	Mot	N	SOT323	MUN2133
6L	MMBF5459		Mot	F	SOT23 n-ch jfet 2N5459
6L	MUN2134	Mot	N	SOT23	pnp dtr 22k+47k
6L	MUN5134	Mot	N	SOT323	MUN2134
6M	MMBF5485		Nat	F	SOT23 n-ch jfet vhf 2N5485
6N	MMBF4861		Nat	F	SOT23 n-ch jfet sw/chopper
6P	MMBFJ111		Nat	F	- J111 n-ch jfet
6P	BCX71HR		Phi	R	SOT23R BCX79
6P	MMBFJ113		Nat	F	- J113 n-ch jfet
6Q	MMBFJ305		Nat	F	- n-ch jfet vhf J305
6R	MMBFJ112		Nat	F	- J112 n-ch jfet
6S	MMBFJ176		Nat	F	- J176 n-ch jfet
6S	MMSD71		Mot	C	- gp Si diode
6T	BCW68GR		Sie	R	- pnp 45V 0.8A 350mW
6T	MMBFJ310		Mot	F	SOT23 uhf n-ch jfet J310
6U	MMBFJ309		Nat	F	SOT23 uhf n-ch jfet J309
6V	BCW65CR		Zet	R	SOT23R npn 32V 0.8A
6V	MMBFJ174		Nat	F	- J174 p-ch jfet sw/chopper
6V2	PZM6.2NB		Phi	C	SOT346 6.2V 0.3W zener
6V8	PZM6.8NB		Phi	C	SOT346 6.8V 0.3W zener
6W	BCW67CR		Zet	R	SOT23R pnp32V 0.8A
6W	MMBFJ175		Mot	F	SOT23 J175 p-ch jfet
6X	MMBFJ174		Nat	F	- J174 p-ch jfet sw/chopper
6Y	MMBFJ177		Mot	F	SOT23 J177 p-ch jfet
6Y2	BZV49-C6V2		Phi	O	SOT89 6.2V 1W zener
6Y8	BZV49-C6V8		Phi	O	SOT89 6.8V 1W zener
6Z	MMBF170		Mot	M	SOT23 tmosfet n-ch Vds 60V
7 (white)	BBY55-02W		Sie	I	SCD80 UHF Varicap
73-	BAS70W		Phi	C	SOT323 schottky diode 70V 50mA
73p	BAS70		Phi	C	SOT23 schottky diode 70V 50mA
73s	BAS70		Sie	C	SOT23 schottky diode 70V 50mA
73S	BFQ73S		Sie	CX	SOT173 npn fT 5.3GHz 15V 100mA
73t	BAS70		Phi	C	SOT23 schottky diode 70V 50mA
73t	BAS70W		Phi	C	SOT323 schottky diode 70V 50mA
74p	BAS70-04		Phi	D	SOT23 dual series BAS70
74s	BAS70-04		Sie	D	SOT23 dual series BAS70
74t	BAS70-04		Phi	D	SOT23 dual series BAS70
74t	BAS70-04W		Phi	D	SOT323 dual series BAS70
74t	BAS70-04W		Phi	D	SOT323 dual series BAS70
75-	BAS70-05W		Phi	B	SOT323 dual cc BAS70
75p	BAS70-05		Phi	B	SOT23 dual cc BAS70
75s	BAS70-05		Sie	B	SOT23 dual cc BAS70



贴片三极管上的印字，与真实名称的对照表.txt

75s	BAS70-05W	Sie	B	SOT323	dual cc BAS70
75t	BAS70-05W	Phi	B	SOT323	dual cc BAS70
75t	BAS70-05	Phi	B	SOT23	dual cc BAS70
75Y	BZV49-C75	Phi	O	SOT89	75V 1W zener
76-	BAS70-06W	Phi	A	SOT323	dual ca BAS70
76p	BAS70-06	Phi	A	SOT23	dual ca BAS70
76s	BAS70-06	Sie	A	SOT23	dual ca BAS70
76t	BAS70-06	Phi	A	SOT23	dual ca BAS70
76t	BAS70-06W	Phi	A	SOT323	dual ca BAS70
77s	BAS70-07	Sie	S	SOT143	dual BAS70
77s	BAS70-07	Sie	S	SOT343	dual BAS70
7A	MMBR901 Mot	N	SOT23	npn RF MRF901	
7A	MUN5211DW1	Mot	DN	SOT363	dual npn dtr 10k+10k
7A5	PZM7.5NB2A	Phi	A	SOT346	dual ca 7.5V 0.3W zener
7B	MMBR920 Mot	N	SOT23	npn RF ?MRF920	
7B	MUN5212DW1	Mot	DN	SOT363	dual npn dtr 22k+22k
7C	MMBR930 Mot	N	SOT23	npn RF ?MRF930	
7C	MUN5213DW1	Mot	DN	SOT363	dual npn dtr 47k+47k
7D	MMBR931 Mot	N	SOT23	npn RF ?MRF931	
7D	HD4A Zet	A	-	ca dual HD3A	
7D	MUN5214DW1	Mot	DN	SOT363	dual npn dtr 10k+47k
7E	FMMT-A42R	Zet	R	-	MPSA42
7E	MMBR2060	Mot	N	-	npn RF fT 1GHz Vce 30V 50mA
7E	MUN5215DW1	Mot	DN	SOT363	dual npn 10k base res
7F	MMBR4957	Mot	N	-	npn RF fT 1.2GHz 30V 30mA
7F	MUN5211DW1	Mot	DN	SOT363	dual npn dtr R1 4k7
7G	MMBR5031	Mot	N	SOT23	npn RF fT 1GHz 10V 20mA
7G	MUN5230DW1	Mot	DN	SOT363	dual npn dtr 1k0+1k0
7H	MMBR5179	Mot	N	SOT23	npn RF 2N5179/BFY90
7H	MUN5231DW1	Mot	DN	SOT363	dual npn dtr 2k2+2k2
7J	FMMT38C Zet	N	SOT23	BCX38C	
7J	MUN5232DW1	Mot	DN	SOT363	dual npn dtr 4k7+4k7
7K	MMBR2857	Mot	N	-	npn RF fT 1GHz Vce 15V 40mA
7K	MUN5233DW1	Mot	DN	SOT363	dual npn dtr 4k7+47k bias
7L	MUN5234DW1	Mot	DN	SOT3636	dual npn dtr 22k+47k bias
7M	MUN5235DW1	Mot	DN	SOT363	dual npn dtr 2k2+47k bias
7M	MMBR521L	Mot	N	SOT23	pnp RF MRF521
7M	BCW66HR Zet	R	SOT23R	npn 45V 0.8A	
7N	MMBR941BL	Mot	N	SOT23	npn RF fT 8GHz MRF941
7N	BCW68HR Zet	R	SOT23	pnp 45V 0.8A	
7P	BCW66FR SGS	R	SOT23R	npn 45V 0.8A 350mW	
7P	MMBR911L	Mot	N	SOT23	npn RF fT 6GHz MRF911
7R	MMBR536 Mot	N	-	npn RF MRF536	
7T	BCW68FR Zet	R	SOT23R	pnp 45V 0.8A	
7V5	PZM7.5NB	Phi	C	SOT346	7.5V 0.3W zener
7X	MMBR571L	Mot	N	SOT23	npn RF fT 8GHz MRF571
7Y	MMBR941L	Mot	N	SOT23	npn RF fT 8GHz MRF941
7Y5	BZV49-C7V5	Phi	O	SOT89	7.5V 1W zener
7Z	MMBR951L	Mot	N	SOT23	npn RF fT7.5GHz MRF951
8 (yellow)	BBY58-03W	Sie	I	SOD323	varicap
81A	MMBZ5250B	Mot	C	SOT23	20V zener 0.225W
81A	PMBZ5250B	Phi	C	SOT23	20V zener 0.225W
81B	MMBZ5251B	Mot	C	SOT23	22V zener 0.225W
81B	PMBZ5251B	Phi	C	SOT23	22V zener 0.225W
81C	MMBZ5252B	Mot	C	SOT23	24V zener 0.225W
81C	PMBZ5252B	Phi	C	SOT23	24V zener 0.225W
81D	MMBZ5253B	Mot	C	SOT23	25V zener 0.225W
81D	PMBZ5253B	Phi	C	SOT23	25V zener 0.225W
81E	MMBZ5254B	Mot	C	SOT23	27V zener 0.225W
81E	PMBZ5254B	Mot	C	SOT23	27V zener 0.225W
81F	MMBZ5255B	Mot	C	SOT23	28V zener 0.225W
81F	PMBZ5255B	Sie	C	SOT23	28V zener 0.225W
81G	MMBZ5256B	Mot	C	SOT23	30V zener 0.225W
81G	PMBZ5256B	Phi	C	SOT23	30V zener 0.225W
81H	MMBZ5257B	Mot	C	SOT23	33V zener 0.225W
81H	PMBZ5257B	Phi	C	SOT23	33V zener 0.225W
82P	BFP182T Tfk	X	-	npn RF fT 7.5GHz 10V 35mA	
83P	BFP183T Tfk	X	-	npn RF fT 7.4GHz 10V 65mA	
83s	BAT68 Sie	C	SOT23	gp Schottky 8V 130mA	
83s	BAT68W Sie	C	SOT323	gp Schottky 8V 130mA	
84s	BAT68-04	Sie	D	SOT23	dual ser gp Schottky 8V 130mA
84s	BAT68-04W	Sie	D	SOT323	dual ser gp Schottky 8V 130mA
85s	BAT68-05	Sie	B	SOT23	gp dual cc Schottky 8V 130mA
85s	BAT68-05W	Sie	B	SOT323	gp dual cc Schottky 8V 130mA
86s	BAT68-06	Sie	A	SOT23	gp dual ca Schottky 8V 130mA



贴片三极管上的印字，与真实名称的对照表.txt

86s	BAT68-06W	Sie	A	SOT323	gp dual ca Schottky 8V 130mA
87s	BAT68-07	Sie	S	SOT143	gp dual schottky 8V 130mA
8A	NJM78L02A	NJR	KQ	SOT89	78L 2.0V 0.1A regulator
8A	MMBZ5226B	Mot	C	SOT23	3.3V zener 0.225W
8A	MUN2211 Mot	N	SOT23	npn dtr	10k +10k
8A	MUN5211 Mot	N	SOT323	npn dtr	10k +10k
8A2	PZM8. 2NB2A	Phi	C	SOT23	dual ca 8.2V 0.3W zener
8B	NJM78L03A	NJR	KQ	SOT89	78L 3.0V 0.1A regulator
8B	MMBZ5227B	Mot	C	SOT23	3.6V zener 0.225W
8B	MUN2212 Mot	N	SOT23	npn dtr	22k+22k
8B	MUN5212 Mot	N	SOT323	npn dtr	22k+22k
8C	NJM78L05A	NJR	KQ	SOT89	78L 5.0V 0.1A regulator
8C	MMBZ5228B	Mot	C	SOT23	3.9V zener 0.225W
8C	MUN2213 Mot	N	SOT23	npn dtr	47k + 47k
8C	MUN5213 Mot	N	SOT323	npn dtr	47k + 47k
8D	MUN2214 Mot	N	SOT23	npn dtr	10k + 47k
8D	MUN5214 Mot	N	SOT323	MUN2214	
8E	NJM78L06A	NJR	KQ	SOT89	78L 6.0V 0.1A regulator
8E	FMNT-A92R	Zet	R	SOT23R	MPSA92
8E	MMBZ5230B	Mot	C	SOT23	4.7V zener 0.225W
8E	MUN2215 Mot	N	SOT23	npn dtr	R1 10k
8E	MUN5215 Mot	N	SOT323	npn dtr	R1 10k
8F	NJM78L07A	NJR	KQ	SOT89	78L 7.0V 0.1A regulator
8F	MMBZ5231B	Mot	C	SOT23	5.1V zener 0.225W
8F	MUN2216 Mot	N	SOT23	npn dtr	R1 4k7
8F	MUN5216 Mot	N	SOT323	MUN2216	
8G	NJM78L08A	NJR	KQ	SOT89	78L 8.0V 0.1A regulator
8G	MMBZ5232B	Mot	C	SOT23	5.6V zener 0.225W
8G	MUN2230 Mot	N	SOT23	npn dtr	1k0+1k0
8G	MUN5230 Mot	N	SOT323	npn dtr	1k0+1k0
8H	NJM78L09A	NJR	KQ	SOT89	78L 9.0V 0.1A regulator
8H	MMBZ5233B	Mot	C	SOT23	6.0V zener 0.225W
8H	MUN2231 Mot	N	SOT23	npn dtr	2k2+2k2
8H	MUN5231 Mot	N	SOT323	npn dtr	2k2+2k2
8J	NJM78L10A	NJR	KQ	SOT89	78L 10V 0.1A regulator
8J	MMBZ5234B	Mot	C	SOT23	6.2V zener 0.225W
8J	MUN2232 Mot	N	SOT23	npn dtr	4k7+ 4k7
8J	MUN5232 Mot	N	SOT323	npn dtr	4k7+ 4k7
8K	NJM78L12A	NJR	KQ	SOT89	78L 12V 0.1A regulator
8K	MMBZ5235B	Mot	C	SOT23	6.8V zener 0.225W
8K	MUN2233 Mot	N	SOT23	npn dtr	4k7+ 47k
8K	MUN5233 Mot	N	SOT323	npn dtr	4k7+ 47k
8L	NJM78L15A	NJR	KQ	SOT89	78L 15V 0.1A regulator
8L	MMBZ5236B	Mot	C	SOT23	7.5V zener 0.225W
8L	MUN2234 Mot	N	SOT23	npn dtr	22k + 47k
8L	MUN5234 Mot	N	SOT323	npn dtr	22k + 47k
8M	NJM78L18A	NJR	KQ	SOT89	78L 18V 0.1A regulator
8M	MMBZ5237B	Mot	C	SOT23	8.2V zener 0.225W
8N	NJM78L20A	NJR	KQ	SOT89	78L 20V 0.1A regulator
8N	MMBZ5238B	Mot	C	SOT23	8.7V zener 0.225W
8P	NJM78L24A	NJR	KQ	SOT89	78L 24V 0.1A regulator
8P	MMBZ5239B	Mot	C	SOT23	9.1V zener 0.225W
8Q	MMBZ5240B	Mot	C	SOT23	10V zener 0.225W
8R	MMBZ5241B	Mot	C	SOT23	11V zener 0.225W
8S	MMBZ5242B	Mot	C	SOT23	12V zener 0.225W
8T	MMBZ5243B	Mot	C	SOT23	13V zener 0.225W
8U	MMBZ5244B	Mot	C	SOT23	14V zener 0.225W
8V	MMBZ5245B	Mot	C	SOT23	15V zener 0.225W
8V2	PZM8. 2NB	Phi	C	SOT23	8.2V 0.3W zener
8W	MMBZ5246B	Mot	C	SOT23	16V zener 0.225W
8X	MMBZ5247B	Mot	C	SOT23	17V zener 0.225W
8Y	MMBZ5248B	Mot	C	SOT23	18V zener 0.225W
8Y2	BZV49-C8V2	Phi	O	SOT89	8.2V 1W zener
8Z	NJM78L62A	NJR	KQ	SOT89	78L 6.2V 0.1A regulator
8Z	MMBZ5249B	Mot	C	SOT23	19V zener 0.225W
91A	FMNT730A	Zet	N	SOT23	pnp 40V 1A 0.5W fT 150 MHz
92V	BFP92A Tfk	W	-	npn RF	6GHz 16V 30mA
9A	FMNT2369AR	Zet	R	SOT23	2N2369A
9A	DTA125TUA	Roh	N	SC70	pnp dtr R1 200k 50V 100mA
9A	DTA125TKA	Roh	N	SC59	pnp dtr R1 200k 50V 100mA
9A	PLVA650A	Phi	C	SOT23	5.0V avalanche reg diode
9A1	PZM9. 1NB2A	Phi	A	SOT346	dual ca 9.1V 0.3W zener
9B	NJM79L03UA	NJR	KQR	SOT89	79L reg 3.0V 0.1A
9B	PLVA653A	Phi	C	SOT23	5.3V avalanche reg diode
9C	NJM79L05UA	NJR	KQR	SOT89	79L reg 5.0V 0.1A



贴片三极管上的印字，与真实名称的对照表.txt

9C	PLVA656A	Phi	C	SOT23	5.6V avalanche reg diode
9D	PLVA659A	Phi	C	SOT23	5.9V avalanche reg diode
9E	NJM79L06UA	NJR	KQR	SOT89	79L reg 6.0V 0.1A
9E	PLVA662A	Phi	C	SOT23	6.2V avalanche reg diode
9F	PLVA665A	Phi	C	SOT23	6.5V avalanche reg diode
9G	NJM79L08UA	NJR	KQR	SOT89	79L reg 8.0V 0.1A
9G	PLVA668A	Phi	C	SOT23	6.8V avalanche reg diode
9H	NJM79L09UA	NJR	KQR	SOT89	79L reg 9.0V 0.1A
9J	PLVA2650A	Phi	A	SOT23	dual ca 5.0V reg diode
9K	NJM79L12UA	NJR	KQR	SOT89	79L reg 12V 0.1A
9K	PLVA2653A	Phi	A	SOT23	dual ca 5.3V reg diode
9L	NJM79L15UA	NJR	KQR	SOT89	79L reg 15V 0.1A
9L	PLVA2656A	Phi	A	SOT23	>dual 5.60V reg diode
9M	NJM79L18UA	NJR	KQR	SOT89	79L reg 18V 0.1A
9M	PLVA2659A	Phi	A	SOT23	dual ca 5.9V reg diode
9N	PLVA2662A	Phi	A	SOT23	dual ca 6.2V reg diode
9O	PLVA2665A	Phi	A	SOT23	dual ca 6.5V reg diode
9P	NJM79L24UA	NJR	KQR	SOT89	79L reg 24V 0.1A
9P	PLVA2668A	Phi	A	SOT23	dual ca 6.8V reg diode
9P	BCX70HR Zet	R	SOT23	BCX70H	
9R	FMMT2369R	Zet	R	SOT23	2N2369
9V1	PZM9.1NB	Phi	C	SOT346	9.1V 0.3W zener
9Y1	BZV49-C9V1	Phi	O	SOT89	9.1V 1W zener
A	MRF947 Mot	N	SOT323	nnp RF 8 GHz	
A	BA892 Sie	I	SCD80	35V 100mA pin	
A	1SS355 Roh	I	USM	100V 50mA sw	
A0	HSMS-2800	HP	C	SOT23	HP2800 schottky
A0	HSMS-280B	HP	C	SOT323	HP2800 schottky
A03	VAM-03 MC	AQ	-	modamp MAR 3 Similar	
A06	VAM-06 MC	AQ	-	modamp MAR 6 Similar	
A07	VAM-07 MC	AQ	-	modamp MAR 7 Similar	
A1	HSMS-2801	HP	K	-	HP2800 schottky
A1	BAW56W Phi	A	SOT323	dual ca BAW62 (1N4148)	
A1	BAW56 Phi	A	SOT23	dual ca BAW62 (1N4148)	
A1	BAW56 Phi	A	SOT23	dual ca BAW62 (1N4148)	
A11	MMBD1501A	Fch	C	SOT23	180V 200mA diode
A13	MMBD1503A	Fch	D	SOT23	180V 200mA dual diode series
A14	MMBD1504A	Fch	B	SOT23	180V 200mA dual diode cc
A15	MMBD1505A	Fch	A	SOT23	180V 200mA dual diode ca
A16	ZC934A Zet	C	SOT23	25-95pF hyperabrupt varicap	
A17	ZC933A Zet	C	SOT23	12-42pF hyperabrupt varicap	
A1p	BAW56 Phi	A	SOT23	dual ca BAW62 (1N4148)	
A1s	BAW56W Sie	A	SOT323	dual ca BAW62 (1N4148)	
A1s	BAW56 Sie	A	SOT23	dual ca BAW62 (1N4148)	
A1s	BAW56U Sie	A	SC74	dual ca BAW62 (1N4148)	
A1t	BAW56T Phi	A	SOT416	dual ca BAW62 (1N4148)	
A1t	BAW56S Phi	A	SOT363	dual ca BAW62 (1N4148)	
A1X	MBAW56 Mot	A	-	ditto	
A2	HSMS-2802	HP	D	SOT23	dual HP2800
A2	HSMS-280C	HP	D	SOT323	dual HP2800
A2	BAT18 Phi	C	SOT23	BA482	
A2	MMBD2836	Mot	A	SOT23	dual ca sw diode 75V
A2	CFY30 Sie	CQ	SOT143	n-ch GaAsfet 6 GHz	
A2	MBT3906DW1	Mot	DO	SOT363	dual 2N3906
A22	BAS21 Phi	C	SOD27	BAV21	
A2s	BAT18 Sie	C	SOT23	BA482	
A2X	MMBD2836	Mot	A	SOT23	dual ca sw 75V 100mA 15ns
A3	BAP64-03	Phi	I	SOD323	3 GHz pin diode
A3	HSMS-2803	HP	D	SOT23	HP2800 ser pair
A3	MMBD1005	Mot	A	SOT23	dual ca Si diode low leakage
A3	BAS16 Zet	C	-	Si sw 75V 100mA	
A3	BAT17 Phi	C	SOT23	BA481	
A3	MBT3906DW	Mot	N	SOT363	dual 2N3906
A3p	BAT17 Phi	C	SOT23	BA481	
A3t	BAT17 Phi	C	SOT23	BA481	
A3X	MMBD2835	Mot	A	SOT23	dual ca sw 35V 100mA 15nS
A4	HSMS-2804	HP	B	SOT23	dual cc HP2800 schottky
A4	BAV70W Phi	B	SOT323	dual cc BAW62	
A4p	BAV70 Phi	B	SOT23	dual cc BAW62	
A4s	BAV70W Sie	B	SOT323	dual cc BAW62	
A4s	BAV70 Sie	B	SOT23	dual cc BAW62	
A4s	BAV70T Sie	B	SOT416	dual cc BAW62	
A4s	BAV70U Sie	B	SC74	dual cc BAW62	
A4t	BAV70 Phi	B	SOT23	dual cc BAW62	
A4t	BAV70 Phi	B	SOT363	dual cc BAW62	



贴片三极管上的印字，与真实名称的对照表.txt

A4X	MBAV70	Mot	B	-	ditto	
A5	BAP51-03	Phi	I	SOD323	GP RF pin diode	
A5	HSMS-2805	HP	S	SOT143	dual HP2800 schottky	
A5	MMBD1010	Mot	B	SOT23	dual cc Si diodes	
A5	MMBD2837	Mot	B	SOT23	dual cc diodes 30V 150mA	
A51	BRY62	Phi	-	SOT143	-	
A5p	BRY61	Phi	-	SOT143	-	
A5t	BRY61	Phi	-	SOT143	-	
A6	BAS16W	Phi	C	SOT323	BAW62 (1N4148)	
A6	BAS16T	Phi	C	SOT416	BAW62 (1N4148)	
A6	BAS216	Phi	I	SOD110	BAW62 (1N4148)	
A6	MMBD2836	Mot	B	SOT23	dual sw diode cc 75V	
A6A	MMUN2111	Mot	N	SOT23	pnv dtr 10k+10k	
A6B	MMUN2112	Mot	N	SOT23	pnv dtr 22k+22k	
A6C	MMUN2113	Mot	N	SOT23	pnv dtr 47k+47k	
A6D	MMUN2114	Mot	N	SOT23	pnv dtr 100k+100k	
A6E	MMUN2115	Mot	N	SOT23	pnv dtr R1 10k	
A6F	MMUN2116	Mot	N	SOT23	pnv dtr R1 4k7	
A6G	MMUN2130	Mot	N	SOT23	pnv dtr 1k0+1k0	
A6H	MMUN2131	Mot	N	SOT23	pnv dtr 2k2+2k2	
A6J	MMUN2132	Mot	N	SOT23	pnv dtr 4k7+4k7	
A6K	MMUN2133	Mot	N	SOT23	pnv dtr 4k7+47k	
A6L	MMUN2134	Mot	N	SOT23	pnv dtr 22k+47k	
A6p	BAS16	Phi	C	SOT23	BAW62 (1N4148)	
A6p	BAS316	Phi	I	SOD323	BAW62 (1N4148)	
A6s	BAS16W	Sie	C	SOT323	BAW62 (1N4148)	
A6s	BAS16	Sie	C	SOT23	BAW62 (1N4148)	
A6s	BAS16U	Sie	C	SC74	BAW62 (1N4148)	
A6t	BAS16	Phi	C	SOT23	BAW62 (1N4148)	
A6X	MMBD2838	Mot	B	SOT23	dual sw 50V 100mA	
A7	BAV99W	Phi	D	SOT323	dual ser BAW92	
A7	BAV99	Phi	D	SOT23	dual ser BAW92	
A7	HSMS-2807	HP	RQ	SOT143	HP2800 ring quad	
A7s	BAV99	Sie	D	SOT23	dual ser BAW92	
A7s	BAV99W	Sie	D	SOT323	dual ser BAW92	
A7s	BAV99T	Sie	D	SC75	dual ser BAW92	
A7s	BAV99U	Sie	D	SC74	dual ser BAW92	
A8	HSMS-2808	HP	BQ	SOT143	HP2800 bridge quad	
A8	BAP50-03	Phi	I	SOD323	GP RF pin diode	
A8	BAS19	Phi	C	SOT23	BAV19	
A8	SI2308DS	Sil	M	SOT23	"N-ch mosfet, 60V 0.1A"	
A81	BAS20	Phi	C	SOT23	BAV20	
A82	BAS21	Phi	C	SOT23	BAV21	
A8A	MMUN2211	Mot	N	SOT23	npn dtr 10k +10k	
A8B	MMUN2212	Mot	N	SOT23	npn dtr 22k +22k	
A8C	MMUN2213	Mot	N	SOT23	npn dtr 47k+47k	
A8D	MMUN2214	Mot	N	SOT23	npn dtr 100k+100k	
A8E	MMUN2215	Mot	N	SOT23	npn dtr R1 10k	
A8F	MMUN2216	Mot	N	SOT23	npn dtr R1 4k7	
A8G	MMUN2230	Mot	N	SOT23	npn dtr 1k0 +1k0	
A8H	MMUN2231	Mot	N	SOT23	npn dtr 2k2+2k2	
A8J	MMUN2232	Mot	N	SOT23	npn dtr 4k7+4k7	
A8K	MMUN2233	Mot	N	SOT23	npn dtr 4k7+47k	
A8L	MMUN2234	Mot	N	SOT23	npn dtr 22k+47k	
A9	SI2309DS	Sil	M	SOT23	"P-ch mosfet, 60V 0.1A"	
A91	BAS17	Phi	C	SOT23	BA314	
AA	BCX51	Sie	P	SOT89	pnv 45V audio comp BCX54	
AA	BCW60A	TT	N	SOT23	BCY58-vii	
AA	ZMV829A	Zet	I	SOD323	varicap hyperabrupt 28V 8.2pF@2V	
AAA	MMBF4856	Mot	F	SOT23	2N4856 n-ch chopper jfet	
AAAA	MAX809LXR	MAX	ZB	SOT23	microproc -ve reset gen 5.0V	
AAAX	MAX2470	MAX	DT	SOT23-6	VCO Buffer Amplifiers	
AAAY	MAX2471	MAX	DT	SOT23-6	VCO Buffer Amplifiers	
AAG	MMBR951AL	Mot	N	SOT23	npn RF 8GHz	
AAH	MAX6326_R22-T	Max	ZB	SC70	microproc -ve reset gen 2.200V	
AAI	MAX6327_R22-T	Max	ZB	SC70	microproc +ve reset gen 2.200V	
AAJ	MAX6328_R22-T	Max	ZB	SC70	microproc -ve reset gen 2.200V	
AAK	MAX6410BS33-T	Max	UC4	UCSP-4	"Volt. Detect. (3.300 V /	
Push-Pull, Active-High)"						
AAL	MAX6410BS34-T	Max	UC4	UCSP-4	"Volt. Detect. (3.400 V /	
Push-Pull, Active-High)"						
AAM	MAX6410BS35-T	Max	UC4	UCSP-4	"Volt. Detect. (3.500 V /	



贴片三极管上的印字，与真实名称的对照表.txt

Push-Pull, Active-High)"					
AAN	MAX6410BS36-T	Max	UC4	UCSP-4	"Volt. Detect. (3.600 V /
Push-Pull, Active-High)"					
AAN	MAX809LXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
AAO	MAX6410BS37-T	Max	UC4	UCSP-4	"Volt. Detect. (3.700 V /
Push-Pull, Active-High)"					
AAO	MAX809MXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
AAP	MAX6410BS38-T	Max	UC4	UCSP-4	"Volt. Detect. (3.800 V /
Push-Pull, Active-High)"					
AAP	MAX809TXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
AAQ	MAX6410BS39-T	Max	UC4	UCSP-4	"Volt. Detect. (3.900 V /
Push-Pull, Active-High)"					
AAQ	MAX809SXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
AAR	MAX6410BS40-T	Max	UC4	UCSP-4	"Volt. Detect. (4.000 V /
Push-Pull, Active-High)"					
AAR	MAX809RXR	Max	ZB	SC70	microproc -ve reset gen 3.0V
AAs	BCW60A	Sie	N	SOT23	BCY58-vii
AAS	MAX6410BS41-T	Max	UC4	UCSP-4	"Volt. Detect. (4.100 V /
Push-Pull, Active-High)"					
AAS	MAX803ZXR	Max	ZB	SC70	microproc -ve reset gen 2.5V
AAT	MAX6410BS42-T	Max	UC4	UCSP-4	"Volt. Detect. (4.200 V /
Push-Pull, Active-High)"					
AAT	MAX810LXR	Max	ZB	SC70	microproc +ve reset gen 5.0V
AAU	MAX6410BS43-T	Max	UC4	UCSP-4	"Volt. Detect. (4.300 V /
Push-Pull, Active-High)"					
AAU	MAX810MXR	Max	ZB	SC70	microproc +ve reset gen 5.0V
AAV	MAX6410BS44-T	Max	UC4	UCSP-4	"Volt. Detect. (4.380 V /
Push-Pull, Active-High)"					
AAV	MAX810TXR	Max	ZB	SC70	microproc +ve reset gen 3.3V
AAW	MAX6410BS45-T	Max	UC4	UCSP-4	"Volt. Detect. (4.500 V /
Push-Pull, Active-High)"					
AAW	MAX810RXR	Max	ZB	SC70	microproc +ve reset gen 3.0V
AAX	MAX6410BS46-T	Max	UC4	UCSP-4	"Volt. Detect. (4.630 V /
Push-Pull, Active-High)"					
AAX	MAX810SXR	Max	ZB	SC70	microproc +ve reset gen 3.3V
AAZ	MAX6411BS33-T	Max	UC4	UCSP-4	"Volt. Detect. (3.300 V/Open
Drain, Active-Low)"					
AAZ	MAX810ZXR	Max	ZB	SC70	microproc +ve reset gen 2.5V
AAZ	MAX6411BS34-T	Max	UC4	UCSP-4	"Volt. Detect. (3.400 V/Open
Drain, Active-Low)"					
AAZ	MAX803LXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
AB	BCW60B	ITT	N	SOT23	BCY58-viii
AB	ZMV830A	Zet	I	SOD323	varicap hyperabrupt 28V 10pF@2V
ABA	MAX6411BS35-T	Max	UC4	UCSP-4	"Volt. Detect. (3.500 V/Open
Drain, Active-Low)"					
ABA	MAX803TXR	Max	ZB	SC70	microproc -ve reset gen 5.0V
ABAA	MAX809MXR	Max	ZB	SOT23	microproc -ve reset gen 5.0V
ABB	MAX6411BS36-T	Max	UC4	UCSP-4	"Volt. Detect. (3.600 V/Open
Drain, Active-Low)"					
ABB	MAX803MXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
ABC	MAX6411BS37-T	Max	UC4	UCSP-4	"Volt. Detect. (3.700 V/Open
Drain, Active-Low)"					
ABC	MAX803SXR	Max	ZB	SC70	microproc -ve reset gen 3.3V
ABD	MAX6411BS38-T	Max	UC4	UCSP-4	"Volt. Detect. (3.800 V/Open
Drain, Active-Low)"					
ABD	MAX803RXR	Max	ZB	SC70	microproc -ve reset gen 3.0V
ABE	MAX6411BS39-T	Max	UC4	UCSP-4	"Volt. Detect. (3.900 V/Open



贴片三极管上的印字，与真实名称的对照表.txt

Drain, Active-Low) "					
ABE	MAX803ZXR	Max	ZB	SC70	microproc -ve reset gen 2.5V
ABF	MAX6411BS40-T	Max	UC4	UCSP-4	"Volt. Detect. (4.000 V/Open
Drain, Active-Low) "					
ABF	LM4041AIX3-1.2	Max	L	SC70	1.225V 0.1% shunt V ref
ABG	MAX6411BS41-T	Max	UC4	UCSP-4	"Volt. Detect. (4.100 V/Open
Drain, Active-Low) "					
ABG	LM4041BIX3-1.2	Max	L	SC70	1.225V 0.2% shunt V ref
ABH	MAX6411BS42-T	Max	UC4	UCSP-4	"Volt. Detect. (4.200 V/Open
Drain, Active-Low) "					
ABH	LM4041DIX3-1.2	Max	L	SC70	1.225V 0.5% shunt V ref
ABI	MAX6411BS43-T	Max	UC4	UCSP-4	"Volt. Detect. (4.300 V/Open
Drain, Active-Low) "					
ABI	LM4041DIX3-1.2	Max	L	SC70	1.225V 1.5% shunt V ref
ABJ	MAX6411BS44-T	Max	UC4	UCSP-4	"Volt. Detect. (4.380 V/Open
Drain, Active-Low) "					
ABJ	LM4040AIX3-2.1	Max	L	SC70	2.048V 0.1% shunt V ref
ABK	MAX6411BS45-T	Max	UC4	UCSP-4	"Volt. Detect. (4.500 V/Open
Drain, Active-Low) "					
ABK	LM4040BIX3-2.1	Max	L	SC70	2.048V 0.2% shunt V ref
ABL	MAX6411BS46-T	Max	UC4	UCSP-4	"Volt. Detect. (4.640 V/Open
Drain, Active-Low) "					
ABL	LM4040CIX3-2.1	Max	L	SC70	2.048V 0.5% shunt V ref
ABM	LM4040DIX3-2.1	Max	L	SC70	2.048V 1% shunt V ref
ABN	LM4040AIX3-2.5	Max	L	SC70	2.5001% shunt V ref
ABO	LM4040BIX3-2.5	Max	L	SC70	2.500V 0.2% shunt V ref
ABp	BCW60B Phi	N	SOT23	BCY58-viii	
ABP	LM4040CIX3-2.5	Max	L	SC70	2.500V 0.5% shunt V ref
ABQ	LM4040DIX3-2.5	Max	L	SC70	2.500V 1% shunt V ref
ABR	LM4040AIX3-3.0	Max	L	SC70	3.000V 0.1% shunt V ref
ABs	BCW60B Sie	N	SOT23	BCY58-viii	
ABS	LM4040BIX3-3.0	Max	L	SC70	3.000V 0.2% shunt V ref
ABt	BCW60B Phi	N	SOT23	BCY58-viii	
ABT	LM4040CIX3-3.0	Max	L	SC70	3.000V 0.5% shunt V ref
ABU	LM4040DIX3-3.0	Max	L	SC70	3.000V 1% shunt V ref
ABV	LM4040AIX3-4.1	Max	L	SC70	4.096V 0.1% shunt V ref
ABW	LM4040BIX3-4.1	Max	L	SC70	4.096V 0.2% shunt V ref
ABX	LM4040CIX3-4.1	Max	L	SC70	4.096V 0.5% shunt V ref
ABY	LM4040DIX3-4.1	Max	L	SC70	4.096V 1% shunt V ref
ABZ	LM4040AIX3-5.0	Max	L	SC70	5.000V 0.1% shunt V ref
AC	BCX51-100	Sie	P	SOT89	45V pnp audio hfe 100
AC	BCX51-10	Phi	P	SOT89	45V pnp audio hfe 100
AC	BCW60C Phi	N	SOT23	BCY58-ix	
AC	ZMV831A Zet	I	SOD323	varicap	hyperabrupt 28V 15pF@2V
ACA	LM4040BIX3-5.0	Max	L	SC70	5.000V 0.2% shunt V ref
ACAA	MAX809TXR	Max	ZB	SOT23	microproc -ve reset gen 3.3V
ACB	LM4040CIX3-5.0	Max	L	SC70	5.000V 0.5% shunt V ref
ACC	LM4040DIX3-5.0	Max	L	SC70	5.000V 1% shunt V ref
ACE	MAX6326_R31-T	Max	ZB	SC70	microproc -ve reset gen 3.080V
ACF	MAX6347_R46-T	Max	ZB	SC70	microproc +ve reset gen 4.630V
ACH	MAX6326_R23-T	Max	ZB	SC70	microproc -ve reset gen 2.320V
ACI	MAX6326_R26-T	Max	ZB	SC70	microproc -ve reset gen 2.630V
ACJ	MAX6328_R26-T	Max	ZB	SC70	microproc -ve reset gen 2.630V
ACK	MAX6346_R44-T	Max	ZB	SC70	microproc -ve reset gen 4.380V
ACL	MAX6347_R44-T	Max	ZB	SC70	microproc +ve reset gen 4.380V
ACM	MAX6348_R46-T	Max	ZB	SC70	microproc -ve reset gen 4.630V
ACN	MAX6348_R44-T	Max	ZB	SC70	microproc -ve reset gen 4.380V
ACO	MAX6346_R46-T	Max	ZB	SC70	microproc -ve reset gen 4.630V
ACp	BCW60C Phi	N	SOT23	BCY58-ix	
ACP	MAX6326_R29-T	Max	ZB	SC70	microproc -ve reset gen 2.930V
ACQ	MAX6327_R23-T	Max	ZB	SC70	microproc +ve reset gen 2.320V
ACR	MAX6327_R26-T	Max	ZB	SC70	microproc +ve reset gen 2.630V
ACs	BCW60C Sie	N	SOT23	BCY58-ix	
ACS	MAX6327_R29-T	Max	ZB	SC70	microproc +ve reset gen 2.930V
ACt	BCW60C Phi	N	SOT23	BCY58-ix	
ACT	MAX6327_R31-T	Max	ZB	SC70	microproc +ve reset gen 3.080V
ACU	MAX6328_R23-T	Max	ZB	SC70	microproc -ve reset gen 2.320V
ACV	MAX6328_R29-T	Max	ZB	SC70	microproc -ve reset gen 2.930V



贴片三极管上的印字，与真实名称的对照表.txt

ACW	MAX6326_R31-T	Max	ZB	SC70	microproc -ve reset gen 3.080V
AD	BCX51-160	Sie	P	SOT89	45V pnp audio hfe 160
AD	BCX51-16	Phi	P	SOT89	45V pnp audio hfe 160
AD	BCW60D Phi	N	SOT23	BCY58-x	
AD	ZMV832A Zet	I	SOD323	varicap	hyperabrupt 28V 22pF@2V
ADAA	MAX809SXR	Max	ZB	SOT23	microproc -ve reset gen 3.3V
ADN	2SC3838K	Roh	N	-	nnp 11V 3.2GHz TV tuners
ADp	BCW60D Phi	N	SOT23	BCY58-x	
ADs	BCW60D Sie	N	SOT23	BCY58-x	
ADt	BCW60D Ph	N	SOT23	BCY58-x	
ADW	MAX6406BS22-T	Max	UC4	UCSP-4	"Volt. Detect. (2.200 V / Push-Pull, Active-Low)"
ADX	MAX6406BS23-T	Max	UC4	UCSP-4	"Volt. Detect. (2.320 V / Push-Pull, Active-Low)"
ADY	MAX6406BS24-T	Max	UC4	UCSP-4	"Volt. Detect. (2.400 V / Push-Pull, Active-Low)"
ADZ	MAX6406BS25-T	Max	UC4	UCSP-4	"Volt. Detect. (2.500 V / Push-Pull, Active-Low)"
AE	BCX52 Sie	P	SOT89	pnp 60V audio comp BCX55	
AE	ZMV833A Zet	I	SOD323	varicap	hyperabrupt 28V 33pF@2V
AEA	MAX6406BS26-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.630 V / Push-Pull, Active-Low)"
AEB	MAX6406BS27-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.700 V / Push-Pull, Active-Low)"
AEC	MAX6406BS28-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.800 V / Push-Pull, Active-Low)"
AED	MAX6406BS29-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.930 V / Push-Pull, Active-Low)"
AEE	MAX6406BS30-T	MAX	UC4	UCSP-4	"Volt. Detect. (3.000 V / Push-Pull, Active-Low)"
AEF	MAX6406BS31-T	MAX	UC4	UCSP-4	"Volt. Detect. (3.080 V / Push-Pull, Active-Low)"
AEG	MAX6407BS22-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.200 V / Push-Pull, Active-High)"
AEH	MAX6407BS23-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.300 V / Push-Pull, Active-High)"
AEI	MAX6407BS24-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.400 V / Push-Pull, Active-High)"
AEJ	MAX6407BS25-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.500 V / Push-Pull, Active-High)"
AEK	MAX6407BS26-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.630 V / Push-Pull, Active-High)"
AEL	MAX6407BS27-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.700 V / Push-Pull, Active-High)"
AEM	MAX6407BS28-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.800 V / Push-Pull, Active-High)"
AEN	MAX6407BS29-T	MAX	UC4	UCSP-4	"Volt. Detect. (2.930 V / Push-Pull, Active-High)"
AEN	2SC3839K	Roh	N	-	nnp 20V 2.0GHz TV tuners
AEO	MAX6407BS30-T	Max	UC4	UCSP-4	"Volt. Detect. (3.000 V / Push-Pull, Active-High)"
AEP	MAX6407BS31-T	Max	UC4	UCSP-4	"Volt. Detect. (3.000 V / Push-Pull, Active-High)"
AEQ	MAX6408BS22-T	Max	UC4	UCSP-4	"Volt. Detect. (2.200 V/Open, Active-High)"



贴片三极管上的印字，与真实名称的对照表.txt

Drain, Active-Low)"	AER	MAX6408BS23-T	Max	UC4	UCSP-4	"Volt. Detect. (2.320 V/Open
Drain, Active-Low)"	AES	MAX6408BS24-T	Max	UC4	UCSP-4	"Volt. Detect. (2.400 V/Open
Drain, Active-Low)"	AET	MAX6408BS25-T	Max	UC4	UCSP-4	"Volt. Detect. (2.500 V/Open
Drain, Active-Low)"	AEU	MAX6408BS26-T	Max	UC4	UCSP-4	"Volt. Detect. (2.630 V/Open
Drain, Active-Low)"	AEV	MAX6408BS27-T	Max	UC4	UCSP-4	"Volt. Detect. (2.700 V/Open
Drain, Active-Low)"	AEW	MAX6138AEXR12-T	Max	L	SC70-3	Shunt Voltage Ref. (output 1.2205 V / 0.1%)
	AEW	MAX6408BS28-T	Max	UC4	SC70-3	"Volt. Detect. (2.800 V/Open
Drain, Active-Low)"	AEX	MAX6138BEXR12-T	Max	L	SC70-3	Shunt Voltage Ref. (output 1.2205 V / 0.2%)
	AEX	MAX6408BS29-T	Max	UC4	UCSP-4	"Volt. Detect. (2.930 V/Open
Drain, Active-Low)"	AEY	MAX6138CEXR12-T	Max	L	SC70-3	Shunt Voltage Ref. (output 1.2205 V / 0.5%)
	AEY	MAX6408BS30-T	Max	UC4	UCSP-4	"Volt. Detect. (3.000 V/Open
Drain, Active-Low)"	AEZ	MAX6408BS31-T	Max	UC4	UCSP-4	"Volt. Detect. (3.080 V/Open
Drain, Active-Low)"	AF	ZMV834A Zet	I	SOD323	varicap	hyperabrupt 28V 47pF@2V
	AFA	MAX6138AEXR21-T	Max	L	SC70-3	Shunt Voltage Ref. (output 2.0480 V / 0.1%)
	AFA	MAX6409BS33-T	Max	-	UCSP-4	"Volt. Detect. (3.300 V / Push-Pull,
Active-Low)"	AFAA	MAX809RXR	Max	ZB	SOT23	microproc -ve reset gen 3.0V
	AFB	MAX6138BEXR21-T	Max	L	SC70-3	Shunt Voltage Ref. (output 2.0480 V / 0.2%)
	AFB	MAX6409BS34-T	Max	UC4	UCSP-4	"Volt. Detect. (3.400 V / Push-Pull,
Active-Low)"	AFC	MAX6138CEXR21-T	Max	L	SC70-3	Shunt Voltage Ref. (output 2.0480 V / 0.5%)
	AFC	MAX6409BS35-T	Max	UC4	UCSP-4	"Volt. Detect. (3.500 V / Push-Pull,
Active-Low)"	AFD	MAX6409BS36-T	Max	UC4	UCSP-4	"Volt. Detect. (3.600 V / Push-Pull,
Active-Low)"	AFE	MAX6138AEXR25-T	Max	L	SC70-3	Shunt Voltage Ref. (output 2.5000 V / 0.1%)
	AFE	MAX6409BS37-T	Max	UC4	UCSP-4	"Volt. Detect. (3.700 V / Push-Pull,
Active-Low)"	AFF	MAX6138BEXR25-T	Max	L	SC70-3	Shunt Voltage Ref. (output 2.5000 V / 0.2%)
	AFF	MAX6409BS38-T	Max	UC4	UCSP-4	"Volt. Detect. (3.800 V / Push-Pull,
Active-Low)"	AFG	MAX6138CEXR25-T	Max	L	SC70-3	Shunt Voltage Ref. (output 2.5000 V / 0.5%)
	AFG	MAX6409BS39-T	Max	UC4	UCSP-4	"Volt. Detect. (3.900 V / Push-Pull,
Active-Low)"	AFH	MAX6409BS40-T	Max	UC4	UCSP-4	"Volt. Detect. (4.000 V / Push-Pull,
Active-Low)"	AFI	MAX6138AEXR30-T	Max	L	SC70-3	Shunt Voltage Ref. (output 3.0000 V / 0.1%)
	AFI	MAX6409BS41-T	Max	UC4	UCSP-4	"Volt. Detect. (4.100 V / Push-Pull,
Active-Low)"	AFJ	MAX6138BEXR30-T	Max	L	SC70-3	Shunt Voltage Ref. (output 3.0000 V / 0.2%)
	AFJ	MAX6409BS42-T	Max	UC4	UCSP-4	"Volt. Detect. (4.200 V / Push-Pull,
Active-Low)"	AFK	MAX6138CEXR30-T	Max	L	SC70-3	Shunt Voltage Ref. (output 3.0000 V / 0.5%)
	AFK	MAX6409BS43-T	Max	UC4	UCSP-4	"Volt. Detect. (4.300 V / Push-Pull,
Active-Low)"						



贴片三极管上的印字，与真实名称的对照表.txt

AFL	MAX6409BS44-T	Max	UC4	UCSP-4	"Volt. Detect. (4.380 V / Push-Pull,
Active-Low)"					
AFM	MAX6138AEXR41-T	Max	L	SC70-3	Shunt Voltage Ref. (output 4.0960 V / 0.1%)
AFM	MAX6409BS45-T	Max	UC4	UCSP-4	"Volt. Detect. (4.500 V / Push-Pull,
Active-Low)"					
AFN	MAX6138BEXR41-T	Max	L	SC70-3	Shunt Voltage Ref. (output 4.0960 V / 0.2%)
AFN	MAX6409BS46-T	Max	UC4	UCSP-4	"Volt. Detect. (4.630 V / Push-Pull,
Active-Low)"					
AFO	MAX6138CEXR41-T	Max	L	SC70-3	Shunt Voltage Ref. (output 4.0960 V / 0.5%)
AFQ	MAX6138AEXR50-T	Max	L	SC70-3	Shunt Voltage Ref. (output 5.0000 V / 0.1%)
AFR	MAX6138BEXR50-T	Max	L	SC70-3	Shunt Voltage Ref. (output 5.0000 V / 0.2%)
AFs	BCW60FF	Sie	N	SOT23	BCY58
AFS	MAX6138CEXR50-T	Max	L	SC70-3	Shunt Voltage Ref. (output 5.0000 V / 0.5%)
AG	ZMV835A	Zet	I	SOD323	varicap hyperabrupt 28V 68pF@2V
AG	BCX70G	Phi	N	SOT23	BCY59-vii BC107
AG	BCX52-10	Sie	P	SOT89	60V npn BCX52 hfe 100
AGAA	MAX810LXR	Max	ZB	SOT23	microproc +ve reset gen 5.0V
AGp	BCX70G	Phi	N	SOT23	BCY59-vii BC107
AGs	BCX70G	Sie	N	SOT23	BCY59-vii BC107
AGt	BCX70G	Phi	N	SOT23	BCY59-vii BC107
AH	BCX70H	Phi	N	SOT23	BCY59-viii BC107B
AH	BCP53	Mot	P	SOT223	pnp amp 80V 150mA
AH	BCX53	Sie	P	SOT89	pnp 80V audio comp BCX56
AH	ZMV930	Zet	I	SOD323	2.9-8.3pF hyperabrupt varicap
AHAA	MAX810MXR	Max	ZB	SOT23	microproc +ve reset gen 5.0V
AHp	BCX70H	Phi	N	SOT23	BCY59-viii BC107B
AHs	BCX70H	Sie	N	SOT23	BCY59-viii BC107B
AHt	BCX70H	Phi	N	SOT23	BCY59-viii BC107B
AJ	BCX70J	Phi	N	SOT23	BCY59-ix BC107
AJ	ZMV931	Zet	I	SOD323	4-13.5pF hyperabrupt varicap
AJ s	BCX70J	Sie	N	SOT23	BCY59-ix BC107
AJAA	MAX810TXR	MAX	ZB	SOT23	microproc +ve reset gen 3.3V
AJp	BCX70J	Phi	N	SOT23	BCY59-ix BC107
AJt	BCX70J	Phi	N	SOT23	BCY59-ix BC107
AK	BCX70K	Phi	N	SOT23	BCY59-x BC107
AK	ZMV932	Zet	I	SOD323	5.5-17pF hyperabrupt varicap
AK	BCX53-10	Sie	P	SOT89	pnp 80V BCX53 hfe 100
AKAA	MAX810SXR	MAX	ZB	SOT23	microproc +ve reset gen 3.3V
AKp	BCX70K	Phi	N	SOT23	BCY59-x BC107
AKp	BCX70K	Phi	N	SOT23	BCY59-x BC107
AKs	BCX70K	Sie	N	SOT23	BCY59-x BC107
AL	BCX53-16	Sie	P	SOT89	80V npn BCX53 hfe 100
AL	MMBTA55L	Mot	N	SOT23	pnp 25V (MPSA55)
AL	ZMV933	Zet	I	SOD323	12-42pF hyperabrupt varicap
ALAA	MAX810SXR	MAX	ZB	SOT23	microproc +ve reset gen 3.0V
ALs	BFP405	Sie	MQ	SOT343	-
AM	MMBT3904W	Mot	N	SOT323	2N3904
AM	BCX52-16	Sie	P	SOT89	pnp 60V BCX52 hfe 160
AM	BSS64	Mot	N	SOT23	nnp 80V 0.1A ft 60MHz
AM	ZMV933A	Zet	I	SOD323	12-42pF hyperabrupt varicap
AMp	BSS64	Phi	N	SOT23	nnp 80V 0.1A ft 60MHz
AMs	BFP420	Sie	MQ	SOT343	nnp ft 25GHz 4.5V 35mA
AMs	BSS64	Sie	N	SOT23	nnp 80V 0.1A ft 60MHz
AMt	BSS64	Phi	N	SOT23	nnp 80V 0.1A ft 60MHz
AN	BCW60FN	Sie	N	SOT23	gp npn 35V 0.2A
AN	ZMV934	Zet	I	SOD323	25-95pF hyperabrupt varicap
ANs	BFP450	Sie	MQ	SOT343	nnp ft 25GHz 4.5V 100mA
AO	BCW60AR	ITT	R	SOT23R	BCY58-vii
AO	ZMV934A	Zet	I	SOD323	25-95pF hyperabrupt varicap
AP	BCW60BR	ITT	R	SOT23R	BCY58-viii
APs	BFP520	Sie	MQ	SOT343	nnp ft 40GHz 2.5V 40mA
A-Q	2PD1820AQ	Phi	N	SOT323	gp sw amp 50V npn hfe 85-170
A-Q	2PD1820AR	Phi	N	SOT323	gp sw amp 50V npn hfe 120-240
AR	BCW60CR	ITT	R	SOT23R	BCY58-ix
AR	MSD709R	Mot	N	-	pnp gp 25V
AR1	BSR40	Phi	P	SOT89	nnp 70V 1A 1.35W hfe 40-120
AR2	BSR41	Phi	P	SOT89	nnp 70V 1A 1.35W hfe 100-300
AR3	BSR42	Phi	P	SOT89	nnp 90V 1A 1.35W hfe 40-120
AR4	BSR43	Phi	P	SOT89	nnp 90V 1A 1.35W hfe 100-300
AS	BCW60DR	ITT	R	SOT23R	BCY58-x
AS	MSD709S	Mot	N	-	pnp gp 25V
A-S	2PD1820AS	Phi	N	SOT323	gp sw amp 50V npn hfe 170-340



贴片三极管上的印字，与真实名称的对照表.txt

AS1	BST50	Mot	P	SOT89	nnp darlington 0.5A 60V
AS2	BST51	Mot	P	SOT89	nnp darlington 0.5A 80V
AS3	BST52	Mot	P	SOT89	nnp darlington 0.5A 90V
AS3	BSP52	Mot	P	SOT223	nnp darlington 0.5A hfe 2000
ASs	BAT18-05		Sie	B	SOT23 dual BAT18 RF pin
AtQ	2PD1820AQ		Phi	N	SOT323 gp sw amp 50V npn hfe 85-170
AtQ	2PD1820AR		Phi	N	SOT323 gp sw amp 50V npn hfe 120-240
AtS	2PD1820AS		Phi	N	SOT323 gp sw amp 50V npn hfe 170-340
ATs	BAT18-06		Sie	A	SOT23 dual ca BAT18 RF pin
ATs	BFP540	Sie	MQ	SOT343	nnp microwave
AU	BCW60GR	ITT	R	SOT23R	BCY58
AUs	BAT18-04		Sie	D	SOT23 dual BAT18 RF pin
AV	DAN212K	Roh	C	-	80V 100mA sw
AW	BCW60HR	ITT	R	SOT23R	BCY58
AX	BCX70JR	ITT	R	SOT23R	BCY59-ix
AY	BCX70KR	ITT	R	SOT23R	BCY59-x
AY	MMBD1000		Mot	C	SOT23 Si sw diode 30V 0.2A
B	MRF957	Mot	N	SOT323	nnp RF fT 9GHz
B	BAS16-03W		Sie	I	SOD323 Varicap 18pF 1V
B	BB555	Sie	I	SCD80	Varicap 18pF 1V
B0	BZX399C4V3		Phi	I	SOD323 4.3V 0.3W zener
B0	HSMS-2810		HP	C	SOT23 HP2810 schottky
B0	HSMS-281B		HP	C	SOT323 HP2810 schottky
B08	SST6908	Sil	ZQ	-	2N6908 prot n-ch jfet
B09	SST6909	Sil	ZQ	-	2N6909 prot n-ch jfet
B1	BZX399C1V8		Phi	I	SOD323 1.8V 0.3W zener
B1	HSMS-2811		HP	K	SOT23 HP2811 schottky
B1	BAS40	Mot	C	SOT23	schottky sw diode
B10	SST6910	Sil	ZQ	-	2N6910 prot n-ch jfet
B2	BZX399C2V0		Phi	I	SOD323 2.0V 0.3W zener
B2	BSV52	Phi	N	SOT23	BSX20 12V fT 400MHz sw
B2	HSMS-2812		HP	D	SOT23 dual HP2810 schottky
B2	HSMS-281C		HP	D	SOT323 dual HP2810 schottky
B26	BF570	Phi		SOT23	-
B2p	BSV52	Phi	N	SOT23	BSX20 12V fT 400MHz sw
B2t	BSV52	Phi	N	SOT23	BSX20 12V fT 400MHz sw
B3	BZX399C2V2		Phi	I	SOD323 2.2V 0.3W zener
B3	HSMS-2813		HP	A	SOT23 dual ca HP2810 schottky
B3	MMBD717L		Mot	A	SOT323 dual ca schottky
B4	BZX399C2V4		Phi	I	SOD323 2.4V 0.3W zener
B4	BSV52R	Phi	R	SOT23R	BSX20
B4	HSMS-2814		HP	B	SOT23 dual cc HP2810 schottky
B5	BZX399C2V7		Phi	I	SOD323 2.7V 0.3W zener
B5	HSMS-2815		HP	S	SOT143 dual HP2810 schottky
B6	BZX399C3V0		Phi	I	SOD323 3.0V 0.3W zener
B6	BAT54A	Mot	A	SOT23	dual ca 30V schottky
B7	BZX399C3V3		Phi	I	SOD323 3.3V 0.3W zener
B7	HSMS-2817		HP	RQ	SOT143 HP2810 ring quad
B8	BZX399C3V6		Phi	I	SOD323 3.6V 0.3W zener
B8	HSMS-2818		HP	BQ	SOT143 HP2810 bridge quad
B9	BZX399C3V9		Phi	I	SOD323 3.9V 0.3W zener
B9	2SC4617	Mot	N	SC90	nnp gp
BA	BCX54	Sie	P	SOT89	nnp AF 45V comp BCX51
BA	BCW61A	Phi	N	SOT23	BCY78-vii
BA	DAN217	Roh	D	-	80V 100mA dual
BA	BZX399C4V7		Phi	I	SOD323 4.7V 0.3W zener
BAp	BCW61A	Phi	N	SOT23	BCY78-vii
BAt	BCW61A	Phi	N	SOT23	BCY78-vii
BB	BCW61B	Phi	N	SOT23	BCY78-viii
BB	BAR81	Sie	NQ	SOT143	Dual pin shunt switch
BB	BZX399C5V1		Phi	I	SOD323 5.1V 0.3W zener
BBp	BCW61B	Phi	N	SOT23	BCY78-viii
BBs	BCW61B	Sie	N	SOT23	BCY78-viii
BBs	BAR81W	Sie	NQ	SOT343	Dual pin shunt switch
BBt	BCW61B	Phi	N	SOT23	BCY78-viii
BC	BCW61C	Phi	N	SOT23	BCY78-ix
BC	BCX54-10		Sie Phi	P	SOT89 npn hfe100
BC	BZX399C5V6		Phi	I	SOD323 5.6V 0.3W zener
BCp	BCW61C	Phi	N	SOT23	BCY78-ix
BCs	BCW61C	Sie	N	SOT23	BCY78-ix
BCt	BCW61C	Phi	N	SOT23	BCY78-ix
BD	BCW61D	Phi	N	SOT23	BCY78-x
BD	BCX54-16		Sie	P	SOT89 npn hfe160 comp BCX51-16
BD	BZX399C6V2		Phi	I	SOD323 6.2V 0.3W zener
BD	ZHCS400	Zet	E	SOT23	40V 0.4A schottky diode



贴片三极管上的印字，与真实名称的对照表.txt

BDp	BCW61D	Phi	N	SOT23	BCY78-x
Bds	BCW61D	Sie	N	SOT23	BCY78-x
BDt	BCW61D	Phi	N	SOT23	BCY78-x
BE	BAS70	Mot	C	SOT23	schottky sw diode
BE	BCX55	Sie	P	SOT89	npn AF 60V comp BCX52
BE	BZX399C6V8	Phi	I	SOD323	6.8V 0.3W zener
BF	BCW61FF	Sie	N	SOT23	low noise BCW61
BF	BZX399C7V5	Phi	I	SOD323	7.5V 0.3W zener
BG	BCX71G	Phi	N	SOT23	BCY79-vii
BG	BCX55-10	Sie Phi	P	SOT89	npn hfe 100
BG	BZX399C8V2	Phi	I	SOD323	8.2V 0.3W zener
BGp	BCX71G	Phi	N	SOT23	BCY79-vii
BGs	BCX71G	Sie	N	SOT23	BCY79-vii
BGt	BCX71G	Phi	N	SOT23	BCY79-vii
BH	BCP56	Mot	P	SOT223	npn amp 80V 150mA
BH	BCX56	Sie	P	SOT89	npn AF 80V
BH	BZX399C9V1	Phi	I	SOD323	9.1V 0.3W zener i
BH	BCX71H	Phi	N	SOT23	BCY79-viii
BHp	BCX71H	Phi	N	SOT23	BCY79-viii
BHs	BCX71H	Sie	N	SOT23	BCY79-viii
BHt	BCX71H	Phi	N	SOT23	BCY79-viii
BJ	BCX71J	Phi	N	SOT23	BCY79-ix
BJ	BZX399C10	Phi	I	SOD323	10V 0.3W zener
BJp	BCX71J	Phi	N	SOT23	BCY79-ix
BJs	BCX71J	Sie	N	SOT23	BCY79-ix
BJt	BCX71J	Phi	N	SOT23	BCY79-ix
BK	BCP56-10	Mot	P	SOT223	npn amp 80V 150mA
BK	BCX71K	Phi	N	SOT23	BCY79
BK	BCX56-10	Sie	P	SOT89	npn hfe 100
BK	BZX399C11	Phi	I	SOD323	11V 0.3W zener
BKp	BCX71K	Phi	N	SOT23	BCY79
BKs	BCX71K	Sie	N	SOT23	BCY79
BKt	BCX71K	Phi	N	SOT23	BCY79
BL	MBD54DW	Mot	DL	SOT363	2x schottky detector diodes
BL	BCP56-16	Mot	P	SOT223	npn amp 80V 150mA
BL	BCX56-16	Sie	P	SOT89	npn hfe 160
BL	BZX399C12	Phi	I	SOD323	12V 0.3W zener
BL	BGA310	Sie	GQ	SOT143	MMIC amp 9dB @1GHz
BLs	BGA420	Sie	HQ	SOT343	MMIC amp 13 dB @1.8GHz
BM	BSS63L	Mot	N	SOT23	100v pnp comp BSS64
BM	BCX55-16	Sie	P	SOT89	npn hfe 160
BM	BGA312	Sie	GQ	SOT143	MMIC amp 11dB @1GHz
BM	BZX399C13	Phi	I	SOD323	13V 0.3W zener
BMp	BSS63	Phi	N	SOT23	100v pnp comp BSS64
BMs	BG427	Sie	HQ	SOT343	MMIC amp 18 dB @1.8GHz
BMt	BSS63	Phi	N	SOT23	100v pnp comp BSS64
BN	BZX399C15	Phi	I	SOD323	15V 0.3W zener
BN	BGA318	Sie	GQ	SOT143	MMIC amp 16dB @1GHz
BNs	BCW61FN	Sie	N	SOT23	low noise BCW61
BO	BCW61AR	Phi	N	SOT23	"BCX78, BCY78-vii"
BP	BCW61BR	Phi	N	SOT23	BCY78-viii
BP	BZX399C16	Phi	I	SOD323	16V 0.3W zener
BQ	BZX399C18	Phi	I	SOD323	18V 0.3W zener in SOD323
BQ	2PB709AQ	Phi	N	SC-59	PNP 45V 0.1A hfe 160-260
BR	BCW61CR	Phi	N	SOT23	BCY78-ix
BR	2SC2412K	Roh	N	-	npn 50V 150mA min hfe 180
BR	2SC4081	Roh	N	UMT	2SC2412K above
BR	2SC4617	Roh	N	EM3	2SC2412K above
BR	MSB1218A	Mot	N	SOT323	gp pnp 45V
BR	BZX399C20	Phi	I	SOD323	20V 0.3W zener
BR	2PB709AR	Phi	N	SC-59	pnp45V 0.1A hfe 210-340
BR1	BSR30	Phi	P	SOT89	pnp 70V 1A 1.35W hfe 40-120
BR2	BSR31	Phi	P	SOT89	pnp 70V 1A 1.35W hfe 100-300
BR4	BSR33	Phi	P	SOT89	pnp 90V 1A 1.35W hfe 100-300
BS	BCW61DR	Phi	R	SOT23	BCY78-x
BS	BZX399C22	Phi	I	SOD323	22V 0.3W zener
BS	2PB709AS	Phi	N	SC-59	pnp 45V 0.1A hfe 290-460
BS1	BST60	Mot	P	SOT89	pnp darlington 0.5A 60V
BS2	BST61	Mot	P	SOT89	pnp darlington 0.5A 80V
BS3	BST62	Mot	P	SOT89	pnp darlington 0.5A 90V
BS3	BSP62	Mot	P	SOT89	pnp darlington 0.5A hfe 2000
BT	BZX399C24	Phi	I	SOD323	24V 0.3W zener
BT2	BSP16	Mot	P	SOT223	pnp -300V 1A
BT2	BST16	Phi	P	SOT89	pnp -300V 1A
BU	BCX71GR	Phi	N	SOT23	BCX79-vii



贴片三极管上的印字，与真实名称的对照表.txt

BU	BZX399C27	Phi	I	SOD323	27V 0.3W zener
BV	BZX399C30	Phi	I	SOD323	30V 0.3W zener
BW	BCW71HR	Phi	N	SOT23R	BCX79-viii
BW	BZX399C33	Phi	I	SOD323	33V 0.3W zener
BX	BCW71JR	Phi	N	SOT23R	BCX79-ix
BX	BZX399C36	Phi	I	SOD323	36V 0.3W zener
BY	BCW71KR	Phi	N	SOT23R	BCX79-x
BY	BZX399C39	Phi	I	SOD323	39V 0.3W zener
BZ	BZX399C43	Phi	I	SOD323	43V 0.3W zener
C	BB565	Sie	I	SCD80	uhf varicap 2-20pF
C	KV1832E	Tok	I	URD	uhf varicap 4-17pf
C white	BAT165	Sie	I	-	40V 750mA sw Schottky
C0	HSMS-2820	HP	C	SOT23	HP2835 schottky
C0	HSMS-282B	HP	C	SOT323	HP2835 schottky
C1	HSMS-2821	HP	K	SOT23	HP2835 schottky
C1	BCW29	Phi	N	SOT23	BC178A
C1	BFQ51C	Phi	CX	SOT173	pnv BFR90A complement
C11	SST111	Sil	F	SOT23	J111 n-ch fet
C12	SST112	Sil	F	SOT23	J112 n-ch fet
C13	SST113	Sil	F	SOT23	J113 n-ch fet
C1p	BCW29	Phi	N	SOT23	BC178A
C1t	BCW29	Phi	N	SOT23	BC178A
C2	BCW30	Phi	N	SOT23	BC178B
C2	BFQ32C	Phi	CX	SOT173	pnv 4.5GHz 15V 100mA
C2	HSMS-2822	HP	D	SOT23	dual HP2835 schottky
C2	HSMS-282C	HP	D	SOT323	dual HP2835 schottky
C2	SST112	Tem	F	SOT23	J112 analog sw n-ch jfet
C2A	ZDC833A	Zet	B	SOT23	dual cc 28V varicap 15pF @2V
C2p	BCW30	Phi	N	SOT23	BC178B
C2t	BCW30	Phi	N	SOT23	BC178B
C3	HSMS-2823	HP	A	SOT23	dual HP2835 schottky
C3	BFQ23C	Phi	CX	SOT173	pnv complement BFP91A
C3	SMBT4126	Sie	N	-	2N4126
C3	SST113	Tem	F	SOT23	J113 analog sw jfet
C38	SST5638	Sil	F	SOT23	2N5638
C39	SST5639	Sil	F	SOT23	2N5639
C4	BCW29R	Phi	R	SOT23R	BC178A
C4	HSMS-2824	HP	B	SOT23	dual HP2835 schottky
C40	SST5640	Sil	F	SOT23	2N5640
C41	SST4091	Sil	F	SOT23	2N4091
C42	SST4092	Sil	F	SOT23	2N4092
C43	SST4093	Sil	F	SOT23	2N4093
C5	MMBA811C5	Mot	N	-	2N5086 pnv hfe 135-270
C5	BCW30R	Phi	R	SOT23R	BC178B
C5	HSMS-2825	HP	S	SOT143	dual HP2835 schottky
C56	SST4856	Sil	F	SOT23	2N4856
C57	SST4857	Sil	F	SOT23	2N4857
C58	SST4858	Sil	F	SOT23	2N4858
C59	SST4859	Sil	F	SOT23	2N4859
C5A	ZDC834A	Zet	B	SOT23	dual cc 28V varicap 47pF @2V
C6	MMBA811C6	Mot	N	-	2N5086 pnv hfe 200-400
C60	SST4860	Sil	F	SOT23	2N4860
C61	SST4861	Sil	F	SOT23	2N4861
C7	MMBA811C7	Mot	N	-	2N5086 pnv hfe 300-600
C7	HSMS-2827	HP	RQ	SOT143	HP2835 ring quad
C8	HSMS-2828	HP	BQ	SOT143	HP2835 bridge quad
C8	BCF30	SGS	N	SOT23	BC559B
C8	MMBA811C8	Mot	N	-	2N5086 pnv hfe 450-900
C91	SST4391	Sil	F	SOT23	2N4391
C92	SST4392	Sil	F	SOT23	2N4392
C93	SST4393	Sil	F	SOT23	2N4393
CA	BCW61AR	Phi	R	SOT23R	BCY78-vii
CA	BCP68	Mot	P	SOT223	20V 1A npn
CA	ZMV829B	Zet	I	SOD323	varicap hyperab 28V 8.2pF@2V
CB	BCX68-10	Sie	P	SOT89	npn AF 20V 2A hfe 100
CB	BCW61BR	Phi	R	SOT23R	BCY78-viii
CB	ZMV830B	Zet	I	SOD323	varicap hyperabrupt 28V 10pF@2V
CC	BCW61CR	Phi	R	SOT23R	BCY78-ix
CC	BCX68-16	Sie	P	SOT89	npn AF 20V 2A hfe 160
CC	ZMV831B	Zet	I	SOD323	varicap hyperabrupt 28V 15pF@2V
CC	ZMDC831B	Zet	B	SOT323	dual cc ZMV831B (above)
CD	BCW61DR	Phi	R	SOT23R	BCY78-x
CD	BCX68-25	Sie	P	SOT89	npn AF 20V 2A hfe 250
CD	ZMV832B	Zet	I	SOD323	varicap hyperabrupt 28V 22pF@2V
CD	ZMDC832B	Zet	B	SOT323	dual cc ZMV832B (above)



贴片三极管上的印字，与真实名称的对照表.txt

CDs	BSS81B	Sie	N	SOT23	npn sw 35V 0.8A
CE	BCP69	Mot	P	SOT223	20V 1A pnp
CE	ZMV833B	Zet	I	SOD323	varicap hyperabrupt 28V 33pF@2V
CEs	BSS79B	Sie	N	SOT23	npn 40V 0.8A hfe 40-120
CF	BSS79C	Sie	N	SOT23	npn 40V 0.8A hfe 100 min
CF	BCX69-10	Sie	P	SOT89	pnp AF 20V 2A hfe 100
CF	ZMV834B	Zet	I	SOD323	varicap hyperabrupt 28V 47pF@2V
CG	BCX71GR	Phi	R	SOT23R	BCY79-vii
CG	BCX69-16	Sie	P	SOT89	pnp AF 20V 2A hfe 160
CG	ZMV835B	Zet	I	SOD323	varicap hyperabrupt 28V 68pF@2V
CGs	BSS81C	Sie	N	SOT23	npn sw 35V 1A
CH	BSS82BL	Mot	N	SOT23	pnp 60V
CH	BCX69-25	Sie	N	SOT89	pnp AF 20V 2A hfe 250
CHs	BSS80B	Sie	N	SOT23	pnp 40V 0.8A hfe 40-120
CJs	BSS80C	Sie	N	SOT23	pnp 40V 0.8A hfe 100 min
CK	BCX71JR	Phi	R	SOT23R	BCY79-viii
CLs	BSS82B	Sie	N	SOT23	pnp 60V 0.8A hfe 40-120
CMs	BSS82C	Sie	N	SOT23	pnp 60V 0.8A hfe 100 min
CQ	2SC2411K		Roh	N	- npn darlington
CQ	MSD710Q	Mot	N	SOT346	pnp gp 25V 150mA
CR	MSD701R	Mot	N	SOT346	pnp gp 25V 150mA
D	BB659	Sie	I	SCD80	2-38p varicap
D	BAS21-03W	Sie	I	SOD323	-
D	1SS376	Roh	I	USM	300V 50mA sw
D	MRF577	Mot	N	SOT323	npn RF fT 7GHz
D0	HSMP-3800		HP	C	SOT23 HP3800 pin atten diode
D1	BCW31	Phi	N	SOT23	BC108A
D1	HSMP-3801		HP	K	- HP3800 pin atten diode
D1	SST211	Tem	XQ	-	n-ch mosfet 30V InS
D11	SST211	Sil	XQ	-	n-ch mosfet sw
D11	SST215	Sil	XQ	-	n-ch mosfet sw
D13	SST213	Sil	XQ	-	n-ch mosfet sw
D1p	BCW31	Phi	N	SOT23	BC108A
D1t	BCW31	Phi	N	SOT23	BC108A
D2	BCW32	Phi	N	SOT23	BC108B
D2	HSMP-3802		HP	D	- dual HP3800 pin atten diode
D2p	BCW32	Phi	N	SOT23	BC108B
D2t	BCW32	Phi	N	SOT23	BC108B
D3	BCW33	Phi	N	SOT23	BC108C
D3B	RB420D	Roh	C	-	25V 100mA schottky
D3E	RB411D	Roh	C	SOT23	20V 500mA schottky
D3J	RB420D	Roh	C	-	25V 100mA schottky
D3L	RB706D-40		Roh	B	- dual 45V 30mA schottky
D3p	BCW33	Phi	N	SOT23	BC108C
D3t	BCW33	Phi	N	SOT23	BC108C
D4	BCW31R	Phi	R	SOT23R	BC108A
D4	HSMP-3804		HP	B	SOT23 dual cc HP3800 pin atten diode
D5	SST215	Tem	XQ	-	n-ch mosfet 20V InS
D5	BCW32R	Phi	R	SOT23R	BC108B
D58	FLLD261	Zet	B	SOT23	low leakage dual cc Si diode
D6	BCW33R	Phi	R	SOT23R	BC108C
D6	MMBC1622D6		Mot	N	- MPS3904 hfe 200-400
D63	FLLD263	Zet	A	SOT23	low leakage dual ca Si diode
D7	MMBC1622D7		Mot	N	- MPS3904 hfe 300-600
D76	BAR18J	SGS	I	SOD232	schottky 70V 15mA
D76	BAR18	SGS	C	SOT23	schottky 70V 30mA
D7p	BCF32	Phi	N	SOT23	-
D7t	BCF32	Phi	N	SOT23	-
D85	BAT17DS	SGS	D	-	2xBA481
D86	BAT54J	ST	I	SOD232	schottky 30V 300mA
D86	BAT54	ST	C	SOT23	schottky 30V 300mA
D87	BAT54C	ST	B	SOT23	dual cc schottky 30V 300mA
D88	BAT54S	ST	D	SOT23	dual series schottky 30V 300mA
D8p	BCF33	Phi	N	SOT23	BC146/03
D94	BAR42	SGS	C	SOT23	schottky 30V 100mA
D95	BAR43	SGS	C	SOT23	schottky 30V 100mA
D96	BAS70-04		SGS	D	SOT23 2xBA18
D97	BAS70-05		SGS	B	SOT23 2xBA18
D98	BAS70-06		SGS	A	SOT23 2xBA18
DA	BCW67A	SGS	N	SOT23	pnp 32V 0.8A hfe 100 min
DA	BF622	Sie	P	SOT89	npn 250V video o/p
DA5	BAR43S	SGS	D	SOT23	2xBA43
DB	BCW67B	SGS	N	SOT23	pnp 32V 0.8A hfe 160 min
DB	BF623	Sie	P	SOT89	pnp 250V video o/p
DB1	BAR43A	SGS	A	SOT23	2xBA43



贴片三极管上的印字，与真实名称的对照表.txt

DB2	BAR43C	SGS	B	SOT23	2xBAR43
DC	BCW67C	SGS	N	SOT23	npn 32V 0.8A hfe 250 min
DC	BF720	Mot	P	SOT223	npn 1.5W 300V
DC	BFN20	Sie	P	SOT89	npn video o/p 300V comp BFN21
DD	BFN16	Sie	P	SOT89	npn video o/p 250V comp BFN17
DE	BFN18	Sie	P	SOT89	npn video o/p 300Vcomp BFN19
DF	BCW68F	SGS	N	SOT23	npn 45V 0.8A hfe 100 min
DF	BF721	Mot	P	SOT223	npn 1.5W 300V
DF	BFN21	Sie	P	SOT89	npn 300V video o/p comp BFN20
DG	BCW68G	SGS	N	SOT23	npn 45V 0.8A hfe 160 min
DG	BFN17	Sie	P	SOT89	npn video o/p 250V comp BFN16
DH	BCW68H	SGS	N	SOT23	npn 45V 0.8A hfe 250 min
DH	BCW68G	Mot	N	SOT23	npn 45V 0.8A hfe 160 min
DH	MMBD2000		Mot	C	SOT323 Si sw diode 20V 0.2A SOT323
DH	BFN19	Sie	P	SOT89	npn video o/p 300V comp BFN18
DK	BCX42	Sie	N	SOT23	gp audio npn 125V comp BCX41
DP	MMBD2010		Mot	B	SOT323 dual cc MMBD2000
DQ	2P710AQ	Phi	N	SOT346	gp npn hfe 85-170
DR	2P710AR	Phi	N	SOT346	gp npn hfe 120-240
DS	2P710AS	Phi	N	SOT346	gp npn hfe 170-340
DT	BCW67AR	SGS	R	SOT23R	npn 32V 0.8A hfe 100 min
DU	BCW67BR	SGS	R	SOT23R	npn 32V 0.8A hfe 160 min
DW	BCW67CR	SGS	R	SOT23R	npn 32V 0.8A hfe 250 min
DX	BCW68FR	SGS	R	SOT23R	npn 45V 0.8A hfe 100 min
DY	BCW68GR	SGS	R	SOT23R	npn 45V 0.8A hfe 160 min
DZ	BCW68HR	SGS	R	SOT23R	npn 45V 0.8A hfe 250 min
e	BAT64-02W		Sie	I	SCD80 -
E	1SS780	Roh	I	USM	40V 100mA lo leakage
E	BB689	Sie	I	SCD80	2-55pF varicap
E0	HSMP-3810		HP	C	SOT23 HP3810 pin atten diode
E0	HSMP-381B		HP	C	SOT323 HP3810 pin atten diode
E01	DTDG14EP		Roh	P	SOT89 "npn dtr 60V 1A R2 10k, + c to b zener "
E02	DTDG23YP		Roh	P	SOT89 "npn dtr 60V 1A 2k2+ 10k, + c to b zener "
E1	HSMP-3811		HP	K	SOT23 HP3810 pin atten diode
E11	DTA113ZE		Roh	N	EMT3 npn dtr 1k0 + 10k 50V 100mA
E11	DTA113ZKA		Roh	N	SC59 npn dtr 1k0 + 10k 50V 100mA
E13	DTA143ZE		Roh	N	EMT3 npn dtr 4k7 + 47k 50V 100mA
E13	DTA143ZKA		Roh	N	SC59 npn dtr 4k7 + 47k 50V 100mA
E1p	BFS17	Phi	N	SOT23	BFY90 BFW92
E1p	BFS17W	Phi	N	SOT323	BFY90 BFW92
E2	BFS17A	Phi	N	SOT23	npn RF 3GHz 25mA
E2	BAL99	Zet	C	-	sw diode 75V 100mA
E2	HSMP-3812		HP	D	SOT23 dual series HP3810 pin atten diode
E23	DTC143ZCA		Roh	N	SOT23 npn dtr 4k7 + 47k 50V 100mA
E23	DTC143ZE		Roh	N	EMT3 npn dtr 4k7 + 47k 50V 100mA
E23	DTC143ZKA		Roh	N	SC59 npn dtr 4k7 + 47k 50V 100mA
E3	BAR99	Zet	C	-	sw diode 75V 100mA
E3	HSMP-3813		HP	A	SOT23 dual HP3810 pin atten diode
E32	DTA123JE		Roh	N	EMT3 npn dtr 2k2 + 47k 50V 100mA
E32	DTA123JKA		Roh	N	SC59 npn dtr 2k2 + 47k 50V 100mA
E4	BFS17R	Phi	R	-	BFY90 BFW92
E4	HSMP-3814		HP	B	SOT23 dual cc HP3810 pin atten diode
E42	DTC123JE		Roh	N	EMT3 npn dtr 2k2 + 47k 50V 100mA
E42	DTC123JKA		Roh	N	SC59 npn dtr 2k2 + 47k 50V 100mA
E5	BFS17AR	Tfk	R	-	npn rf 3 GHz 25mA
E56	DTA144VKA		Roh	N	SC59 npn dtr 47k + 10k 50V 100mA
E6	ZC2800E	Zet	C	-	HP2800
E66	DTC144VKA		Roh	N	SC59 npn dtr 47k + 10k 50V 100mA
E8	ZC2811E	Zet	C	-	HP2811
E9	ZC5800E	Zet	C	-	HP5800
EAs	BCW65A	Sie	N	SOT23	npn 32V 800mA hfe 100 min
EB	HSMP-4810		HP	J	SOT23 0.5-3GHz pin 2 cathode connections
EB	MSC1022-B		Mot	H	- npn RF 150MHz fT 20V
EBs	BCW65B	Sie	N	SOT23	npn 32V 800mA hfe 160 min
EC	MSC1022-C		Mot	H	- npn RF 150MHz fT 20V
ECs	BCW65C	Sie	N	SOT23	npn 32V 800mA hfe 250 min
ED	BCV28	Sie	P	SOT89	npn darlington 30V 0.8A comp BCV29
EE	BCV48	Sie	P	SOT89	npn darlington 60V 0.8A comp BCV49
EF	BCV29	Sie	P	SOT89	npn darlington 30V 0.8A comp BCV28
EF	BCW66F	Sie	N	SOT23	npn 45V 800mA hfe 100 min
EG	BCV49	Sie	P	SOT89	npn darlington 60V 0.8A comp BCV48
EGs	BCW66G	Sie	N	SOT23	npn 45V 800mA hfe 160 min
EHAA	MAX6326_R22-T		Max	ZB	SOT23 microproc -ve reset gen 2.200V
EHS	BCW66H	Sie	N	SOT23	npn 45V 800mA hfe 240 min
EIAA	MAX6327_R22-T		Max	ZB	SOT23 microproc +ve reset gen 2.200V

贴片三极管上的印字，与真实名称的对照表.txt

EJAA	MAX6328_R22-T	Max	ZB	SOT23	microproc -ve reset gen 2.200V
Eks	BCX41 Sie	N	SOT23	gp npn 125V 1A comp BCX42	
ET	BCW65AR Sie	R	SOT23R	nnp 32V 800mA hfe 100 min	
EU	BCW65BR Sie	R	SOT23R	nnp 32V 800mA hfe 160 min	
EW	BCW65CR Sie	R	SOT23R	nnp 32V 800mA hfe 240 min	
EWAA	MAX6326_R23-T	Max	ZB	SOT23 microproc -ve reset gen 2.320V	
EX	BCW65FR Sie	R	SOT23R	nnp 45V 800mA hfe 100 min	
EXAA	MAX6326_R24-T	Max	ZB	SOT23 microproc -ve reset gen 2.400V	
EY	BCW65GR Sie	R	SOT23R	nnp 45V 800mA hfe 160 min	
EYAA	MAX6326_R25-T	Max	ZB	SOT23 microproc -ve reset gen 2.500V	
EZ	BCW65HR Sie	R	SOT23R	nnp 45V 800mA hfe 240 min	
EZAA	MAX6326_R26-T	Max	ZB	SOT23 microproc -ve reset gen 2.630V	
f	BAS20-02W	Sie	I	SCD80 -	
F	KV1831E Tok	I	URD	uhf varicap 2.5-22pf	
F	MRP927 Mot	N	SOT323	nnp RF fT 8GHz	
F0	HSMP-3820	HP	C	SOT23 35V RF pin sw diode	
F02	DTD123TK	Roh	N	SC59 npn dtr R1 2k2 40V 100mA	
F03	DTD143TK	Roh	N	SC59 npn dtr R1 4k7 40V 100mA	
F05	TSDF1205	Tfk	X	- fT 12GHz npn RF 4V 12mA	
F1	HSMP-3821	HP	K	SOT23 35V RF pin sw diode	
F1	BFS18 Phi	N	SOT23	BF495	
F1	MMBC1009F1	Mot	N	- RF npn fT 150MHz hfe30-60	
F11	DTB113EK	Roh	N	SC59 pnp dtr 1k + 1k 50V 500mA	
F12	DTB123EK	Roh	N	SC59 pnp dtr 2k2 + 2k2 50V 500mA	
F13	DTB143EK	Roh	N	SOT23 pnp dtr 4k7+ 4k7 50V 500mA	
F13	DTB143EK	Roh	N	SC59 pnp dtr 4k7+ 4k7 50V 500mA	
F14	DTB114EK	Roh	N	SC59 pnp dtr 10k + 10k 50V 500mA	
F2	HSMP-3822	HP	D	SOT23 dual series HP3820 pin sw diode	
F2	BFS19 SGS	N	SOT23	BF184 BF494	
F20	TSDF1220	Tfk	X	- fT 12GHz npn 6V 20mA	
F21	DTD113EK	Roh	N	SC59 npn dtr 1k + 1k 50V 500mA	
F22	DTD123EK	Roh	N	SC59 npn dtr 2k2 + 2k2 50V 500mA	
F23	DTD143EK	Roh	N	SOT23 npn dtr 4k7 + 4k7 50V 500mA	
F23	DTD143EK	Roh	N	SC59 npn dtr 4k7 + 4k7 50V 500mA	
F24	DTD114EK	Roh	N	SC59 npn dtr 10k + 10k 50V 500mA	
F2p	BFS19 Phi	N	SOT23	BF184 BF494	
F2t	BFS19 Phi	N	SOT23	BF184 BF494	
F3	MMBC1009F3	Mot	N	- RF npn fT150MHz hfe60-120	
F4	BFS18R Phi	N	-	BF495	
F4	HSMP-3824	HP	B	SOT23 dual cc HP3820 pin sw diode	
F5	BFS19R Phi	N	-	BF184 BF494	
F52	DTB123YK	Roh	N	SOT23 pnp dtr 2k2 + 10k 50V 100mA	
F52	DTB123YK	Roh	N	SC59 pnp dtr 2k2 + 10k 50V 100mA	
F62	DTD123YK	Roh	N	SC59 npn dtr 2k2 + 10k 50V 100mA	
F8p	BF824 Phi	N	SOT23	-	
F8t	BF824 Phi	N	SOT23	-	
F8t	BF824W Phi	N	SOT323	-	
F92	DTB123TK	Roh	N	SC59 pnp dtr R1 2k2 40V 100mA	
F93	DTB143TK	Roh	N	SC59 pnp dtr R1 4k7 40V 100mA	
F94	DTB114TK	Roh	N	SC59 pnp dtr R110k 40V 100mA	
FA	HSMP-4820	HP	B	SOT23 0.5-3GHz cc pin dual anode	
FA	BFQ17 Phi	P	SOT89	nnp RF 1.5GHz 300mA	
FA	BFP81 Sie	X	-	BFQ69	
FA	BFQ19 Phi	P	SOT89	nnp RF Ft 5.5GHz 100mA	
FAAA	MAX6326_R27-T	Max	ZB	SOT23 microproc -ve reset gen 2.700V	
FB	BFP17 Sie	X	-	BFW92	
FBAA	MAX6328_R31-T	Max	ZB	SOT23 microproc -ve reset gen 2.800V	
FC	BFQ64 Sie	P	-	BFT98T	
FC	BFP29 Sie	X	-	BFT97	
FCAA	MAX6326_R29-T	Max	ZB	SOT23 microproc -ve reset gen 2.930V	
FD	BCV26 SGS	N	SOT23	pnp darlington	
FD	BFQ17P Sie	P	SOT89	BFW16A	
FD	BFP35A Sie	X	-	BFR34A	
FDAA	MAX6326_R31-T	Max	ZB	SOT23 microproc -ve reset gen 3.080V	
FDp	BCV26 Phi	N	SOT23	pnp darlington	
FDt	BCV26 Phi	N	SOT23	pnp darlington	
FE	BCV46 SGS	N	SOT23	pnp darlington	
FE	BFP93A Sie	X	SOT143	BFR91A	
FEAA	MAX6326_R30-T	Max	ZB	SOT23 microproc -ve reset gen 3.000V	
FEp	BCV46 Phi	N	SOT23	pnp darlington	
FEs	BFQ19P Sie	P	SOT89	BFR96	
FEt	BCV46 Phi	N	SOT23	pnp darlington	
FF	BCV27 SGS	N	SOT23	nnp darlington	
FF	BBY65-02V	Inf	I	SC79 hyperabrupt varicap 2.7-30pF	
FFAA	MAX6327_R23-T	Max	ZB	SOT23 microproc +ve reset gen 2.320V	



贴片三极管上的印字，与真实名称的对照表.txt

FFMA	MAX6327_R31-T	Max	ZB	SOT23	microproc +ve reset gen 3.080V
FFNA	MAX6327_R30-T	Max	ZB	SOT23	microproc +ve reset gen 3.000V
FFp	BCV27_Phi	N	SOT23	npn darlington	
FFt	BCV27_Phi	N	SOT23	npn darlington	
FG	BCV47_Phi	N	SOT23	npn darlington	
FG	BFQ19S_Sie	P	SOT89	BFR96S	
FGAA	MAX6327_R24-T	Max	ZB	SOT23 microproc +ve reset gen 2.400V	
FGp	BCV47_Phi	N	SOT23	npn darlington	
FGt	BCV47_Phi	N	SOT23	npn darlington	
FHAA	MAX6327_R25-T	Max	ZB	SOT23 microproc +ve reset gen 2.500V	
FHs	BFN24_Sie	N	SOT23	npn 250V comp to BFN25	
FIAA	MAX6327_R26-T	Max	ZB	SOT23 microproc +ve reset gen 2.630V	
FJ	BFN26_Sie	N	SOT23	npn 300V comp to BFN27	
FJAA	MAX6327_R27-T	Max	ZB	SOT23 microproc +ve reset gen 2.700V	
FK	BFN25_Sie	N	SOT23	pnp 250V comp to BFN24	
FKAA	MAX6327_R28-T	Max	ZB	SOT23 microproc +ve reset gen 2.800V	
FL	BFN27_Sie	N	SOT23	pnp 300V comp to BFN26	
FLAA	MAX6327_R29-T	Max	ZB	SOT23 microproc +ve reset gen 2.930V	
FOAA	MAX6328_R23-T	Max	ZB	SOT23 microproc -ve reset gen 2.320V	
FPAA	MAX6328_R24-T	Max	ZB	SOT23 microproc -ve reset gen 2.400V	
F-Q	2PA1576Q	Phi	N	SOT323 gp pnp SC70 hfe 120-270	
FQAA	MAX6328_R25-T	Max	ZB	SOT23 microproc -ve reset gen 2.500V	
FR	2SA1037AK	Roh	N	- hfe 150@1ma preamp pnp	
FR	2SA1576A	Roh	N	UMT see 2SA1037K above	
FR	2SA1774 Roh	N	EM3	see 2SA1037K above	
F-R	2PA1576R	Phi	N	SOT323 gp pnp hfe 180-390	
FRAA	MAX6328_R26-T	Max	ZB	SOT23 microproc -ve reset gen 2.630V	
F-S	2PA1576S	Phi	N	SOT323 gp pnp hfe 270-560	
FSAA	MAX6328_R27-T	Max	ZB	SOT23 microproc -ve reset gen 2.700V	
FTAA	MAX6328_R28-T	Max	ZB	SOT23 microproc -ve reset gen 2.800V	
FtQ	2PA1576Q	Phi	N	SOT323 gp pnp SC70 hfe 120-270	
FtR	2PA1576R	Phi	N	SOT323 gp pnp hfe 180-390	
FtS	2PA1576S	Phi	N	SOT323 gp pnp hfe 270-560	
FUAA	MAX6328_R29-T	Max	ZB	SOT23 microproc -ve reset gen 2.930V	
FVAA	MAX6328_R31-T	Max	ZB	SOT23 microproc -ve reset gen 3.080V	
FWAA	MAX6328_R30-T	Max	ZB	SOT23 microproc -ve reset gen 3.000V	
FZAP	MAX6012A	Max	ZC	SOT23 precision reference 1.247V	
FZAQ	MAX6025A	Max	ZC	SOT23 precision reference 2.500V	
FZAR	MAX6041A	Max	ZC	SOT23 precision reference 4.096V	
FZAS	MAX6045A	Max	ZC	SOT23 precision reference 4.500V	
FZAT	MAX6050A	Max	ZC	SOT23 precision reference 5.000V	
FZAU	MAX6021A	Max	ZC	SOT23 precision reference 2.048V	
FZAV	MAX6346_R33-T	Max	ZB	SOT23 micrproc -ve reset gen 3.300V	
FZAW	MAX6346_R34-T	Max	ZB	SOT23 micrproc -ve reset gen 3.400V	
FZAX	MAX6346_R35-T	Max	ZB	SOT23 micrproc -ve reset gen 3.500V	
FZAY	MAX6346_R36-T	Max	ZB	SOT23 micrproc -ve reset gen 3.600V	
FZAZ	MAX6346_R37-T	Max	ZB	SOT23 micrproc -ve reset gen 3.700V	
FZBA	MAX6346_R38-T	Max	ZB	SOT23 micrproc -ve reset gen 3.800V	
FZBB	MAX6346_R39-T	Max	ZB	SOT23 micrproc -ve reset gen 3.900V	
FZBC	MAX6346_R40-T	Max	ZB	SOT23 micrproc -ve reset gen 4.0800V	
FZBD	MAX6346_R41-T	Max	ZB	SOT23 micrproc -ve reset gen 4.100V	
FZBE	MAX6346_R42-T	Max	ZB	SOT23 micrproc -ve reset gen 4.200V	
FZBF	MAX6346_R43-T	Max	ZB	SOT23 micrproc -ve reset gen 4.300V	
FZBG	MAX6346_R44-T	Max	ZB	SOT23 micrproc -ve reset gen 4.380V	
FZBH	MAX6346_R45-T	Max	ZB	SOT23 micrproc -ve reset gen 4.500V	
FZBI	MAX6346_R46-T	Max	ZB	SOT23 micrproc -ve reset gen 4.630V	
FZBJ	MAX6347_R33-T	Max	ZB	SOT23 micrproc +ve reset gen 3.300V	
FZBK	MAX6347_R34-T	Max	ZB	SOT23 micrproc +ve reset gen 3.400V	
FZBL	MAX6347_R35-T	Max	ZB	SOT23 micrproc +ve reset gen 3.500V	
FZBM	MAX6347_R36-T	Max	ZB	SOT23 micrproc +ve reset gen 3.600V	
FZBN	MAX6347_R37-T	Max	ZB	SOT23 micrproc +ve reset gen 3.700V	
FZBO	MAX6347_R38-T	Max	ZB	SOT23 micrproc +ve reset gen 3.800V	
FZBP	MAX6347_R39-T	Max	ZB	SOT23 micrproc +ve reset gen 3.900V	
FZBQ	MAX6347_R40-T	Max	ZB	SOT23 micrproc +ve reset gen 4.0800V	
FZBR	MAX6347_R41-T	Max	ZB	SOT23 micrproc +ve reset gen 4.100V	
FZBS	MAX6347_R42-T	Max	ZB	SOT23 micrproc +ve reset gen 4.200V	
FZBT	MAX6347_R43-T	Max	ZB	SOT23 micrproc +ve reset gen 4.300V	
FZBU	MAX6347_R44-T	Max	ZB	SOT23 micrproc +ve reset gen 4.380V	
FZBV	MAX6347_R45-T	Max	ZB	SOT23 micrproc +ve reset gen 4.500V	
FZBW	MAX6347_R46-T	Max	ZB	SOT23 micrproc +ve reset gen 4.630V	
FZBX	MAX6348_R33-T	Max	ZB	SOT23 microproc -ve reset gen 3.300V	
FZBY	MAX6348_R34-T	Max	ZB	SOT23 microproc -ve reset gen 3.400V	
FZBZ	MAX6348_R35-T	Max	ZB	SOT23 microproc -ve reset gen 3.500V	
FZCA	MAX6348_R36-T	Max	ZB	SOT23 microproc -ve reset gen 3.600V	
FZCB	MAX6348_R37-T	Max	ZB	SOT23 microproc -ve reset gen 3.700V	



贴片三极管上的印字，与真实名称的对照表.txt

FZCC	MAX6348_R38T	Max	ZB	SOT23	microproc -ve reset gen 3.800V
FZCD	MAX6348_R39-T	Max	ZB	SOT23	microproc -ve reset gen 3.900V
FZCE	MAX6348_R40-T	Max	ZB	SOT23	microproc -ve reset gen 4.000V
FZCF	MAX6348_R41-T	Max	ZB	SOT23	microproc -ve reset gen 4.100V
FZCG	MAX6348_R42T	Max	ZB	SOT23	microproc -ve reset gen 4.200V
FZCH	MAX6348_R43-T	Max	ZB	SOT23	microproc -ve reset gen 4.380V
FZCI	MAX6348_R44-T	Max	ZB	SOT23	microproc -ve reset gen 4.400V
FZCJ	MAX6348_R45-T	Max	ZB	SOT23	microproc -ve reset gen 4.500V
FZCK	MAX6348_R46-T	Max	ZB	SOT23	microproc -ve reset gen 4.600V
FZCX	MAZ6001UR	Max	ZC	SOT23	1.250V V reference
FZCY	MAZ6002UR	Max	L	SOT23	2.500V V reference
FZCZ	MAZ6004UR	Max	L	SOT23	4.096V V reference
FZDA	MAZ6005UR	Max	L	SOT23	5.000V V reference
FZDB	MAX6012B	Max	ZC	SOT23	precision reference 1.247V
FZDC	MAX6025B	Max	ZC	SOT23	precision reference 2.500V
FZDD	MAX6041B	Max	ZC	SOT23	precision reference 4.096V
FZDE	MAX6045B	Max	ZC	SOT23	precision reference 4.500V
FZdE	MAX6050B	Max	ZC	SOT23	precision reference 5.000V
FZDF	MAX6021B	Max	ZC	SOT23	precision reference 2.047V
FZDK	MAZ6003UR	Max	L	SOT23	3.000V V reference
FZDW	MAX6030A	Max	ZC	SOT23	precision reference 3.000V
FZDX	MAX6012B	Max	ZC	SOT23	precision reference 3.000V
FZEB	LM4041AIM3-1.2	Max	L	SOT23	1.225V 0.1% shunt V ref
FZEC	LM4041BIM3-1.2	Max	L	SOT23	1.225V 0.2% shunt V ref
FZED	LM4041DIM3-1.2	Max	L	SOT23	1.225V 0.5% shunt V ref
FZEE	LM4041DIM3-1.2	Max	L	SOT23	1.225V 1.5% shunt V ref
FZEF	LM4040A IM3-2.1	Max	L	SOT23	2.048V shunt reference 0.1%
FZEG	LM4040B IM3-2.1	Max	L	SOT23	2.048V shunt reference 0.2 %
FZEH	LM4040C IM3-2.1	Max	L	SOT23	2.048V shunt reference 0.5%
FZEI	LM4040D IM3-2.1	Max	L	SOT23	2.048V shunt reference 1.0%
FZEJ	LM4040A IM3-2.5	Max	L	SOT23	2.500V shunt reference 0.1%
FZEK	LM4040B IM3-2.5	Max	L	SOT23	2.500V shunt reference 0.2 %
FZEL	LM4040C IM3-2.5	Max	L	SOT23	2.500V shunt reference 0.5%
FZEM	LM4040D IM3-2.5	Max	L	SOT23	2.500V shunt reference 1.0%
FZEN	LM4040A IM3-3.0	Max	L	SOT23	3.000V shunt reference 0.1%
FZEO	LM4040B IM3-3.0	Max	L	SOT23	3.000V shunt reference 0.2 %
FZEP	LM4040C IM3-3.0	Max	L	SOT23	3.000V shunt reference 0.5%
FZEQ	LM4040D IM3-3.0	Max	L	SOT23	3.000V shunt reference 1.0%
FZER	LM4040A IM3-4.1	Max	L	SOT23	4.096V shunt reference 0.1%
FZES	LM4040B IM3-4.1	Max	L	SOT23	4.096V shunt reference 0.2 %
FZET	LM4040C IM3-4.1	Max	L	SOT23	4.096V shunt reference 0.5%
FZEU	LM4040D IM3-4.1	Max	L	SOT23	4.096V shunt reference 1.0%
FZEV	LM4040A IM3-5.0	Max	L	SOT23	5.000V shunt reference 0.1%
FZEW	LM4040B IM3-5.0	Max	L	SOT23	5.000V shunt reference 0.2 %
FZEX	LM4040C IM3-5.0	Max	L	SOT23	5.000V shunt reference 0.5%
FZEY	LM4040D IM3-5.0	Max	L	SOT23	5.000V shunt reference 1.0%
FZEZ	MAZ803LUR	Max	ZB	SOT23	"microproc -ve reset gen, 5.0V"
FZF A	MAZ803MUR	Max	ZB	SOT23	"microproc -ve reset gen, 5.0V"
FZF B	MAZ803TUR	Max	ZB	SOT23	"microproc -ve reset gen, 3.3V"
FZF C	MAZ803SUR	Max	ZB	SOT23	"microproc -ve reset gen, 3.3V"
FZF D	MAZ803RUR	Max	ZB	SOT23	"microproc -ve reset gen, 3.0V"
FZGH	MAZ6006AUR	Max	L	SOT23	1.250V 0.2% shunt V reference
FZGI	MAZ6006BUR	Max	L	SOT23	1.250V 0.5% shunt V reference
FZGJ	MAZ6006CUR	Max	L	SOT23	1.250V 1.0% shunt V reference
FZGK	MAZ6007AUR	Max	L	SOT23	2.480V 0.2% shunt V reference
FZGL	MAZ6007BUR	Max	L	SOT23	2.480V 0.5% shunt V reference
FZGM	MAZ6007CUR	Max	L	SOT23	2.480V 1.0% shunt V reference
FZGN	MAZ6008AUR	Max	L	SOT23	2.500V 0.2% shunt V reference
FZGO	MAZ6008BUR	Max	L	SOT23	2.500V 0.5% shunt V reference
FZGP	MAZ6008CUR	Max	L	SOT23	2.500V 1.0% shunt V reference
FZGQ	MAZ6009AUR	Max	L	SOT23	3.000V 0.2% shunt V reference
FZGR	MAZ6009BUR	Max	L	SOT23	3.000V 0.5% shunt V reference
FZGS	MAZ6009CUR	Max	L	SOT23	3.000V 1.0% shunt V reference
G	BAR63-02W	Sie	I	SCD80	RF pin to 3GHz
G	BAR63-03W	Sie	I	SOD323	RF pin to 3GHz
G	KV1181E Tok	I	URD		uhf varicap 2-16pF
G	MRF947A Mot	N	SOT323		npn RF 8GHz
G0	HSMP-3890	HP	C	SOT23	HP3890 pin sw diode
G0	HSMP-389B	HP	C	SOT323	HP3890 pin sw diode
G08	DTD133HKA	Roh	N	SC59	npn dtr 3k3+10k 50V 500mA
G1	BFS20 Phi	N	SOT23	BF199	
G1	BFS20 Phi	N	SOT23	BF199	
G1	MMBT5551	Mot	N	SOT23	2N5551 npn Vce 140V
G11	DTB113ZKA	Roh	N	SC59	pnp dtr 1k0 +10k 50V 500mA
G1E	BC847A Rho	N	SOT23	BC547A	



贴片三极管上的印字，与真实名称的对照表.txt

G1F	BC847B	Rho	N	SOT23	BC547B
G1G	BC847C	Rho	N	SOT23	BC547C
G1J	BC848A	Rho	N	SOT23	BC548A
G1K	BC848B	Rho	N	SC70	BC548B
G1K	BC848B	Rho	N	SOT23	BC548B
G1L	BC848C	Rho	N	SOT23	BC548C
G1p	BFS20	Phi	N	SOT23	BF199
G1t	HSMP-3891	HP	K	SOT23	HP3890 pin sw diode
G2	HSMP-3892	HP	D	SOT23	dual ser HP3890 pin sw diode
G2	CGY50	Sie	IQ	SOT143	GaAs MMIC amp
G21	DTD113ZKA	Roh	N	SC59	npn dtr 1k0 +10k 50V 500mA
G3	HSMP-3893	HP	A	SOT23	dual HP3890 pin sw diode
G3	BAR63	Sie	C	SOT23	single 3GHz pin
G3C	DTB122JK	Roh	N	SC59	pnp dtr 220R + 470R 50V 500mA
G3E	BC857A	Roh	N	SOT23	BC557A
G3F	BC857B	Roh	N	SOT23	BC557B
G3J	BC858A	Roh	N	SOT23	BC558A
G3K	BC858B	Roh	N	SOT23	BC558B
G3K	BC858B	Roh	N	SC70	BC558B
G3L	BC858C	Roh	N	SOT23	BC558C
G4	BFS20R	Phi	N	SOT23	BF199
G4	HSMP-3894	HP	B	SOT23	dual HP3890 pin sw diode
G4	BAR63-04	Sie	D	SOT23	dual series 3GHz pin
G4C	DTD122JK	Roh	N	SC59	npn dtr 220R + 470R 50V 500mA
G4s	BAR63-04W	Sie	D	SOT323	dual series 3GHz pin
G5	HSMP-3895	HP	S	SOT143	dual HP3890 pin sw diode
G5	BAR63-05	Sie	B	SOT23	dual cc 3GHz pin
G5B	BC807-25	Roh	N	SOT23	BC327-25
G5s	BAR63-05W	Sie	B	SOT323	dual cc 3GHz pin
G6	BAR63-06	Sie	A	SOT23	dual ca 3GHz pin
G6A	BC817-16	Roh	N	-	BC337-16
G6B	BC817-25	Roh	N	SOT23	BC337-25
G6s	BAR63-06W	Sie	A	SOT323	dual ca 3GHz pin
G7	BF579	Tfk	N	-	BF979 pnp uhf fT 1.75GHz
G98	DTB133HKA	Roh	N	SC59	pnp dtr 3k3+10k 50V 500mA
GA	HSMP-4890	HP	B	SOT23	0.5-3GHz dual cc pin limiter
GA	BAW78A	Sie	LQ	SOT89	50V1A sw diode
GAB	BCW60B	Rho	N	SOT23	BCY58-viii
GAC	BCW60C	Rho	N	SOT23	BCY58-ix
GAD	BCW60D	Rho	N	SOT23	BCY58-x
GAH	BCX70H	Rho	N	SOT23	BCY59-viii BC107B
GAJ	BCX70J	Rho	N	SOT23	BCY59-ix BC107
GAK	BCX70K	Rho	N	SOT23	BCY59-x BC107
GB	BAW78B	Sie	LQ	SOT89	100V 1A sw diode
GBB	BCW61B	Rho	N	SOT23	BCY78-viii
GBC	BCW61C	Rho	N	SOT23	BCY78-ix
GBG	BCX71G	Rho	N	SOT23	BCY79-vii
GBH	BCX71H	Rho	N	SOT23	BCY79-viii
GBJ	BCX71J	Rho	N	SOT23	BCY79-ix
GC	BAW78C	Sie	LQ	SOT89	200V 1A sw diode
GC1	BCW29	Roh	N	SOT23	BC178A
GC2	BCW30	Roh	N	SOT23	BC178B
GD	BAW78D	Sie	LQ	SOT89	400V 1A sw diode
GD1	BCW31	Roh	N	SOT23	BC108C
GD2	BCW32	Roh	N	SOT23	BC108B
GD3	BCW33	Roh	N	SOT23	BC108A
GE	BFR35AP	Sie	N	SOT23	BFR34A
GE	BAW79A	Sie	JQ	SOT89	dual cc 50V 1A switch diodes
GEC	BCW65C	Rho	N	SOT23	npn 32V 800mA hfe 250 min
GF	BFR92P	Sie	N	SOT23	BFR90
GF	BAW79B	Sie	JQ	SOT89	dual cc 100V 1A switch diodes
GG	BF579R	Tfk	R	-	BF979 pnp uhf fT1.75GHz
GG	BFR93P	Sie	N	SOT23	BFR91A
GG	BAW79C	Sie	JQ	SOT89	dual cc 200V 1A switch diodes
GH	BAW79D	Sie	JQ	SOT89	dual cc 400V 1A switch diodes
GH1	BCW69	Roh	N	SOT23	BC177A
GH2	BCW70	Roh	N	SOT23	BC177B
GK1	BCW71	Roh	N	SOT23	BC107A
GK2	BCW72	Roh	N	SOT23	BC107B ZXT300
GLP	MMBT1010	Mot	N	SOT23	pnp 15V hfe 300-600 @100mA
GLP	MMBT1010	Mot	N	SOT346	pnp 15V hfe 300-600 @100mA
GMA	BFS17	Roh	N	SOT23	BFW92
GT1	BCX17	Roh	N	SOT23	BC327
GT2	BCX18	Roh	N	SOT23	BC328
GU1	BCX19	Roh	N	SOT23	BC337



贴片三极管上的印字，与真实名称的对照表.txt

GU2	BCX20	Roh	N	SOT23	BC338	
H	MRF947B	Mot	N	SOT323	npn RF 8GHz	
H	BB659C	Sie	I	SCD80	2.5-39 pF varicap in	
H	BBY51-03W	Sie	I	SOD323	3-5 pF varicap in	
H	MRF947B	Mot	N	SOT323	npn RF 8GHz	
H	BB659C	Sie	I	SCD80	2.5-39 pF varicap in	
H	BBY51-03W	Sie	I	SOD323	3-5 pF varicap in	
H02	DTC323TU	Rho	N	SC70	"npn dtr 15V 0.6A, R1 2k2 , for muting"	
H02	DTC323TU	Rho	N	SC70	"npn dtr 15V 0.6A, R1 2k2 , for muting"	
H04	DTC323TU	Rho	N	SC70	"npn dtr 15V 0.6A, R1 10k , for muting"	
H04	DTC323TU	Rho	N	SC70	"npn dtr 15V 0.6A, R1 10k , for muting"	
H1	BCW69	Phi	N	SOT23	BC177A	
H1	BCW69	Phi	N	SOT23	BC177A	
H11	UMH11TN	Roh	DI	-	npn/pnpdtr pair 10k+10k	
H11	UMH11TN	Roh	DI	-	npn/pnpdtr pair 10k+10k	
H16	SST4416	Sil	F	-	2N4416 n-ch jfet	
H16	SST4416	Sil	F	-	2N4416 n-ch jfet	
H1p	BCW69	Phi	N	SOT23	BC177A	
H1p	BCW69	Phi	N	SOT23	BC177A	
H1t	BCW69	Phi	N	SOT23	BC177A	
H1t	BCW69	Phi	N	SOT23	BC177A	
H2	BCW70	Phi	N	SOT23	BC177B	
H2	BCW70	Phi	N	SOT23	BC177B	
H27	DTC323TU	Rho	N	SC70	"npn dtr 15V 0.6A, R1 6k8 , for muting"	
H27	DTC323TU	Rho	N	SC70	"npn dtr 15V 0.6A, R1 6k8 , for muting"	
H2p	BCW70	Phi	N	SOT23	BC177B	
H2p	BCW70	Phi	N	SOT23	BC177B	
H2t	BCW70	Phi	N	SOT23	BC177B	
H2t	BCW70	Phi	N	SOT23	BC177B	
H3	BCW89	Phi	N	SOT23	BC556	
H3	BCW89	Phi	N	SOT23	BC556	
H31	BCW89R	Phi	N	SOT23R	BC556	
H31	BCW89R	Phi	N	SOT23R	BC556	
H3p	BCW89	Phi	N	SOT23	BC556	
H3p	BCW89	Phi	N	SOT23	BC556	
H3t	BCW89	Phi	N	SOT23	BC556	
H3t	BCW89	Phi	N	SOT23	BC556	
H4	BCW69R	Phi	R	SOT23R	BC177A	
H4	BCW69R	Phi	R	SOT23R	BC177A	
H5	BCW70R	Phi	R	SOT23R	BC177B	
H5	MBD770DW	Mot	DL	-	Dual UHF schottky diode	
H5	BCW70R	Phi	R	SOT23R	BC177B	
H5	MBD770DW	Mot	DL	-	Dual UHF schottky diode	
H6	BCW89R	Phi	R	SOT23R	BC556	
H6	BCW89R	Phi	R	SOT23R	BC556	
H84	SST5484	Sil	F	SOT23	2N5484	
H84	SST5484	Sil	F	SOT23	2N5484	
H85	SST5485	Sil	F	SOT23	2N5485	
H85	SST5485	Sil	F	SOT23	2N5485	
H86	SST5486	Sil	F	SOT23	2N5486	
H86	SST5486	Sil	F	SOT23	2N5486	
HB	BFN22	SGS	P	SOT23	npn Vce 250V	
HB	BFN22	SGS	P	SOT23	npn Vce 250V	
HC	BFN23	SGS	P	SOT23	pnp Vce 250V	
HC	BFN23	SGS	P	SOT23	pnp Vce 250V	
HG	CFY77-08	Sie	DM	-	20GHz HEMT 0.8dB nf	
HG	CFY77-08	Sie	DM	-	20GHz HEMT 0.8dB nf	
HH	CFY77-10	Sie	DM	-	20GHz HEMT 1.0 dB nf	
HH	BBY51-07	Sie	S	SOT143	dual varicap like BBY51	
HH	CFY77-10	Sie	DM	-	20GHz HEMT 1.0 dB nf	
HH	BBY51-07	Sie	S	SOT143	dual varicap like BBY51	
HQ	2SA1036K	Roh	N	-	pnp 500mA driver	
HQ	2SA1036K	Roh	N	-	pnp 500mA driver	
J0	HSMS-2840	HP	C	SOT23	schottky diode	
J01	SO2906R	-	N	-	2N2906	
J03	SO2907AR	-	R	-	2N2907A	
J05	SO2907R	-	R	-	2N2907	
J1	HSMS-2841	HP	K	SOT23	schottky diode	
J1	ZC830	Zet	C	-	ZC820 varicaps	
J1	BSS138L	Mot	M	SOT23	n-ch enh TMOS fet	
J12	SO2906AR	-	R	-	2N2906A	
J1A	ZC830A	Zet	C	SOT23	varicap hyperabrupt 28V 10pF@2V	
J1B	ZC830B	Zet	C	SOT23	varicap hyperabrupt 28V 10pF@2V	
J2	ZC833	Zet	C	SOT23	ZC823	
J2A	ZC833A	Zet	C	SOT23	varicap hyperabrupt 28V 33pF@2V	



贴片三极管上的印字，与真实名称的对照表.txt

J2B	ZC833B	Zet	C	SOT23	varicap hyperabrupt 28V 33pF@2V
J3	ZC831	Zet	C	SOT23	ZC821
J32	S05400R	SGS	R	-	2N5400
J33	S05401R	SGS	R	-	2N5401
J39	S0692R	SGS	-	-	pnp Vce 300V
J3A	ZC831A	Zet	C	SOT23	varicap hyperabrupt 28V 15pF@2V
J3B	ZC831B	Zet	C	SOT23	varicap hyperabrupt 28V 15pF@2V
J3D	MSB81T1	Mot	-	-	vhf pnp fT 0.6GHz
J4	ZC832	Zet	C	SOT23	ZC823
J4A	MBV109	Mot	C	SOT23	29pF VHF varicap diode
J4A	ZC832A	Zet	C	SOT23	varicap hyperabrupt 28V 22pF@2V
J4B	ZC832B	Zet	C	SOT23	varicap hyperabrupt 28V 22pF@2V
J5	ZC834	Zet	C	SOT23	ZC824
J5A	ZC834A	Zet	C	SOT23	varicap hyperabrupt 28V 47pF@2V
J5B	ZC834B	Zet	C	SOT23	varicap hyperabrupt 28V 47pF@2V
J6	M1M174	Mot	C	-	gp Si diode 100V
J6	ZC835	Zet	C	SOT23	ZC825
J6A	ZC835A	Zet	C	SOT23	varicap hyperabrupt 28V 68pF@2V
J6B	ZC835B	Zet	C	SOT23	varicap hyperabrupt 28V 68pF@2V
J7	ZC836	Zet	C	SOT23	ZC826
J7A	ZC830A	Zet	C	SOT23	varicap hyperabrupt 28V 100pF@2V
J7B	ZC830B	Zet	C	SOT23	varicap hyperabrupt 28V 100pF@2V
J8	BCX71JR	Phi	R	SOT23R	BCY79-ix
J9A	ZC829A	Zet	I	SOT23	varicap hyperabrupt 28V 8.2pF@2V
J9B	ZC829B	Zet	I	SOT23	varicap hyperabrupt 28V 8.2pF@2V
JA	BAV74	Zet	B	SOT23	dual diode cc 50V 0.1A
JA	BAV74	Mot	B	SOT23	dual sw diodes
JBs	BAR74	Sie	C	SOT23	fast sw diode 50V 0.25A
JCs	BAL74	Sie	V	SOT23	fast sw diode 50V 0.25A
JFs	BAL99	Sie	V	SOT23	fast sw diode 70V 0.25A
JG	BAR99	Sie	E	-	fast sw diode 70V 0.25A
JKs	BF1009	Sie	W	SOT143	biased n-ch dg mosfet 1GHz 9V
JL	MRF949	Mot	N	SOT323	nnp RF fT 9GHz
JLs	BF1009S	Sie	W	SOT143	biased n-ch dg mosfet 1GHz 9V
JPs	BAS19	Sie	C	SOT23	120V 250mA fast sw diode
JPs	BAW101	Sie	S	SOT143	pair isolated 300V sw diodes
JRs	BAS20	Sie	C	SOT23	150V 250mA fast sw diode
JS	BAW100	Sie	Y	SOT143	dual isolated fast sw diodes
JSs	BAS21	Sie	C	SOT143	200V 250mA fast sw diode
JTs	BAS28	Sie	S	SOT143	dual isolated fast sw diodes
JTs	BAS28W	Sie	FQ	SOT343	dual isolated fast sw diodes
JV	BAS116	Sie	C	SOT23	250V 75mA Ir 5nA
JX	BAV170	Mot	B	SOT23	dual cc Si diode low Ir
JY	BAV199	Mot	D	SOT23	dual series Si diode low Ir
JZ	BAW156	Mot	A	SOT23	dual ca Si diode low Ir
K	BAT68-03W	Sie	I	SOD323	BAT68 Schottky
K	BBY52-02W	Sie	I	SCD80	UHF varicap 1.75-1.25pF
K	MRF917	Mot	N	SOT323	nnp RF fT 6GHz
K0	HSMP-3830	HP	C	SOT23	gp pin diode HP3830
K1	HSMP-3831	HP	K	SOT23	gp pin diode HP3830
K1	BCW71	Phi	N	SOT23	BC107A
K14	DTA114GE	Roh	N	EMT3	pnp dtr 50V 100mA R2 10k
K14	DTA114GUA	Roh	N	SC70	pnp dtr 50V 100mA R2 10k
K14	DTA114GKA	Roh	N	SC59	pnp dtr 50V 100mA R2 10k
K15	DTA124GKA	Roh	N	SC59	pnp dtr 50V 50mA R2 22k
K16	DTA144GUA	Roh	N	SC70	nnp dtr 50V 100mA R2 47k
K16	DTA144GKA	Roh	N	SC59	nnp dtr 50V 100mA R2 47k
K19	DTA115GUA	Roh	N	SC70	nnp dtr 50V 100mA R2 100k
K19	DTA115GKA	Roh	N	SC59	nnp dtr 50V 100mA R2 100k
K1p	BCW71	Phi	N	SOT23	BC107A
K1t	BCW71	Phi	N	SOT23	BC107A
K2	BCW72	Phi	N	SOT23	BC107B ZXT300
K2	HSMP-3832	HP	D	SOT23	dual HP3830 pin diode
K24	DTC114GUA	Roh	N	SC70	nnp dtr 50V 100mA R2 22k
K24	DTC114GKA	Roh	N	SC59	nnp dtr 50V 100mA R2 22k
K25	DTA124GUA	Roh	N	SC70	pnp dtr 50V 50mA R2 22k
K25	DTA124GKA	Roh	N	SC59	pnp dtr 50V 50mA R2 22k
K26	DTC144GE	Roh	N	EMT3	nnp dtr 50V 100mA R2 47k
K26	DTC144GUA	Roh	N	SC70	nnp dtr 50V 100mA R2 47k
K26	DTC144GKA	Roh	N	SC59	nnp dtr 50V 100mA R2 47k
K29	DTC115GUA	Roh	N	SC70	nnp dtr 50V 100mA R2 100k
K29	DTC115GKA	Roh	N	SC59	nnp dtr 50V 100mA R2 100k
K2p	BCW72	Phi	N	SOT23	BC107B ZXT300
K2t	BCW72	Phi	N	SOT23	BC107B ZXT300
K3	HSMP-3833	HP	A	SOT23	dual HP3830 pin diode



贴片三极管上的印字，与真实名称的对照表.txt

K3	BCW81	Phi	N	SOT23	npn 50V 0.1A 0.2W hfe 420
K31	BCW81R	Phi	R	-	npn 50V 0.1A 0.2W hfe 420
K3p	BCW81	Phi	N	SOT23	npn 50V 0.1A 0.2W hfe 420
K3t	BCW81	Phi	N	SOT23	npn 50V 0.1A 0.2W hfe 420
K4	BCW71R	Phi	R	SOT23R	BC107A
K4	HSMP-3834	HP	B	SOT23	dual HP3830 pin diode
K5	BCW72R	Phi	R	SOT23R	BC107B ZTX300
K6	BCV71R	Phi	R	SOT23R	BC546A
K7	BCV71	Phi	N	SOT23	BC546A
K7p	BCV71	Phi	N	SOT23	BC546A
K7t	BCV71	Phi	N	SOT23	BC546A
K8	BCV72	Phi	N	SOT23	BC546B
K8p	BCV72	Phi	N	SOT23	BC546B
K8t	BCV72	Phi	N	SOT23	BC546B
K9	BCV72R	Phi	R	SOT23R	BC546B
KB	MMBT8099L	Mot	N	SOT23	npn 80V gp
KC	BFQ29P	Sie	N	-	BFT66
KM	BST80	Phi	T	-	VN10
KN	BST84	Phi	T	-	Nch VMOS 200V 0.25A
K0	BST86	Phi	T	-	nch VMOS 180V 0.3A
L	BAT62-03W	Sie	I	SOD323	BAT62 schottky detector
L	BBY53-02W	Sie	I	SCD80	varicap 5.3-2.2 pF
L0	HSMP-386B	HP	C	SOT323	gp RF pin diode
L0	HSMP-3860	HP	C	SOT23	dual series pin diode
L0	BAT721S	Phi	C	SOT23	dual series 40V 200mA schottky
L05	ZLLS500	Zet	C	SOT23	schottky 40V 0.7A low leakage high temp
L1	BSS65	Zet	N	-	npn 12V 0.1A 400MHz sw
L10	ZLLS1000	Zet	C	SOT23	schottky 40V 1.1A low leakage high temp
L14	DTB114GK	Rho	N	SC59	"npn dtr 0.5A, R2 10k "
L14	DTD114GK	Rho	N	SC59	"npn dtr 0.5A, R2 10k "
L2	HSMP-3862	HP	D	SOT23	dual RF pin diode
L2	BSS69	Zet	N	-	npn 40V 0.1A 200MHz sw
L20	BAS29	Nat	C	SOT23	Si diode 120V 50mA
L21	BAS31	Nat	D	SOT23	dual BAS29 diodes
L22	BAS35	Nat	A	SOT23	dual BAS29 diodes
L3	BSS70	Zet	N	-	npn 40V 0.1A 200MHz sw
L3	MMBC1623L3	Mot	N	-	npn 40V gp
L3	HSMP-3863	HP	A	SOT23	ca gp RF pin diode
L30	BAV23	Phi	S	SOT143	dual 200V 225mA diodes
L4	HSMP-3864	HP	B	SOT23	cc gp RF pin diode
L4	BAT54W	Phi	C	SOT323	BAT85 schottky
L4	MMBC1623L4	Mot	N	-	npn 40V gp
L41	BAT74	Phi	S	SOT143	2x BAT85
L42p	BAT54A	Phi	A	SOT23	dual c anode schottky
L43p	BAT54C	Phi	B	SOT23	dual c cathode schottky
L44p	BAT54S	Phi	D	SOT23	dual series schottky
L4p	BAT54	Phi	C	SOT23	BAT85 schottky
L4Z	BAT54	Zet	C	SOT23	BAT85 schottky
L5	BSS65R	Zet	R	-	npn 12V 0.1A 400MHz sw
L5	MMBC1623L5	Mot	N	-	MPS3904 hfe 135-270
L51	BAS56	Phi	S	SOT143	dual 60V 200mA diodes
L6	BAR17	Sie	C	-	pin diode
L6	BSS69R	Zet	N	-	npn 40V 0.1A 200MHz sw
L6	MMBC1623L6	Mot	N	-	MPS3904 hfe 200-400
L7	BSS70R	Zet	N	-	npn 40V 0.1A 200MHz sw
L7	MMBC1623L7	Mot	N	-	MPS3904 hfe 300-600
L7	BAR14-1	Sie	D	-	dual pin 100mA max
L8	BAT721A	Phi	A	SOT23	dual c anode 40V 200mA schottky
L8	BAR15-1	Sie	A	-	dual pin 100mA max
L9	BAT721C	Phi	B	SOT23	dual c cathode 40V 200mA schottky
L9	BAR16-1	Sie	B	-	dual pin 100mA max
LAp	BF550	Phi	N	SOT23	npn 40V 25mA
LB	S525T	Tfk	G	-	n-ch vhf mosfet 200MHz
LBs	BF999	Sie	G	SOT23	n-ch vhf mosfet 300MHz
LDs	BF543	Sie	G	SOT23	n-ch vhf mosfet 300MHz
LEs	BF660	Sie	N	SOT23	BF606A npn vhf osc fT 800MHz
LGs	BF775A	Sie	N	SOT23	npn RF fT 5.6GHz for IF amp
LH	BF569R	Tfk	R	-	BF970 npn RF
LHs	BF569	Sie	N	SOT23	BF970 npn RF
LKs	BF799	Sie	N	SOT23	BF959
LKs	BF799W	Sie	N	SOT323	BF959
LKs	BF799	Sie	N	SOT23	BF959
LKs	BF799W	Sie	N	SOT323	BF959
LM	BST120	Phi	T	-	p-ch DMOSfet 60V 0.3A
LN	BST122	Phi	T	-	p-ch DMOSfet 50V 0.25A



贴片三极管上的印字，与真实名称的对照表.txt

LOs	BF775	Sie	N	SOT23	BFQ69
LOs	BF775W	Sie	N	SOT323	BFQ69
LRs	BF517	Sie	T	SOT23	BF763 2.5 GHz
LSs	BF770A	Sie	N	SOT23	"npn low noise RF, Ft 6GHz"
M	BAR64-02W	Sie	I	SCD80	pin diode
M	BAR65-07	Sie	S	SOT143	dual pin diode
M (blue)	BAR65-03W	Sie	I	SOD323	pin diode
M (white)	BBY55-03W	Sie	I	SOD323	5.4-2.3pF varicap in
M08	PMBFJ308	Phi	F	SOT23	VHF n-ch JFET J308
M09	PMBFJ309	Phi	F	SOT23	VHF n-ch JFET J309
M1	BFR30	Phi	F	SOT23	BFW11 BF245
M10	PMBFJ310	Phi	F	SOT23	VHF n-ch JFET J310
M10	PMBFJ310	Phi	F	SOT23	J310 n-ch jfet
M1B	MMBT2222L	Mot	N	SOT23	2N2222
M1E	MMBTA43L	Mot	N	SOT23	MPSA43 200V Vce npn
M1F	MMBT5550L	Mot	N	SOT23	2N5550 npn 140V
M1J	MMBT2369L	Mot	N	SOT23	2N2369A
M2	BFR31	Phi	F	SOT23	BFW12 BF245
M2B	MMBT2907L	Mot	N	SOT23	2N2907 pnp gp
M2C	MMBTA70L	Mot	N	SOT23	gp pnp MPSA70
M3	BFT46	Phi	F	SOT23	n-ch fet gp low level amp
M3	MMBA812M3	Mot	N	-	2N5086 hfe 60-120 pnp
M31	BSD20	Phi	XQ	-	n-ch depl sw mosfet 10V
M32	BSD22	Phi	XQ	-	n-ch depl sw mosfet 20V
M3A	MMBTH24L	Mot	N	SOT23	npn VHF amp 400MHz fT 30V
M3B	MMBT918L	Mot	N	SOT23	2N918 UHF amp
M3J	MMBTH69L	Mot	N	SOT23	pnp VHF amp 2GHz fT 15V
M4	BSR56	Phi	F	-	2N4856 n-ch fet
M4	MBD110DW	Mot	DL	SOT363	dual UHF schottky
M4A	MMBV109	Mot	C	SOT323	Hyperabrupt varicap
M4B	MMBV432	Mot	B	SOT23	dual cc varicap 45pF/2V
M4C	MMBV3102	Mot	C	SOT23	Hyperabrupt varicap
M4E	MMBV105G	Mot	C	SOT23	Hyperabrupt varicap
M4F	MMBD353	Mot	D	SOT23	dual MBD101 in series
M4G	MMBV2101	Mot	C	SOT23	varicap 6.8pF MV2101
M5	BSR57	Phi	F	-	2N5457 n-ch fet
M5	MMBA812M5	Mot	N	-	2N5086 hfe 135-270 pnp
M5	MMBD352W	Mot	Z	SOT323	2x MBD101 in series
M56	BF1100	Phi	W	SOT143	dg mosfet 14V 30mA 0.2W
M57	BF1100R	Phi	UQ	SOT143R	dg mosfet 14V 30mA 0.2W
M5C	MMBD7000	Mot	D	SOT23	100V 2x series sw diodes
M6	BSR58	Phi	F	SOT23	2N4858 n-ch fet
M6	MMBA812M6	Mot	N	-	2N5086 hfe 200-400 pnp
M6	BSS66	Zet	N	-	npn 40V 0.1A sw fT 250MHz
M6A	MMBF4416	Mot	F	SOT23	2N4416 n-ch rf jfet
M6B	MMBF5484	Mot	F	SOT23	2N5484 n-ch rf jfet
M6C	MMBFU310	Mot	F	SOT23	U310 n-ch rf jfet
M6E	MMBF5460	Mot	F	SOT23	2N5460 n-ch rf jfet
M6H	MMBD354	Mot	A	SOT23	dual MBD101 cc
M7	BSS67	Zet	N	-	npn 40V 0.1A sw fT 300MHz
M7	MMBA812M7	Mot	N	-	2N5086 hfe 300-600 pnp
M74	BSS83	Phi	XQ	-	n-ch enh sw mosfet
M8	BSS66R	Zet	R	-	npn 40V 0.1A sw fT 250MHz
M8	BSH103	Phi	M	SOT23	n-ch 50V 0.11A mosfet
M89	BF989	Phi	K	-	BF960
M8p	BSN20	Phi	M	SOT23	n-ch 50V 0.11A mosfet
M9	BSS67R	Zet	R	-	npn 40V 0.1A sw fT 300MHz
M90	BF990	Phi	W	-	BF980
M91	BF991	Phi	W	-	BF981
M92	BF992	Phi	W	-	BF982
M94	BF994	Phi	W	-	BF964
M96	BF996	Phi	W	-	BF966
M97	BFR101A	-	-	-	-
M98	BFR101B	-	-	-	-
MA	M1MA151AT	Mot	E	SOT346	40V 100mA sw diode
MA	MBT3904DW1	Mot	DN	SOT363	dual 2N3904
MA	M1MA152AT	Mot	E	SOT346	80V 100mA sw diode
MA	BFS17	-	N	SOT23	BFW92
MB	BF995	Sie	W	-	n-ch vhf dg mosfet BF961
MB	MBT3904DW9	Mot	-	-	dual 2N3904
MC	ZVN3306F	Zet	M	SOT23	n-ch mosfet 60V 150mA
MCs	BFS17P	Sie	N	SOT23	BFW92
MCs	BFS17PW	Sie	N	SOT323	BFW92
MF	ZVN3310F	Zet	M	SOT23	n-ch mosfet 100V 100mA
MG	BF994S	Tfk	W	-	BF964 n-ch dg vhf mosfet



贴片三极管上的印字，与真实名称的对照表.txt

MH	BF996S	Tfk	W	-	BF966	n-ch dg vhf mosfet
MH	M1MA141KT		Mot	C	SOT323	40V 100mA sw diode
MH	M1MA151KT		Mot	C	SOT346	40V 100mA sw diode
MI	M1MA142KT		Mot	C	SOT323	80V 100mA sw diode
MI	M1MA152KT		Mot	C	SOT346	80V 100mA sw diode
ML	ZVP3306F		Zet	M	SOT23	p-ch mosfet 60V 90mA
MN	M1MA141WA		Mot	A	SOT323	d diode ca 40V 100mA
MN	M1MA151WA		Mot	A	SOT346	d diode ca 40V 100mA
MO	M1MA142W		Mot	A	SOT323	d diode ca 80V 100mA
MO	M1MA152W		Mot	A	SOT346	d diode ca 80V 100mA
MOR	BF998R	Tfk	UQ	SOT143R	n-ch vhf dg mosfet	BF988
MOS	BF998	Sie	W	SOT143	n-ch vhf dg mosfet	BF988
MR	BF998W	Sie	UQ	SOT343	n-ch vhf dg mosfet	BF988
MR	ZVP3310F		Zet	M	SOT23	p-ch mosfet 100V 75mA
MS	CF739	Sie	W	-	dg GaAsfet	2GHz
MT	M1MA141WK		Mot	B	SOT323	dual diode cc 40V 100mA
MT	M1MA151WK		Mot	B	SOT346	dual diode cc 40V 100mA
MU	M1MA142WK		Mot	B	SOT323	dual diode cc 80V 100mA
MU	M1MA152WK		Mot	B	SOT346	dual diode cc 80V 100mA
MU	ZVN3320F		Zet	M	SOT23	n-ch mosfet 200V 60mA
MX	CF750	Sie	U	-	"biased dg GaAsfet,	3-6V"
MY	VN10LF	Zet	M	SOT23	n-ch mosfet	60V 150mA
MY	BF1012	Sie	W	-	n-ch dg mosfet	1GHz 12V
MZ	ZVN4106F		Zet	M	SOT23	n-ch mosfet 60V 200mA
MZ	BF1005	Sie	W	-	n-ch dg mosfet	1GHz 5V
N	DAN202K	Roh	B	-	80V 100mA dual diode	
N0	TN0200T	Nat	M	SOT23	n-ch mosfet	0.6A Id
N05	S02484	SGS	N	-	2N2484	
N08	S0930	SGS	N	-	2N930	
N1	MMBT100	Nat	N	-	npn gp sw	500mA
N1	MMBF201N		Mot	M	SOT23	n-ch tmosfet 20V 0.3A Id
N1	MRF571	Mot	N	SOT416	8 GHz 40mA npn RF	
N1	TN0201T	Tem	M	SOT23	n-ch mosfet	0.3A Id 0.2W
N10	S0918	SGS	N	-	2N918	
N11	S02369	SGS	N	-	2N2369	
N12	S02221	SGS	N	-	2N2221	
N13	S02222	SGS	N	-	2N2222	
N18	S01711	SGS	N	-	2N1711	
N2	MGSF1N02LT1		Mot	M	SOT23	"n-ch mosfet, 20V 85mA"
N2	MMBC1653N2		Mot	N	-	npn 130V 50mA hfe 50-130
N2	BFS520	Phi	N	SOT323	npn RF 9GHz	70mA
N20	S02222A	SGS	N	-	2N2222A	
N27	S01893	SGS	N	-	2N1893	
N28	BFR520	Phi	N	SOT23	npn RF 9GHz	70mA
N29	BFR540	Phi	N	SOT23	npn RF 9GHz	120mA
N3	MMBC1653N3		Mot	N	-	npn 130V 50mA hfe 100-220
N3	MGSF1N03L		Mot	M	SOT23	n-ch TMOS mosfet 30V 0.75A
N30	BFR505	Phi	N	SOT23	npn RF 9GHz	15V 18mA
N33	BFG505	Phi	TQ	SOT143	npn RF 9GHz	15V 18mA
N36	BFG520	Phi	X	SOT143	npn RF 9GHz	70mA
N37	BFG540	Phi	X	SOT143	npn RF 9GHz	120mA
N38	BFG590	Phi	TQ	SOT143	npn RF 5GHz	15V 0.2A
N39	BFG505X	Phi	X	-	npn RF 9GHz	15V 18mA
N4	MMBC1653N4		Mot	N	-	npn 130V 50mA hfe 150-330
N44	BFG590X	Phi	X	-	npn RF 5GHz	15V 0.2A
N5	MMBC1654N5		Mot	N	-	npn 160V 50mA hfe 50-130
N54	S02221A	SGS	N	-	2N2221A	
N6	MMBC1653N6		Mot	N	-	npn 160V 50mA hfe 100-220
N6	BFS25A	Phi	N	SOT323	npn RF 5GHz	6.5mA 32 mW
N7	MMBC1653N7		Mot	N	-	npn 160V 50mA hfe 150-330
N70	BFG10	Phi	TQ	SOT143	npn 8V 250mA	1.8GHz pwr amp
N71	S03904	SGS	N	-	2N3904	
N71	BFG10X	Phi	X	-	8V 250mA	1.8GHz pwr amp
N72	BFG11	Phi	TQ	SOT143	8V 400mA	1.8GHz pwr amp
N72	S03903	SGS	N	-	2N3903	
N73	BFG11X	Phi	X	-	8V 400mA	1.8GHz pwr amp
N79	S05550	SGS	N	-	2N5550	
N80	S05551	SGS	N	-	2N5551	
N81	S02369A	SGS	N	-	2N2369A	
N9	DAN222	Mot	B	SOT416	dual cc si diode	
N91	S0642	SGS	N	-	npn Vce	300V
N94	S0517	SGS	N	-	npn darlington	
NA	CFY35-20		Sie	DM	-	10GHz GaAsfet
NB	CFY35-23		Sie	DM	-	10GHz GaAsfet
NY	BF1012s	Sie	W	-	n-ch dg mosfet	1GHz 12V

贴片三极管上的印字，与真实名称的对照表.txt

NZ	MGSF1N02L	Mot	M	-	n-ch TMOS FET
O (white)	BAT14-03W		Sie	I	SOD323 RF Schottky 4V 90mA
005	S02484R SGS	R	-	2N2484	
008	S0930R SGS	R	-	2N930	
010	S0918R SGS	R	-	2N918	
012	S02221R SGS	R	-	2N2221	
013	S02222R SGS	R	-	2N2222	
02	BST82 Phi	M	SOT23	n-ch mosfet 80V 175mA	
020	S02222AR	SGS	R	-	2N2222A
027	S01893R SGS	R	-	2N1893	
054	S02221AR	SGS	R	-	2N2221A
079	S05550R SGS	R	-	2N5550	
080	S05551R SGS	R	-	2N5551	
091	S0642R SGS	R	-	npn Vce 300V	
P	KV1841E Tok	I	URD	uhf varicap 7-15pF	
P	DAP202K Roh	A	-	80V 100mA dual	
P (white)	BAT15-03W		Sie	I	SOD323 RF Schottky 4V 100mA
P0	BFP90A Phi	CX	SOT173	BFG90A	
P0	TP0101T Tem	M	SOT23	p-ch mosfet 0.5A 12V	
P0	HSMS-285B	HP	C	SOT323 zero-bias schottky diode uW det	
P0	HSMS-2850	HP	C	SOT23 zero-bias schottky diode uW det	
p01	PDTA143ET	Phi	N	SOT23 pnp dtr 4k7+4k7	
P01	S02906 SGS	N	-	2N2906	
P01	SST201 Sil	F	SOT23	J201 n-ch fet	
p02	PDTC143ET	Phi	N	SOT23 npn 4k7+4k7 bias res	
P02	SST202 Sil	F	SOT23	J202 n-ch fet	
P03	S02907A SGS	N	-	2N2907A	
P03	SST203 Sil	F	SOT23	J203 n-ch fet	
P04	SST204 Sil	F	SOT23	J204 n-ch fet	
P05	S02907 SGS	N	-	2N2907	
P06	S02894 SGS	N	-	2N2894	
P1	BFP91A Phi	CX	SOT173	BFG91A	
P1	SST201 Tem	F	SOT23	J201 n-ch jfet	
P1	BFR92 Phi	N	SOT23	BFR90	
p11	PDTA114TT	Phi	N	SOT23 pnp dtr	
p12	PDTC114TT	Phi	N	SOT23 npn dtr	
P12	S02906A SGS	N	-	2N2906A	
p16	PDTC114ET	Phi	N	SOT23 npn dtr	
p17	PDTC124ET	Phi	N	SOT23 npn dtr	
p18	PDTC143ZT	Phi	N	SOT23 npn dtr 4k7+47k	
p19	PDTA143ZT	Phi	N	SOT23 pnp dtr 4k7+47k	
p1A	PMMT3904	Phi	N	SOT23 2N3904	
p1A	PXT3904 Phi	N	SOT89	2N3904	
p1B	PMBT2222	Phi	N	SOT23 2N2222	
p1D	PMBTA42 Phi	N	SOT23	MPSA42 300V npn	
p1D	PXTA42 Phi	N	SOT89	MPSA42 300V npn	
P1D	PZTA42 Mot	P	-	MPSA42 10mA 300V npn	
P1D	PZTA42 Mot	P	-	MPSA42 300V npn	
p1F	PMBT5550	Phi	N	SOT23 2N5550 140V npn	
P1F	PZT2222A	Mot	P	-	2N2222A sw npn
p1G	PMMTA06 Phi	N	SOT23	MPSA06	
p1J	PMBT2369	Phi	N	SOT23 2N2369	
p1K	PMBT6428	Phi	N	SOT23 MPSA18 50V	
p1L	PMBT6429	Phi	N	SOT23 MPSA18 45V	
p1M	PXTA13 Phi	N	SOT89	MPSA13 darlington	
p1M	PMBTA13 Phi	N	SOT23	MPSA13 darlington	
p1N	PMBTA14 Mot	N	SOT23	MPSA14 darlington	
p1N	PXTA14 Mot	N	SOT89	MPSA14 darlington	
P1N	PZTA14 Mot	P	-	MPSA14 darlington	
P1N	PZTA14 Mot	P	-	npn darlington MPSA14	
p1P	PMBT2222A	Phi	N	SOT23 2N2222A	
p1P	PXT2222A	Phi	N	SOT89 2N2222A	
p1Q	PMBT5088	Phi	N	SOT23 MPSA18 Vce 30V	
P2	BFR92A Phi	N	SOT23	BFR90A	
P2	HSMSM-285C	HP	D	SOT323 dual series HSMS-285B	
P2	HSMSM-2852	HP	D	SOT23 dual series HSMS-285B	
P25	S03906 SGS	N	-	2N3906	
P26	S03905 SGS	N	-	2N3905	
p2A	PMBT3906	Phi	N	SOT23 2N3906	
p2A	PXT3906 Phi	O	SOT89	2N3906	
p2B	PMBT2907	Phi	N	SOT23 2N2907	
p2D	PMBTA92 Phi	N	SOT23	MPSA92 pnp Vce 300V	
p2D	PXTA92 Phi	O	SOT89	MPSA92 pnp Vce 300V	
P2D	PZTA92 Mot	P	-	MPSA92 300V pnp	
p2F	PMBT2907A	Phi	N	SOT23 2N2907A	



贴片三极管上的印字，与真实名称的对照表.txt

p2F	PXT2907A	Phi	O	SOT89	2N2907A
P2F	PZT2907A	Mot	P	-	2N2907A sw pnp
p2G	PMBTA56	Phi	N	SOT23	MPSA56
p2L	PMBT5401	Phi	N	SOT23	2N5401 pnp 150V
P2p	BFR92AW	Phi	N	SOT323	BFR90A
p2T	PMBT4403	Phi	N	SOT23	2N4403
p2T	PXT4403	Phi	O	SOT89	2N4403
p2V	PXTA64	Phi	O	SOT89	MPSA64 darlington
P2V	PZTA64	Mot	P	-	MPSA64 darlington
p2X	PMBT4401	Phi	N	SOT23	2N4401
p2X	PxT4401	Phi	O	SOT89	2N4401
P3	MMBF2202P	Mot	M	SOT23	p-ch TMOSfet 0.3A 20V
P3	TP0202T	Tem	M	-	p-ch mosfet 0.3A 20V
p31	PDTA143XT	Phi	N	SOT23	pnp dtr 4k7+10k
p32	PDTC143XT	Phi	N	SOT23	pnp dtr 4k7+10k
P32	SO5400	SGS	N	-	2N5400
P33	SO5401	SGS	N	-	2N5401
P38	SST4338	Sil	F	SOT23	2N4338
P39	SST4339	Sil	F	-	2N4339
P39	SO692	SGS	-	-	pnp Vce 300V
P4	BFR92R	Phi	R	SOT23R	BFR90
P40	SST4340	Sil	F	SOT23	2N4340
P41	SST4341	Sil	F	SOT23	2N4341
P5	BFR92AR	Phi	R	SOT23R	BFR90A
P5	FMMT2369A	Zet	N	-	2N2369A
P5	HSMSM-2855	HP	S	SOT143	separate pair HSMS-2850
P57	SST5457	Sil	F	SOT23	2N5457
P58	SST5458	Sil	F	SOT23	2N5458
P59	SST5459	Sil	F	SOT23	2N5459
P6	BFP96	Phi	CX	SOT173	BFG96
P60	SST5460	Sil	F	SOT23	2N5460
P61	SST5461	Sil	F	SOT23	2N5461
P62	SST5462	Sil	F	SOT23	2N5462
P63	SST5463	Sil	F	SOT23	2N5463
P64	SST5464	Sil	F	SOT23	2N5464
P65	SST5465	Sil	F	SOT23	2N5465
p6G	PMBF4393	Phi	F	SOT23	n-ch jfet 2N4393
p6J	MMBF4391	Phi	F	SOT23	n-ch jfet 2N4391
p6K	MMBF4932	Phi	F	SOT23	n-ch jfet 2N4932
p6S	PMBFJ176	Phi	F	-	J176 n-ch jfet
p6W	PMBFJ175	Phi	F	SOT23	J175 p-ch jfet
p6X	PMBFJ174	Phi	F	-	J174 p-ch jfet sw/chopper
p6Y	PMBFJ177	Phi	F	SOT23	J177 p-ch jfet
P8A	FLLD258	Zet	B	SOT23	low leakage dual ca Si diode
P9	BCX70KR	Phi	R	SOT23R	BCY59-x
P9	DAP222	Mot	A	SOT416	dual ca sw diode
PC	MGSF1P02L	Mot	M	SOT23	p ch enh tmosfet
PD	BSS84L	Mot	M	SOT23	p-ch enh tmosfet
pG3	PMST5551	Phi	N	SOT323	2N5551
PH2	SST4302	Sil	F	SOT23	2N4302
PH3	SST4303	Sil	F	SOT23	2N4303
PH4	SST4304	Sil	F	SOT23	2N4304
pJ1	BSH101	Phi	M	SOT23	n-ch 60V 0.7A mosfet
pJ2	BSH102	Phi	M	SOT23	n-ch 30V 1A mosfet
pJ3	BSH103	Phi	M	SOT23	n-ch 30V 0.8A mosfet
PL	BB149A	Phi	I	SOD323	2-18pF varicap
POs	BAR64	Sie	C	SOT23	single 200V RF pin
PPs	BAR64-04	Sie	D	SOT23	dual series 200V RF pin
PPs	BAR64-04W	Sie	D	SOT323	dual series 200V RF pin
PRs	BAR64-05	Sie	B	SOT23	dual cc 200V RF pin
PRs	BAR64-05W	Sie	B	SOT323	dual cc 200V RF pin
PSs	BAR64-06	Sie	A	SOT23	dual ca 200V RF pin
PSs	BAR64-06W	Sie	A	SOT323	dual ca 200V RF pin
Q3	MMBC1321Q3	Mot	N	-	npn VHF amp fT 0.6GHz
Q4	MMBC1321Q4	Mot	N	-	npn VHF amp fT 0.6GHz
Q5	MMBC1321Q5	Mot	N	-	npn VHF amp fT 0.6GHz
QQ	2SC4536	Nec	P	-	npn RF fT 5.7GHz 2W hFE 40-80
QR	2SC4536	Nec	P	-	npn RF fT 5.7GHz 2W hFE 60-120
QS	2SC4536	Nec	P	-	npn RF fT 5.7GHz 2W hFE 100-200
R	BA895	Sie	I	SCD80	-
R	BA585	Sie	I	SOD123	pin diode 50mA max
R (white)	BA595	Sie	I	SOD323	UHF pin diode 50mA max
R (yellow)	BA597	Sie	I	SOD323	UHF pin diode 100mA max
R1	UMT4401	Rho	N	SC70	2N4401
R1	BFR93	SGS	N	SOT23	BFR91



贴片三极管上的印字，与真实名称的对照表.txt

R1	HSMS-8101	HP	K	SOT23	10-14GHz schottky mixer
R13	2SC4885	Nec	WQ	SOT143	npn RF fT 3.5GHz
R1A	SST3904 Rho	N	SOT23	2N3904	
R1A	UMT3904 Rho	N	SC70	2N3904	
R1A	MMST3904	Rho	N	SC59	2N3904
R1G	SSTA06 Rho	N	SOT23	MPSA06	
R1G	MMSTA06 Rho	N	SC59	MPSA06	
R1H	SSTA05 Rho	N	SOT23	MPSA05	
R1J	SST6427 Rho	N	SOT23	-	
R1K	MMST6428	Rho	N	SC59	-
R1M	SSTA13 Rho	N	SOT23	MPSA13	
R1M	MMSTA13 Rho	N	SC59	MPSA13	
R1N	SSTA14 Rho	N	SOT23	MPSA14	
R1N	MMSTA14 Rho	N	SC59	MPSA14	
R1O	MMST5088	Rho	N	SC59	2N5088
R1P	SST2222A	Rho	N	SOT23	2N2222A
R1P	UMT2222A	Rho	N	SC70	2N2222A
R1P	MMST2222A	Rho	N	SC59	2N2222A
R2	BFR93A Phi	N	SOT23	BFR91A	
R2	2SC2351P	Nec	N	SOT23	npn RF fT 4.5 GHz hfe 40-120
R2	2SC4225	Nec	N	SOT323	npn RF fT 4GHz hfe 40-120
R22	2SC3356	Nec	N	SOT23	npn RF fT 7GHz 20V 0.2W
R23	2SC3356Q	Nec	N	SOT23	npn RF fT 7GHz hfe 50-100
R23	2SC4226	Nec	N	SOT323	npn RF fT 4.5 GHz hfe 40-80
R24	2SC3356R	Nec	N	SOT23	npn RF fT 7GHz hfe 80-160
R24	2SC4226	Nec	N	SOT323	npn RF fT 4.5 GHz hfe 70-140
R25	2SC3356S	Nec	N	SOT23	npn RF fT 7GHz hfe 125-250
R25	2SC4226	Nec	N	SOT323	npn RF fT 4.5 GHz hfe 125-250
R26	2SC4093Q	Nec	WQ	SOT143	npn RF fT 6.5 GHz hfe 50-100
R26	2SC5011Q	Nec	WQ	SOT343	npn RF fT 6.5 GHz hfe 50-100
R27	2SC4093R	Nec	WQ	SOT143	npn RF fT 6.5 GHz hfe 80-160
R27	2SC5011R	Nec	WQ	SOT343	npn RF fT 6.5 GHz hfe 80-160
R28	2SC4093S	Nec	WQ	SOT143	npn RF fT 6.5 GHz hfe 125-250
R28	2SC5011S	Nec	WQ	SOT343	npn RF fT 6.5 GHz hfe 125-250
R2A	SST3906 Rho	N	SOT23	2N3906	
R2A	UMT3906 Rho	N	SC70	2N3906	
R2A	MMST3906	Rho	N	SC59	2N3906
R2B	MMST2907	Rho	N	SC59	2N2907
R2F	SST2907A	Rho	N	SOT23	2N2907A
R2F	UMT2907A	Rho	N	SC70	2N2907A
R2F	MMST2907A	Rho	N	SC59	2N2907A
R2G	SSTA56 Rho	N	SOT23	MPSA56	
R2G	MMSTA56 Rho	N	SC59	MPSA56	
R2K	MMST8598	Rho	N	SC59	-
R2O	MMST5087	Rho	N	SC59	-
R2P	MMST5086	Rho	N	SC59	-
R2T	SST4403 Rho	N	SOT23	2N4403	
R2T	UMT4403 Rho	N	SC70	2N4403	
R2T	MMST4403	Rho	N	SC59	2N4403
R2V	MMSTA64 Rho	N	SC59	MPSA64	
R2X	SST4401 Rho	N	SCOT23	2N4401	
R2X	MMST4401	Rho	N	SC59	2N4401
R3	2SC2351Q	Nec	N	SOT23	npn RF fT 4.5 GHz hfe 100-200
R3	2SC4225	Nec	N	SOT323	npn RF fT 4GHz hfe 100-200
R32	2SC3583	Nec	N	SOT23	npn RF fT 9GHz @ 20mA
R33	2SC3583Q	Nec	N	SOT23	npn RF fT 9GHz hfe 50-100
R33	2SC4227	Nec	N	SOT323	npn RF fT 7 GHz hfe 40-90
R34	2SC3583R	Nec	N	SOT23	npn RF fT 9GHz hfe 80-160
R34	2SC4227	Nec	N	SOT323	npn RF fT 7 GHz hfe 70-150
R35	2SC3583S	Nec	N	SOT23	npn RF fT 9GHz hfe 125-250
R35	2SC4227	Nec	N	SOT323	npn RF fT 7 GHz hfe 110-240
R36	2SC4094Q	Nec	WQ	SOT143	npn RF fT 9GHz hfe 50-100
R36	2SC5012	Nec	WQ	SOT343	npn RF fT 9GHz hfe 50-100
R37	2SC4094R	Nec	WQ	SOT143	npn RF fT 9GHz hfe 80-160
R37	2SC5012	Nec	WQ	SOT343	2SC4094 but min-mold pkg
R38	2SC4094S	Nec	WQ	SOT143	npn RF fT 9GHz hfe 125-250
R38	2SC5012	Nec	WQ	SOT343	npn RF fT 9GHz hfe 125-250
R3B	SST918 Rho	N	SOT23	2N918	
R3B	MMST918 Rho	N	SC59	2N918	
R4	BFR93R Tfk	R	-	BFR91	
R4	2SC4092	Nec	WQ	SOT143	npn RF fT 6GHz hfe 40-120
R42	2SC3585	Nec	N	SOT23	npn RF fT 10GHz @ 10mA
R43	2SC3585Q	Nec	N	SOT23	npn RF l fT 10GHz hfe 50-100
R43	2SC4228	Nec	N	SOT323	npn RF fT 8.5GHz hfe 50-100
R44	2SC3585R	Nec	N	SOT23	npn RFfT 10GHz hfe 80-160



贴片三极管上的印字，与真实名称的对照表.txt

R44	2SC4228	Nec	N	SOT323	npn RF fT 8.5GHz hfe 80-160
R45	2SC3585S	Nec	N	SOT23	npn RF fT 10GHz hfe 125-250
R45	2SC4228	Nec	N	SOT323	npn RF fT 8.5GHz hfe 125-250
R46	2SC4095Q	Nec	WQ	SOT143	npn fT10GHz
R46	2SC5013Q	Nec	WQ	SOT343	npn fT10GHz
R47	2SC4095R	Nec	WQ	SOT143	npn fT10GHz
R47	2SC5013R	Nec	WQ	SOT343	npn fT10GHz
R48	2SC4095S	Nec	WQ	SOT143	npn fT10GHz
R48	2SC5013S	Nec	WQ	SOT343	npn fT10GHz
R5	HSMS-8205	HP	S	SOT143	separate pair HSMS-8101
R5	BFR93AR	SGS	R	SOT23R	BFR91A
R5	2SC4092	Nec	WQ	SOT143	npn RF fT 6GHz hfe 100-200
R62	2SC3663	Nec	N	SOT23	npn RF fT 4GHz @1mA
R64	2SC4091	Nec	WQ	-	npn RF fT 4GHz @1mA
R66	2SC4091Q	Nec	WQ	SOT143	npn RF fT 4GHz hfe 50-100
R67	2SC4091R	Nec	WQ	SOT143	npn RF fT 4GHz hfe 80-160
R68	2SC4091S	Nec	WQ	SOT143	npn RF fT 4GHz hfe 125-250
R6A	2SC4187	Nec	N	SOT323	npn RF fT 4GHz hfe 50-100
R6B	2SC4187	Nec	N	SOT323	npn RF fT 4GHz hfe 80-160
R6C	2SC4187	Nec	N	SOT323	npn RF fT 4GHz hfe 125-250
R7	HSMS-8207	HP	RQ	SOT145	HSMS-8101 ring quad mixer
R7	BFR106	Phi	N	SOT23	BFR96S
R8	BFG93A	Sie	TQ	SOT143	BFG90
R97	SST1S97	Rho	N	SOT23	TIS97
RA	BFQ81	Sie	N	SOT23	BFQ69 npn fT 5.8GHz
RA	BF772	Sie	X	SOT143	npn RF TV tuners
RAT	SSTA28	Rho	N	SOT23	MPSA28
RAT	MMSTA28	Rho	N	SC59	MPSA28
RAV	MMST8908	Rho	N	SC59	-
RB	MSC1621	Mot	H	-	npn sw 20V 200MHz
RBR	SST6838	Rho	N	SOT23	-
RBs	BF771	Sie	N	SOT23	npn RF fT 8GHz
RBs	BF771W	Sie	N	SOT323	npn RF fT 8GHz
RCs	BFP193	Sie	X	SOT143	BFQ82 npn fT 8GHz
RCs	BFP193W	Sie	Sie	WQ	SOT343 BFQ82 npn fT 8GHz
RCs	BFR193	Sie	N	SOT23	BFQ82 npn fT 8GHz
RCs	BFR193T	Sie	N	SC75	BFQ82 npn fT 8GHz
RDs	BFP180	Sie	X	SOT143	npn RF 8V 4mA fT 7GHz
RDs	BFP180W	Sie	Sie	WQ	SOT343 npn RF 8V 4mA fT 7GHz
RDs	BFR180	Sie	N	SOT23	npn RF 8V 4mA fT 7GHz
RDs	BFR180W	Sie	N	SOT323	npn RF 8V 4mA fT 7GHz
RE	2SC3357	Nec	P	SOT89	npn RF 1.2W fT 6.5GHz
REs	BFS480	Sie	DJ	SOT363	dual RF npn fT 7GHz
REs	BFR280	Sie	N	SOT23	npn RF 8V 8mA fT 7.5GHz
REs	BFR280W	Sie	N	SOT323	npn RF 8V 8mA fT 7.5GHz
REs	BFP280	Sie	X	SOT143	npn RF 8V 8mA fT 7.5GHz
REs	BFP280W	Sie	Sie	WQ	SOT343 npn RF 8V 8mA fT 7.5GHz
RF	2SC3357	Nec	P	SOT89	npn RF 1.2W fT 6.5GHz
RFQ	SST6839	Rho	N	SOT23	-
RFs	BFR181	Sie	N	SOT23	npn RF 12V 20mA fT 8GHz
RFs	BFP181	Sie	X	SOT143	npn RF 12V 20mA fT 8GHz
RFs	BFP181W	Sie	Sie	WQ	SOT343 npn RF 12V 20mA fT 8GHz
RFs	BFS481	Sie	DJ	SOT363	Dual BFR181
RGs	BFR182	Sie	N	SOT23	npn RF12V 35mA fT 8GHz
RGs	BFR182W	Sie	N	SOT323	npn RF12V 35mA fT 8GHz
RGs	BFP182	Sie	X	SOT143	npn RF12V 35mA fT 8GHz
RGs	BFP182W	Sie	Sie	WQ	SOT343 npn RF12V 35mA fT 8GHz
RGs	BFR182T	Sie	N	SC75	npn RF12V 35mA fT 8GHz
RGs	BFS482	Sie	DJ	SOT363	Dual BFR182
RH	2SC3357	Nec	P	SOT89	npn RF 1.2W fT 6.5GHz
RHs	BFR183	Sie	N	SOT23	npn RF 12V 65mA fT 8GHz
RHs	BFR183W	Sie	N	SOT323	npn RF 12V 65mA fT 8GHz
RHs	BFR183T	Sie	N	SC75	npn RF 12V 65mA fT 8GHz
RHs	BFP183	Sie	X	SOT143	npn RF 12V 65mA fT 8GHz
RHs	BFP183W	Sie	Sie	WQ	SOT343 npn RF 12V 65mA fT 8GHz
RHs	BFS483	Sie	DJ	SOT363	Dual BFR183 npn RF
RI	BFP196	Sie	X	SOT143	npn RF 12V 100mA Ft 7.5GHz
RK	2SC3357	Nec	P	SOT89	npn RF 1.2W fT 6.5GHz
RKM	RK7002	Rho	-	SOT23	-
RKs	BFP194	Sie	X	SOT143	npn RF 15V 100mA Ft 5GHz
RKs	BFR194	Sie	N	SOT233	npn RF 15V 100mA Ft 5GHz
RR	BBY59-02V	Inf	I	SC79	hyperabrupt varicap 7-28pF
RR	BFR93P	Sie	N	SOT23	BFR91
RVZ	MMST4126	Rho	N	SC59	2N4126
RW	BFR194	Sie	N	-	npn RF amp 1.5GHz

贴片三极管上的印字，与真实名称的对照表.txt

RZC	SST4124	Rho	N	SOT23	2N4124
RZC	MMST4124	Rho	N	SC59	2N4124
S	BB811 Sie	I	-	-	9.8pF @ 1V 30V max
S	BAP64-02	Phi	I	SOD523	3GHz pin diode
S (blue)	BA592	Sie	I	SOD323	BA282
S (red)	BB640	Sie	I	SOD323	70-3pF varicap
S (white)	BB535	Sie	I	SOD323	18-2pF varicap
S (yellow)	BB639	Sie	I	SOD323	39-2.7pF varicap
S0	HSMP-3880	HP	C	SOT23	pin sw diode
S1	HSMP-3881	HP	K	SOT23	pin sw diode
S1	BBY31 Phi	C	SOT23	BB405	
S12	BBY39 Phi	B	SOT23	2x BBY31	
S14	SST5114 Sil	F	SOT23	2N5114	
S15	SST5115 Sil	F	SOT23	2N5115	
S16	SST5116 Sil	F	SOT23	2N5116	
S16	ZHCS1006	Zet	E	SOT23	60V 1A schottky diode
S1A	S1A Fch	I	DO214	1N4001	
S1B	S1B Fch	I	DO214	1N4002	
S1D	S1D Fch	I	DO214	1N4003	
S1G	S1G Fch	I	DO214	1N4004	
S1J	S1J Fch	I	DO214	1N4005	
S2	BBY40 Phi	C	SOT23	BB809	
S2	BFQ31 Zet	N	-	-	npn vhf 15V 0.1A
S3	BFQ31R Zet	R	-	-	npn vhf 15V 0.1A
S3	BBY51 Sie	B	SOT23	dual cc varicap	
S4	BFQ31A Zet	N	-	-	npn vhf 15V 0.1A
S5	BFQ31AR Zet	R	-	-	npn vhf 15V 0.1A
S5	BBY52 Sie	B	SOT23	dual cc varicap	
S5	BAT15-099	Sie	NQ	SOT143	Dual BAT15 schottky
S56	ZHCS506 Zet	E	SOT23	60V 0.5A schottky diode	
S6	BAT15-099R	Sie	DQ	-	Ring quad BAT15 schottky
S6	BF510 Phi	G	-	BF410A	
S7	BF511 Phi	G	-	BF410B	
S7	SST177 Tem	F	SOT23	J177 p-ch analog sw jfet	
S7	BAT114-099	Sie	NQ	SOT143	Dual schottky
S70	SST270 Sil	F	SOT23	J270 p-ch jfet	
S71	SST271 Sil	F	SOT23	J271 p-ch jfet	
S74	SST174 Sil	F	SOT23	J174 p-ch fet	
S75	SST175 Sil	F	SOT23	J175 p-ch fet	
S76	SST176 Sil	F	SOT23	J176 p-ch fet	
S76	ZHCS756 Zet	E	SOT23	60V 0.75A schottky diode	
S77	SST177 Sil	F	SOT23	J177 p-ch fet	
S7s	BBY53-05	Sie	B	SOT23	dual cc varicap
S7s	BBY53-05W	Sie	B	SOT323	dual cc varicap
S8	BF512 Phi	G	-	BF410C	
S8	BAT14-099	Sie	NQ	SOT143	Dual schottky
S9	BAT14-099R	Sie	DQ	-	Quad crossover ring schottky
S9	BF513 Phi	G	-	BF410D	
SA	BSS123 Sie	M	SOT23	n-ch mosfet 100V 0.17A	
SD	BSS284 Sie	M	SOT23	p-ch mosfet 50V 0.13A	
SE	2SC4703 Nec	P	-	-	npn RF 1.8W fT 6GHz
SF	2SC4703 Nec	P	-	-	npn RF 1.8W fT 6GHz
SFs	BB804 Sie	A	SOT23	dual 45-26pF cc VHF varicap	
SH	2SC4703 Nec	P	-	-	npn RF 1.8W fT 6GHz
SH2	BB814 Sie	A	SOT23	dual 45-20pF cc varicap	
SM	BB914 Sie	B	SOT23	dual varicap for FM radio	
SP	BSS84 Sie	M	SOT23	p-ch mosfet 50V 0.13A	
SR	BSS131 Sie	M	SOT23	n-ch mosfet 240V 0.1A	
SS	BSS138 Sie	M	SOT23	n-ch mosfet 50V 0.22A	
sSG	SN7002 Sie	M	SOT23	n-ch mosfet 60V 0.19A	
ST	BSS139 Sie	M	SOT23	n-ch dep mosfet 250V 0.04A	
T	BB515 Sie	I	SOD323	varicap 17.7pf @ 1V 30V max	
T	BAR67-02W	Sie	I	SCD80	-
T0	TP0601T Tem	M	-	-	p-ch mosfet 60V 0.12A
T0	HSMS-2860	HP	C	SOT23	zero bias schottky diode
T0	HSMS-286B	HP	C	SOT323	zero bias schottky diode
t01	PDTA143ET	Phi	N	SOT23	npn dtr 4k7+4k7
t02	PDTC143ET	Phi	N	SOT23	npn 4k7+4k7 bias res
t04	PMBS3904	Phi	N	SOT23	2N3904
t06	PMBS3906	Phi	N	SOT23	2N3906
T1	BCX17 Phi	N	SOT23	BC327	
T1	IMT1A Roh	DA	-	-	2 x 2SA1037AK pnp
T1	BSS63 Mot	N	SOT23	pnp 100V 0.1A	
t11	PDTA114TT	Phi	N	SOT23	npn dtr
t12	PDTC114TT	Phi	N	SOT23	npn dtr



贴片三极管上的印字，与真实名称的对照表.txt

t16	PDTC114EU	Phi	N	SOT323	npn dtr
t17	PDTC124EU	Phi	N	SOT323	npn dtr
t18	PDTC143ZT	Phi	N	SOT23	npn dtr 4k7+47k
t19	PDTA143ZT	Phi	N	SOT23	pnp dtr 4k7+47k
t1A	PMMT3904	Phi	N	SOT23	2N3904
t1A	PMST3904	Phi	N	SOT323	2N3904
t1B	PMBT2222	Phi	N	SOT23	2N2222
t1B	PMST2222	Phi	N	SOT233	2N2222
t1D	PMBTA42 Phi	N	SOT23	MPSA42	300V npn
t1D	PMSTA42 Phi	N	SOT323	MPSA42	300V npn
t1E	PMBTA43 Mot	N	SOT23	MPSA43	200V npn
t1E	PMSTA43 Mot	N	SOT323	MPSA43	200V npn
t1F	PMBT5550	Phi	N	SOT23	2N5550 140V npn
t1F	PMST5550	Phi	N	SOT323	2N5550 140V npn
t1G	PMMTA06 Phi	N	SOT23	MPSA06	
t1G	PMMTA06 Phi	N	SOT323	MPSA06	
t1H	MMBTA05 Phi	N	SOT323	MPSA05	
t1J	PMBT2369	Phi	N	SOT23	2N2369
t1J	PMBT2369	Phi	N	SOT323	2N2369
t1K	PMBT6428	Phi	N	SOT23	MPSA18 50V
t1K	PMBT6428	Phi	N	SOT323	MPSA18 50V
t1L	PMBT6429	Phi	N	SOT23	MPSA18 45V
t1L	PMBT6429	Phi	N	SOT323	MPSA18 45V
t1M	PMBTA13 Phi	N	SOT23	MPSA13	darlington
t1N	PMBTA14 Mot	N	SOT23	MPSA14	darlington
t1P	PMBT2222A	Phi	N	SOT23	2N2222A
t1P	PMST2222A	Phi	N	SOT323	2N2222A
T1p	BCX17 Phi	N	SOT23	BC327	
t1Q	PMBT5088	Phi	N	SOT23	MPSA18 Vce 30V
t1Q	PMST5088	Phi	N	SOT323	MPSA18 Vce 30V
t1R	PMST5089	Phi	N	SOT323	MPSA18 Vce 25V
T1t	BCX17 Phi	N	SOT23	BC327	
T2	BCX18 Phi	N	SOT23	BC328	
T2	IMT2A Roh	DB	-	2 x 2SA1037AK	pnp
T2	HSMS-286C	HP	D	SOT323	dual series HSMS-286B
T2	HSMS-2862	HP	D	SOT23	dual series HSMS-286B
t23	PDTA114TU	Phi	N	SOT323	pnp dtr R1 10k
t24	PDTC114TU	Phi	N	SOT323	npn dtr R1 10k
t2A	PMBT3906	Phi	N	SOT23	2N3906
t2A	PMST3906	Phi	N	SOT323	2N3906
t2B	PMBT2907	Phi	N	SOT23	2N2907
t2D	PMBTA92 Phi	N	SOT23	MPSA92	pnp Vce 300V
t2D	PMSTA92 Phi	N	SOT323	MPSA92	pnp Vce 300V
t2E	PMBTA93 Phi	N	SOT23	MPSA93	pnp Vce 200V
t2E	PMSTA93 Phi	N	SOT323	MPSA93	pnp Vce 200V
t2F	PMBT2907A	Phi	N	SOT23	2N2907A
t2F	PMBT2907A	Phi	N	SOT323	2N2907A
t2G	PMBTA56 Phi	N	SOT23	MPSA56	
t2G	PMSTA56 Phi	N	SOT323	MPSA56	
t2H	PMBTA55 Phi	N	SOT23	MPSA55	
t2H	PMSTA55 Phi	N	SOT323	MPSA55	
t2L	PMBT5401	Phi	N	SOT23	2N5401 pnp 150V
t2L	PMST5401	Phi	N	SOT323	2N5401 pnp 150V
T2p	BCX18 Phi	N	SOT23	BC328	
t2T	PMBT4403	Phi	N	SOT23	2N4403
t2T	PMST4403	Phi	N	SOT323	2N4403
T2t	BCX18 Phi	N	SOT23	BC328	
t2U	PMBTA63 Phi	N	SOT23	MPSA63	darlington
t2V	PMBTA64 Phi	H	SOT23	MPSA64	darlington
t2X	PMBT4401	Phi	N	SOT23	2N4401
t2X	PMST4401	Phi	N	SOT323	2N4401
T3	BSS63 Phi	N	SOT23	BSS68	
T3	HSMS-286E	HP	A	SOT323	ca dual HSMS-286B
T3	HSMS-2863	HP	A	SOT23	ca dual HSMS-286B
t31	PDTA143XT	Phi	N	SOT23	pnp dtr 4k7+10k
t32	PDTC143XT	Phi	N	SOT23	pnp dtr 4k7+10ks
T32	2SC4182 Nec	N	SOT23	npn RF fT 1.1GHz @3V hfe 60-105	
T33	2SC4182 Nec	N	SOT23	npn RF fT 1.1GHz @3V hfe 85-150	
T34	2SC4182 Nec	N	SOT23	npn RF fT 1.1GHz @3V hfe 120-220	
T4	BCX17R Phi	R	SOT23R	BC327	
T4	HSMS-286F	HP	B	SOT323	cc dual HSMS-286B
T4	HSMS-2864	HP	B	SOT23	cc dual HSMS-286B
T4	MBD330DW	Mot	DL	SOT363	dual UHF schottky diode
T42	2SC3545P	Nec	N	-	npn RF fT 2GHz hfe 50-100
T42	2SC4184 Nec	N	SOT323	npn RF fT1.8GHz hfe 40-80	



贴片三极管上的印字，与真实名称的对照表.txt

T43	2SC3545Q	Nec	N	-	UHF osc/mix fT 2GHz hfe 70-140
T43	2SC4184	Nec	N	SOT323	npn fT1.8GHz hfe 60-120
T44	2SC3545R	Nec	N	-	npn RF fT 2GHz hfe 120-250
T44	2SC4184	Nec	N	SOT323	npn RF fT1.8GHz hfe 100-200
T5	HSMS-2865	HP	S	SOT143	separate dual HSMS-286B
T5	BCX18R	Phi	R	SOT23R	BC328
T6	BSS63R	Phi	R	SOT23R	BSS68
T62	2SC3841P	Nec	N	SOT23	npn RF fT 4GHz hfe 40-80
T62	2SC4186	Nec	N	SOT323	npn RF fT 4GHz hfe 40-80
T63	2SC3841Q	Nec	N	SOT23	npn RF fT 4GHz hfe 60-120
T63	2SC4186	Nec	N	SOT323	npn RF fT 4GHz hfe 60-120
T64	2SC3841R	Nec	N	SOT23	npn RF fT 4GHz hfe 100-200
T64	2SC4186	Nec	N	SOT323	npn RF fT 4GHz hfe 100-200
T7	BSR15	SGS	N	SOT23	2N2907
T71	BSR15R	SGS	R	SOT23R	2N2907
T72	2SC4568	Nec	N	SOT23	npn RF ft 5.5GHz hfe 40-80
T72	2SC4570	Nec	N	SOT323	npn RF ft 5.5GHz hfe 40-80
T73	2SC4568	Nec	N	SOT23	npn RF ft 5.5GHz hfe 60-120
T73	2SC4570	Nec	N	SOT323	npn RF ft 5.5GHz hfe 60-120
T74	2SC4568	Nec	N	SOT23	npn RF ft 5.5GHz hfe 100-200
T74	2SC4570	Nec	N	SOT323	npn RF ft 5.5GHz hfe 100-200
T75	2SC4569	Nec	N	SOT23	npn RF fT 5GHz hfe 40-80
T75	2SC4571	Nec	N	SOT323	npn RF fT 5GHz hfe 40-80
T76	2SC4569	Nec	N	SOT23	npn RF fT 5GHz hfe 60-120
T76	2SC4571	Nec	N	SOT323	npn RF fT 5GHz hfe 60-120
T76	2SC4571	Nec	N	SOT323	npn RF fT 5GHz hfe 100-200
T77	2SC4569	Nec	N	SOT23	npn RF fT 5GHz hfe 100-200
T78	2SC5507	Nec	WQ	SOT343	npn RF fT 25GHz 3V 10mA
T79	2SC5508	Nec	WQ	SOT343	npn RF fT 25GHz 3V 30mA
T7p	BSR15	Phi	N	SOT23	2N2907
T7t	BSR15	Phi	N	SOT23	2N2907
T8	BSR16	SGS	N	SOT23	2N2907A
T80	2SC5507	Nec	WQ	SOT343	npn RF fT 17GHz 3V 90mA
T81	BSR16R	SGS	R	SOT23R	2N2907A
T82	2SC4954	Nec	N	SOT23	npn RF fT12GHz @3V 5mA
T82	2SC4956	Nec	WQ	SOT143	npn RF fT 12GHz @3V 5mA
T82	2SC4958	Nec	N	SOT323	npn RF fT 12GHz @3V 5mA
T82	2SC5014	Nec	WQ	SOT343	npn RF fT 12GHz @3V 5mA
T83	2SC4955	Nec	N	SOT23	npn RF fT 12GHz @3V 10mA
T83	2SC4957	Nec	WQ	SOT143	npn RF fT 12GHz @3V 10mA
T83	2SC4959	Nec	N	SOT323	npn RF fT 12GHz @3V 10mA
T83	2SC5015	Nec	WQ	SOT343	npn RF fT 12GHz @3V 10mA
T84	2SC5177	Nec	N	SOT23	npn RF fT 13GHz @2V 7mA
T84	2SC5179	Nec	N	SOT323	npn RF fT 13GHz @2V 7mA
T84	2SC5178	Nec	WQ	SOT143	npn RF fT 13GHz @2V 7mA
T84	2SC5180	Nec	WQ	SOT343	npn RF fT 13GHz @2V 7mA
T86	2SC5182	Nec	N	SOT23	npn RF fT 12GHz @2V 20mA
T86	2SC5183	Nec	WQ	SOT143	npn RF fT 12GHz @2V 20mA
T86	2SC5184	Nec	N	SOT323	npn RF fT 12GHz @2V 20mA
T86	2SC5183	Nec	WQ	SOT343	npn RF fT 12GHz @2V 20mA
T88	2SC5191	Nec	N	SOT23	npn RF fT 8.5GHz @3V 20mA
T88	2SC5192	Nec	WQ	SOT143	npn RF fT 8.5GHz @3V 20mA
T88	2SC5193	Nec	N	SOT323	npn RF fT 8.5GHz @3V 20mA
T88	2SC5193	Nec	WQ	SOT343	npn RF fT 8.5GHz @3V 20mA
T89	2SC5288	Nec	WQ	SOT143	npn RF
T8p	BSR16	Phi	N	SOT23	2N2907A
T8t	BSR16	Phi	N	SOT23	2N2907A
T90	2SC5289	Nec	WQ	SOT143	npn RF
T92	BSR18A	Fch	N	SOT23	2N3904
T92	2SA1977	Nec	N	SOT23	pnnp RF fT 8.5GHz
T92P	BSR18A	Phi	N	SOT23	2N3904
T93	2SA1978	Nec	N	SOT23	pnnp RF fT 8.5GHz
TA	2SC5431EB	Nec	N	SC59	npn RF fT 4.3GHz 12V 60mA
TB	2SC5431FB	Nec	N	SC59	npn RF fT 4.3GHz 12V 60mA
TC	2SC5432EB	Nec	N	SC59	npn RF fT 4.5GHz 12V 100mA
TD	2SC5432FB	Nec	N	SC59	npn RF fT 4.5GHz 12V 100mA
TE	2SC5433EB	Nec	N	SC59	npn RF fT 7GHz 10V 65mA
TF	2SC5433FB	Nec	N	SC59	npn RF fT 7GHz 10V 65mA
TFX	BAL99	Mot	V	SOT23	switching diode
tG1	PMBT5551	Phi	N	SOT23	2N5551 npn Vce 140V
tG1	PMST5551	Phi	N	SOT323	2N5551 npn Vce 140V
TH	2SC5434EB	Nec	N	SC59	npn RF fT 8GHz 10V 35mA
TJ	2SC5434FB	Nec	N	SC59	npn RF fT 8GHz 10V 35mA
TK	2SC5435EB	Nec	N	SC59	npn RF fT 12GHz 9V 30mA
TL	2SC5435FB	Nec	N	SC59	npn RF fT 12GHz 9V 30mA



贴片三极管上的印字，与真实名称的对照表.txt

TN	2SC5436EB	Nec	N	SC59	nnp RF fT 14GHz 5V 30mA
TP	2SC5436FB	Nec	N	SC59	nnp RF fT 14GHz 5V 30mA
TS	2SC5437EB	Nec	N	SC59	nnp RF fT 9.5GHz 9V 50mA
TT	2SC5437FB	Nec	N	SC59	nnp RF fT 9.5GHz 9V 50mA
TV	2SC5599	Nec	N	SC-70	nnp RF fT 5GHz 5.5V 5mA
TV	2SC5600	Nec	N	SC-59	nnp RF fT 5GHz 5.5V 15mA
TV	MMBF112L		Mot	F	SOT23 RF jfet
TW	2SC5602	Nec	N	SC-70	nnp RF fT 13.5GHz 6V 5mA
TW	2SC5603	Nec	N	SC-59	nnp RF fT 13.5GHz 6V 15mA
U	BB545	Sie	I	SOD323	20-2pF varicap
U1	BCX19	Mot	N	SOT23	BC337
U1	BGX50A	Sie	BQ	SOT143	quad ring Si sw diodes
U16	2SC4183	Nec	N	-	nnp RF 5V fT1GHz hFE 60-120
U17	2SC4183	Nec	N	-	nnp RF 5V fT1GHz hFE 90-180
U18	2SC4183	Nec	N	-	nnp RF 5V fT1GHz hFE 120-240
U1A	3SK230A	Nec	UQ	SOT143	dg RF mosfet
U1B	3SK230B	Nec	UQ	SOT143	dg RF mosfet
U1C	3SK231C	Nec	UQ	SOT143	dg RF mosfet
U1D	3SK231D	Nec	UQ	SOT143	dg RF mosfet
U1E	3SK252E	Nec	UQ	SOT143	dg RF mosfet
U1E	3SK254E	Nec	UQ	SOT343	dg RF mosfet
U1G	3SK253G	Nec	UQ	SOT143	dg RF mosfet
U1G	3SK255G	Nec	UQ	SOT343	dg RF mosfet
U1p	BCX19	Phi	N	SOT23	BC337
U1t	BCX19	Phi	N	SOT23	BC337
U2	BCX20	Phi	N	SOT23	BC338
U21	2SC4185	Nec	N	-	nnp RF 10V fT2.4GHz hFE 40-80
U22	2SC4185	Nec	N	-	nnp RF 10V fT2.4GHz hFE 60-120
U23	2SC4185	Nec	N	-	nnp RF 10V fT2.4GHz hFE 90-180
U2t	BCX20	Phi	N	SOT23	BC338
U3	BSS64	Phi	N	SOT23	120V 0.25A 0.2W
U4	BCX19R	Phi	R	SOT23R	BC337
U5	BCX20R	Phi	R	SOT23R	BC338
U55	3SK134B	Nec	UQ	SOT143	dg mosfet
U55	3SK245	Nec	UQ	SOT343	dg mosfet
U56	3SK134B	Nec	UQ	SOT143	dg mosfet
U56	3SK245	Nec	UQ	SOT343	dg mosfet
U6	BSS64R	Phi	R	SOT23R	120V 0.25A 0.2W
U65	3SK135A	Nec	UQ	SOT143	dg mosfet
U66	3SK135A	Nec	UQ	SOT143	dg mosfet
U7	BSR13	SGS	N	SOT23	2N2222
U71	BSR13R	SGS	R	SOT23R	2N2222
U71	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss 5-15mA
U71	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 5-15mA
U72	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss10-25mA
U72	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 10-25mA
U73	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss 20-35mA
U73	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 20-35mA
U74	3SK177	Nec	UQ	SOT143	dg GaAsfet Idss 30-40mA
U74	3SK299	Nec	UQ	SOT343	dg GaAsfet Idss 30-40mA
U76	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 10-25mA
U77	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 20-35mA
U78	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 30-50mA
U79	3SK206	Nec	UQ	SOT143	dg GaAsfet Idss 45-80mA
U7p	BSR13	Phi	N	SOT23	2N2222
U7t	BSR13	Phi	N	SOT23	2N2222
U8	BSR14	SGS	N	SOT23	2N2222A
U81	BSR14R	SGS	R	SOT23R	2N2222A
U87	3SK176A	Nec	UQ	SOT143	dg mosfet
U88	3SK176A	Nec	UQ	SOT143	dg mosfet
U8p	BSR14	Phi	N	SOT23	2N2222A
U8t	BSR14	Phi	N	SOT23	2N2222A
U90	3SK223	Nec	UQ	SOT143	dg mosfet
U90	3SK243	Nec	UQ	SOT343	dg mosfet
U91	3SK223	Nec	UQ	SOT143	dg mosfet
U91	3SK243	Nec	UQ	SOT143	dg mosfet
U92	BSR17A	Fch	N	SOT23	2N3904
U92p	BSR17A	Phi	N	SOT23	2N3904
U94	3SK224D	Nec	UQ	SOT143	dg mosfet
U94	3SK244D	Nec	UQ	SOT343	dg mosfet
U95	3SK224E	Nec	UQ	SOT143	dg mosfet
U95	3SK244E	Nec	UQ	SOT143	dg mosfet
UB	2SB852K	Roh	N	-	pnp darlington comp 2SD1383K
UC	MSC2404-C	Mot	H	-	nnp RF 450MHz fT 20V
V01	VN50300T	Sil	M	-	n-ch enh mosfet 500V 22mA



贴片三极管上的印字，与真实名称的对照表.txt

V02	VN0605T	Sil	M	-	n-ch enh mosfet 60V/0.18A
V04	VN45350T	Sil	M	-	n-ch enh mosfet 450V 20mA
V1	MRF959	Mot	N	SC75	npn RF fT 9GHz
V11	3SK131	Nec	UQ	SOT143	dg VHF mosfet
V11	3SK242	Nec	UQ	SOT343	dg VHF mosfet
V12	3SK131	Nec	UQ	SOT143	dg VHF mosfet
V12	3SK242	Nec	UQ	SOT343	dg VHF mosfet
V13	3SK131	Nec	UQ	SOT143	dg VHF mosfet
V13	ZC932	Zet	C	SOT23	5 - 17pF hyperabrupt varicap
V13	3SK242	Nec	UQ	SOT343	dg VHF mosfet
V14	ZC931	Zet	C	SOT23	4 -13.5pF hyperabrupt varicap
V15	ZC930	Zet	C	SOT23	3 - 9pF hyperabrupt varicap
V16	ZC934	Zet	C	SOT23	25 - 95pF hyperabrupt varicap
V17	ZC933	Zet	C	SOT23	12 - 42pF hyperabrupt varicap
V1p	BFT25	Phi	N	SOT23	npn RF 5V 6.5mA 2.3GHz
V2	BFQ67	Tfk	N	-	npn RF fT 7.5 GHz 50mA
V21	3SK222	Nec	UQ	SOT143	dg VHF mosfet
V21	3SK246	Nec	UQ	SOT343	dg VHF mosfet
V22	3SK222	Nec	UQ	SOT143	dg VHF mosfet
V22	3SK246	Nec	UQ	SOT343	dg VHF mosfet
V3	BFG67	Phi	X	SOT143	npn RF fT 8GHz 50mA
V5	BFG197	Phi	X	SOT143	npn RF 7.5GHz 100mA
V50	VP0610T	Sil	M	-	p-ch enh mosfet -60V 120mA
VB	MSC2295-B	Mot	H	-	npn RF 150MHz fT 20V
VC	MSC2295-C	Mot	H	-	npn RF 150MHz fT 20V
W0F	TSDF1205RW	Tfk	WQ	SOT343	12GHz npn 5mA 4V
W18	BFP181TW	Tfk	X	-	npn RF fT 7.8GHz 10V 20mA
W18	BFP181TRW	Tfk	WQ	-	npn RF fT 7.8GHz 10V 20mA
W1s	BFT92	Sie	N	SOT23	BFQ51/BFQ76
W1s	BCR10PN	Sie	DP	SOT363	npn/npn dig 0.1A 10k+10k
W2	TSDF1220RW	Tfk	WQ	SOT343	12GHz npn 6V 20mA
W22	S822TW	Tfk	X	-	npn rf fT 5.2 GHz 6V 8mA
W22	S822TRW	Tfk	WQ	-	npn rf fT 5.2 GHz 6V 8mA
W28	BFP280TRW	Tfk	WQ	-	npn rf fT 7 GHz 8V 10mA
W28	BFP280TW	Tfk	X	-	npn rf fT 7 GHz 8V 10mA
W3	BZX84-C2V4	Phi	C	SOT23	0.3W zener 2.4V±5%
W4	BZX84-C2V7	Phi	C	SOT23	0.3W zener 2.7V±5%
W5	BZX84-C3V0	Phi	C	SOT23	0.3W zener 3.0V±5%
W52	S852TW	Tfk	X	-	npn rf fT 5.2 GHz 6V 8mA
W6	BZX84-C3V3	Phi	C	SOT23	0.3W zener 3.3V±5%
W67	BFP67W	Tfk	X	-	npn rf fT 7.5 GHz 10V 50mA
W7	BZX84-C3V6	Phi	C	SOT23	0.3W zener 3.6V±5%
W8	BZX84-C3V9	Phi	C	SOT23	0.3W zener 3.9V±5%
W8	BZV49C3V9	Zet	0	SOT89	1W zener 3.9V±5%
W82	BFP182TRW	Tfk	WQ	-	npn rf fT 7.5 GHz 10V 35mA
W82	BFP182TW	Tfk	X	-	npn rf fT 7.5 GHz 10V 35mA
W83	BFP183TRW	Tfk	WQ	-	npn rf fT 7.4 GHz 10V 65mA
W83	BFP183T	Tfk	X	-	npn rf fT 7.4 GHz 10V 65mA
W9	BZX84-C4V3	Phi	C	SOT23	0.3W zener 4.3V±5%
W9	BZV49C4V3	Zet	0	SOT89	1W zener 4.3V±5%
W92	BFP92AW	Tfk	X	SOT343	npn rf fT 6 GHz 15V 30mA
WB	2SD1383K	Roh	N	-	npn darlington comp 2SB852K
WCs	BCR133	Sie	N	SOT23	npn dig 50V 0.1A 10k+10k
WCs	BCR133T	Sie	N	SC75	npn dig 50V 0.1A 10k+10k
WCs	BCR133U	Sie	N	SOT457	npn dig 50V 0.1A 10k+10k
WCs	BCR133W	Sie	N	SOT323	npn dig 50V 0.1A 10k+10k
WCs	BCR133S	Sie	DN	SOT363	dual BCR133
WDs	BCR141	Sie	N	SOT23	npn 50V 0.1A dig 22k +22k
WDs	BCR141T	Sie	N	SC75	npn 50V 0.1A dig 22k +22k
WDs	BCR141W	Sie	N	SOT323	npn 50V 0.1A dig 22k +22k
WDs	BCR141S	Sie	DN	SOT363	dual BCR141
WE1	BFS17W	Tfk	N	-	npn rf fT 2.1GHz SOT-323
WE2	BFS17AW	Tfk	N	-	npn rf fT 3.2GHz SOT-323
WEs	BCR148	Sie	N	SOT23	npn 50V 0.1A dig 47k +47k
WEs	BCR148T	Sie	N	SC75	npn 50V 0.1A dig 47k +47k
WEs	BCR148U	Sie	N	SOT457	npn 50V 0.1A dig 47k +47k
WEs	BCR148W	Sie	N	SOT323	npn 50V 0.1A dig 47k +47k
WEs	BCR148S	Sie	DN	SOT363	dual BCR148
WFO	TSDF1205W	Tfk	X	SOT343	12 GHz npn 5mA 4V
WF2	TSDF1220W	Tfk	X	SOT343	12GHz npn 6V 20mA
WFE	BFP93A	Tfk	X	SOT343	BFP93A (FE) in 6GHz npn
WFs	BCR08PN	Sie	DP	SOT363	npn/npn dig 0.1A 2k2+47k
WFs	BCR112	Sie	N	SOT23	npn dig 50V 0.1A 4k7+4k7
WGs	BCR116	Sie	N	SOT23	npn dig 50V 0.1A 4k7+47k
WGs	BCR116W	Sie	N	SOT323	npn dig 50V 0.1A 4k7+47k



贴片三极管上的印字，与真实名称的对照表.txt

WHs	BCR108	Sie	N	SOT23	npn dig 50V 0.1A 2k2+47k
WHs	BCR108T	Sie	N	SC75	npn dig 50V 0.1A 2k2+47k
WHs	BCR108W	Sie	N	SOT323	npn dig 50V 0.1A 2k2+47k
WHs	BCR108S	Sie	DN	SOT363	dual BCR108
WIs	BCR158	Sie	N	SOT23	npn dig 50V 0.1A 2k2+47k
WIs	BCR158T	Sie	N	SC75	npn dig 50V 0.1A 2k2+47k
WIs	BCR158W	Sie	N	SOT323	npn dig 50V 0.1A 2k2+47k
WJs	BCR135	Sie	N	SOT23	npn dig 50V 0.1A 10k+47k
WJs	BCR135T	Sie	N	SC75	npn dig 50V 0.1A 10k+47k
WJs	BCR135W	Sie	N	SOT323	npn dig 50V 0.1A 10k+47k
WJs	BCR135S	Sie	DN	SOT363	dual BCR135
Wks	BCR119	Sie	N	SOT23	npn dig 50V 0.1A 4k7
Wks	BCR119S	Sie	DN	SOT363	npn dig 50V 0.1A 4k7
Wks	BCR119W	Sie	N	SOT323	npn dig 50V 0.1A 4k7
Wls	BCR146	Sie	N	SOT23	dual npn dig 50V 47k+22k
Wls	BCR146W	Sie	N	SOT323	dual npn dig 50V 47k+22k
WMO	BF998RW	Tfk	UQ	SOT343R	vhf dg mosfet BF988
Wms	BCR183	Sie	N	SOT23	npn dig 50V 10k+10k
Wms	BCR183W	Sie	N	SOT323	npn dig 50V 10k+10k
Wms	BCR183T	Sie	N	SC75	npn dig 50V 10k+10k
Wms	BCR183U	Sie	N	SOT457	npn dig 50V 10k+10k
Wms	BCR183S	Sie	DO	SOT363	dual npn dig 50V 10k+10k
Wns	BCR185	Sie	N	SOT23	npn dig 50V 0.1A 10k+47k
Wns	BCR185U	Sie	N	SOT457	npn dig 50V 0.1A 10k+47k
Wns	BCR185W	Sie	N	SOT323	npn dig 50V 0.1A 10k+47k
Wns	BCR185S	Sie	DO	SOT363	dual BCR185
WO	BZX284-B2V4	Phi	I	SOD110	0.4W zener 2.4V E24 ±2%
Wos	BCR191	Sie	N	SOT23	npn dig 50V 0.1A 22k+22k
Wos	BCR191W	Sie	N	SOT323	npn dig 50V 0.1A 22k+22k
Wos	BCR191S	Sie	DO	SOT363	dual BCR191
WP	BZX284-B2V7	Phi	I	SOD110	0.4W zener 2.7V E24 ±2%
WP2	BFR92A	Tfk	N	SOT23	BRF90A
WPs	BCR192	Sie	N	SOT23	npn dig 50V 0.1A 22k+47k
WPs	BCR192T	Sie	N	SC75	npn dig 50V 0.1A 22k+47k
WPs	BCR192W	Sie	N	SOT323	npn dig 50V 0.1A 22k+47k
WPs	BCR22PN	Sie	DP	SOT363	npn/npn dig 0.1A 22k+22k
WQ	BZX284-B3V0	Phi	I	SOD110	0.4W zener 3.0V E24 ±2%
WR	MSD602R	Mot	N	SOT346	npn gp 25V 150mA
WR	BZX284-B3V3	Phi	I	SOD110	0.4W zener 3.3V E24 ±2%
WR2	BFR93AW	Tfk	N	-	BFR91A
WRE	BFR280TW	Tfk	N	-	npn RF fT 7.5GHz
WRF	BFR181TW	Tfk	N	-	npn RF fT 7.8GHz
WRG	BFR182TW	Tfk	N	-	npn RF fT 7GHz
WRH	BFR183TW	Tfk	N	-	npn RF fT 7.4GHz
WRs	BCR198	Sie	N	SOT23	npn dig 50V 0.1A 47k+47k
WRs	BCR198W	Sie	NN	SOT323	npn dig 50V 0.1A 47k+47k
WRs	BCR198S	Sie	D	SOT363	dual BCR198
WS	BCR169	Sie	N	SOT23	npn dig 50V 0.1A 4k7
WS	BCR169W	Sie	N	SOT323	npn dig 50V 0.1A 4k7
WS	BCR169S	Sie	DO	SOT363	dual BC169
WS	BZX284-B3V6	Phi	I	SOD110	0.4W zener 3.6V E24 ±2%
WT	BCR166	Sie	N	SOT23	npn dig 50V 0.1A 4k7+47k
WT	BCR166W	Sie	N	SOT323	npn dig 50V 0.1A 4k7+47k
WT	BCR48PN	Sie	DP	SOT363	npn/npn dig npn 2x47k npn 2k2+47k
WT	BZX284-B3V9	Phi	I	SOD110	0.4W zener 3.9V E24 ±2%
WU	BCR162	Sie	N	SOT23	npn dig 50V 0.1A 4k7+4k7
WU	BCR162T	Sie	N	SC75	npn dig 50V 0.1A 4k7+4k7
WU	BCR35PN	Sie	DP	SOT363	npn/npn dig 0.1A 10k+47k
WU	BZX284-B4V3	Phi	I	SOD110	0.4W zener 4.3V E24 ±2%
WU	MRF2947A	Mot	DG	SOT363	dual MRF941 npn RF 9GHz
X (white)	BB833	Sie	I	SOT323	9.3-0.75pF varicap
X (yellow)	BB835	Sie	I	SOT323	9.1-0.6pF varicap
X1	BFT93	Sie	N	SOT23	BFQ23 BFQ75
X1	IMX1	Roh	DC	-	dual 2SC2412K npn
X1	BZX84-C27	Phi	C	SOT23	0.3W zener 27V ±5%
X1p	BFT93	Phi	N	SOT23	BFQ23 BFQ75
X2	IMX2	Roh	DD	-	dual 2SC2412K npn
X2	BZX99-C13	Phi	C	SOT23	13V 0.3W zener ±5%
X2	BZX84-C30	Zet	C	SOT23	0.3W zener 30V ±5%
X2	BZV49C30	Zet	O	SOT89	1W zener 30V ±5%
X3	BZX99-C15	Phi	C	SOT23	15V 0.3W zener ±5%
X3	BZX84-C33	Zet	C	SOT23	0.3W zener 33V ±5%
X4	BFT93R	Sie	R	SOT23R	BFQ23 BFQ75
X4	BZX84-C36	Zet	C	SOT23	0.3W zener 36V ±5%
X5	BZV49C39	Zet	O	SOT89	1W zener 39V ±5%

贴片三极管上的印字，与真实名称的对照表.txt

X5	MMBV409G	Mot	C	SOT23	Hyperabrupt varicap
X6	BZV49C43	Zet	0	SOT89	1W zener 43V±5%
X6	BZX84-C43	Zet	C	SOT23	0.3W zener 43V±5%
X7	BZX84-C47	Zet	C	SOT23	0.3W zener 47V±5%
XA	BZX284-B7V5	Phi	I	SOD110	0.4W zener 7.5V E24 ±2%
XA	BZX99-C4V7	Phi	C	SOT23	4.7V 0.3W zener
XAs	BCR503 Sie	N	SOT23	npn dtr	50V 0.5A 2k2 +2k2
XB	BZX284-B8V2	Phi	I	SOD110	0.4W zener 8.2V E24 ±2%
XB	BZX99-C5V1	Phi	C	SOT23	5.1V 0.3W zener
XBs	BCR553 Sie	N	SOT23	npn dtr	50V 0.5A 2k2 +2k2
XC	BZX284-B9V1	Phi	I	SOD110	0.4W zener 9.1V E24 ±2%
XC	BZX99-C5V6	Phi	C	SOT23	5.6V 0.3W zener
XCs	BCR533 Sie	N	SOT23	npn dtr	50V 0.5A 10k + 10k
XD	BZX284-B10	Phi	I	SOD110	0.4W zener 10V E24 ±2%
XD	BZX99-C6V2	Phi	C	SOT23	6.2V 0.3W zener
XDs	BCR555 Sie	N	SOT23	npn dtr	50V 0.5A 2k2 +10k
XE	BZX284-B11	Phi	I	SOD110	0.4W zener 11V E24 ±2%
XE	BZX99-C6V8	Phi	C	SOT23	6.8V 0.3W zener
XF	BZX284-B12	Phi	I	SOD110	0.4W zener 12V E24 ±2%
XF _s	BCR512 Sie	N	SOT23	npn dtr	50V 0.5A 4k7+ 4k7
XG	BZX284-B13	Phi	I	SOD110	0.4W zener 13V E24 ±2% S
XG _s	BCR523 Sie	N	SOT23	npn dtr	50V 0.5A 1k0 +10k
XH	BZX284-B15	Phi	I	SOD110	0.4W zener 15V E24 ±2%
XH	MMSD701 Mot	I	SOD123	MMBD701	
XH _s	BCR573 Sie	N	SOT23	npn dtr	50V 0.5A 1k0 +10k
XI	BZX284-B16	Phi	I	SOD110	0.4W zener 16V E24 ±2%
XJ	BZX284-B18	Phi	I	SOD110	0.4W zener 18V E24 ±2%
XK	BZX284-B20	Phi	I	SOD110	0.4W zener 20V E24 ±2%
XK _s	BCR519 Sie	N	SOT23	npn dtr	50V 0.5A R1 4k7
XL	BZX284-B22	Phi	I	SOD110	0.4W zener 22V E24 ±2%
XL	BZX99-C2V4	Phi	C	SOT23	2.4V 0.3W zener
XL _s	BCR569 Sie	N	SOT23	npn dtr	50V 0.5A R1 4k7
XM	BZX284-B24	Phi	I	SOD110	0.4W zener 24V E24 ±2%
XM	BZX99-C2V7	Phi	C	SOT23	2.7V 0.3W zener
XM _s	BCR583 Sie	N	SOT23	npn dtr	50V 0.5A 10k +10k
XN	BZX284-B27	Phi	I	SOD110	0.4W zener 27V E24 ±2%
XN	BZX99-C3V0	Phi	C	SOT23	3.0V 0.3W zener
XO	BZX284-B30	Phi	I	SOD110	0.4W zener 30V E24 ±2%
XP	MMBD3000	Mot	C	SOT346	Si diode 30V 0.2A
XP	BZX284-B33	Phi	I	SOD110	0.4W zener 33V E24 ±2%
XP	BZX99-C3V3	Phi	C	SOT23	3.3V 0.3W zener
XQ	MMBD3005	Mot	A	SOT346	dual ca MMBD3000
XQ	BZX284-B36	Phi	I	SOD110	0.4W zener 36V E24 ±2%
XQ	2PD602AQ	Phi	N	SOT346	gp npn hfe 85-170
XR	BZX284-B39	Phi	I	SOD110	0.4W zener 39V E24 ±2%
XR	BZX99-C3V6	Phi	C	SOT23	3.6V 0.3W zener
XR	MRF2947RA	Mot	DH	SOT363	dual MRF941 npn RF 9GHz
XR	2PD602AR	Phi	N	SOT346	gp npn hfe 120-240
XS	MMBD3010	Mot	B	SOT346	dual cc MMBD3000
XS	BZX284-B43	Phi	I	SOD110	0.4W zener 43V E24 ±2%
XS	BZX99-C3V9	Phi	C	SOT23	3.9V 0.3W zener
XS	2PD602AS	Phi	N	SOT346	gp npn hfe 170-340
XT	BZX284-B47	Phi	I	SOD110	0.4W zener 47V E24 ±2%
XT	MMSD301 Mot	I	SOD123	MBD301	
XT	BZX99-C4V3	Phi	C	SOT23	4.3V 0.3W zener
XU	BZX284-B51	Phi	I	SOD110	0.4W zener 51V E24 ±2%
XU	MRF2947RA	Mot	DH	-	dual MRF941 npn RF 9GHz
XU	BZX99-C7V5	Phi	C	SOT23	7.5V 0.3W zener
XU _s	BCR562 Sie	N	SOT23	npn dtr	50V 0.5A 4k7+ 4k7
XV	BZX284-B56	Phi	I	SOD110	0.4W zener 56V E24 ±2%
XV	BZX99-C8V2	Phi	C	SOT23	8.2V 0.3W zener
XV _s	BCR521 Sie	N	SOT23	npn dtr	50V 0.5A 1k0 +1k0
XW	BZX284-B62	Phi	I	SOD110	0.4W zener 62V E24 ±2%
XW	BZX99-C9V1	Phi	C	SOT23	9.1V 0.3W zener
XW _s	BCR505 Sie	N	SOT23	npn dtr	50V 0.5A 2k2 +10k
XX	BZX284-B68	Phi	I	SOD110	0.4W zener 68V E24 ±2%
XX	BZX99-C10	Phi	C	SOT23	10V 0.3W zener
XX _s	BCR571 Sie	N	SOT23	npn dtr	50V 0.5A 1k0 +1k0
XY	BZX99-C11	Phi	C	SOT23	11V 0.3W zener
XY	BZX284-B75	Phi	I	SOD110	0.4W zener 75V E24 ±2%
XZ	BZX99-C12	Phi	C	SOT23	12V 0.3W zener
Y0 _s	CGY121B Sie	-	-	GaAs MMIC	
Y1	BZX84-C11	Phi	C	SOT23	0.3W zener 11V±5%
Y1	BZV49C11	Zet	0	SOT89	1W zener 11V ±5%
Y10	BZX84-C27	Phi	C	SOT23	0.3W zener 27V±5%

贴片三极管上的印字，与真实名称的对照表.txt

Y11	BZX84-C30	Phi	C	SOT23	0.3W zener	30V ±5%
Y12	BZX84-C33	Phi	C	SOT23	0.3W zener	33V ±5%
Y13	BZX84-C36	Phi	C	SOT23	0.3W zener	36V ±5%
Y14	BZX84-C39	Phi	C	SOT23	0.3W zener	39V ±5%
Y15	BZX84-C43	Phi	C	SOT23	0.3W zener	43V ±5%
Y16	BZX84-C47	Phi	C	SOT23	0.3W zener	47V ±5%
Y17	BZX84-C51	Phi	C	SOT23	0.3W zener	51V ±5%
Y18	BZX84-C56	Phi	C	SOT23	0.3W zener	56V ±5%
Y19	BZX84-C62	Phi	C	SOT23	0.3W zener	62V ±5%
Y1p	BZX84-C11	Phi	C	SOT23	0.3W zener	11V ±5%
Y2	CLY2 Sie	DR	MW6	3GHz GaAsfet	0.25W 3GHz	
Y2	BZX84-C12	Phi	C	SOT23	0.3W zener	12V ±5%
Y20	BZX84-C68	Phi	C	SOT23	0.3W zener	68V ±5%
Y21	BZX84-C75	Phi	C	SOT23	0.3W zener	75V ±5%
Y3	BZX84-C13	Phi	C	SOT23	0.3W zener	13V ±5%
Y36	BZX84-C13V6	Phi	C	SOT23	0.3W zener	13.6V ±5%
Y4	BZX84-C15	Phi	C	SOT23	0.3W zener	15V ±5%
Y4	BZV49C15	Zet	0	SOT89	1W zener	15V ±5%
Y5	BZX84-C16	Phi	C	SOT23	0.3W zener	16V ±5%
Y5	BZV49C16	Zet	0	SOT89	1W zener	16V ±5%
Y50	BZX84-A2V4	Phi	C	SOT23	0.3W zener	2.4V ±1%
Y51	BZX84-A2V7	Phi	C	SOT23	0.3W zener	2.7V ±1%
Y52	BZX84-A3V0	Phi	C	SOT23	0.3W zener	3.0V ±1%
Y53	BZX84-A3V3	Phi	C	SOT23	0.3W zener	3.3V ±1%
Y54	BZX84-A3V6	Phi	C	SOT23	0.3W zener	3.6V ±1%
Y55	BZX84-A3V9	Phi	C	SOT23	0.3W zener	3.9V ±1%
Y56	BZX84-A4V3	Phi	C	SOT23	0.3W zener	4.3V ±1%
Y57	BZX84-A4V7	Phi	C	SOT23	0.3W zener	4.7V ±1%
Y58	BZX84-A5V1	Phi	C	SOT23	0.3W zener	5.1V ±1%
Y59	BZX84-A5V6	Phi	C	SOT23	0.3W zener	5.6V ±1%
Y5s	CGY59 Sie	DS	SOT363	GaAs	0.9/1.8GHz preamp	
Y6	BZX84-C18	Phi	C	SOT23	0.3W zener	18V ±5%
Y60	BZX84-A6V2	Phi	C	SOT23	0.3W zener	6.2V ±1%
Y61	BZX84-A6V8	Phi	C	SOT23	0.3W zener	6.8V ±1%
Y62	BZX84-A7V5	Phi	C	SOT23	0.3W zener	7.5V ±1%
Y63	BZX84-A8V2	Phi	C	SOT23	0.3W zener	8.2V ±1%
Y64	BZX84-A9V1	Phi	C	SOT23	0.3W zener	9.1V ±1%
Y65	BZX84-A10	Phi	C	SOT23	0.3W zener	10V ±1%
Y66	BZX84-A11	Phi	C	SOT23	0.3W zener	11V ±1%
Y67	BZX84-A12	Phi	C	SOT23	0.3W zener	12V ±1%
Y68	BZX84-A13	Phi	C	SOT23	0.3W zener	13V ±1%
Y69	BZX84-A15	Phi	C	SOT23	0.3W zener	15V ±1%
Y6s	CGY62 Sie	DS	MW6	GaAs MMIC		
Y7	CGY60 Sie	DS	MW6	GaAs preamp	MMIC 1.8GHz	
Y7	BZX84-C20	Phi	C	SOT23	0.3W zener	20V ±5%
Y70	BZX84-A16	Phi	C	SOT23	0.3W zener	16V ±1%
Y71	BZX84-A18	Phi	C	SOT23	0.3W zener	18V ±1%
Y72	BZX84-A20	Phi	C	SOT23	0.3W zener	20V ±1%
Y73	BZX84-A22	Phi	C	SOT23	0.3W zener	22V ±1%
Y74	BZX84-A24	Phi	C	SOT23	0.3W zener	24V ±1%
Y75	BZX84-A27	Phi	C	SOT23	0.3W zener	27V ±1%
Y76	BZX84-A30	Phi	C	SOT23	0.3W zener	30V ±1%
Y77	BZX84-A33	Phi	C	SOT23	0.3W zener	33V ±1%
Y78	BZX84-A36	Phi	C	SOT23	0.3W zener	36V ±1%
Y79	BZX84-A39	Phi	C	SOT23	0.3W zener	39V ±1%
Y8	CGY120 Sie	-	MW6	GaAs MMIC		
Y8	BZX84-C22	Phi	C	SOT23	0.3W zener	22V ±5%
Y8	BZV49C22	Zet	0	SOT89	1W zener	22V ±5%
Y80	BZX84-A43	Phi	C	SOT23	0.3W zener	43V ±1%
Y81	BZX84-A47	Phi	C	SOT23	0.3W zener	47V ±1%
Y82	BZX84-A51	Phi	C	SOT23	0.3W zener	51V ±1%
Y83	BZX84-A56	Phi	C	SOT23	0.3W zener	56V ±1%
Y84	BZX84-A62	Phi	C	SOT23	0.3W zener	62V ±1%
Y85	BZX84-A68	Phi	C	SOT23	0.3W zener	68V ±1%
Y86	BZX84-A75	Phi	C	SOT23	0.3W zener	75V ±1%
Y9	BZX84-C24	Phi	C	SOT23	0.3W zener	24V ±5%
Y9	BZV49C24	Zet	0	SOT89	1W zener	24V ±5%
Y9s	CGY121A Sie	-	MW6	GaAs MMIC		
YBs	BSS84 Inf	M	SOT23	p-ch mosfet	50V 0.13A	
YO	BZX284-C2V4	Phi	I	SOD110	0.4W zener	2.4V E12 ±5%
YP	BZX284-C2V7	Phi	I	SOD110	0.4W zener	2.7V E12 ±5%
YQ	BZX284-C3V0	Phi	I	SOD110	0.4W zener	3.0V E12 ±5%
YR	MSD601R Mot	N	SOT346	nnp gp	25V	
YR	BZX284-C3V3	Phi	I	SOD110	0.4W zener	3.3V E12 ±5%
YS	MSD601S Mot	N	SOT346	nnp gp	25V	



贴片三极管上的印字，与真实名称的对照表.txt

YS	BZX284-C3V6	Phi	I	SOD110	0.4W zener	3.6V E12	±5%
YT	BZX284-C3V9	Phi	I	SOD110	0.4W zener	3.9V E12	±5%
YU	BZX284-C4V3	Phi	I	SOD110	0.4W zener	4.3V E12	±5%
YV	BZX284-C4V7	Phi	I	SOD110	0.4W zener	4.7V E12	±5%
YW	BZX284-C5V1	Phi	I	SOD110	0.4W zener	5.1V E12	±5%
YX	BZX284-C5V6	Phi	I	SOD110	0.4W zener	5.6V E12	±5%
YY	BZX284-C6V2	Phi	I	SOD110	0.4W zener	6.2V E12	±5%
YZ	BZX284-C6V8	Phi	I	SOD110	0.4W zener	6.8V E12	±5%
Z0	SST310	Tem	F	SOT23	J310 n-ch	jfet	
Z0	PDZ2.4B	Phi	I	SOD323	2.4V 0.4W	zener	
Z08	SST308	Sil	F	SOT23	J308 n-ch	jfet	
Z09	SST309	Sil	F	SOT23	J309 n-ch	jfet	
Z1	BZX84-C4V7	Phi	C	SOT23	0.3W zener	4.7V	
Z1	SSTJ211	Sil	F	SOT23	J211 n-ch	jfet	
Z1	PDZ2.7B	Phi	I	SOD323	2.7V 0.4W	zener	
Z1	IMZ1A	Roh	DE	-	"2SC2414 npn, 2SA1037AK pnp"		
Z1	BZV49C4V7	Zet	0	SOT89	1W ±5%	zener 4.7V	
Z1	BZV49C10	Zet	0	SOT89	1W ±5%	zener 10V	
Z10	SST310	Sil	F	SOT23	J310 n-ch	jfet	
Z10	SST310	Sil	F	SOT23	J310 n-ch	jfet	
Z11	BZX84-C2V4	Phi	C	SOT23	0.3W zener	2.4V ±5%	
Z12	BZX84-C2V7	Phi	C	SOT23	0.3W zener	2.7V ±5%	
Z13	BZX84-C3V0	Phi	C	SOT23	0.3W zener	3.0V ±5%	
Z14	BZX84-C3V3	Phi	C	SOT23	0.3W zener	3.3V ±5%	
Z15	BZX84-C3V6	Phi	C	SOT23	0.3W zener	3.6V ±5%	
Z16	BZX84-C3V9	Phi	C	SOT23	0.3W zener	3.9V ±5%	
Z17	BZX84-C4V3	Phi	C	SOT23	0.3W zener	4.3V ±5%	
Z2	BZX84-C5V1	Phi	C	SOT23	0.3W zener	4.7V	
Z2	SSTJ212	Sil	F	SOT23	J212 n-ch	jfet	
Z2	IMZ2A	Roh	DF	-	"2SC2414 npn, 2SA1037AK pnp"		
Z2	PDZ3.0B	Phi	I	SOD323	3.0V 0.4W	zener	
Z2	BZV49C5V1	Zet	0	SOT89	1W ±5%	zener 5.1V	
Z21	DTC113ZE	Rho	N	EMT3	n-pn dtr 1k0 + 10k	50V 100mA	
Z21	DTC113ZUA	Rho	N	SC70	n-pn dtr 1k0 + 10k	50V 100mA	
Z21	DTC113ZKA	Rho	N	SC59	n-pn dtr 1k0 + 10k	50V 100mA	
Z2U	FMMTA63	Zet	N	SOT23	MPSA63		
Z2V	FMMTA64	Zet	N	SOT23	MPSA64		
Z3	BZX84-C5V6	Phi	C	SOT23	0.3W zener	5.6V	
Z3	PDZ3.3B	Phi	I	SOD323	3.3V 0.4W	zener	
Z3	2SK1078	Tos	T	SOT89	n-ch mosfet 60V	0.8A	
Z3	BZV49C5V6	Zet	0	SOT89	1W ±5%	zener 5.6V	
Z4	BZX84-C6V2	Phi	C	SOT23	0.3W zener	6.2V	
Z4	PDZ3.6B	Phi	I	SOD323	3.6V 0.4W	zener	
Z4	2SK1079	Tos	T	SOT89	n-ch mosfet 100V	0.6A	
Z4	BZV49C6V2	Zet	0	SOT89	1W ±5%	zener 6.2V	
Z5	BZX84-C6V8	Phi	C	SOT23	0.3W zener	6.8V	
Z5	PDZ3.9B	Phi	I	SOD323	3.9V 0.4W	zener	
Z5	2SK1717	Tos	T	SOT89	n-ch mosfet 60V	2A	
Z5	BZV49C6V8	Zet	0	SOT89	1W ±5%	zener 6.8V	
Z50	BZX84-B2V4	Phi	C	SOT23	0.3W zener	2.4V ±2%	
Z51	BZX84-B2V7	Phi	C	SOT23	0.3W zener	2.7V ±2%	
Z52	BZX84-B3V0	Phi	C	SOT23	0.3W zener	3.0V ±2%	
Z53	BZX84-B3V3	Phi	C	SOT23	0.3W zener	3.3V ±2%	
Z54	BZX84-B3V6	Phi	C	SOT23	0.3W zener	3.6V ±2%	
Z55	BZX84-B3V9	Phi	C	SOT23	0.3W zener	3.9V ±2%	
Z56	BZX84-B4V3	Phi	C	SOT23	0.3W zener	4.3V ±2%	
Z57	BZX84-B4V7	Phi	C	SOT23	0.3W zener	4.7V ±2%	
Z58	BZX84-B5V1	Phi	C	SOT23	0.3W zener	5.1V ±2%	
Z59	BZX84-B5V6	Phi	C	SOT23	0.3W zener	5.6V ±2%	
Z6	BZX84-C7V5	Phi	C	SOT23	0.3W zener	7.5V	
Z6	PDZ4.3B	Phi	I	SOD323	4.3V 0.4W	zener	
Z6	2SJ238	Tos	T	SOT89	p-ch mosfet 60V	1A	
Z6	BZV49C7V5	Zet	0	SOT89	1W ±5%	zener 7.5V	
Z60	BZX84-B6V2	Phi	C	SOT23	0.3W zener	6.2V ±2%	
Z61	BZX84-B6V8	Phi	C	SOT23	0.3W zener	6.8V ±2%	
Z62	BZX84-B7V5	Phi	C	SOT23	0.3W zener	7.5V ±2%	
Z63	BZX84-B8V2	Phi	C	SOT23	0.3W zener	8.2V ±2%	
Z64	BZX84-B9V1	Phi	C	SOT23	0.3W zener	9.1V ±2%	
Z65	BZX84-B10	Phi	C	SOT23	0.3W zener	10V ±2%	
Z66	BZX84-B11	Phi	C	SOT23	0.3W zener	11V ±2%	
Z67	BZX84-B12	Phi	C	SOT23	0.3W zener	12V ±2%	
Z68	BZX84-B13	Phi	C	SOT23	0.3W zener	13V ±2%	
Z69	BZX84-B15	Phi	C	SOT23	0.3W zener	15V ±2%	
Z7	BZX84-C8V2	Phi	C	SOT23	0.3W zener	8.2V	
Z7	PDZ4.7B	Phi	I	SOD323	4.7V 0.4W	zener	



贴片三极管上的印字，与真实名称的对照表.txt

Z7	BZV49C8V2	Zet	O	SOT89	1W ±5% zener	8.2V
Z70	BZX84-B16	Phi	C	SOT23	0.3W zener	16V ±2%
Z71	BZX84-B18	Phi	C	SOT23	0.3W zener	18V ±2%
Z72	BZX84-B20	Phi	C	SOT23	0.3W zener	20V ±2%
Z73	BZX84-B22	Phi	C	SOT23	0.3W zener	22V ±2%
Z74	BZX84-B24	Phi	C	SOT23	0.3W zener	24V ±2%
Z75	BZX84-B27	Phi	C	SOT23	0.3W zener	27V ±2%
Z76	BZX84-B30	Phi	C	SOT23	0.3W zener	30V ±2%
Z77	BZX84-B33	Phi	C	SOT23	0.3W zener	33V ±2%
Z78	BZX84-B36	Phi	C	SOT23	0.3W zener	36V ±2%
Z79	BZX84-B39	Phi	C	SOT23	0.3W zener	39V ±2%
Z8	BZX84-C9V1	Phi	C	SOT23	0.3W zener	9.1V
Z8	PDZ5.1B Phi	I	SOD323	5.1V 0.4W zener		
Z8	BZV49C9V1	Zet	O	SOT89	1W ±5% zener	9.1V
Z80	BZX84-B43	Phi	C	SOT23	0.3W zener	43V ±2%
Z81	BZX84-B47	Phi	C	SOT23	0.3W zener	47V ±2%
Z82	BZX84-B51	Phi	C	SOT23	0.3W zener	51V ±2%
Z83	BZX84-B56	Phi	C	SOT23	0.3W zener	56V ±2%
Z84	BZX84-B62	Phi	C	SOT23	0.3W zener	62V ±2%
Z85	BZX84-B68	Phi	C	SOT23	0.3W zener	68V ±2%
Z86	BZX84-B75	Phi	C	SOT23	0.3W zener	75V ±2%
Z9	BZX84-C10	Phi	C	SOT23	0.3W zener	10V
Z9	PDZ5.6B Phi	I	SOD323	5.6V 0.4W zener		
ZA	BZX284-C7V5	Phi	I	SOD110	0.4W zener	7.5V ±5%
ZA	PDZ6.2B Phi	I	SOD323	6.2V 0.4W zener		
ZB	FMMT4123	Zet	N	SOT23	2N4123	
ZB	PDZ6.8B Phi	I	SOD323	6.8V 0.4W zener		
ZB	BZX284-C8V2	Phi	I	SOD110	0.4W zener	8.2V ±5%
ZC	FMMT4124	Zet	N	SOT23	2N4124	
ZC	BZX284-C9V1	Phi	I	SOD110	0.4W zener	9.1V ±5%
ZC	PDZ7.5B Phi	I	SOD323	7.5V 0.4W zener		
ZD	FMMT4125	Zet	N	SOT23	2N4125	
ZD	MMBT4125	Mot	N	SOT23	2N4125	
ZD	BZX284-C10	Phi	I	SOD110	0.4W zener	10V ±5%
ZD	PDZ8.2B Phi	I	SOD323	8.2V 0.4W zener		
ZE	FMMT4126	Zet	N	SOT23	2N4126	
ZE	MMBT4123	Nat	N	SOT23	2N4123	
ZE	BZX284-C11	Phi	I	SOD110	0.4W zener	11V ±5%
ZE	PDZ9.1B Phi	I	SOD323	9.1V 0.4W zener		
ZF	BZX284-C12	Phi	I	SOD110	0.4W zener	12V ±5%
ZF	PDZ10B Phi	I	SOD323	10V 0.4W zener		
ZG	BZX284-C13	Phi	I	SOD110	0.4W zener	13V ±5%
ZG	PDZ11B Phi	I	SOD323	11V 0.4W zener		
ZH	BZX284-C15	Phi	I	SOD110	0.4W zener	15V ±5%
ZH	PDZ12B Phi	I	SOD323	12V 0.4W zener		
ZHK	SM2Z5V1 STM	I	2W SMD	5.1V 2W zener		
ZHL	SM2Z5V6 STM	I	2W SMD	5.6V 2W zener		
ZHW	SM2Z12 STM	I	2W SMD	12V 2W zener		
ZI	BZX284-C16	Phi	I	SOD110	0.4W zener	16V ±5%
ZI	BZX284-C18	Phi	I	SOD110	0.4W zener	18V ±5%
ZJ	PDZ13B Phi	I	SOD323	13V 0.4W zener		
ZJF	SM2Z18 STM	I	2W SMD	18V 2W zener		
ZJQ	SM2Z30 STM	I	2W SMD	30V 2W zener		
ZK	BZX284-C20	Phi	I	SOD110	0.4W zener	20V ±5%
ZK	PDZ15B Phi	I	SOD323	15V 0.4W zener		
ZKR	SM2Z150 STM	I	2W SMD	150V 2W zener		
ZL	BZX284-C22	Phi	I	SOD110	0.4W zener	22V ±5%
ZL	PDZ16B Phi	I	SOD323	16V 0.4W zener		
ZM	BZX284-C24	Phi	I	SOD110	0.4W zener	24V ±5%
ZM	PDZ18B Phi	I	SOD323	18V 0.4W zener		
ZN	BZX284-C27	Phi	I	SOD110	0.4W zener	27V ±5%
ZN	PDZ20B Phi	I	SOD323	20V 0.4W zener		
ZO	BZX284-C30	Phi	I	SOD110	0.4W zener	30V ±5%
ZP	BZX284-C33	Phi	I	SOD100	0.4W zener	33V ±5%
ZP	PDZ22B Phi	I	SOD323	22V 0.4W zener		
ZQ	BZX284-C36	Phi	I	SOD110	0.4W zener	36V ±5%
ZQ	PDZ24B Phi	I	SOD323	24V 0.4W zener		
Z-Q	2PC4081Q	Phi	N	SOT323	gp npn hfe	120-270
ZR	MSD1819A	Mot	N	SOT323	nnp gp	50V
ZR	BZX284-C39	Phi	I	SOD110	0.4W zener	39V ±5%
ZR	PDZ27B Phi	I	SOD323	27V 0.4W zener		
Z-R	2PC4081R	Phi	N	SOT323	gp npn hfe	180-390
ZS	BZX284-C43	Phi	I	SOD110	0.4W zener	43V ±5%
ZS	PDZ30B Phi	I	SOD323	30V 0.4W zener		
Z-S	2PC4081S	Phi	N	SOT323	gp npn hfe	270-560



贴片三极管上的印字，与真实名称的对照表.txt

ZS1	ZHCS1000	Zet	E	SOT23	30V 1A schottky diode
ZS1	ZHCS1000	Zet	C	SOT23	schottky 1A 30V
ZS5	ZHCS500	Zet	E	SOT23	40V 0.5A schottky diode
ZS7	ZHCS750	Zet	E	SOT23	30V 0.75A schottky diode
ZS7	ZHCS750	Zet	C	SOT23	schottky 0.75A 30V
ZT	BZX284-C47	Phi	I	SOD110	0.4W zener 47V ±5%
ZT	PDZ33B	Phi	I	SOD323	33V 0.4W zener
ZtQ	2PC4081Q	Phi	N	SOT323	gp npn hfe 120-270
ZtR	2PC4081R	Phi	N	SOT323	gp npn hfe 180-390
ZtS	2PC4081S	Phi	N	SOT323	gp npn hfe 270-560
ZU	BZX284-C51	Phi	I	SOD110	0.4W zener 51V ±5%
ZU	PDZ36B	Phi	I	SOD323	36V 0.4W zener
ZV	BZX284-C56	Phi	I	SOD110	0.4W zener 56V ±5%
ZW	BZX284-C62	Phi	I	SOD110	0.4W zener 62V ±5%
ZX	BZX284-C68	Phi	I	SOD110	0.4W zener 68V ±5%
ZY	BZX284-C75	Phi	I	SOD110	0.4W zener 75V ±5%

