

## 2 K × 9 & 4 K × 9 CMOS Parallel FIFO

### Introduction

The M67203/204 implement a first-in first-out algorithm, featuring asynchronous read/write operations. The FULL and EMPTY flags prevent data overflow and underflow. The Expansion logic allows unlimited expansion in word size and depth with no timing penalties. Twin address pointers automatically generate internal read and write addresses, and no external address information are required for the TEMIC FIFOs. Address pointers are automatically incremented with the write pin and read pin. The 9 bits wide data are used in data communications applications where a parity bit for error checking is necessary. The Retransmit pin resets the Read pointer to zero without affecting the write pointer. This is very useful for retransmitting data when an error is detected in the system.

### Features

- First-in first-out dual port memory
- 2048 × 9 organisation (M 67203)
- 4096 × 9 organisation (M 67204)
- Fast access time  
Commercial : 20\*, 25, 35, 45, 55 ns  
Industrial and automotive : 25\*, 35, 45, 55 ns  
Military : 25\*, 30, 40, 50 ns
- Wide temperature range : - 55 °C to + 125 °C
- 67203L/204L low power  
67203V/204V very low power

\* Preview. Please Consult Sales.

Using an array of eight transistors (8 T) memory cell and fabricated with the state of the art 1.0 μ lithography named SCMOS, the M 67203/204 combine an extremely low standby supply current (typ = 1.0 μA) with a fast access time at 25 ns over the full temperature range. All versions offer battery backup data retention capability with a typical power consumption at less than 2 μW.

For military/space applications that demand superior levels of performance and reliability the M 67203/204 is processed according to the methods of the latest revision of the MIL STD 883 (class B or S) and/or ESA SCC 9000.


- Fully expandable by word width or depth
- Asynchronous read/write operations
- Empty, full and half flags in single device mode
- Retransmit capability
- Bi-directional applications
- Battery back-up operation 2 V data retention
- TTL compatible
- Single 5 V ± 10 % power supply (1)
- High performance SCMOS technology

(1) 3.3 V versions are also available please consult sales.



## Interface



### Block Diagram



### Pin Configuration

\* SO plastic 28 pin 300 mils  
 DIL plastic 28 pin 300 mils  
 DIL ceramic 28 pin 600 mils  
 FP 28 pin 400 mils (Preview)

32 pin LCC and PLCC



(\*) On request

**Pin Names**

| NAMES      | DESCRIPTION  |
|------------|--------------|
| I0-8       | Inputs       |
| Q0-8       | Outputs      |
| $\bar{W}$  | Write Enable |
| $\bar{R}$  | Read Enable  |
| $\bar{RS}$ | Reset        |
| $\bar{EF}$ | Empty Flag   |

| NAMES               | DESCRIPTION                  |
|---------------------|------------------------------|
| $\bar{FF}$          | Full Flag                    |
| $\bar{XO}/\bar{HF}$ | Expansion Out/Half-Full Flag |
| $\bar{XI}$          | Expansion IN                 |
| $\bar{FL}/\bar{RT}$ | First Load/Retransmit        |
| VCC                 | Power Supply                 |
| GND                 | Ground                       |

**Signal Description**

**Data In (I0 - I8)**


Data inputs for 9-bit data

**Reset ( $\bar{RS}$ )**

Reset occurs whenever the Reset ( $\bar{RS}$ ) input is taken to a low state. Reset returns both internal read and write

pointers to the first location. A reset is required after power-up before a write operation can be enabled. Both the Read Enable ( $\bar{R}$ ) and Write Enable ( $\bar{W}$ ) inputs must be in the high state during the period shown in figure 1 (i.e.  $t_{RSS}$  before the rising edge of  $\bar{RS}$ ) and should not change until  $t_{RSR}$  after the rising edge of  $\bar{RS}$ . The Half-Full Flag ( $\bar{HF}$ ) will be reset to high after Reset ( $\bar{RS}$ ).

**Figure 1. Reset.**



- Notes :**
- $\bar{EF}$ ,  $\bar{FF}$  and  $\bar{HF}$  may change status during reset, but flags will be valid at  $t_{RSC}$ .
  - $\bar{W}$  and  $\bar{R}$  =  $V_{IH}$  around the rising edge of  $\bar{RS}$ .

**Write Enable ( $\bar{W}$ )**

A write cycle is initiated on the falling edge of this input if the Full Flag ( $\bar{FF}$ ) is not set. Data set-up and hold times must be maintained in the rise time of the leading edge of the Write Enable ( $\bar{W}$ ). Data is stored sequentially in the Ram array, regardless of any current read operation.

Once half of the memory is filled, and during the falling edge of the next write operation, the Half-Full Flag ( $\bar{HF}$ ) will be set to low and remain in this state until the difference between the write and read pointers is less than

or equal to half of the total available memory in the device. The Half-Full Flag ( $\bar{HF}$ ) is then reset by the rising edge of the read operation.

To prevent data overflow, the Full Flag ( $\bar{FF}$ ) will go low, inhibiting further write operations. On completion of a valid read operation, the Full Flag ( $\bar{FF}$ ) will go high after TRFF, allowing a valid write to begin. When the FIFO stack is full, the internal write pointer is blocked from  $\bar{W}$ , so that external changes to  $\bar{W}$  will have no effect on the full FIFO stack.

## Read Enable ( $\overline{R}$ )

A read cycle is initiated on the falling edge of the Read Enable ( $\overline{R}$ ) provided that the Empty Flag ( $\overline{EF}$ ) is not set. The data is accessed on a first in/first out basis, not with standing any current write operations. After Read Enable ( $\overline{R}$ ) goes high, the Data Outputs (Q0 – Q8) will return to a high impedance state until the next Read operation. When all the data in the FIFO stack has been read, the Empty Flag ( $\overline{EF}$ ) will go low, allowing the “final” read cycle, but inhibiting further read operations whilst the data outputs remain in a high impedance state. Once a valid write operation has been completed, the Empty Flag ( $\overline{EF}$ ) will go high after tWEF and a valid read may then be initiated. When the FIFO stack is empty, the internal read pointer is blocked from  $\overline{R}$ , so that external changes to  $\overline{R}$  will have no effect on the empty FIFO stack.

## First Load/Retransmit ( $\overline{FL/RT}$ )

This is a dual-purpose input. In the Depth Expansion Mode, this pin is connected to ground to indicate that it is the first loaded (see Operating Modes). In the Single Device Mode, this pin acts as the retransmit input. The Single Device Mode is initiated by connecting the Expansion In ( $\overline{XI}$ ) to ground.

The M 67203/204 can be made to retransmit data when the Retransmit Enable Control ( $\overline{RT}$ ) input is pulsed low. A retransmit operation will set the internal read point to the first location and will not affect the write pointer. Read Enable ( $\overline{R}$ ) and Write Enable ( $\overline{W}$ ) must be in the high state during retransmit. The retransmit feature is intended for use when a number of writes equals to or less than the depth of the FIFO have occurred since the last  $\overline{RS}$  cycle. The retransmit feature is not compatible with the Depth Expansion Mode and will affect the Half-Full Flag ( $\overline{HF}$ ), in accordance with the relative locations of the read and write pointers.

## Expansion In ( $\overline{XI}$ )

This input is a dual-purpose pin. Expansion In ( $\overline{XI}$ ) is connected to GND to indicate an operation in the single device mode. Expansion In ( $\overline{XI}$ ) is connected to Expansion Out ( $\overline{XO}$ ) of the previous device in the Depth Expansion or Daisy Chain modes.

## Full Flag ( $\overline{FF}$ )

The Full Flag ( $\overline{FF}$ ) will go low, inhibiting further write operations when the write pointer is one location less than the read pointer, indicating that the device is full. If the read pointer is not moved after Reset ( $\overline{RS}$ ), the Full Flag ( $\overline{FF}$ ) will go low after 2048/4096 writes.

## Empty Flag ( $\overline{EF}$ )

The Empty Flag ( $\overline{EF}$ ) will go low, inhibiting further read operations when the read pointer is equal to the write pointer, indicating that the device is empty.

## Expansion Out/Half-full Flag ( $\overline{XO/HF}$ )

This is a dual-purpose output. In the single device mode, when Expansion In ( $\overline{XI}$ ) is connected to ground, this output acts as an indication of a half-full memory.

After half the memory is filled and on the falling edge of the next write operation, the Half-Full Flag ( $\overline{HF}$ ) will be set to low and will remain set until the difference between the write and read pointers is less than or equal to half of the total memory of the device. The Half-Full Flag ( $\overline{HF}$ ) is then reset by the rising edge of the read operation.

In the Depth Expansion Mode, Expansion In ( $\overline{XI}$ ) is connected to Expansion Out ( $\overline{XO}$ ) of the previous device. This output acts as a signal to the next device in the Daisy Chain by providing a pulse to the next device when the previous device reaches the last memory location.

## Data Output (Q0 – Q8)

DATA output for 9-bit wide data. This data is in a high impedance condition whenever Read ( $\overline{R}$ ) is in a high state.

## Functional Description


### Operating Modes

#### Single Device Mode

A single M 67203/204 may be used when the application requirements are for 2048/4096 words or less. The M

67203/204 is in a Single Device Configuration when the Expansion In ( $\overline{XI}$ ) control input is grounded (see Figure 2). In this mode the Half-Full Flag ( $\overline{HF}$ ), which is an active low output, is shared with Expansion Out ( $\overline{XO}$ ).

**Figure 2. Block Diagram of Single 2K × 9 and 4K × 9 FIFO.**




#### Width Expansion Mode

Word width may be increased simply by connecting the corresponding input control signals of multiple devices.

Status flags ( $\overline{EF}$ ,  $\overline{FF}$  and  $\overline{HF}$ ) can be detected from any device. Figure 3 demonstrates an 18-bit word width by using two M 67203/204. Any word width can be attained by adding additional M 67203/204.

**Figure 3. Block Diagram of 2048 / 4096 × 18 FIFO Memory Used in Width Expansion Mode.**



**Note :** 3. Flag detection is accomplished by monitoring the  $\overline{FF}$ ,  $\overline{EF}$  and the  $\overline{HF}$  signals on either (any) device used in the width expansion configuration. Do not connect any output control signals together.

**Table 1 : Reset and retransmit  
Single Device Configuration/Width Expansion Mode**

| MODE       | INPUTS          |                 |                 | INTERNAL STATUS          |                          | OUTPUTS         |                 |                 |
|------------|-----------------|-----------------|-----------------|--------------------------|--------------------------|-----------------|-----------------|-----------------|
|            | $\overline{RS}$ | $\overline{RT}$ | $\overline{XI}$ | Read Pointer             | Write Pointer            | $\overline{EF}$ | $\overline{FF}$ | $\overline{HF}$ |
| Reset      | 0               | X               | 0               | Location Zero            | Location Zero            | 0               | 1               | 1               |
| Retransmit | 1               | 0               | 0               | Location Zero            | Unchanged                | X               | X               | X               |
| Read/Write | 1               | 1               | 0               | Increment <sup>(4)</sup> | Increment <sup>(4)</sup> | X               | X               | X               |

Note : 4. Pointer will increment if flag is high.

**Table 2 : Reset and First Load Truth Table  
Depth Expansion/Compound Expansion Mode**

| MODE                    | INPUTS          |                 |                 | INTERNAL STATUS |               | OUTPUTS         |                 |
|-------------------------|-----------------|-----------------|-----------------|-----------------|---------------|-----------------|-----------------|
|                         | $\overline{RS}$ | $\overline{FL}$ | $\overline{XI}$ | Read Pointer    | Write Pointer | $\overline{EF}$ | $\overline{FF}$ |
| Reset First Device      | 0               | 0               | (5)             | Location Zero   | Location Zero | 0               | 1               |
| Reset All Other Devices | 0               | 1               | (5)             | Location Zero   | Location Zero | 0               | 1               |
| Read/Write              | 1               | X               | (5)             | X               | X             | X               | X               |

Note : 5.  $\overline{XI}$  is connected to  $\overline{XO}$  of previous device.  
See fig. 5.

## Depth Expansion (Daisy Chain) Mode

The M 67203/204 can be easily adapted for applications which require more than 2048/4096 words. Figure 4 demonstrates Depth Expansion using three M 67203/204s. Any depth can be achieved by adding additional 67203/204.

The M 67203/204 operate in the Depth Expansion configuration if the following conditions are met :

1. The first device must be designated by connecting the First Load ( $\overline{FL}$ ) control input to ground.
2. All other devices must have  $\overline{FL}$  in the high state.
3. The Expansion Out ( $\overline{XO}$ ) pin of each device must be connected to the Expansion In ( $\overline{XI}$ ) pin of the next device. See figure 4.
4. External logic is needed to generate a composite Full Flag ( $\overline{FF}$ ) and Empty Flag ( $\overline{EF}$ ). This requires that all  $\overline{EF}$ 's and all  $\overline{FF}$ 's be  $\emptyset$ Red (i.e. all must be set to generate the correct composite  $\overline{FF}$  or  $\overline{EF}$ ). See figure 4.
5. The Retransmit ( $\overline{RT}$ ) function and Half-Full Flag ( $\overline{HF}$ ) are not available in the Depth Expansion Mode.

## Compound Expansion Module

It is quite simple to apply the two expansion techniques described above together to create large FIFO arrays (see figure 5).

## Bidirectional Mode


Applications which require data buffering between two systems (each system being capable of Read and Write operations) can be created by coupling M 67203/204 as shown in figure 6. Care must be taken to ensure that the appropriate flag is monitored by each system (i.e.  $\overline{FF}$  is monitored on the device on which  $\overline{W}$  is in use ;  $\overline{EF}$  is monitored on the device on which  $\overline{R}$  is in use). Both Depth Expansion and Width Expansion may be used in this mode.

## Data Flow - Through Modes

Two types of flow-through modes are permitted : a read flow-through and a write flow-through mode. In the read flow-through mode (figure 17) the FIFO stack allows a



**Figure 6. Bidirectional FIFO Mode.**



## Electrical Characteristics

### Absolute Maximum Ratings

Supply voltage (VCC – GND) ..... – 0.3 V to 7.0 V  
 Input or Output voltage applied : .... (GND – 0.3 V) to (Vcc + 0.3 V)  
 Storage temperature : ..... – 65 °C to + 150 °C

| OPERATING RANGE | OPERATING SUPPLY VOLTAGE | OPERATING TEMPERATURE |
|-----------------|--------------------------|-----------------------|
| Military        | Vcc = 5 V ± 10 %         | – 55 °C to + 125 °C   |
| Automotive      | Vcc = 5 V ± 10 %         | – 40 °C to + 125 °C   |
| Industrial      | Vcc = 5 V ± 10 %         | – 40 °C to + 85 °C    |
| Commercial      | Vcc = 5 V ± 10 %         | 0 °C to + 70 °C       |

### DC Parameters

| Parameter              | Description              | Version | M 67203/204    | M 67203/204 |                                    | M 67203/204 | M 67203/204 |             | UNIT | VALUE |
|------------------------|--------------------------|---------|----------------|-------------|------------------------------------|-------------|-------------|-------------|------|-------|
|                        |                          |         | – 20           | – 25        |                                    | – 30        | – 35        |             |      |       |
|                        |                          |         | COM<br>PREVIEW | COM         | IND<br>AUTO<br>MIL<br>PRE-<br>VIEW | MIL<br>only | COM         | IND<br>AUTO |      |       |
| I <sub>CCOP</sub> (8)  | Operating supply current | V       | 155            | 140         | 150                                | 140         | 130         | 140         | mA   | Max   |
|                        |                          | L       | 155            | 140         | 150                                | 140         | 130         | 140         | mA   | Max   |
| I <sub>CCSB</sub> (9)  | Standby supply current   | V       | 2              | 2           | 2                                  | 1.5         | 1.5         | 1.5         | mA   | Max   |
|                        |                          | L       | 2              | 2           | 2                                  | 1.5         | 1.5         | 1.5         | mA   | Max   |
| I <sub>CCPD</sub> (10) | Power down current       | V       | 100            | 100         | 200                                | 200         | 100         | 200         | µA   | Max   |
|                        |                          | L       | 1 000          | 1 000       | 2 000                              | 2 000       | 1 000       | 2 000       | µA   | Max   |

## DC Parameters (continued)

| Parameter              | Description              | Version | M 67203/204 |       | M 67203/204 |          | M 67203/204 |          | M 67203/204 |     | UNIT | VALUE |
|------------------------|--------------------------|---------|-------------|-------|-------------|----------|-------------|----------|-------------|-----|------|-------|
|                        |                          |         | - 40        |       | - 45        |          | - 50        |          | - 55        |     |      |       |
|                        |                          |         | MIL only    | COM   | IND AUTO    | MIL only | COM         | IND AUTO |             |     |      |       |
| I <sub>CCOP</sub> (8)  | Operating supply current | V       | 135         | 125   | 135         | 125      | 120         | 125      | mA          | Max |      |       |
|                        |                          | L       | 135         | 125   | 135         | 125      | 120         | 125      | mA          | Max |      |       |
| I <sub>CCSB</sub> (9)  | Standby supply current   | V       | 1.5         | 1.5   | 1.5         | 1.5      | 1.5         | 1.5      | mA          | Max |      |       |
|                        |                          | L       | 1.5         | 1.5   | 1.5         | 1.5      | 1.5         | 1.5      | mA          | Max |      |       |
| I <sub>CCPD</sub> (10) | Power down current       | V       | 200         | 100   | 200         | 200      | 100         | 200      | μA          | Max |      |       |
|                        |                          | L       | 2 000       | 1 000 | 2 000       | 2 000    | 1 000       | 2 000    | μA          | Max |      |       |

Notes : 8. I<sub>cc</sub> measurements are made with outputs open. F = F max

9.  $\bar{R} = \bar{W} = \bar{RS} = \bar{FL}/\bar{RT} = \text{VIH}$ .

10. All input = V<sub>cc</sub>.

| PARAMETER  | DESCRIPTION            | M 67203/204     |                          | UNIT | VALUE |
|------------|------------------------|-----------------|--------------------------|------|-------|
|            |                        | - 20/- 25/- 30/ | - 35/- 40/- 45/- 50/- 55 |      |       |
| ILI (11)   | Input leakage current  | ± 1             | ± 1                      | μA   | Max   |
| ILO (12)   | Output leakage current | ± 10            | ± 10                     | μA   | Max   |
| VIL (13)   | Input low voltage      | 0.8             | 0.8                      | V    | Max   |
| VIH (13)   | Input high voltage     | 2.2             | 2.2                      | V    | Min   |
| VOL (14)   | Output low voltage     | 0.4             | 0.4                      | V    | Max   |
| VOH (14)   | Output high voltage    | 2.4             | 2.4                      | V    | Min   |
| C IN (15)  | Input capacitance      | 8               | 8                        | pF   | Max   |
| C OUT (15) | Output capacitance     | 8               | 8                        | pF   | Max   |

Notes : 11.  $0.4 \leq V_{in} \leq V_{cc}$ .

12.  $\bar{R} = \text{VIH}$ ,  $0.4 \leq V_{OUT} \leq V_{CC}$ .

13.  $\text{VIH max} = V_{cc} + 0.3 \text{ V}$ .  $\text{VIL min} = -0.3 \text{ V}$  or  $-1 \text{ V}$  pulse width 50 ns.

## AC Test Conditions

Input pulse levels : Gnd to 3.0 V


Input rise/Fall times : 5 ns

Input timing reference levels : 1.5 V

Output reference levels : 1.5 V

Output load : See figure 7

Figure 7. Output Load.



# M67203/M67204

| SYMBOL<br>(16)          | SYMBOL<br>(17) | PARAMETER (18) (22)              | M 67203/204<br>COM<br>– 20 |      | M 67203/204<br>COM, MIL,<br>IND, AUTO<br>(PREVIEW)<br>– 25 |      | M 67203/204<br>MIL ONLY<br>– 30 |      | M 67203/204<br>COM, IND,<br>AUTO<br>– 35 |      | UNIT |
|-------------------------|----------------|----------------------------------|----------------------------|------|--|------|---------------------------------|------|--|------|------|
|                         |                |                                  | MIN.                       | MAX. | MIN.   | MAX. | MIN.                            | MAX. | MIN.                                     | MAX. |      |
| <b>READ CYCLE</b>       |                |                                  | PREVIEW                    |      |  |      |                                 |      |  |      |      |
| TRLRL                   | tRC            | Read cycle time                  | 30                         | –    | 35   | –    | 40                              | –    | 45                                       | –    | ns   |
| TRLQV                   | tA             | Access time                      | –                          | 20   | –  | 25   | –                               | 30   | –  | 35   | ns   |
| TRHRL                   | tRR            | Read recovery time               | 10                         | –    | 10   | –    | 10                              | –    | 10                                       | –    | ns   |
| TRLRH                   | tRPW           | Read pulse width (19)            | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |
| TRLQX                   | tRLZ           | Read low to data low Z (20)      | 5                          | –    | 5  | –    | 5                               | –    | 5  | –    | ns   |
| TWHQX                   | tWLZ           | Write low to data low Z (20, 21) | 5                          | –    | 5  | –    | 10                              | –    | 10                                       | –    | ns   |
| TRHQX                   | tDV            | Data valid from read high        | 5                          | –    | 5  | –    | 5                               | –    | 5  | –    | ns   |
| TRHQZ                   | tRHZ           | Read high to data high Z (20)    | –                          | 15   | –  | 18   | –                               | 20   | –  | 20   | ns   |
| <b>WRITE CYCLE</b>      |                |                                  | PREVIEW                    |      |  |      |                                 |      |  |      |      |
| TWLWL                   | tWC            | Write cycle time                 | 30                         | –    | 35   | –    | 40                              | –    | 45                                       | –    | ns   |
| TWLWH                   | tWPW           | Write pulse width (19)           | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |
| TWHWL                   | tWR            | Write recovery time              | 10                         | –    | 10   | –    | 10                              | –    | 10                                       | –    | ns   |
| TDVWH                   | tDS            | Data set-up time                 | 12                         | –    | 15   | –    | 18                              | –    | 18                                       | –    | ns   |
| TWHDX                   | tDH            | Data hold time                   | 0                          | –    | 0  | –    | 0                               | –    | 0  | –    | ns   |
| <b>RESET CYCLE</b>      |                |                                  | PREVIEW                    |      |  |      |                                 |      |  |      |      |
| TRSLWL                  | tRSC           | Reset cycle time                 | 30                         | –    | 35   | –    | 40                              | –    | 45                                       | –    | ns   |
| TRSLRSH                 | tRS            | Reset pulse width (19)           | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |
| TWHRSH                  | tRSS           | Reset set-up time                | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |
| TRSHWL                  | tRSR           | Reset recovery time              | 10                         | –    | 10   | –    | 10                              | –    | 10                                       | –    | ns   |
| <b>RETRANSMIT CYCLE</b> |                |                                  | PREVIEW                    |      |  |      |                                 |      |  |      |      |
| TRTLWL                  | tRTC           | Retransmit cycle time            | 30                         | –    | 35   | –    | 40                              | –    | 45                                       | –    | ns   |
| TRTLRTH                 | tRT            | Retransmit pulse width (19)      | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |
| TWHRTH                  | tRTS           | Retransmit set-up time (20)      | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |
| TRTHWL                  | tRTR           | Retransmit recovery time         | 10                         | –    | 10   | –    | 10                              | –    | 10                                       | –    | ns   |
| <b>FLAGS</b>            |                |                                  | PREVIEW                    |      |  |      |                                 |      |  |      |      |
| TRSLEFL                 | tEFL           | Reset to EF low                  | –                          | 30   | –  | 35   | –                               | 40   | –  | 45   | ns   |
| TRSLFFH                 | tHFH, tFFH     | Reset to HF/FF high              | –                          | 30   | –  | 35   | –                               | 40   | –  | 45   | ns   |
| TRLEFL                  | tREF           | Read low to EF low               | –                          | 20   | –  | 25   | –                               | 30   | –  | 30   | ns   |
| TRHFFH                  | tRFF           | Read high to FF high             | –                          | 20   | –  | 25   | –                               | 30   | –  | 30   | ns   |
| TEFHRH                  | tRPE           | Read width after EF high         | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |
| TWHEFH                  | tWEF           | Write high to EF high            | –                          | 20   | –  | 25   | –                               | 30   | –  | 30   | ns   |
| TWLFFL                  | tWFF           | Write low to FF low              | –                          | 20   | –  | 25   | –                               | 30   | –  | 30   | ns   |
| TWLHFL                  | tWHF           | Write low to HF low              | –                          | 30   | –  | 35   | –                               | 40   | –  | 45   | ns   |
| TRHFFH                  | tRHF           | Read high to HF high             | –                          | 30   | –  | 35   | –                               | 40   | –  | 45   | ns   |
| TFFHWH                  | tWPF           | Write width after FF high        | 20                         | –    | 25   | –    | 30                              | –    | 35                                       | –    | ns   |


| SYMBOL<br>(16)          | SYMBOL<br>(17) | PARAMETER (18) (22)              | M 67203/204<br>MIL only<br>- 40 |      | M 67203/204<br>COM, IND,<br>AUTO<br>- 45 |      | M 67203/204<br>MIL only<br>- 50 |      | M 67203/204<br>COM, IND,<br>AUTO<br>- 55 |      | UNIT |
|-------------------------|----------------|----------------------------------|---------------------------------|------|--|------|---------------------------------|------|--|------|------|
|                         |                |                                  | MIN.                            | MAX. | MIN.                                     | MAX. | MIN.                            | MAX. | MIN.                                     | MAX. |      |
| <b>READ CYCLE</b>       |                |                                  |                                 |      |  |      |                                 |      |  |      |      |
| TRLRL                   | tRC            | Read cycle time                  | 50                              | -    | 55                                       | -    | 65                              | -    | 70                                       | -    | ns   |
| TRLQV                   | tA             | Access time                      | -                               | 40   | -  | 45   | -                               | 50   | -  | 55   | ns   |
| TRHRL                   | tRR            | Read recovery time               | 10                              | -    | 10                                       | -    | 15                              | -    | 15                                       | -    | ns   |
| TRLRH                   | tRPW           | Read pulse width (19)            | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |
| TRLQX                   | tRLZ           | Read low to data low Z (20)      | 5                               | -    | 5  | -    | 10                              | -    | 10                                       | -    | ns   |
| TWHQX                   | tWLZ           | Write low to data low Z (20, 21) | 10                              | -    | 10                                       | -    | 15                              | -    | 15                                       | -    | ns   |
| TRHQX                   | tDV            | Data valid from read high        | 5                               | -    | 5  | -    | 5                               | -    | 5  | -    | ns   |
| TRHQZ                   | tRHZ           | Read high to data high Z (20)    | -                               | 25   | -  | 25   | -                               | 30   | -  | 30   | ns   |
| <b>WRITE CYCLE</b>      |                |                                  |                                 |      |  |      |                                 |      |  |      |      |
| TWLWL                   | tWC            | Write cycle time                 | 50                              | -    | 55                                       | -    | 65                              | -    | 70                                       | -    | ns   |
| TWLWH                   | tWPW           | Write pulse width (19)           | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |
| TWHWL                   | tWR            | Write recovery time              | 10                              | -    | 10                                       | -    | 15                              | -    | 15                                       | -    | ns   |
| TDVWH                   | tDS            | Data set-up time                 | 20                              | -    | 20                                       | -    | 30                              | -    | 30                                       | -    | ns   |
| TWHDX                   | tDH            | Data hold time                   | 0                               | -    | 0  | -    | 0                               | -    | 0  | -    | ns   |
| <b>RESET CYCLE</b>      |                |                                  |                                 |      |  |      |                                 |      |  |      |      |
| TRSLWL                  | tRSC           | Reset cycle time                 | 50                              | -    | 55                                       | -    | 65                              | -    | 70                                       | -    | ns   |
| TRSLRSH                 | tRS            | Reset pulse width (19)           | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |
| TWHRSH                  | tRSS           | Reset set-up time                | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |
| TRSHWL                  | tRSR           | Reset recovery time              | 10                              | -    | 10                                       | -    | 15                              | -    | 15                                       | -    | ns   |
| <b>RETRANSMIT CYCLE</b> |                |                                  |                                 |      |  |      |                                 |      |  |      |      |
| TRTLWL                  | tRTC           | Retransmit cycle time            | 50                              | -    | 55                                       | -    | 65                              | -    | 70                                       | -    | ns   |
| TRTLRTH                 | tRT            | Retransmit pulse width (19)      | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |
| TWHRTH                  | tRTS           | Retransmit set-up time (20)      | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |
| TRTHWL                  | tRTR           | Retransmit recovery time         | 10                              | -    | 10                                       | -    | 15                              | -    | 15                                       | -    | ns   |
| <b>FLAGS</b>            |                |                                  |                                 |      |  |      |                                 |      |  |      |      |
| TRSLEFL                 | tEFL           | Reset to EF low                  | -                               | 50   | -  | 55   | -                               | 60   | -  | 65   | ns   |
| TRSLFFH                 | tHFH, tFFH     | Reset to HF/FF high              | -                               | 50   | -  | 55   | -                               | 60   | -  | 65   | ns   |
| TRLEFL                  | tREF           | Read low to EF low               | -                               | 30   | -  | 40   | -                               | 45   | -  | 50   | ns   |
| TRHFFH                  | tRFF           | Read high to FF high             | -                               | 35   | -  | 40   | -                               | 45   | -  | 50   | ns   |
| TEFHRH                  | tRPE           | Read width after EF high         | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |
| TWHEFH                  | tWEF           | Write high to EF high            | -                               | 35   | -  | 40   | -                               | 45   | -  | 50   | ns   |
| TWLFFL                  | tWFF           | Write low to FF low              | -                               | 35   | -  | 40   | -                               | 45   | -  | 50   | ns   |
| TWLHFL                  | tWHF           | Write low to HF low              | -                               | 50   | -  | 55   | -                               | 60   | -  | 65   | ns   |
| TRHHFH                  | tRHF           | Read high to HF high             | -                               | 50   | -  | 55   | -                               | 60   | -  | 65   | ns   |
| TFFHWH                  | tWPF           | Write width after FF high        | 40                              | -    | 45                                       | -    | 50                              | -    | 55                                       | -    | ns   |

| SYMBOL (16) | SYMBOL (17) | PARAMETER (18) (22)   | M 67203/204 COM - 20 |      | M 67203/204 COM, MIL, IND, AUTO (PREVIEW) - 25 |      | M 67203/204 MIL only - 30 |      | M 67203/204 COM, IND, AUTO - 35 |      | UNIT |
|-------------|-------------|-----------------------|----------------------|------|--|------|---------------------------|------|---------------------------------|------|------|
|             |             |                       | MIN.                 | MAX. | MIN.   | MAX. | MIN.                      | MAX. | MIN.                            | MAX. |      |
| EXPANSION   |             |                       | PREVIEW              |      |  |      |                           |      |                                 |      |      |
| TWLXOL      | tXOL        | Read/Write to XO low  | -                    | 20   | -  | 25   | -                         | 30   | -                               | 35   | ns   |
| TWHXOH      | tXOH        | Read/Write to XO high | -                    | 20   | -  | 25   | -                         | 30   | -                               | 35   | ns   |
| TXILXIH     | tXI         | XI pulse width        | 20                   | -    | 25   | -    | 30                        | -    | 35                              | -    | ns   |
| TXIHXIL     | tXIR        | XI recovery time      | 10                   | -    | 10   | -    | 10                        | -    | 10                              | -    | ns   |
| TXILRL      | tXIS        | XI set-up time        | 10                   | -    | 10   | -    | 10                        | -    | 10                              | -    | ns   |


| SYMBOL (16) | SYMBOL (17) | PARAMETER (18) (22)   | M 67203/204 MIL only - 40 |      | M 67203/204 COM, IND, AUTO - 45 |      | M 67203/204 MIL only - 50 |      | M 67203/204 COM, IND, AUTO - 55 |      | UNIT |
|-------------|-------------|-----------------------|---------------------------|------|---------------------------------|------|---------------------------|------|---------------------------------|------|------|
|             |             |                       | MIN.                      | MAX. | MIN.                            | MAX. | MIN.                      | MAX. | MIN.                            | MAX. |      |
| EXPANSION   |             |                       | PREVIEW                   |      |                                 |      |                           |      |                                 |      |      |
| TWLXOL      | tXOL        | Read/Write to XO low  | -                         | 40   | -                               | 45   | -                         | 50   | -                               | 55   | ns   |
| TWHXOH      | tXOH        | Read/Write to XO high | -                         | 40   | -                               | 45   | -                         | 50   | -                               | 55   | ns   |
| TXILXIH     | tXI         | XI pulse width        | 40                        | -    | 45                              | -    | 50                        | -    | 55                              | -    | ns   |
| TXIHXIL     | tXIR        | XI recovery time      | 10                        | -    | 10                              | -    | 10                        | -    | 10                              | -    | ns   |
| TXILRL      | tXIS        | XI set-up time        | 10                        | -    | 10                              | -    | 15                        | -    | 15                              | -    | ns   |

- Notes :
- 16. STD symbol.
  - 17. ALT symbol.
  - 18. Timings referenced as in ac test conditions.
  - 19. Pulse widths less than minimum value are not allowed.
  - 20. Values guaranteed by design, not currently tested.
  - 21. Only applies to read data flow-through mode.
  - 22. All parameters tested only.


Figure 8. Asynchronous Write and Read Operation.




**Figure 9. Full Flag from Last Write to First Read.**



**Figure 10. Empty Flag from Last Read to First Write.**




**Figure 11. Retransmit.**




**Notes :** 23.  $\bar{EF}$ ,  $\bar{FF}$  and  $\bar{HF}$  may change status during Retransmit, but flags will be valid at  $t_{RTC}$ .

**Figure 12. Empty Flag Timing**



**Figure 13. Full Flag Timing**



**Figure 14. Half-Full Flag Timing.**




Figure 15. Expansion Out.




Figure 16. Expansion In.




Figure 17. Read Data Flow – Through Mode.





Figure 18. Write Data Flow – Through Mode.



## Ordering Information

| TEMPERATURE RANGE   | PACKAGE  | DEVICE   | SPEED | FLOW   |   |  |  |
|---|--|--|-------|--------|---|--|--|
| C   | M  | 3P   | —     | 67204L | — | 25   |  |
|   | M = 5 V version<br>L = 3.3 V version   | 1I = 28 pin DIL ceramic 600 mils<br>3P = 28 pin DIL plastic 300 mils<br>*TI = 28 pin SOL plastic 300 mils<br>*UI = 28 pin SOJ plastic 300 mils<br>4J = 32 pin LCC rectangular<br>S1 = 32 pin PLCC<br>DP = 28 pin FP 400 mils<br>CP = Side brazed 28 pins 300 mils<br>0 = Dice form |       |        |   | 20 ns<br>25 ns<br>30 ns<br>35 ns<br>40 ns<br>45 ns<br>50 ns<br>55 ns | blank = MHS standards<br>/883 = MIL STD 883 Class B or S<br>P883 = MIL STD 883 + PIND test<br>SB/SC = SCC 9000 level B/C<br>SHXXX = Special customer request<br>FHXXX = Flight models (space)<br>EHXXX = Engineering models (space)<br>MHXXX = Mechanical parts (space)<br>LHXXX = Life test parts (space)<br>: R = Tape and reel<br>: RD = Tape and reel dry pack<br>: D = Dry pack |
| C = Commercial<br>I = Industrial<br>A = Automotive<br>M = Military<br>S = Space | 0° to +70°C<br>-40° to +85°C<br>-40° to +125°C<br>-55° to +125°C<br>-55° to +125°C | 67203 = 2048 × 9 FIFO<br>67204 = 4096 × 9 FIFO<br>L = Low power<br>V = Very low power  |       |        |   |  |  |

\* On request only

**Military and Space Versions**

The following tables give package/consumption/access time/process flow available combinations

| Temp. range | Packages                  | Consumption           |                       | Access Time (ns)      |                       |                       | Std process 67203<br>Mil flows (including SMD5962-88669 SMD5962-89567) | RT process 67203E |                                    |
|-------------|---------------------------|-----------------------|-----------------------|-----------------------|-----------------------|-----------------------|--|-------------------|------------------------------------|
|             |                           | V                     | L                     | 30                    | 40                    | 50                    |  | Mil flows         | Space flows (including SCC9301035) |
| M           | 1I<br>4J<br>CP<br>DP<br>0 | ●<br>●<br>●<br>●<br>X | ●<br>●<br>●<br>●<br>● | X<br>X<br>X<br>X<br>X | ●<br>●<br>●<br>●<br>X | ●<br>●<br>●<br>●<br>● | ●<br>●<br>●<br>●<br>●  |                   |                                    |
| S           | 4J<br>CP<br>DP<br>0       | ●<br>●<br>●<br>X      | ●                     | X<br>X<br>X<br>X      | ●<br>●<br>●<br>X      | ●<br>●<br>●<br>●      |  | ●<br>●<br>●<br>●  | X<br>X<br>●<br>X                   |

| Temp. range | Packages                  | Consumption           |                       | Access Time (ns)      |                       |                       | Std process 67204<br>Mil flows (including SMD5962-89568) | RT process 67204E |                  |
|-------------|---------------------------|-----------------------|-----------------------|-----------------------|-----------------------|-----------------------|--|-------------------|------------------|
|             |                           | V                     | L                     | 30                    | 40                    | 50                    |  | Mil flows         | Space flows      |
| M           | 1I<br>4J<br>CP<br>DP<br>0 | ●<br>●<br>●<br>●<br>X | ●<br>●<br>●<br>●<br>● | X<br>X<br>X<br>X<br>X | X<br>X<br>X<br>X<br>X | ●<br>●<br>●<br>●<br>● | ●<br>●<br>●<br>●<br>●                                    |                   |                  |
| S           | 4J<br>CP<br>DP<br>0       | ●<br>●<br>●<br>X      | ●                     | X<br>X<br>X<br>X      | X<br>X<br>X<br>X      | ●<br>●<br>●<br>●      |  | ●<br>●<br>●<br>●  | ●<br>●<br>●<br>● |

● = product in production  
X = call sales office for availability

*The information contained herein is subject to change without notice. No responsibility is assumed by TEMIC for using this publication and/or circuits described herein : nor for any possible infringements of patents or other rights of third parties which may result from its use.*