


### NPN Silicon AF Transistors

- For AF driver and output stages
- High collector current
- Low collector-emitter saturation voltage
- Complementary types: BCP 51M...BCP 53M(PNP)



Type	Marking	Ordering Code	Pin Configuration					Package
BCP 54M	BAs	Q62702-C2595	1 = B	2 = C	3 = E	4 n.c.	5 = C	SCT-595
BCP 55M	BEs	Q62702-C2606						
BCP 56M	BHs	Q62702-C2607						

### Maximum Ratings

Parameter	Symbol	BCP 54M	BCP 55M	BCP 56M	Unit
Collector-emitter voltage	$V_{CEO}$	45	60	80	V
Collector-base voltage	$V_{CBO}$	45	60	100	
Emitter-base voltage	$V_{EBO}$	5	5	5	
DC collector current	$I_C$	1			mA
Peak collector current	$I_{CM}$	1.5			
Base current	$I_B$	100			mA
Peak base current	$I_{BM}$	200			
Total power dissipation, $T_S \leq 77 \text{ }^\circ\text{C}$	$P_{tot}$	1.7			W
Junction temperature	$T_j$	150			$^\circ\text{C}$
Storage temperature	$T_{stg}$	-65...+150			

### Thermal Resistance

Junction ambient <sup>1)</sup>	$R_{thJA}$	$\leq 98$	K/W
Junction - soldering point	$R_{thJS}$	$\leq 43$	

1) Package mounted on pcb 40mm x 40mm x 1.5mm / 6cm<sup>2</sup> Cu


**Electrical Characteristics** at  $T_A = 25^\circ\text{C}$ , unless otherwise specified.

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
<b>DC Characteristics</b>					
Collector-emitter breakdown voltage $I_C = 10\text{ mA}, I_B = 0$	$V_{(BR)CEO}$				V
BCP 54M		45	-	-	
BCP 55M		60	-	-	
BCP 56M		80	-	-	
Collector-base breakdown voltage $I_C = 100\ \mu\text{A}, I_B = 0$	$V_{(BR)CBO}$				
BCP 54M		45	-	-	
BCP 55M		60	-	-	
BCP 56M		100	-	-	
Emitter-base breakdown voltage $I_E = 10\ \mu\text{A}, I_C = 0$	$V_{(BR)EBO}$	5	-	-	
Collector cutoff current $V_{CB} = 30\text{ V}, I_E = 0$	$I_{CBO}$	-	-	100	nA
Collector cutoff current $V_{CB} = 30\text{ V}, I_E = 0, T_A = 150^\circ\text{C}$	$I_{CBO}$	-	-	20	$\mu\text{A}$
DC current gain 1) $I_C = 5\text{ mA}, V_{CE} = 2\text{ V}$	$h_{FE}$	25	-	-	-
DC current gain 1) $I_C = 150\text{ mA}, V_{CE} = 2\text{ V}$	$h_{FE}$	40	-	250	-
DC current gain 1) $I_C = 500\text{ mA}, V_{CE} = 2\text{ V}$	$h_{FE}$	25	-	-	-
Collector-emitter saturation voltage1) $I_C = 500\text{ mA}, I_B = 50\text{ mA}$	$V_{CEsat}$	-	-	0.5	V
Base-emitter voltage 1) $I_C = 500\text{ mA}, V_{CE} = 2\text{ V}$	$V_{BE(ON)}$	-	-	1	
<b>AC Characteristics</b>					
Transition frequency $I_C = 50\text{ mA}, V_{CE} = 10\text{ V}, f = 100\text{ MHz}$	$f_T$	-	100	-	MHz

1) Pulse test:  $t \leq 300\ \mu\text{s}$ ,  $D = 2\%$


### Total power dissipation $P_{tot} = f(T_A^*; T_S)$

\* Package mounted on epoxy




### DC current gain $h_{FE} = f(I_C)$

$V_{CE} = 2V$




### Permissible Pulse Load $R_{thJS} = f(t_p)$




### Permissible Pulse Load

$P_{totmax} / P_{totDC} = f(t_p)$




### Collector cutoff current $I_{CBO} = f(T_A)$

$V_{CB} = 30V$




### Transition frequency $f_T = f(I_C)$

$V_{CE} = 10V$



### Base-emitter saturation voltage

$I_C = f(V_{BEsat}), h_{FE} = 10$



### Collector-emitter saturation voltage

$I_C = f(V_{CEsat}), h_{FE} = 10$

