



HM9114/A/C

TONE/PULSE SWITCHABLE & 15 MEMORY DIALER

Features

- Tone/Pulse Switchable Dialer.
- Stores Ten 16-Digit Numbers for Repertory Dialing.
- Four 16-Digit Numbers for Emergency Calling Memory.
- One 31-Digit for Last Number Redial Memory.
- Auto Pause Access; 3.1 sec. per pause for HM9114, 3.6 sec per for HM9114A/C (2 sec pause time can be obtained by metal option.)
- Key-Tone Output for valid keypad Entry recognition for both pulse mode and tone mode.
- Minimum tone duration=100ms and minimum intertone pause=106ms for rapid key-in.
- Use 3.579545MHz crystal.
- Pin selectable for M/B rate, flash time and pulse rate.
- Automatic Switching from Pulse mode to Tone mode in EM4.
- M/B rate, flash time, pulse rate can be selected by M/B & DRS pin.

	M/B	DRS	M/B rate	Flash time	Pulse rate
HM9114/A	1	1	40:60	600ms	10PPS
	0	1	33:66	100ms	10PPS
	0	0	33:66	600ms	20PPS
	M/B	DRS	M/B rate	Flash time	Pulse rate
HM9114C	1	1	40:60	100ms	10PPS
	0	1	33:66	600ms	10PPS
	0	0	33:66	600ms	20PPS

Pin Assignment

HM9114/A/C

COL1	1	22	ROW5
COL2	2	21	ROW4
COL3	3	20	ROW3
COL4	4	19	ROW2
GND	5	18	ROW1
OSC.IN	6	17	V _{DD}
OSC.OUT	7	16	M/B
T/P MUTE	8	15	DRS
HKS	9	14	MODE
PULSE OUT	10	13	TONE MUTE
TONE OUT	11	12	KEY TONE OUT

Keyboard Scheme

COL1	COL2	COL3	COL4	
1	2	3	EM1	ROW1
4	5	6	EM2	ROW2
7	8	9	EM3	ROW3
*	0	#	EM4	ROW4
R/P	S	A	F	ROW5

S: Store A: Auto Dialing
 EM1-EM4: Emergency 1-4 F: Flash
 R/P: First touch after off-hook is redial function.
 Others execute pause function.
 EM4: With pulse to tone function.