

Toshiba Photoreflexive sensor Infrared LED + Phototransistor

# TLP921


## Inkjet printer's ink-level monitoring

TLP921 is a reflective photosensor combining a GaAs infrared LED with a Si phototransistor.

- Flush-mount package on PCB: Applied PCB thickness = 1.6 mm or thinner
- Positioning pin and single-sided screw-mount type
- Short lead type: Lead length =  $2.8 \pm 0.3$  mm
- Phototransistor impermeable to visible light
- Package material: polybutylene-terephthalate (UL94V-0, black)

### Maximum Ratings (Ta = 25°C)


Characteristics		Symbol	Rating	Unit
LED	Forward current	$I_F$	50	mA
	Forward current derating (Ta > 25°C)	$\Delta I_F/^\circ\text{C}$	-0.33	mA/°C
	Reverse voltage	$V_R$	5	V
Detector	Collector-Emitter voltage	$V_{CEO}$	35	V
	Emitter-Collector voltage	$V_{ECO}$	5	V
	Collector power dissipation	$P_C$	75	mW
	Collector power dissipation derating (Ta > 25°C)	$\Delta P_C/^\circ\text{C}$	-1	mW/°C
	Collector current	$I_C$	50	mA
Operating temperature		$T_{opr}$	-30~85	°C
Storage temperature		$T_{stg}$	-40~100	°C
Soldering temperature (5 s) (Note 1)		$T_{sol}$	260	°C



Weight: 0.35 g (typ.)

Note 1: Soldering is performed 1.5 mm from the bottom of the package.


### Marking




## Electrical and Optical Characteristics (Ta = 25°C)

Characteristics		Symbol	Test Condition	Min	Typ.	Max	Unit
LED	Forward voltage	$V_F$	$I_F = 20 \text{ mA}$	—	1.25	1.4	V
	Reverse current	$I_R$	$V_R = 5 \text{ V}$	—	—	10	$\mu\text{A}$
	Peak emission wavelength	$\lambda_P$	$I_F = 20 \text{ mA}$	—	940	—	nm
Detector	Dark current	$I_D (I_{CEO})$	$V_{CE} = 24 \text{ V}, I_F = 0$	—	—	0.1	$\mu\text{A}$
	Peak sensitivity wavelength	$\lambda_P$	—	—	870	—	nm
Coupled	Collector current	$I_C$	$V_{CE} = 5 \text{ V}, I_F = 20 \text{ mA}$ (Note 2)	580	—	2600	$\mu\text{A}$
	Leakage current	$I_{LEAK}$	$V_{CE} = 5 \text{ V}, I_F = 20 \text{ mA}$ (Note 3)	—	—	120	$\mu\text{A}$
	Collector-Emitter saturation voltage	$V_{CE(sat)}$	$I_F = 20 \text{ mA}, I_C = 0.3 \text{ mA}$	—	0.1	0.4	V
	Rise time	$t_r$	$V_{CE} = 2 \text{ V}, I_C = 0.5 \text{ mA}$	—	38	90	$\mu\text{s}$
	Fall time	$t_f$	$R_L = 1 \text{ k}\Omega, d = 8 \text{ mm}$ (Note 4)	—	48	110	



Note 2: The following drawings show condition and the layout of reflectors.



Note 3: Measurement layout drawing for leakage current



Note 4: Measurement circuit and waveforms for Switching time




**Handling Precautions**

- When removing flux with chemicals after soldering, clean only the soldered part of the leads. Do not immerse the entire package in the cleaning solvent. Chemical residue on the LED emitter or the photodetector inside the phototransistor case may adversely affect the optical characteristics of the device and may drastically reduce the collector current.
- The case is made of polybutylene-terephthalate. Oil or chemicals may cause the package to melt or crack. Care must be taken in relation to the environment in which the device is to be installed.
- Mount the device on a level surface.
- The collector current characteristic will deteriorate over time due to current flowing in the infrared LED. The design of circuits which incorporate the device must take into account the change in collector current over time.
- When the 2-mm hole is used as screw fixation, please fastening torque 0.1 N or less.


## Package Dimensions







Unit: mm  
 ( ): reference value  
 Tolerance is  $\pm 0.2$  unless  
 otherwise specified.












Weight: 0.35g (typ.)

## Pin connection









**RESTRICTIONS ON PRODUCT USE**

000707EAC

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.  
In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- Gallium arsenide (GaAs) is a substance used in the products described in this document. GaAs dust and fumes are toxic. Do not break, cut or pulverize the product, or use chemicals to dissolve them. When disposing of the products, follow the appropriate regulations. Do not dispose of the products with other industrial waste or with domestic garbage.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.