

Low Voltage Dual 1:4, 1:5 Differential Fanout Buffer ECL/PECL Compatible

The MC100LVE210 is a low voltage, low skew dual differential ECL fanout buffer designed with clock distribution in mind. The device features two fanout buffers, a 1:4 and a 1:5 buffer, on a single chip. The device features fully differential clock paths to minimize both device and system skew. The dual buffer allows for the fanout of two signals through a single chip, thus reducing the skew between the two fundamental signals from a part-to-part skew down to an output-to-output skew. This capability reduces the skew by a factor of 4 as compared to using two LVE111's to accomplish the same task. The MC100LVE210 works from a -3.3V supply while the MC100E210 provides identical function and performance from a standard -4.5V 100E voltage supply.

- Dual Differential Fanout Buffers
- 200ps Part-to-Part Skew
- 50ps Typical Output-to-Output Skew
- Low Voltage ECL/PECL Compatible
- 28-lead PLCC Packaging


For applications which require a single-ended input, the V_{BB} reference voltage is supplied. For single-ended input applications the V_{BB} reference should be connected to the CLK input and bypassed to ground via a 0.01 μ f capacitor. The input signal is then driven into the CLK input.

To ensure that the tight skew specification is met it is necessary that both sides of the differential output are terminated into 50 Ω , even if only one side is being used. In most applications all nine differential pairs will be used and therefore terminated. In the case where fewer than nine pairs are used it is necessary to terminate at least the output pairs adjacent to the output pair being used in order to maintain minimum skew. Failure to follow this guideline will result in small degradations of propagation delay (on the order of 10–20ps) of the outputs being used, while not catastrophic to most designs this will result in an increase in skew. Note that the package corners isolate outputs from one another such that the guideline expressed above holds only for outputs on the same side of the package.

The MC100LVE210, as with most ECL devices, can be operated from a positive V_{CC} supply in PECL mode. This allows the LVE210 to be used for high performance clock distribution in +3.3V systems. Designers can take advantage of the LVE210's performance to distribute low skew clocks across the backplane or the board. In a PECL environment series or Thevenin line terminations are typically used as they require no additional power supplies, if parallel termination is desired a terminating voltage of $V_{CC}-2.0V$ will need to be provided. For more information on using PECL, designers should refer to Motorola Application Note AN1406/D.

MC100LVE210
MC100E210


LOW VOLTAGE
DUAL 1:4, 1:5 DIFFERENTIAL
FANOUT BUFFER



FN SUFFIX
PLASTIC PACKAGE
CASE 776-02




MC100LVE210 MC100E210



PIN NAMES

| Pins | Function |
|--------------|--------------------------|
| CLKa, CLKb | Differential Input Pairs |
| Qa0:4, Qb0:3 | Differential Outputs |
| VBB | VBB Output |

LOGIC SYMBOL



MC100LVE210
ECL DC CHARACTERISTICS

| Symbol | Characteristic | -40°C | | | 0°C | | | 25°C | | | 85°C | | | Unit |
|-----------------|--------------------------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| V _{OH} | Output HIGH Voltage | -1.085 | -1.005 | -0.880 | -1.025 | -0.955 | -0.880 | -1.025 | -0.955 | -0.880 | -1.025 | -0.955 | -0.880 | V |
| V _{OL} | Output LOW Voltage | -1.830 | -1.695 | -1.555 | -1.810 | -1.705 | -1.620 | -1.810 | -1.705 | -1.620 | -1.810 | -1.705 | -1.620 | V |
| V _{IH} | Input HIGH Voltage | -1.165 | | -0.880 | -1.165 | | -0.880 | -1.165 | | -0.880 | -1.165 | | -0.880 | V |
| V _{IL} | Input LOW Voltage | -1.810 | | -1.475 | -1.810 | | -1.475 | -1.810 | | -1.475 | -1.810 | | -1.475 | V |
| V _{BB} | Output Reference Voltage | -1.38 | | -1.26 | -1.38 | | -1.26 | -1.38 | | -1.26 | -1.38 | | -1.26 | V |
| V _{EE} | Power Supply Voltage | -3.0 | | -3.8 | -3.0 | | -3.8 | -3.0 | | -3.8 | -3.0 | | -3.8 | V |
| I _{IH} | Input HIGH Current | | | 150 | | | 150 | | | 150 | | | 150 | μA |
| I _{EE} | Power Supply Current | | | 55 | | | 55 | | | 55 | | | 65 | mA |

MC100LVE210
PECL DC CHARACTERISTICS

| Symbol | Characteristic | -40°C | | | 0°C | | | 25°C | | | 85°C | | | Unit |
|-----------------|---------------------------------------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| V _{OH} | Output HIGH Voltage ¹ | 2.215 | 2.295 | 2.42 | 2.275 | 2.345 | 2.420 | 2.275 | 2.345 | 2.420 | 2.275 | 2.345 | 2.420 | V |
| V _{OL} | Output LOW Voltage ¹ | 1.47 | 1.605 | 1.745 | 1.490 | 1.595 | 1.680 | 1.490 | 1.595 | 1.680 | 1.490 | 1.595 | 1.680 | V |
| V _{IH} | Input HIGH Voltage ¹ | 2.135 | | 2.420 | 2.135 | | 2.420 | 2.135 | | 2.420 | 2.135 | | 2.420 | V |
| V _{IL} | Input LOW Voltage ¹ | 1.490 | | 1.825 | 1.490 | | 1.825 | 1.490 | | 1.825 | 1.490 | | 1.825 | V |
| V _{BB} | Output Reference Voltage ¹ | 1.92 | | 2.04 | 1.92 | | 2.04 | 1.92 | | 2.04 | 1.92 | | 2.04 | V |
| V _{CC} | Power Supply Voltage | 3.0 | | 3.8 | 3.0 | | 3.8 | 3.0 | | 3.8 | 3.0 | | 3.8 | V |
| I _{IH} | Input HIGH Current | | | 150 | | | 150 | | | 150 | | | 150 | μA |
| I _{EE} | Power Supply Current | | | 55 | | | 55 | | | 55 | | | 65 | mA |

1. These values are for V_{CC} = 3.3V. Level Specifications will vary 1:1 with V_{CC}.

MC100LVE210
AC CHARACTERISTICS (V_{EE} = V_{EE} (min) to V_{EE} (max); V_{CC} = V_{CCO} = GND)

| Symbol | Characteristic | -40°C | | | 0°C | | | 25°C | | | 85°C | | | Unit | Condition |
|--------------------------------------|--|------------|----------|-----------------|------------|----------|-----------------|------------|----------|-----------------|------------|----------|-----------------|------|------------------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | | |
| t _{PLH} t _{PHL} | Propagation Delay to Output IN (differential) IN (single-ended) | 475 400 | | 675 700 | 475 400 | | 675 700 | 500 450 | | 700 750 | 500 450 | | 700 750 | ps | Note 1 Note 2 |
| t _{skew} | Within-Device Skew Q _a →Q _b Q _a →Q _a , Q _b →Q _b Part-to-Part Skew (Diff) | | 50 50 | 75 75 200 | | 50 30 | 75 50 200 | | 50 30 | 75 50 200 | | 50 30 | 75 50 200 | ps | Note 3 |
| V _{PP} | Minimum Input Swing | 500 | | | 500 | | | 500 | | | 500 | | | mV | Note 4 |
| V _{CMR} | Common Mode Range | -1.5 | | -0.4 | -1.5 | | -0.4 | -1.5 | | -0.4 | -1.5 | | -0.4 | V | Note 5 |
| t _r /t _f | Output Rise/Fall Time | 200 | | 600 | 200 | | 600 | 200 | | 600 | 200 | | 600 | ps | 20%–80% |

1. The differential propagation delay is defined as the delay from the crossing points of the differential input signals to the crossing point of the differential output signals. See *Definitions and Testing of ECLinPS AC Parameters* in Chapter 1 (page 1–12) of the Motorola High Performance ECL Data Book (DL140/D).
2. The single-ended propagation delay is defined as the delay from the 50% point of the input signal to the 50% point of the output signal. See *Definitions and Testing of ECLinPS AC Parameters* in Chapter 1 (page 1–12) of the Motorola High Performance ECL Data Book (DL140/D).
3. The within-device skew is defined as the worst case difference between any two similar delay paths within a single device.
4. V_{PP}(min) is defined as the minimum input differential voltage which will cause no increase in the propagation delay. The V_{PP}(min) is AC limited for the LVE210 as a differential input as low as 50 mV will still produce full ECL levels at the output.
5. V_{CMR} is defined as the range within which the V_{IH} level may vary, with the device still meeting the propagation delay specification. The V_{IL} level must be such that the peak to peak voltage is less than 1.0 V and greater than or equal to V_{PP}(min).

MC100LVE210 MC100E210

MC100E210

ECL DC CHARACTERISTICS

| Symbol | Characteristic | -40°C | | | 0°C | | | 25°C | | | 85°C | | | Unit |
|-----------------|--------------------------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|--------|------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| V _{OH} | Output HIGH Voltage | -1.085 | -1.005 | -0.880 | -1.025 | -0.955 | -0.880 | -1.025 | -0.955 | -0.880 | -1.025 | -0.955 | -0.880 | V |
| V _{OL} | Output LOW Voltage | -1.830 | -1.695 | -1.555 | -1.810 | -1.705 | -1.620 | -1.810 | -1.705 | -1.620 | -1.810 | -1.705 | -1.620 | V |
| V _{IH} | Input HIGH Voltage | -1.165 | | -0.880 | -1.165 | | -0.880 | -1.165 | | -0.880 | -1.165 | | -0.880 | V |
| V _{IL} | Input LOW Voltage | -1.810 | | -1.475 | -1.810 | | -1.475 | -1.810 | | -1.475 | -1.810 | | -1.475 | V |
| V _{BB} | Output Reference Voltage | -1.38 | | -1.26 | -1.38 | | -1.26 | -1.38 | | -1.26 | -1.38 | | -1.26 | V |
| V _{EE} | Power Supply Voltage | -5.25 | | -4.2 | -5.25 | | -4.2 | -5.25 | | -4.2 | -5.25 | | -4.2 | V |
| I _{IH} | Input HIGH Current | | | 150 | | | 150 | | | 150 | | | 150 | μA |
| I _{EE} | Power Supply Current | | | 55 | | | 55 | | | 55 | | | 65 | mA |

MC100E210

PECL DC CHARACTERISTICS

| Symbol | Characteristic | -40°C | | | 0°C | | | 25°C | | | 85°C | | | Unit |
|-----------------|---------------------------------------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| V _{OH} | Output HIGH Voltage ¹ | 3.915 | 3.995 | 4.12 | 3.975 | 4.045 | 4.12 | 3.975 | 4.045 | 4.12 | 3.975 | 4.045 | 4.12 | V |
| V _{OL} | Output LOW Voltage ¹ | 3.170 | 3.305 | 3.445 | 3.19 | 3.295 | 3.38 | 3.19 | 3.295 | 3.38 | 3.19 | 3.295 | 3.38 | V |
| V _{IH} | Input HIGH Voltage ¹ | 3.835 | | 4.12 | 3.835 | | 4.12 | 3.835 | | 4.12 | 3.835 | | 4.12 | V |
| V _{IL} | Input LOW Voltage ¹ | 3.190 | | 3.525 | 3.190 | | 3.525 | 3.190 | | 3.525 | 3.190 | | 3.525 | V |
| V _{BB} | Output Reference Voltage ¹ | 3.62 | | 3.74 | 3.62 | | 3.74 | 3.62 | | 3.74 | 3.62 | | 3.74 | V |
| V _{CC} | Power Supply Voltage | 4.75 | | 5.25 | 4.75 | | 5.25 | 4.75 | | 5.25 | 4.75 | | 5.25 | V |
| I _{IH} | Input HIGH Current | | | 150 | | | 150 | | | 150 | | | 150 | μA |
| I _{EE} | Power Supply Current | | | 55 | | | 55 | | | 55 | | | 65 | mA |

1. These values are for V_{CC} = 5.0V. Level Specifications will vary 1:1 with V_{CC}.

MC100E210


AC CHARACTERISTICS (V_{EE} = V_{EE} (min) to V_{EE} (max); V_{CC} = V_{CCO} = GND)

| Symbol | Characteristic | -40°C | | | 0°C | | | 25°C | | | 85°C | | | Unit | Condition |
|--------------------------------------|--|------------|----------|-----------------|------------|----------|-----------------|------------|----------|-----------------|------------|----------|-----------------|------|------------------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | | |
| t _{PLH} t _{PHL} | Propagation Delay to Output IN (differential) IN (single-ended) | 475 400 | | 675 700 | 475 400 | | 675 700 | 500 450 | | 700 750 | 500 450 | | 700 750 | ps | Note 1 Note 2 |
| t _{skew} | Within-Device Skew Q _a →Q _b Q _a →Q _a , Q _b →Q _b Part-to-Part Skew (Diff) | | 50 50 | 75 75 200 | | 50 30 | 75 50 200 | | 50 30 | 75 50 200 | | 50 30 | 75 50 200 | ps | Note 3 |
| V _{PP} | Minimum Input Swing | 500 | | | 500 | | | 500 | | | 500 | | | mV | Note 4 |
| V _{CMR} | Common Mode Range | -1.5 | | -0.4 | -1.5 | | -0.4 | -1.5 | | -0.4 | -1.5 | | -0.4 | V | Note 5 |
| t _r /t _f | Output Rise/Fall Time | 200 | | 600 | 200 | | 600 | 200 | | 600 | 200 | | 600 | ps | 20%–80% |

1. The differential propagation delay is defined as the delay from the crossing points of the differential input signals to the crossing point of the differential output signals. See *Definitions and Testing of ECLinPS AC Parameters* in Chapter 1 (page 1–12) of the Motorola High Performance ECL Data Book (DL140/D).
2. The single-ended propagation delay is defined as the delay from the 50% point of the input signal to the 50% point of the output signal. See *Definitions and Testing of ECLinPS AC Parameters* in Chapter 1 (page 1–12) of the Motorola High Performance ECL Data Book (DL140/D).
3. The within-device skew is defined as the worst case difference between any two similar delay paths within a single device.
4. V_{PP}(min) is defined as the minimum input differential voltage which will cause no increase in the propagation delay. The V_{PP}(min) is AC limited for the E210 as a differential input as low as 50 mV will still produce full ECL levels at the output.
5. V_{CMR} is defined as the range within which the V_{IH} level may vary, with the device still meeting the propagation delay specification. The V_{IL} level must be such that the peak to peak voltage is less than 1.0 V and greater than or equal to V_{PP}(min).

OUTLINE DIMENSIONS


FN SUFFIX
PLASTIC PLCC PACKAGE
CASE 776-02
ISSUE D



NOTES:

- DATUMS -L-, -M-, AND -N- DETERMINED WHERE TOP OF LEAD SHOULDER EXITS PLASTIC BODY AT MOLD PARTING LINE.
- DIM G1, TRUE POSITION TO BE MEASURED AT DATUM -T-, SEATING PLANE.
- DIM R AND U DO NOT INCLUDE MOLD FLASH. ALLOWABLE MOLD FLASH IS 0.010 (0.250) PER SIDE.
- DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
- CONTROLLING DIMENSION: INCH.
- THE PACKAGE TOP MAY BE SMALLER THAN THE PACKAGE BOTTOM BY UP TO 0.012 (0.300). DIMENSIONS R AND U ARE DETERMINED AT THE OUTERMOST EXTREMES OF THE PLASTIC BODY EXCLUSIVE OF MOLD FLASH, TIE BAR BURRS, GATE BURRS AND INTERLEAD FLASH, BUT INCLUDING ANY MISMATCH BETWEEN THE TOP AND BOTTOM OF THE PLASTIC BODY.
- DIMENSION H DOES NOT INCLUDE DAMBAR PROTRUSION OR INTRUSION. THE DAMBAR PROTRUSION(S) SHALL NOT CAUSE THE H DIMENSION TO BE GREATER THAN 0.037 (0.940). THE DAMBAR INTRUSION(S) SHALL NOT CAUSE THE H DIMENSION TO BE SMALLER THAN 0.025 (0.635).

| DIM | INCHES | | MILLIMETERS | |
|-----|-----------|-------|-------------|-------|
| | MIN | MAX | MIN | MAX |
| A | 0.485 | 0.495 | 12.32 | 12.57 |
| B | 0.485 | 0.495 | 12.32 | 12.57 |
| C | 0.165 | 0.180 | 4.20 | 4.57 |
| E | 0.090 | 0.110 | 2.29 | 2.79 |
| F | 0.013 | 0.019 | 0.33 | 0.48 |
| G | 0.050 BSC | | 1.27 BSC | |
| H | 0.026 | 0.032 | 0.66 | 0.81 |
| J | 0.020 | — | 0.51 | — |
| K | 0.025 | — | 0.64 | — |
| R | 0.450 | 0.456 | 11.43 | 11.58 |
| U | 0.450 | 0.456 | 11.43 | 11.58 |
| V | 0.042 | 0.048 | 1.07 | 1.21 |
| W | 0.042 | 0.048 | 1.07 | 1.21 |
| X | 0.042 | 0.056 | 1.07 | 1.42 |
| Y | — | 0.020 | — | 0.50 |
| Z | 2° | 10° | 2° | 10° |
| G1 | 0.410 | 0.430 | 10.42 | 10.92 |
| K1 | 0.040 | — | 1.02 | — |

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution;
P.O. Box 20912; Phoenix, Arizona 85036. 1-800-441-2447 or 602-303-5454

MFAX: RMFAX0@email.sps.mot.com – TOUCHTONE 602-244-6609
INTERNET: <http://Design-NET.com>

JAPAN: Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, 6F Seibu-Butsuryu-Center,
3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 03-81-3521-8315

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298



Copyright © Each Manufacturing Company.

All Datasheets cannot be modified without permission.

This datasheet has been download from :

www.AllDataSheet.com

100% Free DataSheet Search Site.

Free Download.

No Register.

Fast Search System.

www.AllDataSheet.com