



ELECTRONICS, INC.
44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089

NTE1128 Integrated Circuit TV Video IF Amplifier

Features:

- High Power Gain: 48dB Typ @ f = 58MHz
- AGC Operating by External DC Control Voltage
- High Gain Reduction: 60dB Min @ f = 58MHz
- Low Reverse Transfer Admittance: 1.0μmho Typ @ f = 58MHz
- Nearly Constant Input and Output Admittance Over Entire AGC Range

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Supply Voltage (V_5), V_{CC}	15V
Output Terminal Voltage, V_6 , V_7	18V
Gain Control Voltage, V_3	0V to V_{CC}
Input Terminal Voltage, V_1 , V_2	10V _{P-P}
Power Dissipation, P_D	400mW
Derate Above 25°C	4mW/°C
Operating Temperature Range, T_{opr}	-20° to +65°C
Storage Temperature Range, T_{stg}	-55° to +125°C

Electrical Characteristics: ($V_{CC} = 12\text{V}$, $f = 58\text{MHz}$, $T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Supply Voltage (V_5)	V_{CC}		10.8	12.0	13.2	V
Supply Current (I_5)	I_{CC}		9.0	11.0	15.0	mA
IF Input Terminal Voltage	V_1, V_2		-	3.3	-	V
AGC Terminal Voltage	V_3	-30dB AGC	-	7.5	7.8	V
		0dB AGC	6.2	6.6	-	V
Output Stage Current ($I_6 + I_7$)	I_{OUT}		1.4	2.0	3.0	mA
AGC Range	AGC	f = 58MHz	60	70	-	dB
Power Gain	G_P	f = 58MHz	4.5	4.8	-	dB
Noise Figure	NF	$R_S = 50\Omega$, f = 58MHz	-	6.0	-	dB
Maximum Output Voltage	V_{OM}	$V_6, V_7 = 15\text{V}$	150	-	-	mV _{P-P}
Total Power Dissipation	P_D		-	180	-	mW



Electrical Characteristics (Cont'd): ($V_{CC} = 12V$, $f = 58MHz$, $T_A = +25^\circ C$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Input Admittance Input Conductance	g_i	$f = 50MHz$	–	0.8	–	mmhos
Parallel Input Capacitance	C_{ip}		–	5.0	–	pF
Output Admittance Output Conductance	g_o	$f = 58MHz$	–	150	–	μ mhos
Parallel Output Capacitance	C_{op}		–	2	–	pF
Reverse Transfer Admittance	y_r	$f = 58MHz$	–	< 1.0	–	μ mhos
Forward Transfer Admittance	y_f	$f = 58MHz$	–	130	–	mmhos

Pin Connection Diagram
(Front View)

