


**PHASE NOISE (1 Hz BW, typical)**



FEATURES
<ul style="list-style-type: none"> <li>• Frequency Range: 1658 - 1718 MHz</li> <li>• Tuning Voltage: 1-4 Vdc</li> <li>• MINI-14MS - Style Package</li> </ul>
APPLICATIONS
<ul style="list-style-type: none"> <li>• Earthstations</li> <li>• Satellite Modems</li> <li>• Handheld Phones</li> </ul>

PERFORMANCE SPECIFICATIONS	VALUE	UNITS
Oscillation Frequency Range	1658 - 1718	MHz
Phase Noise @ 10 kHz offset (1 Hz BW, typ.)	-107	dBc/Hz
Harmonic Suppression (2nd, typ.)	-25	dBc
Tuning Voltage	1-4	Vdc
Tuning Sensitivity (avg.)	38	MHz/V
Power Output	0.25±3.25	dBm
Load Impedance	50	Ω
Input Capacitance (max.)	50	pF
Pushing	5	MHz/V
Pulling (14 dB Return Loss, Any Phase)	5	MHz
Operating Temperature Range	-40 to 85	°C
Package Style	MINI-14MS	
POWER SUPPLY REQUIREMENTS		
Supply Voltage (Vcc, nom.)	5	Vdc
Supply Current (Icc, typ.)	22	mA


All specifications are typical unless otherwise noted and subject to change without notice.

APPLICATION NOTES
<ul style="list-style-type: none"> <li>• AN-100/1 : Mounting and Grounding of VCOs</li> <li>• AN-102 : Proper Output Loading of VCOs</li> <li>• AN-107 : How to Solder Z-COMM VCOs</li> </ul>


**NOTES:**



**TUNING CURVE, typ.**






**POWER CURVE, typ.**



**PHYSICAL DIMENSIONS**

MINI-14MS  
415-0073 REV. A  
DRAWING NOT TO SCALE



**NOTES:**

1. THE INSIDE RADIUS OF ALL 14 HALF HOLES AT THE PERIMETER OF THE BOARD ARE SOLDER PLATED TO PROVIDE A SURFACE FOR THE ATTACHMENT OF THE VCO TO A MOTHERBOARD, IN 10 LOCATIONS, WITH 4 PADS BEING USED FOR ELECTROMECHANICAL INTERFACE. 14 SOLDER LOCATIONS REQUIRED.
2. THE SURFACE OF THE SHIELD IS TIN PLATED AND MAY BE SOLDERED TO.
3. THE SHIELD'S BASE METAL IS BRASS. THE SHIELD PLATE IS BRASS AND ATTACHES TO A GROUND PLANE ON THE UPPER SIDE OF THE BOARD AS WELL AS THE SHIELD BY PTH.
4. UNLESS OTHERWISE NOTED ALL DIMENSIONS ARE IN INCHES.
5. UNLESS OTHERWISE NOTED ALL TOLERANCES ARE AS FOLLOWS:

TOLERANCES  
.XXX = ± .010

P1=VT  
P2=RF OUT  
P3=Vcc  
P4=MID INPUT (OPTIONAL)

