

KR Electronics

General Description


KR 2865 is a 80 MHz bandpass filter. The filter has a typical 3 dB bandwidth of 13 MHz. Other passband frequencies are available. Please consult the factory.

Features


- 80 MHz Center Frequency
- High Stopband Attenuation
- SMA Connectors
- 50 Ω Source and Load

Typical Performance

Passband Amplitude & Group Delay (1 dB/div and 20 nsec/div)



Overall Response (10 dB/div)



KR Electronics, Inc.
91 Avenel Street
Avenel, NJ 07001

Web www.krfilters.com
Email sales@krfilters.com
Phone (732) 636-1900
Fax (732) 636-1982




KR Electronics 2865

Specifications

Parameter	Specification
Filter type	Bandpass
Center Frequency	80 MHz
Insertion Loss	< 3.5 dB (2.5 dB typical)
3 dB Bandwidth	12.5 MHz min
60 dB Bandwidth	41 MHz typical
Attenuation at 40 MHz	> 60 dB
Attenuation at 240 MHz	> 70 dB
Source and Load	50 Ω

Physical Dimensions



Dimensions in inches
Metal Case