

# KR Electronics

## General Description


KR 2834 is a 40 MHz differential notch filter. The filter is designed for a balanced source and load impedance of 100 Ω. Other passband frequencies are available. Please consult the factory.

## Features

- 40 MHz Notch Frequency
- DIP Package
- 100 Ω Differential Source and Load

## Typical Performance

Overall Response  
(10 dB/div)



KR Electronics, Inc.  
91 Avenel Street  
Avenel, NJ 07001

Web [www.krfilters.com](http://www.krfilters.com)  
Email [sales@krfilters.com](mailto:sales@krfilters.com)  
Phone (732) 636-1900  
Fax (732) 636-1982




# KR Electronics 2834

## Specifications

Parameter	Specification
Filter type	Notch
Notch Frequency	40 MHz
Attenuation at 30 MHz & 52 MHz	< 3 dB
Attenuation at 40 MHz	> 40 dB
Source and Load	100 Ω Differential

## Physical Dimensions



**NOTES:**

1. FILTER IS BI-DIRECTIONAL
2. ALL PINS ARE 0.030" DIA
3. DIMENSIONS ARE IN INCHES

- Pin 1—IN
- Pin 8—IN
- Pin 4—OUT
- Pin 5—OUT

Connect all remaining pins to GND (also connected to Case)