



ELC-10PR

High-density Signal Conditioners 10-RACK

PULSE SCALER

MODEL **10PR**

MODEL & SUFFIX CODE SELECTION

MODEL _____ 10PR-□□0-R
 INPUT _____
 1 : Dry contact (max. frequency 100 kHz)
 2 : Voltage pulse (max. frequency 100 kHz)
 OUTPUT _____
 1 : Open collector (max. frequency 20 kHz)
 2 : 5V pulse (max. frequency 20 kHz)
 3 : Relay contact (max. frequency 2 Hz)
 4 : 24V pulse (max. frequency 20 Hz)
 POWER INPUT _____
 R : 24V DC


ORDERING INFORMATION

Specify code number and variables.

- Code number (e.g. 10PR-110-R)
- Input frequency range (e.g. 0 – 356.7 Hz)
- Output frequency range (e.g. 0 – 1.00 Hz)

REMARKS

1. The 10PR's output waveform is not uniform due to its scaling method.
2. Use input relays which do not cause chattering (e.g. mercury relays). Other relays could be used only with a CR filter, for 10 Hz at maximum.



GENERAL SPECIFICATIONS

Construction: rack-mounted; terminal access via screw terminals at the front and via card-edge connector at the rear; terminal cover provided

Connection: M3.5 screw terminals (nickel-plated steel; torque ≤ 0.8 N·m) and card-edge connector

Housing material: flame-resistant resin (black)

Power input: supplied from card-edge connector


Power fuse: 0.5A

Isolation: input to output to power

Input pulse sensing: capacitor coupled; detecting pulse rise

Sensitivity adjustment: single-turn screwdriver adjustment (front); 25mV p-p – 5V p-p

Scaling factor: 0.9999×10^0 – 0.0001×10^{-6}



Functions & Features

- Converting pulse rate into convenient engineering unit for display on a totalizing counter or meter
- Fuse

Typical Applications

- Positive displacement flowmeters and turbine flowmeters
- Magnetic tachometers

INPUT & OUTPUT

INPUT

Maximum frequency: 100 kHz

Pulse width time requirement: 5 µsec. min. (20 msec. min. for frequencies ≤ 10 Hz)

- Dry Contact: mechanical contact or open collector

Sensing: approx. 7.5V DC @1mA

ON/OFF level: $\leq 20k\Omega$ for ON, $\geq 100k\Omega$ for OFF

- Voltage Pulse: square or sine waveforms**

Input amplitude: 25mV p-p – 50V p-p

Minimum amplitude requirement

With duty ratio 50% $\pm 10\%$

FREQUENCY	AMPLITUDE
0 – 2 kHz	25mV p-p
0 – 20 kHz	50mV p-p
0 – 40 kHz	1V p-p
0 – 100 kHz	5V p-p

With duty ratio other than 50% $\pm 10\%$

PULSE WIDTH	AMPLITUDE
5 µsec.	5V p-p
10 µsec.	3.5V p-p
50 µsec.	2V p-p
100 µsec.	1V p-p
500 µsec.	0.5V p-p

Specifications subject to change without notice

