

Bipolar Power Transistors**Darlington Power Transistors (Continued)**

Type No.	I _C A	V _{CEO} V	h _{FE}		PT W	JEDEC Package	
			I _C A	V _{CE} V			
D45E FAMILY (p-n-p)			Complementary to D44E Family				
D45E1	-10	-40	1000 min.	-5	-5	50	TO-220AB
D45E2	-10	-60	1000 min.	-5	-5	50	
D45E3	-10	-80	1000 min.	-5	-5	50	
D64DV FAMILY (n-p-n)							
D64DV5	50	400	50 min.	50	5	180	TO-204AE/ TO-3
D64DV6	50	450	50 min.	50	5	180	
D64DV7	50	500	50 min.	50	5	180	
D64EV FAMILY (n-p-n)			Devices have Integral Base Speed-up Diode				
D64EV5	50	400	50 min.	50	5	180	TO-204AE/ TO-3
D64EV6	50	450	50 min.	50	5	180	
D64EV7	50	500	50 min.	50	5	180	
D72 FAMILY (n-p-n)							
D72Y1.5D1, 2	1.5	30	4000 min.	0.15	2	10	TO-251/2
The Following are Complementary to the D73 Family Types:							
D72K3D1, 2	3	40	1000 min.	3	2	15	TO-251/2
D72FY4D1, 2	4	80	1000 min.	3	2	15	
D73 FAMILY (p-n-p)			Complementary to D72 Family				
D73K3D1, 2	-3	-40	1000 min.	-3	-2	15	TO-251/2
D73FY4D1, 2	-4	-80	1000 min.	-3	-2	15	