

*National Semiconductor*

May 1999

LM193/LM293/LM393/LM2903 Low Power Low Offset Voltage Dual Comparators

General Description

The LM193 series consists of two independent precision voltage comparators with an offset voltage specification as low as 2.0 mV max for two comparators which were designed specifically to operate from a single power supply over a wide range of voltages. Operation from split power supplies is also possible and the low power supply current drain is independent of the magnitude of the power supply voltage. These comparators also have a unique characteristic in that the input common-mode voltage range includes ground, even though operated from a single power supply voltage.

Application areas include limit comparators, simple analog to digital converters; pulse, squarewave and time delay generators; wide range VCO; MOS clock timers; multivibrators and high voltage digital logic gates. The LM193 series was designed to directly interface with TTL and CMOS. When operated from both plus and minus power supplies, the LM193 series will directly interface with MOS logic where their low power drain is a distinct advantage over standard comparators.

Advantages


- High precision comparators

- Reduced V_{OS} drift over temperature
- Eliminates need for dual supplies
- Allows sensing near ground
- Compatible with all forms of logic
- Power drain suitable for battery operation

Features

- Wide supply
 - Voltage range: 2.0V to 36V
 - single or dual supplies: $\pm 1.0V$ to $\pm 18V$
- Very low supply current drain (0.4 mA) — independent of supply voltage
- Low input biasing current: 25 nA
- Low input offset current: ± 5 nA
- Maximum offset voltage: ± 3 mV
- Input common-mode voltage range includes ground
- Differential input voltage range equal to the power supply voltage
- Low output saturation voltage: 250 mV at 4 mA
- Output voltage compatible with TTL, DTL, ECL, MOS and CMOS logic systems

Schematic and Connection Diagrams




DS005709-2

LM193/LM293/LM393/LM2903 Low Power Low Offset Voltage Dual Comparators


Schematic and Connection Diagrams (Continued)

Metal Can Package



TOP VIEW

Dual-In-Line Package



TOP VIEW

DS005709-1

Order Number LM193H,
LH193H/883 (Note 1), LM193AH-QMLV(Note 2)
M193AH, LM193AH/883,
LM293H, LM293AH, LM393H
or LM393AH
See NS Package Number H08C

Order Number LM193J/883 (Note 1),
LM193AJ/883, LM193AJ-QMLV(Note 2)
LM393J, LM393AJ,
LM393M, LM2903M, LM393N,
LM2903J or LM2903N
See NS Package Number J08A,
M08A or N08E

Note 1: Also available per JM38510/11202


Note 2: See STD Mil DWG 5962-94526

Electrical Characteristics (Continued)


- Note 7:** The direction of the input current is out of the IC due to the PNP input stage. This current is essentially constant, independent of the state of the output so no loading change exists on the reference or input lines.
- Note 8:** The input common-mode voltage or either input signal voltage should not be allowed to go negative by more than 0.3V. The upper end of the common-mode voltage range is $V^+ - 1.5V$ at $25^\circ C$, but either or both inputs can go to 36V without damage, independent of the magnitude of V^+ .
- Note 9:** The response time specified is for a 100 mV input step with 5 mV overdrive. For larger overdrive signals 300 ns can be obtained, see typical performance characteristics section.
- Note 10:** Positive excursions of input voltage may exceed the power supply level. As long as the other voltage remains within the common-mode range, the comparator will provide a proper output state. The low input voltage state must not be less than $-0.3V$ (or $0.3V$ below the magnitude of the negative power supply, if used).
- Note 11:** At output switch point, $V_O \approx 1.4V$, $R_S = 0\Omega$ with V^+ from 5V to 30V; and over the full input common-mode range ($0V$ to $V^+ - 1.5V$), at $25^\circ C$.
- Note 12:** Refer to RETS193AX for LM193AH military specifications and to RETS193X for LM193H military specifications.

Typical Performance Characteristics LM193/LM293/LM393, LM193A/LM293A/LM393A


Supply Current




Input Current




Output Saturation Voltage



Response Time for Various Input Overdrives — Negative Transition




Response Time for Various Input Overdrives — Positive Transition




Typical Performance Characteristics LM2903


Supply Current



Input Current




Output Saturation Voltage




Typical Performance Characteristics LM2903 (Continued)

Response Time for Various Input Overdrives — Negative Transition



Response Time for Various Input Overdrives — Positive Transition



Application Hints

The LM193 series are high gain, wide bandwidth devices which, like most comparators, can easily oscillate if the output lead is inadvertently allowed to capacitively couple to the inputs via stray capacitance. This shows up only during the output voltage transition intervals as the comparator change states. Power supply bypassing is not required to solve this problem. Standard PC board layout is helpful as it reduces stray input-output coupling. Reducing the input resistors to $< 10 \text{ k}\Omega$ reduces the feedback signal levels and finally, adding even a small amount (1.0 to 10 mV) of positive feedback (hysteresis) causes such a rapid transition that oscillations due to stray feedback are not possible. Simply socketing the IC and attaching resistors to the pins will cause input-output oscillations during the small transition intervals unless hysteresis is used. If the input signal is a pulse waveform, with relatively fast rise and fall times, hysteresis is not required.

All pins of any unused comparators should be grounded.

The bias network of the LM193 series establishes a drain current which is independent of the magnitude of the power supply voltage over the range of from $2.0 \text{ V}_{\text{DC}}$ to 30 V_{DC} . It is usually unnecessary to use a bypass capacitor across the power supply line.


The differential input voltage may be larger than V^+ without damaging the device (Note 10). Protection should be pro-

vided to prevent the input voltages from going negative more than $-0.3 \text{ V}_{\text{DC}}$ (at 25°C). An input clamp diode can be used as shown in the applications section.


The output of the LM193 series is the uncommitted collector of a grounded-emitter NPN output transistor. Many collectors can be tied together to provide an output OR'ing function. An output pull-up resistor can be connected to any available power supply voltage within the permitted supply voltage range and there is no restriction on this voltage due to the magnitude of the voltage which is applied to the V^+ terminal of the LM193 package. The output can also be used as a simple SPST switch to ground (when a pull-up resistor is not used). The amount of current which the output device can sink is limited by the drive available (which is independent of V^+) and the β of this device. When the maximum current limit is reached (approximately 16 mA), the output transistor will come out of saturation and the output voltage will rise very rapidly. The output saturation voltage is limited by the approximately $60\Omega r_{\text{SAT}}$ of the output transistor. The low offset voltage of the output transistor (1.0 mV) allows the output to clamp essentially to ground level for small load currents.

Typical Applications ($V^+=5.0 \text{ V}_{\text{DC}}$)


Basic Comparator



Driving CMOS




Driving TTL




Typical Applications ($V^+=5.0$ V_{DC}) (Continued)

Squarewave Oscillator




DS005709-38

Pulse Generator



DS005709-39


Crystal Controlled Oscillator



DS005709-40

* For large ratios of R1/R2,
D1 can be omitted.


Two-Decade High Frequency VCO



DS005709-41


$V^+=+30$ V_{DC}
 $+250 \text{ mV}_{\text{DC}} \leq V_C \leq +50$ V_{DC}
700 Hz $\leq f_0 \leq 100$ kHz

Basic Comparator



DS005709-6


Non-Inverting Comparator with Hysteresis



DS005709-9


Typical Applications ($V^+ = 5.0$ V_{DC}) (Continued)

Inverting Comparator with Hysteresis



DS005709-10


Output Strobing



* OR LOGIC GATE
WITHOUT PULL-UP RESISTOR




DS005709-11

AND Gate




DS005709-12

Typical Applications ($V^+ = 5.0$ V_{DC}) (Continued)




Typical Applications ($V^+ = 5.0$ V_{DC}) (Continued)

**Comparing Input Voltages
of Opposite Polarity**




DS005709-16

ORing the Outputs




DS005709-17

Zero Crossing Detector (Single Power Supply)




DS005709-21

One-Shot Multivibrator




DS005709-22

Bi-Stable Multivibrator



DS005709-24


One-Shot Multivibrator with Input Lock Out



DS005709-23

Typical Applications ($V^+ = 5.0 \text{ V}_{\text{DC}}$) (Continued)


Time Delay Generator



DS005709-7


Split-Supply Applications ($V^+ = +15 \text{ V}_{\text{DC}}$ and $V^- = -15 \text{ V}_{\text{DC}}$)

MOS Clock Driver




DS005709-42

Zero Crossing Detector




DS005709-43

Comparator With a Negative Reference




DS005709-44

Physical Dimensions inches (millimeters) unless otherwise noted





Metal Can Package (H)

Order Number LM193H, LM193H/883, LM193AH, LM193AH/883, LM293H, LM293AH, LM393H or LM393AH
NS Package Number H08C




Order Number LM193J/883, LM193AJ/883 or LM2903J
NS Package Number J08A

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



Order Number LM393M or LM2903M
NS Package Number M08A



Molded Dual-In-Line Package (N)
Order Numbers LM393N or LM2903N
NS Package N08E

Notes

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.



**National Semiconductor
Corporation**
Americas
Tel: 1-800-272-9959
Fax: 1-800-737-7018
Email: support@nsc.com

www.national.com

**National Semiconductor
Europe**
Fax: +49 (0) 1 80-530 85 86
Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 1 80-530 85 85
English Tel: +49 (0) 1 80-532 78 32
Français Tel: +49 (0) 1 80-532 93 58
Italiano Tel: +49 (0) 1 80-534 16 80

**National Semiconductor
Asia Pacific Customer
Response Group**
Tel: 65-2544466
Fax: 65-2504466
Email: sea.support@nsc.com

**National Semiconductor
Japan Ltd.**
Tel: 81-3-5639-7560
Fax: 81-3-5639-7507