

Tone ringer IC for telephone set

BA8206 / BA8206F

The BA8206 and BA8206F are tone ringer ICs which produce a bell sound from a ringing signal. The frequency of the bell sound can be varied by changing the constants of the external resistance and capacitors.

The operation initiation current dissipation can be changed at the RSL pin.

Also, the output load can be selected, as a piezoelectric buzzer, a transformer coupled speaker, or other similar devices.


● Applications

Telephones, multi-function telephones, telephone answering machines, facsimiles, equipment involving telephones

● Features

- 1) Low current dissipation.
- 2) Withstands up to 40V.
- 3) Operation initiation current dissipation can be changed using RSL pin.
- 4) Pin layout is compatible with the BA8205, BA6565A, and ML8205.

● Block diagram



● Absolute maximum ratings (Ta = 25°C)

| Parameter | Symbol | Limits | Unit |
|-----------------------------|------------------|----------|------|
| Power supply voltage | V _{CC} | 40 | V |
| Power dissipation BA8206 | P _d | 500 *1 | mW |
| BA8206F | P _d | 450 *2 | |
| Operating temperature | T _{OPR} | -25~+75 | °C |
| Storage temperature | T _{STG} | -55~+125 | °C |

*1 Reduced by 5mW for each increase in Ta of 1°C over 25°C.

*2 Reduced by 4.5mW for each increase in Ta of 1°C over 25°C.

● Recommended operating conditions (Ta = 25°C)

| Parameter | Symbol | Min. | Typ. | Max. | Unit |
|----------------------|------------------|------|------|------|------|
| Power supply voltage | V _{OVR} | — | — | 38 | V |

● Electrical characteristics (unless otherwise noted, Ta = 25°C, V_{CC} = 24V)

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Conditions | Measurement circuit |
|---|------------------|------|------|------|------------------|---|---------------------|
| Initial supply voltage | V _{SI} | 14 | 16 | 18 | V | *1 | Fig.1 |
| Sustained operation supply voltage | V _{SUS} | 8.2 | 9.8 | 11.2 | V | *2 | Fig.1 |
| Initial current dissipation | I _{SI} | 0.9 | 1.3 | 1.7 | mA | No load, V _{CC} = V _{SI} | Fig.1 |
| Sustained operation current dissipation | I _{SUS} | 0.22 | 0.4 | 0.7 | mA | No load, V _{CC} = V _{SUS} | Fig.1 |
| Oscillation frequency *3 | f _L | 9 | 10 | 11 | Hz | R ₁ =773kΩ, C ₁ =0.1μF | Fig.2 |
| Oscillation frequency *3 | f _{H1} | 461 | 512 | 563 | Hz | R ₂ =595kΩ, C ₂ =0.0022μF | Fig.2 |
| Oscillation frequency *3 | f _{H2} | 576 | 640 | 703 | Hz | R ₂ =595kΩ, C ₂ =0.0022μF | Fig.2 |
| Output high level voltage | V _{OH} | 19.7 | 22.0 | 23.5 | V | I _{OH} =10mA, pin7=GND | Fig.1 |
| Output low level voltage | V _{OL} | 0.5 | 0.9 | 1.4 | V | I _{OL} =10mA, pin7=6V | Fig.1 |
| Ringer threshold voltage | V _{TR} | — | — | 36.0 | V _{rms} | R _{SL} =9.1kΩ | Fig.3 |
| Output leakage current | I _{LE} | — | — | 1.0 | μA | | Fig.3 |

*1 The initial supply voltage is the power supply voltage required for the tone ringer to begin oscillating.

*2 The sustained operation voltage is the power supply voltage required for the tone ringer to continue oscillating.

*3 The oscillation frequency is determined using the following equation.

$$f_L = \frac{1}{1.234 \times R_1 \times C_1} \text{ (Hz)}$$

$$f_{H1} = \frac{1}{1.515 \times R_2 \times C_2} \text{ (Hz)}$$

$$f_{H2} = 1.24 \times f_{H1} \text{ (Hz)}$$


The recommended values for R₁ and R₂ are 300 kΩ or higher.

The ringer threshold voltage is the AC voltage required for the tone ringer to start ringing through the circuit shown in Fig. 6

● Pin descriptions

| Pin No. | Pin name | Name | Function |
|---------|----------|--|---|
| 1 | Vcc | Power supply pin | This is the power supply pin for the IC. It is connected to the (+) pin of the diode bridge. |
| 2 | RSL | RSL pin | This is used to change the operation initiation current when connected to the GND pin. |
| 3 | LFI | Low-frequency time constant connector pin | This is connected to the time constant that determines the oscillation frequency on the warble. |
| 4 | LFO | | |
| 5 | GND | GND pin | This pin has the lowest potential on the IC. It is connected to the (-) pin of the diode bridge. |
| 6 | HFO | High-frequency time constant connector pin | This is connected to the time constant that determines the oscillation frequency on the tone side (the audible frequency side). |
| 7 | HFI | | |
| 8 | OUT | Output pin | This is used to connect a piezoelectric buzzer, or to connect a dynamic speaker through a transformer. |

● Measurement circuit




$$R_1 = 773\text{k}\Omega, \quad C_1 = 0.1\mu\text{F}$$

$$R_2 = 595\text{k}\Omega, \quad C_2 = 0.0022\mu\text{F}$$

(Note) The table below shows the statuses for SW₁ and SW₂.

| Item | SW ₁ | SW ₂ |
|------------------------------------|-----------------|-----------------|
| V _{si} , V _{sus} | 1 | 1 |
| I _{si} , I _{sus} | 1 | 1 |
| V _{OH} | 2 | 2 |
| V _{OL} | 2 | 3 |

Fig. 1



$R_1=773\text{k}\Omega$, $C_1=0.1\ \mu\text{F}$

$R_2=595\text{k}\Omega$, $C_2=0.0022\ \mu\text{F}$

(Note) The table below shows the statuses for SW₁ and SW₂.

| Item | SW ₁ | SW ₂ |
|----------|-----------------|-----------------|
| f_L | 1 | 1 |
| f_{H1} | 3 | 2 |
| f_{H2} | 2 | 2 |

Fig. 2




Fig. 3

● Circuit operation

Using the RSL pin

With the BA8206 and BA8206F, the RSL pin can be used to change the initial supply current (I_{sl}).

As shown in Figure 4, resistor R_{SL} is connected from the R_{SL} pin (Pin 2) to the GND. The operation initiation current consumption can be changed by changing the value of the resistor R_{SL} .

Figure 5 shows the supply voltage (V_{cc}) - supply current (I_{cc}) characteristics when the value of the resistor R_{SL} is changed.




Fig. 4




Fig. 5

● Application example




Fig. 6

● Electrical characteristic curves




Fig. 7 Current dissipation vs. power supply voltage




Fig. 8 Output voltage vs. power supply voltage (transistor on source side)





Fig. 9 Output voltage vs. power supply voltage (transistor on sink side)


● External dimensions (Units: mm)

BA8206



DIP8

BA8206F



SOP8