

# FAN7554

## Versatile PWM Controller

### Features


- Current Mode Control
- Pulse by Pulse Current Limiting
- Low External Components
- Under Voltage Lockout(UVLO): 9V/15V
- Stand-by Current: Typ. 100uA
- Power Saving Mode Current: Typ. 200uA
- Operating Current: Typ. 7mA
- Soft Start
- On/Off Control
- Over Load Protection(OLP)
- Over Voltage Protection(OVP)
- Over Current Protection(OCP)
- Over Current Limit(OCL)
- Operating Frequency up to 500kHz
- 1A Totem-Pole Output Current

### Applications


- Off-Line & DC-DC Converter

### Description

The FAN7554 is a fixed frequency current mode PWM controller. It is specially designed for off-line and DC to DC converter applications with minimal external components. These integrated circuits feature a trimmed oscillator for precise duty cycle control, a temperature compensated reference, an ON/OFF control, a high gain error amplifier, a current sensing comparator, and a high current totem-pole output. The FAN7554 has various protection functions such as an over load protection, an over current protection, and the over voltage protection, which include built-in auto restart circuit. The FAN7554 is available in the 8-DIP package as well as the 8-SOP package.



## Internal Block Diagram



## Absolute Maximum Ratings

(  $T_a = 25^\circ\text{C}$ , unless otherwise specified )

Parameter	Symbol	Value	Unit
Supply Voltage	$V_{cc}$	30	V
Output Current	$I_O$	$\pm 1$	A
Input Voltage to FB Pin	$V_{FB}$	-0.3 to $V_{SD}$	V
Input Voltage to IS Pin	$V_{IS}$	-0.3 to $V_{OC}$	V
Power Dissipation at $T_A \leq 25^\circ\text{C}$			
8-DIP	PD	0.85	W
8-SOP		0.42	
Operating Temperature	$T_{OPR}$	-25 to +85	$^\circ\text{C}$
Storage Temperature	$T_{STG}$	-55 to +150	$^\circ\text{C}$
Thermal Resistance, Junction-to-Air (Note1)			
8-DIP	$R\theta_{ja}$	147.8	$^\circ\text{C}/\text{W}$
8-SOP		291.4	

### Note:


- Junction -to -air thermal resistance test environments.
  - Pneumatic heat sink fixture.
  - Clamping pressure 60psi through 12mm diameter cylinder.
  - Thermal grease applied between PKG and heat sink fixture

## Temperature Characteristics

(  $-25^{\circ}\text{C} \leq T_a \leq 85^{\circ}\text{C}$  )

Parameter	Symbol	Value	Unit
Vref Temperature Stability	$\Delta V_{REF3}$	$\pm 0.5$	%
Fosc Temperature Stability	$\Delta F_{OSC2}$	$\pm 5$	%

## PIN Array



## PIN Definitions

Pin Number	Pin Name	Pin Function Description
1	FB	Inverting(-) Input of PWM Comparator, ON/OFF Control & OLP Sensing Terminal.
2	S/S	Soft Start
3	IS	Non-Inverting(+) Input of PWM Comparator, OCL Sensing Terminal
4	Rt/Ct	Oscillator Time Constant(Rt/Ct)
5	GND	Ground
6	OUT	Output of Gate Driver
7	Vcc	Power Supply
8	Vref	Output of 5V Reference

## Electrical Characteristics

(Ta = 25°C, Vcc=16V, Rt=10kΩ, Ct=3.3nF unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
<b>&lt; REFERENCE SECTION &gt;</b>						
Reference Output Voltage	VREF	Tj = 25°C , Iref = 1mA	4.90	5.00	5.10	V
Line Regulation	ΔVREF1	Vcc = 12V ~ 25V	-	6	20	mV
Load Regulation	ΔVREF2	Iref = 1mA ~ 20mA	-	6	25	mV
Short Circuit Output Current	ISC	Tj = 25°C	-	0.1	0.18	A
<b>&lt; OSCILLATOR SECTION &gt;</b>						
Oscillation Frequency	FOSC	Tj = 25°C	45	50	55	kHz
Frequency Change with Vcc	ΔFOSC1	Vcc = 12V ~ 25V	-	0.05	1.0	%
Ramp High Voltage	VRH	-	-	2.8	-	V
Ramp Low Voltage	VRL	-	-	1.2	-	V
Discharge Current	Idisch	VRT/CT = 3.3V	6.1	-	9.4	mA
<b>&lt; PWM SECTION &gt;</b>						
Sense Threshold Voltage	VTH(IS)	VFB = 5V	0.8	1.0	1.2	V
Feedback Threshold Voltage	VTH(FB)	VIS = 0V	0.2	0.3	0.4	V
Feedback Source Current	IFB	VFB = 0V, VS/S = 5V	-	1.0	-	mA
Max. Duty Cycle	D(MAX)	-	92	95	98	%
Min. Duty Cycle	D(MIN)	-	-	-	0	%
<b>&lt; PROTECTION SECTION &gt;</b>						
Shutdown Delay Current	ISD	4V ≤ VFB ≤ VSD	3.5	5	6.5	uA
Shutdown Feedback Voltage	VSD	VFB > 5V	5.4	6	6.6	V
Over Current Protection	VOC	VIS > 1.5V, ton > 500nS	1.6	2	2.4	V
Over Voltage Protection	VOVP	-	30	34	38	V
<b>&lt; ON/OFF CONTROL SECTION &gt;</b>						
Off Mode Sink Current	ISINK	VFB < VTH(FB), VS/S = 5V	-	4	-	mA
Off Threshold Voltage	VOFF	VFB < VTH(FB)	1.2	1.5	1.8	V
<b>&lt; SOFT-START SECTION &gt;</b>						
Soft Start Current	IS/S	VFB = 5V, VS/S = 0V	-	1.1	-	mA
Soft Start Limit Voltage	VLIM(S/S)	Vcc = 16V	-	5.2	-	V
<b>&lt; OUTPUT SECTION &gt;</b>						
Low Output Voltage1	VOL1	VCC = 18V, IO = 50mA	-	0.15	0.4	V
High Output Voltage1	VOH1	VCC = 18V, IO = -50mA	13	15	17	V
Low Output Voltage2	VOL2	VCC = 18V, IO = 200mA	-	1.5	2.5	V
High Output Voltage2	VOH2	Vcc = 18V, IO = -200mA	12	14	16	V
Rising Time (Note1)	tR	Tj = 25°C, CL = 1nF	-	80	-	ns
Falling Time (Note1)	tF	Tj = 25°C, CL = 1nF	-	40	-	ns
<b>&lt; UVLO SECTION &gt;</b>						
Start Threshold Voltage	VTH(ST)	-	13.2	15	16.2	V
Min. Operating Voltage	VOPR(M)	-	8.2	9	10.2	V

**Electrical Characteristics** (Continued)

(Ta = 25°C, Vcc=16V, Rt =10kΩ, Ct = 3.3nF unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
<b>&lt;TOTAL STAND-BY CURRENT SECTION&gt;</b>						
Start-up Current	I <sub>ST</sub>	-	-	0.1	0.2	mA
Operating Supply Current	I <sub>OP</sub>	-	-	7	10	mA
Off State Current	I <sub>OFF</sub>	V <sub>FB</sub> <V <sub>TH</sub> (FB), V <sub>S/S</sub> <V <sub>OFF</sub>	-	0.2	0.4	mA

**Note:**

1. These parameters, although guaranteed, are not 100% tested in production.

## Typical Performance Characteristics




Figure 1. Rt vs. Frequency




Figure 2. Ct vs. Dead Time




Figure 3. Ct vs. Duty




Figure 4. Cloud vs. Tr & Tf

Typical Performance Characteristics(Continued)




Figure 5. Temperature vs. Start-up Current




Figure 6. Temperature vs. Operating Supply Current




Figure 7. Temperature vs. Reference Voltage




Figure 8. Temperature vs. Oscillation frequency




Figure 9. Temperature vs. Start Threshold Voltage




Figure 10. Temperature vs. Min. Operating Voltage

## Operation Description

The FAN7554 has all the basic features of the current mode SMPS control IC. Its basic configuration includes the UVLO with 6V hysteresis, a band gap reference, the oscillator that can oscillate up to 500kHz according to  $R_t/C_t$  (connected externally), a PWM logic circuit, a gate driver, and the feedback circuit that has the current source and soft start function. The FAN7554 has various functions such as an over load protection, an over current protection, and an over voltage protection. The over load protection forces the FAN7554 to stop its operation if the load current is higher than the preset value. The protection circuit can also be prevented from operating during transient states by ensuring that a certain amount of the time passes before the protection circuit operates. The shutdown circuit is configured for an auto-restart, so the FAN7554 automatically restarts when  $V_{cc}$  drops to 9V (stop voltage).

### Start-Up

The start-up circuit is made up of an under voltage lock out (UVLO), the protection for low voltage conditions, and the 5V reference ( $V_{ref}$ ), which supplies bias voltage to the control circuit after start-up. The start voltage of the UVLO is 15V, and the stop voltage after turn on is 9V. It has a 6V hysteresis. The minimum operating current for start-up threshold is typically 100uA, and this can reduce the power dissipation on the start-up resistor. The  $V_{ref}$  is composed of the band gap reference circuit with its superior temperature characteristics and supplies power to all the FAN7554 circuits and  $R_t/C_t$ , with the exceptions of the ULVO circuit and ON/OFF control circuit.




Figure 11. Low Current Start-Up & Bandgap Reference Circuit




Figure 12. Start-Up & Circuit Characteristics

### Soft Start

The SMPS output load usually contains a capacitive load component. During initial start-up, the output voltage increases at a fixed time constant because of this component. If the feedback loop, which controls the output voltage, was to start without the soft start circuit, the feedback loop would appear to be open during initial start-up, so, at start-up, the feedback voltage applied to the PWM comparator's inverting input (-) reaches its maximum value(1V).

During this time, the peak value of the drain current would stay at the maximum value, and the maximum power would be delivered to the secondary load side from the start. When the maximum power is delivered to the secondary side for this initial fixed time, the entire circuit is seriously stressed. The use of a soft start can avoid such stresses. At start-up, the soft start capacitor  $C_s$  is charged by 1mA and 100uA current sources.

The voltage of the inverting terminal of the PWM comparator increases to 1/3 of the  $C_s$  voltage at a fixed time constant. Subsequently, the drain peak current is limited by the gradual increase in the  $C_s$  voltage and this causes the output voltage to increase smoothly. When the  $C_s$  voltage becomes greater than 3V, the diode  $D_s$  turns off consequently, the feedback capacitor  $C_{fb}$  is charged by 1mA and 5uA current sources. This charge voltage determines the comparator's inverting voltage. Then,  $C_s$  voltage charges to 5V by 100uA current source. The soft start capacitor  $C_s$  is discharged when the UVLO good logic starts, so the soft start is repeated at re-start.






Figure 13. Soft Start Circuit & Circuit Flow

### Oscillator

As shown in figure14, the oscillator frequency is programmed by values selected for timing components  $R_t$  and  $C_t$ . Capacitor  $C_t$  is charged to almost 2.8V through resistor  $R_t$  from the 5V reference and discharged to 1.2V by an internal current source. The oscillator generates the clock signal while the timing capacitor  $C_t$  is discharged. The gate drive output becomes low during the clock time.  $R_t$  and  $C_t$  selection determine the oscillator frequency and maximum duty cycle. Charge and discharge times can be calculated through the equations below.

$$\text{Charging time : } t_c = 0.55 \times R_t \times C_t$$

$$\text{Discharging time : } t_d = R_t \times C_t \times \ln[(0.0063 \times R_t - 2.8) / (0.0063 \times R_t - 3.8)]$$

$$\text{where the oscillator frequency : } f_{osc} = (t_c + t_d)^{-1} (\pm 10\%)$$

$$\text{When } R_t > 5k\Omega, f_{osc} = 1 / (0.55 \times R_t \times C_t) = 1.8 / (R_t \times C_t)$$




Figure 14. Oscillator Circuit




Figure 15. Sawtooth & Clock Waveform






Figure 17-B . Delayed Shutdown &amp; Feedback Waveform

### Gate Driver

The gate drive circuit has the totem-pole output configuration. The output has 1A peak current and 200mA average current drive ability.




Figure 18. Gate Drive Circuit

### ON/OFF Control

The FAN7554 is able to use the feedback pin for ON/OFF control by placing NPN transistor between the cathode of the KA431 and ground as shown in figure 19. When the transistor turns on, the current flows through the photo diode and saturates the photo transistor. As a result, the feedback voltage is dropped to zero. When the feedback voltage is below 0.3V, the soft start voltage starts to discharge by connecting the internal resistor  $1k\Omega$  in parallel with the external capacitor  $C_s$ . When the soft start voltage becomes less than 1.5V, all the blocks in the FAN7554 are turned off, with the exceptions of the UVLO block and ON/OFF control block. The operation current is about 200uA. So the stand-by power is reduced and SMPS efficiency is improved. When the feedback voltage exceeds 0.3V, the FAN7554 normally operates by turning on  $V_{ref}$  block.




Figure 19. ON/OFF Control Circuit





Figure 20. ON-OFF Control Circuit Waveforms



# FAN7554 Flyback Converter Demo Circuit (Fsw:100kHz)





## Part List For FAN7554 Flyback Converter Demo Board

Part	Value	Note	Part	Value	Note
<b>FUSE</b>			<b>CAPACITOR</b>		
FUSE	250 2A	-	C101	100nF/ 275V	Box Capacitor
<b>NTC</b>			C102	100nF/ 275V	Box Capacitor
NTC	5D-11	-	C103	470nF/ 400WV	Electrolytic
<b>RESISTOR</b>			C104	103/ 1kV	Film Capacitor
R101	330k $\Omega$	1W	C105	104	Ceramic
R102	-	-	C106	1uF/ 10V	Electrolytic
R103, R104	100k $\Omega$	1W	C107	101	Ceramic
R105	22 $\Omega$	-	C108	122	Ceramic
R106	4.7k $\Omega$	-	C109	22uF/ 50V	Electrolytic
R107	12k $\Omega$	-	C201	330uF	Electrolytic
R108	10 $\Omega$	-	C202	330uF	Electrolytic
R109	1k $\Omega$	-	C203	104	Ceramic
R110	0.5 $\Omega$	2W	C301	-	-
R201	1k $\Omega$	-	C302	-	-
R202	1k $\Omega$	-			
R203	4.7k $\Omega$	-	<b>INDUCTOR</b>		
R204	1.2k $\Omega$	-	LF101	30mH	-
R205	-	-	L201	6.4uH	-
<b>MOSFET</b>			<b>DIODE</b>		
Q101	FQP6N70	Fairchild	D201	MBRF10100CT	-
<b>IC</b>			D101	UF4007	Fairchild
IC101	FAN7554	Fairchild	D102	1N4148	-
IC201	KA431	Fairchild	D103	UF4004	Fairchild
IC301	Opto-coupler	Fairchild	BD	G3SBA60	-

## Transformer Specification

Schematic Diagram (Top view)



### Winding Specification

No.	Pin(S → F)	Wire	Turns	Winding Method
NP	1 → 3	0.35φ × 1	44	-
N12V	7 → 11	0.35φ × 4	12	-
NP	1 → 3	0.35φ × 1	44	-
NB	5 → 4	0.35φ × 1	13	-

### Electrical Characteristic

Closure	Pin	Spec.	Remarks
Inductance	1 - 3	400uH ±10%	100kHz, 1V
Leakage	1 - 3	10uH MAX .	2 <sup>nd</sup> All short







## Part List For FAN7554 Forward Converter Demo Board

Part	Value	Note	Part	Value	Note
<b>FUSE</b>			<b>CAPACITOR</b>		
FUSE	250 2A	-	C101	470nF/ 275V	Box Capacitor
<b>NTC</b>			C102, C103	470nF/ 400WV	Electrolytic
RT101	DSC 10D-11	-	C104	223/ 630V	Film
<b>RESISTOR</b>			C105	33uF/ 35V	Film Capacitor
R101	330k $\Omega$	1W	C106	104	Ceramic
R102	-	-	C107	1uF/ 35V	Electrolytic
R103, R104	56k $\Omega$	1W	C108	101	Ceramic
R105, R106	220k $\Omega$	1W	C109	122	Ceramic
R107	10 $\Omega$	-	C110	272	Film
R108	20 $\Omega$	-	C111	333	Film
R109	4.7k $\Omega$	-	C201, C202	1000uF/ 35V	Electrolytic
R110	1.2k $\Omega$	-	C203	330uF/ 16V	Electrolytic
R111	0.5 $\Omega$ //0.5 $\Omega$ //0.5 $\Omega$	2W	C204	2200uF/ 16V	Electrolytic
R112	1k $\Omega$	-	C205	104	Ceramic
R113	12k $\Omega$	-	C301, C302	332/ 1kV	Ceramic
R201, R202	10k $\Omega$	-	<b>INDUCTOR</b>		
R203	1k $\Omega$	-	LF101	30mH	-
R204	330 $\Omega$	-	L201	-	-
<b>MOSFET</b>			<b>DIODE</b>		
Q101	SSH8N80	Fairchild	D101	1N4004	-
<b>IC</b>			D102	FR157	-
IC101	FAN7554	Fairchild	D103	UF4007	-
IC201	KA431	Fairchild	D201	MBRF10100CT	-
IC301	Opto-Coupler	Fairchild	D202	MBR3045PT	-
-	-	-	BD	PBS406GU	-

## Transformer specification

Schematic Diagram (Top view)



## Winding Specification

No.	Pin(S → F)	Wire	Turns
NP	1 → 3	0.65 $\phi$ × 1	32
NS, 5	8 → 11	0.65 $\phi$ × 4	4
NS, 12	4 → 9	0.65 $\phi$ × 4	5
NP	1 → 3	0.65 $\phi$ × 1	32
NVCC	7 → 6	0.65 $\phi$ × 1	5

Core : Powder 27 pi 16grade

5V : 12T ( 1  $\phi$  × 2 )


12V : 27T ( 1.2  $\phi$  × 1 )

# Mechanical Dimensions

## Package

Dimensions in millimeters

### 8-SOP




**Mechanical Dimensions** (Continued)

Package

Dimensions in millimeters

**8-DIP**



## Ordering Information

Product Number	Package	Operating Temperature
FAN7554	8-DIP	-25°C ~ 85°C
FAN7554D	8-SOP	

### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.