# DATA SHEET

# MOS FIELD EFFECT TRANSISTOR $\mu PA2706TP$

# SWITCHING N-CHANNEL POWER MOS FET

## DESCRIPTION

The  $\mu$  PA2706TP, which has a heat spreader, is N-channel MOS Field Effect Transistor designed for DC/DC converter and power management application of notebook computer.

#### **FEATURES**

Low on-state resistance

 $R_{DS(on)1}$  = 15 m $\Omega$  MAX. (V<sub>GS</sub> = 10 V, I<sub>D</sub> = 5.5 A)

 $R_{DS(on)2}$  = 22.5 m $\Omega$  MAX. (VGs = 4.5 V, ID = 5.5 A)

• Low Ciss: Ciss = 660 pF TYP. (VDS = 10 V, VGS = 0 V)

• Small and surface mount package (Power HSOP8)

## ABSOLUTE MAXIMUM RATINGS (T<sub>A</sub> = 25°C, Unless otherwise noted, all terminals are connected.)

Drain to Source Voltage (VGS = 0 V)	VDSS	30	V
Gate to Source Voltage (VDS = 0 V)	Vgss	±20	V
Drain Current (DC) (Tc = 25°C)	D(DC)1	±20	А
Drain Current (DC) <sup>Note1</sup>	D(DC)2	±11	А
Drain Current (pulse) Note2	D(pulse)	±44	А
Total Power Dissipation (Tc = $25^{\circ}$ C)	P <sub>T1</sub>	15	W
Total Power Dissipation Note1	Pt2	3	W
Channel Temperature	Tch	150	°C
Storage Temperature	Tstg	–55 to +150	°C
Single Avalanche Current Note3	las	11	А
Single Avalanche Energy Note3	Eas	12.1	mJ

Notes 1. Mounted on glass epoxy board of 1 inch x 1 inch x 0.8 mm, PW = 10 sec

- **2.** PW  $\leq$  10  $\mu$ s, Duty Cycle  $\leq$  1%
- 3. Starting T<sub>ch</sub> = 25°C, V<sub>DD</sub> = 15 V, R<sub>G</sub> = 25  $\Omega$ , L = 100  $\mu$ H, V<sub>GS</sub> = 20  $\rightarrow$  0 V

The information in this document is subject to change without notice. Before using this document, please confirm that this is the latest version. Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.

## ORDERING INFORMATION


PART NUMBER	PACKAGE
$\mu$ PA2706TP	Power HSOP8

Caution Strong electric field, when exposed to this device, can cause destruction of the gate oxide and ultimately degrade the device operation. Steps must be taken to stop generation of static electricity as much as possible, and quickly dissipate it once, when it has occurred.


CHARACTERISTICS	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
Zero Gate Voltage Drain Current	IDSS	V <sub>DS</sub> = 30 V, V <sub>GS</sub> = 0 V			10	μA
Gate Leakage Current	lgss	V <sub>GS</sub> = ±20 V, V <sub>DS</sub> = 0 V			±10	μA
Gate Cut-off Voltage Note	V <sub>GS(off)</sub>	V <sub>DS</sub> = 10 V, I <sub>D</sub> = 1 mA	1.5		2.5	V
Forward Transfer Admittance	<b>y</b> fs	V <sub>DS</sub> = 10 V, I <sub>D</sub> = 5.5 A	4.5			S
Drain to Source On-state Resistance Note	RDS(on)1	V <sub>GS</sub> = 10 V, I <sub>D</sub> = 5.5 A		11	15	mΩ
	RDS(on)2	Vgs = 4.5 V, Id = 5.5 A		16	22.5	mΩ
	RDS(on)3	V <sub>GS</sub> = 4.0 V, I <sub>D</sub> = 5.5 A		19	29	mΩ
Input Capacitance	Ciss	V <sub>DS</sub> = 10 V		660		pF
Output Capacitance	Coss	V <sub>GS</sub> = 0 V		270		pF
Reverse Transfer Capacitance	Crss	f = 1 MHz		83		pF
Turn-on Delay Time	td(on)	V <sub>DD</sub> = 15 V, I <sub>D</sub> = 5.5 A		9		ns
Rise Time	tr	V <sub>GS</sub> = 10 V		5		ns
Turn-off Delay Time	td(off)	R <sub>G</sub> = 10 Ω		29		ns
Fall Time	tr			6		ns
Total Gate Charge	QG	V <sub>DD</sub> = 15 V		7.1		nC
Gate to Source Charge	Q <sub>GS</sub>	V <sub>GS</sub> = 5.0 V		2.1		nC
Gate to Drain Charge	Qgd	ID = 11 A		3.1		nC
Body Diode Forward Voltage Note	VF(S-D)	I⊧ = 11 A, V <sub>GS</sub> = 0 V		0.84		V
Reverse Recovery Time	trr	I⊧ = 11 A, V <sub>GS</sub> = 0 V		25		ns
Reverse Recovery Charge	Qrr	di/dt = 100 A/ <i>μ</i> s		17		nC

Note Pulsed

#### **TEST CIRCUIT 1 AVALANCHE CAPABILITY**





#### **TEST CIRCUIT 3 GATE CHARGE**




#### **TEST CIRCUIT 2 SWITCHING TIME**


୷







## TYPICAL CHARACTERISTICS ( $T_A = 25^{\circ}C$ )







FORWARD BIAS SAFE OPERATING AREA












DRAIN TO SOURCE ON-STATE RESISTANCE vs. DRAIN CURRENT




FORWARD TRANSFER CHARACTERISTICS




FORWARD TRANSFER ADMITTANCE vs. DRAIN CURRENT





DRAIN TO SOURCE ON-STATE RESISTANCE vs. GATE TO SOURCE VOLTAGE



 $R_{DS(on)}$  - Drain to Source On-state Resistance - m $\Omega$ 









PACKAGE DRAWING (Unit: mm)



NEC



#### EQUIVALENT CIRCUIT



**Remark** The diode connected between the gate and source of the transistor serves as a protector against ESD. When this device actually used, an additional protection circuit is externally required if a voltage exceeding the rated voltage may be applied to this device.

- The information in this document is current as of January, 2004. The information is subject to change without notice. For actual design-in, refer to the latest publications of NEC Electronics data sheets or data books, etc., for the most up-to-date specifications of NEC Electronics products. Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.
- No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Electronics. NEC Electronics assumes no responsibility for any errors that may appear in this document.
- NEC Electronics does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from the use of NEC Electronics products listed in this document or any other liability arising from the use of such products. No license, express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Electronics or others.
- Descriptions of circuits, software and other related information in this document are provided for illustrative purposes in semiconductor product operation and application examples. The incorporation of these circuits, software and information in the design of a customer's equipment shall be done under the full responsibility of the customer. NEC Electronics assumes no responsibility for any losses incurred by customers or third parties arising from the use of these circuits, software and information.
- While NEC Electronics endeavors to enhance the quality, reliability and safety of NEC Electronics products, customers agree and acknowledge that the possibility of defects thereof cannot be eliminated entirely. To minimize risks of damage to property or injury (including death) to persons arising from defects in NEC Electronics products, customers must incorporate sufficient safety measures in their design, such as redundancy, fire-containment and anti-failure features.
- NEC Electronics products are classified into the following three quality grades: "Standard", "Special" and "Specific".

The "Specific" quality grade applies only to NEC Electronics products developed based on a customerdesignated "quality assurance program" for a specific application. The recommended applications of an NEC Electronics product depend on its quality grade, as indicated below. Customers must check the quality grade of each NEC Electronics product before using it in a particular application.

- "Standard": Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots.
- "Special": Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support).
- "Specific": Aircraft, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems and medical equipment for life support, etc.

The quality grade of NEC Electronics products is "Standard" unless otherwise expressly specified in NEC Electronics data sheets or data books, etc. If customers wish to use NEC Electronics products in applications not intended by NEC Electronics, they must contact an NEC Electronics sales representative in advance to determine NEC Electronics' willingness to support a given application.

(Note)

- (1) "NEC Electronics" as used in this statement means NEC Electronics Corporation and also includes its majority-owned subsidiaries.
- (2) "NEC Electronics products" means any product developed or manufactured by or for NEC Electronics (as defined above).