

Rectifiers, General Purpose (Continued)

I_O (AMPS)	12	16	20	40
@ T_C (°C)	150	150	150	150
I_{FSM} (AMPS)	300	325	350	800
CASE	 DO-4*			 DO-5*
V_{RRM} (VOLTS)				
100	CR12-010	CR16-010	CR20-010	CR40-010
200	CR12-020	CR16-020	CR20-020	CR40-020
400	CR12-040	CR16-040	CR20-040	CR40-040
600	CR12-060	CR16-060	CR20-060	CR40-060
800	CR12-080	CR16-080	CR20-080	CR40-080
1000	CR12-100	CR16-100	CR20-100	CR40-100
1200	CR12-120	CR16-120	CR20-120	CR40-120

$V_F \text{ MAX @ } I_F = I_O$	1.1V	1.1V	1.1V	1.1V
--------------------------------	------	------	------	------

$I_R \text{ MAX @ } V_{RRM}$	10 μ A	10 μ A	10 μ A	100 μ A
------------------------------	------------	------------	------------	-------------

* Standard polarity is cathode to case. For reverse polarity add "R" suffix to part number.