Industrial Inductive Load Driver

This MicroIntegration™ part provides a single component solution to switch inductive loads such as relays, solenoids, and small DC motors without the need of a free-wheeling diode. It accepts logic level inputs, thus allowing it to be driven by a large variety of devices including logic gates, inverters, and microcontrollers.

Features

- Provides Robust Interface between D.C. Relay Coils and Sensitive Logic
- Capable of Driving Relay Coils Rated up to 150 mA at 12 V, 24 V or 48 V
- Replaces 3 or 4 Discrete Components for Lower Cost
- Internal Zener Eliminates Need for Free-Wheeling Diode
- Meets Load Dump and other Automotive Specs
- Pb-Free Packages are Available

Typical Applications

- Automotive and Industrial Environment
- Drives Window, Latch, Door, and Antenna Relays

Benefits

- Reduced PCB Space
- Standardized Driver for Wide Range of Relays
- Simplifies Circuit Design and PCB Layout
- Compliance with Automotive Specifications



ON Semiconductor®

http://onsemi.com

MARKING DIAGRAMS



SOT-23 CASE 318 STYLE 21



JW8 = Specific Device Code

M = Date Code

= Pb-Free Package

(Note: Microdot may be in either location)



SC-74 CASE 318F STYLE 7



JW8 = Specific Device Code

M = Date Code


= Pb-Free Package

(Note: Microdot may be in either location)

ORDERING INFORMATION

Device	Package	Shipping [†]		
NUD3160LT1	SOT-23	3000/Tape & Reel		
NUD3160LT1G	SOT-23 (Pb-Free)	3000/Tape & Reel		
NUD3160DMT1	SC-74	3000/Tape & Reel		
NUD3160DMT1G	SC-74 (Pb-Free)	3000/Tape & Reel		

[†]For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specification Brochure, BRD8011/D.






Figure 1. Internal Circuit Diagrams

1

$\textbf{MAXIMUM RATINGS} \ (T_J = 25^{\circ}C \ unless \ otherwise \ specified)$

Symbol	Rating	Value	Unit	
V_{DSS}	Drain-to-Source Voltage - Continuous (T _J = 125°C)	60	V	
V_{GSS}	Gate-to-Source Voltage - Continuous (T _J = 125°C)	12	V	
I _D	Drain Current – Continuous (T _J = 125°C) Minimum copper, double sided board, T _A = 80°C SOT-23 SC74 Single device driven SC74 Both devices driven 1 in ² copper, double sided board, T _A = 25°C SOT-23 SC74 Single device driven SC74 Both devices driven	158 157 132 ea 272 263 230 ea	mA	
E _Z	Single Pulse Drain-to-Source Avalanche Energy (For Relay's Coils/Inductive Loads of 80 Ω or Higher) (T _J Initial = 85°C)	200	mJ	
P _{PK}	Peak Power Dissipation, Drain-to-Source (Notes 1 and 2) (T _J Initial = 85°C)	20	W	
E _{LD1}	Load Dump Pulse, Drain-to-Source (Note 3) $R_{SOURCE} = 0.5~\Omega,~T = 300~ms) \\ (For Relay's Coils/Inductive Loads of 80~\Omega or Higher) \\ (T_J Initial = 85°C)$	60	V	
E _{LD2}	Inductive Switching Transient 1, Drain–to–Source (Waveform: R_{SOURCE} = 10 Ω , T = 2.0 ms) (For Relay's Coils/Inductive Loads of 80 Ω or Higher) (T _J Initial = 85°C)	100	V	
E _{LD3}	Inductive Switching Transient 2, Drain-to-Source (Waveform: R_{SOURCE} = 4.0 Ω , T = 50 μ s) (For Relay's Coils/Inductive Loads of 80 Ω or Higher) (T _J Initial = 85°C)	300	V	
Rev-Bat	Reverse Battery, 10 Minutes (Drain-to-Source) (For Relay's Coils/Inductive Loads of 80 Ω or more)	-14	V	
Dual-Volt	Dual Voltage Jump Start, 10 Minutes (Drain-to-Source)	28	V	
ESD	Human Body Model (HBM) According to EIA/JESD22/A114 Specification	2000	V	

THERMAL CHARACTERISTICS

Symbol	Rating			Unit
T _A	Operating Ambient Temperature			°C
TJ	Maximum Junction Temperature		150	°C
T _{STG}	Storage Temperature Range		-65 to 150	°C
P _D	Total Power Dissipation (Note 4) Derating above 25°C	SOT-23	225 1.8	mW mW/°C
P_{D}	Total Power Dissipation (Note 4) Derating above 25°C	SC-74	380 3.0	mW mW/°C
$R_{ hetaJA}$	Thermal Resistance, Junction–to–Ambient Minimum Copper 300 mm ² Copper	SOT-23 SC-74 One Device Powered SC-74 Both Devices Equally Powered SOT-23 SC-74 One Device Powered SC-74 Both Devices Equally Powered	556 556 398 395 420 270	°C/W

- Nonrepetitive current square pulse 1.0 ms duration.
 For different square pulse durations, see Figure 12.
 Nonrepetitive load dump pulse per Figure 3.
 Mounted onto minimum pad board.

ELECTRICAL CHARACTERISTICS ($T_J = 25^{\circ}C$ unless otherwise specified)

Characteristic	Symbol	Min	Тур	Max	Unit
OFF CHARACTERISTICS		1	, ,,		
Drain to Source Sustaining Voltage $(I_D = 10 \text{ mA})$	V _{BRDSS}	61	66	70	V
Drain to Source Leakage Current $ (V_{DS} = 12 \text{ V}, V_{GS} = 0 \text{ V}) \\ (V_{DS} = 12 \text{ V}, V_{GS} = 0 \text{ V}, T_J = 125^{\circ}\text{C}) \\ (V_{DS} = 60 \text{ V}, V_{GS} = 0 \text{ V}) \\ (V_{DS} = 60 \text{ V}, V_{GS} = 0 \text{ V}, T_J = 125^{\circ}\text{C}) $	I _{DSS}	- - - -	- - -	0.5 1.0 50 80	μΑ
Gate Body Leakage Current $ (V_{GS} = 3.0 \text{ V}, V_{DS} = 0 \text{ V}) \\ (V_{GS} = 3.0 \text{ V}, V_{DS} = 0 \text{ V}, T_{J} = 125^{\circ}\text{C}) \\ (V_{GS} = 5.0 \text{ V}, V_{DS} = 0 \text{ V}) \\ (V_{GS} = 5.0 \text{ V}, V_{DS} = 0 \text{ V}, T_{J} = 125^{\circ}\text{C}) $	I _{GSS}	- - -	- - -	60 80 90 110	μΑ
ON CHARACTERISTICS					
Gate Threshold Voltage $ (V_{GS} = V_{DS}, I_D = 1.0 \text{ mA}) $ $ (V_{GS} = V_{DS}, I_D = 1.0 \text{ mA}, T_J = 125^{\circ}\text{C}) $	V _{GS(th)}	1.3 1.3	1.8 -	2.0 2.0	V
Drain to Source On–Resistance $(I_D = 150 \text{ mA}, V_{GS} = 3.0 \text{ V})$ $(I_D = 150 \text{ mA}, V_{GS} = 3.0 \text{ V}, T_J = 125^{\circ}\text{C})$ $(I_D = 150 \text{ mA}, V_{GS} = 5.0 \text{ V})$ $(I_D = 150 \text{ mA}, V_{GS} = 5.0 \text{ V}, T_J = 125^{\circ}\text{C})$	R _{DS(on)}	- - - -	- - - -	2.4 3.7 1.8 2.9	Ω
Output Continuous Current $ (V_{DS} = 0.3 \text{ V}, V_{GS} = 5.0 \text{ V}) \\ (V_{DS} = 0.3 \text{ V}, V_{GS} = 5.0 \text{ V}, T_J = 125^{\circ}\text{C}) $	I _{DS(on)}	150 100	200 -	_ _	mA
Forward Transconductance $(V_{DS} = 12 \text{ V}, I_D = 150 \text{ mA})$	9FS	_	400	-	mmho
DYNAMIC CHARACTERISTICS	•	•	•		
Input Capacitance $(V_{DS} = 12 \text{ V}, V_{GS} = 0 \text{ V}, f = 10 \text{ kHz})$	C _{iss}	_	30	-	pf
Output Capacitance $(V_{DS} = 12 \text{ V}, V_{GS} = 0 \text{ V}, f = 10 \text{ kHz})$	C _{oss}	-	14	-	pf
Transfer Capacitance $(V_{DS} = 12 \text{ V}, V_{GS} = 0 \text{ V}, f = 10 \text{ kHz})$	C _{rss}	_	6.0	-	pf
SWITCHING CHARACTERISTICS					
Propagation Delay Times: High to Low Propagation Delay; Figure 2, $(V_{DS} = 12 \text{ V}, V_{GS} = 3.0 \text{ V})$ Low to High Propagation Delay; Figure 2, $(V_{DS} = 12 \text{ V}, V_{GS} = 3.0 \text{ V})$	t _{PHL} t _{PLH}	- -	918 798	- -	ns
High to Low Propagation Delay; Figure 2, (V_{DS} = 12 V, V_{GS} = 5.0 V) Low to High Propagation Delay; Figure 2, (V_{DS} = 12 V, V_{GS} = 5.0 V)	t _{PHL} t _{PLH}	<u> </u>	331 1160	- -	
Transition Times: Fall Time; Figure 2, $(V_{DS} = 12 \text{ V}, V_{GS} = 3.0 \text{ V})$ Rise Time; Figure 2, $(V_{DS} = 12 \text{ V}, V_{GS} = 3.0 \text{ V})$	t _f t _r	_ _	2290 618	_ _	ns
Fall Time; Figure 2, $(V_{DS} = 12 \text{ V}, V_{GS} = 5.0 \text{ V})$ Rise Time; Figure 2, $(V_{DS} = 12 \text{ V}, V_{GS} = 5.0 \text{ V})$	t _f t _r	- -	622 600	- -	

TYPICAL WAVEFORMS

(T_J = 25°C unless otherwise specified)




Figure 2. Switching Waveforms





Figure 3. Load Dump Waveform Definition

TYPICAL PERFORMANCE CURVES


(T_J = 25°C unless otherwise specified)



80 I_{GSS} GATE LEAKAGE (µA) 60 $V_{GS} = 5 V$ 50 40 $V_{GS} = 3 V$ 30 20 -25 -50 25 50 100 125 T.J., JUNCTION TEMPERATURE (°C)

Figure 4. Drain-to-Source Leakage vs. **Junction Temperature**

Figure 5. Gate-to-Source Leakage vs. **Junction Temperature**







Figure 6. Breakdown Voltage vs. **Junction Temperature**

Figure 7. Output Characteristics






Figure 8. Transfer Function

Figure 9. On Resistance Variation vs **Junction Temperature**

TYPICAL PERFORMANCE CURVES

(T_J = 25°C unless otherwise specified)




Figure 10. On Resistance Variation vs. Gate-to-Source Voltage

Figure 11. Zener Clamp Voltage vs. Zener Current




Figure 12. Maximum Non-repetitive Surge Power vs. Pulse Width




Figure 13. Thermal Performance vs. Board Copper Area

APPLICATIONS INFORMATION





Figure 14. Applications Diagram

PACKAGE DIMENSIONS

SOT-23 (TO-236) CASE 318-08 **ISSUE AN**



NOTES:

- NOTES:

 1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.

 2. CONTROLLING DIMENSION: INCH.

 3. MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL.


 4. 318–01 THRU –07 AND –09 OBSOLETE, NEW STANDARD 318–08.

	MILLIMETERS			INCHES			
DIM	MIN	NOM	MAX	MIN	NOM	MAX	
Α	0.89	1.00	1.11	0.035	0.040	0.044	
A1	0.01	0.06	0.10	0.001	0.002	0.004	
b	0.37	0.44	0.50	0.015	0.018	0.020	
С	0.09	0.13	0.18	0.003	0.005	0.007	
D	2.80	2.90	3.04	0.110	0.114	0.120	
E	1.20	1.30	1.40	0.047	0.051	0.055	
е	1.78	1.90	2.04	0.070	0.075	0.081	
L	0.10	0.20	0.30	0.004	0.008	0.012	
L1	0.35	0.54	0.69	0.014	0.021	0.029	
HE	2.10	2.40	2.64	0.083	0.094	0.104	

STYLE 21: PIN 1. GATE 2. SOURG 3. DRAIN

- SOURCE


SOLDERING FOOTPRINT*




^{*}For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

PACKAGE DIMENSIONS

SC-74 CASE 318F-05 ISSUE L





NOTES:

- DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982
- CONTROLLING DIMENSION: INCH.
 MAXIMUM LEAD THICKNESS INCLUDES
 LEAD FINISH THICKNESS. MINIMUM LEAD
 THICKNESS IS THE MINIMUM THICKNESS
- OF BASE MATERIAL.
 4. 318F-01, -02, -03 OBSOLETE. NEW STANDARD 318F-04.


	MILLIMETERS			INCHES			
DIM	MIN	NOM	MAX	MIN NOM MAX			
Α	0.90	1.00	1.10	0.035	0.039	0.043	
A1	0.01	0.06	0.10	0.001	0.002	0.004	
b	0.25	0.37	0.50	0.010	0.015	0.020	
С	0.10	0.18	0.26	0.004	0.007	0.010	
D	2.90	3.00	3.10	0.114	0.118	0.122	
E	1.30	1.50	1.70	0.051	0.059	0.067	
е	0.85	0.95	1.05	0.034	0.037	0.041	
L	0.20	0.40	0.60	0.008	0.016	0.024	
HE	2.50	2.75	3.00	0.099	0.108	0.118	
θ	0°	_	10°	0°	_	10°	

STYLE 7:

PIN 1. SOURCE 1 2. GATE 1

- DRAIN 2
- 3.
- 4. SOURCE 2
- 5. GATE 2 6. DRAIN 1

SOLDERING FOOTPRINT*



*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

MicroIntegration is a trademark of Semiconductor Components Industries, LLC (SCILLC)

ON Semiconductor and un are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice on semiconductor and war engineer trademarks of semiconductor components industries, Ite (SciLLC) solitate services are injective to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada

Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free USA/Canada

Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center

Phone: 81-3-5773-3850

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative