Freescale AO3406/ MC3406


N-Channel 30-V (D-S) MOSFET

These miniature surface mount MOSFETs utilize a high cell density trench process to provide low $r_{DS(on)}$ and to ensure minimal power loss and heat dissipation. Typical applications are DC-DC converters and power management in portable and battery-powered products such as computers, printers, PCMCIA cards, cellular and cordless telephones.

- Low r_{DS(on)} provides higher efficiency and extends battery life
- Low thermal impedance copper leadframe SOT-23 saves board space
- Fast switching speed
- High performance trench technology

PRODUCT SUMMARY			
V _{DS} (V)	$V_{DS(on)}(\Omega)$ $I_{D}(A)$		
30	$0.085 @ V_{GS} = 10V$	2.5	
	$0.125 @ V_{GS} = 4.5V$	1.7	





ABSOLUTE MAXIMUM RATINGS (T _A = 25 °C UNLESS OTHERWISE NOTED)					
Parameter		Symbol	Maximum	Units	
Drain-Source Voltage		V_{DS}	30	V	
Gate-Source Voltage		V_{GS}	±20	٧	
Continuous Drain Current ^a	$T_A=25^{\circ}C$	T	2.5	_	
Continuous Drain Current	$T_A=25^{\circ}C$ $T_A=70^{\circ}C$	1 _D	2	A	
Pulsed Drain Current ^b		I_{DM}	10		
Continuous Source Current (Diode Conduction) ^a		I_S	0.46	A	
Power Discipation ^a	$T_A=25^{\circ}C$	D	1.25	W	
Power Dissipation ^a	$T_A=25^{\circ}C$ $T_A=70^{\circ}C$	¹ D	0.8	vv	
Operating Junction and Storage Temperature Range		T_J, T_{stg}	-55 to 150	°C	

THERMAL RESISTANCE RATINGS						
Parameter		Symbol	Maximum	Units		
M · I · a	t <= 5 sec	D	150	00.00		
Maximum Junction-to-Ambient ^a	Steady-State	R_{THJA}	200	C/W		

1

Notes

- a. Surface Mounted on 1" x 1" FR4 Board.
- b. Pulse width limited by maximum junction temperature

(C)

Freescale AO3406/ MC3406

		Limits				
Parameter	Symbol	Test Conditions	Min	Тур	Max	Unit
Static				<u> </u>		
Gate-Threshold Voltage	$V_{GS(th)}$	$V_{DS} = V_{GS}, I_D = 250 \text{ uA}$	1.0	1.5	3	V
Gate-Body Leakage	I_{GSS}	$V_{DS}=0\ V,\ V_{GS}=8\ V$		4	100	nA
Zero Gate Voltage Drain Current	I_{DSS}	$V_{DS} = 16 \text{ V}, V_{GS} = 0 \text{ V}$ $V_{DS} = 20 \text{ V}, V_{GS} = 0 \text{ V}, T_J = 55^{\circ}\text{C}$		7	1 10	uA
On-State Drain Current ^A	I _{D(on)}	$V_{DS} = 5 \text{ V}, V_{GS} = 4.5 \text{ V}$	6		10	A
A		$V_{GS} = 10 \text{ V}, I_D = 2.5 \text{ A}$		62	85	mΩ
Drain-Source On-Resistance ^A	$r_{\mathrm{DS(on)}}$	$V_{GS} = 4.5 \text{ V}, I_D = 1.7 \text{ A}$		102	125	
Forward Tranconductance ^A	g_{fs}	$V_{DS} = 5 \text{ V}, I_D = 3.0 \text{ A}$		3.5		S
Diode Forward Voltage	V_{SD}	$I_S = 0.46 \text{ A}, V_{GS} = 0 \text{ V}$		0.65		V
Dynamic ^b						
Total Gate Charge	Q_{g}	$V_{DS} = 10 \text{ V}, V_{GS} = 4.5 \text{ V},$		3.5	7	nC
Gate-Source Charge	Q_{gs}	$V_{DS} = 10 \text{ V}, V_{GS} = 4.3 \text{ V},$ $I_{D} = 2.5 \text{ A}$		0.8	2	
Gate-Drain Charge	Q_{gd}	1) = 2.3 A		1.0	2	
Input Capacitance	C _{iss}	$V_{DS} = 15 \text{ V}, V_{GS} = 0 \text{ V},$		720	1500	
Output Capacitance	C_{oss}	$\mathbf{v}_{\mathrm{DS}} = 13 \mathbf{v}, \mathbf{v}_{\mathrm{GS}} = 0 \mathbf{v},$ $\mathbf{f} = 1 \mathrm{MHz}$		165	400	pF
Reverse Transfer Capacitance	C_{rss}	I = IWHIZ		60	200	
Turn-On Delay Time	$t_{d(on)}$			10	20	
Rise Time	$t_{\rm r}$	$V_{\rm DD}=10~V, \qquad I_{\rm D}=1~A~, \label{eq:Vdd}$		13	30	ns
Turn-Off Delay Time	$t_{d(off)}$	$R_{\scriptscriptstyle G} = 6~\Omega, ~~V_{\scriptscriptstyle GEN} = 4.5~v$		14	30	
Fall-Time	t_{f}			4	20	

Notes

- a. Pulse test: $PW \le 300us duty cycle \le 2\%$.
- b. Guaranteed by design, not subject to production testing.

FREESCALE reserves the right to make changes without further notice to any products herein. FREESCALE makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does FREESCALE assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in FREESCALE data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typical" must be validated for each customer application by customer's technical experts. FREESCALE does not convey any license under its patent rights nor the rights of others. FREESCALE products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the FREESCALE product could create a situation where personal injury or death may occur. Should Buyer purchase or use FREESCALE products for any such unintended or unauthorized application, Buyer shall indemnify and hold FREESCALE and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that FREESCALE was negligent regarding the design or manufacture of the part. FREESCALE is an Equal Opportunity/Affirmative Action Employer.



Freescale AO3406/ MC3406

Typical Electrical Characteristics





Figure 1. On-Region Characteristics



Drain Current and Gate Voltage




Figure 3. On-Resistance Variation with Temperature




Figure 4. On-Resistance Variation with **Drain Current and Temperature**




Figure 5. Transfer Characteristics

3




Figure 6. Gate Threshold Variation with **Temperature**

Freescale AO3406/ MC3406

Typical Electrical Characteristics




Figure 7. Gate Charge Characteristic




Figure 8. Capacitance Characteristic




Figure 9. Maximum Safe Operating Area




Figure 10. Breakdown Voltage Variation with Temperature

Normalized Thermal Transient Impedance, Junction to Ambient





Figure 11. Transient Thermal Response Curve.

Package Information



5