

查询4885-24供应商

捷多邦, 专业

PCB打样

FILTRAN

Power Transformers

Low Profile




4881 - 4885

, 24小时加急出货

INTERNATIONAL LOW PROFILE SERIES Power Transformers for PCB mounting.

- Five sizes: 10, 12, 18, 24, 30 VA ratings.
- Dual bobbins for increased dielectric strength.
- 115/230 volts, 50/60 Hz primary windings.
- Potted under vacuum.
- Compact size.
- CSA listed (LR 47366) and U.L. recognized (E100878).
- Exceeds VDE 0550, BSI 7002 and IEC 950 requirements.

MECHANICAL



Dimensions, mm

P/N	H
4881-	22.0
4882-	24.0
4883-	27.0
4884-	31.0
4885-	35.0

ELECTRICAL SPECIFICATION

Part No.	VA	Parallel		Series		Part No.	VA	Parallel		Series	
		Volts	Amps	Volts	Amps			Volts	Amps	Volts	Amps
4881-6	10	6	1.66	12	0.83	4884-6	24	6	4.00	12	2.00
4881-9	10	9	1.11	18	0.55	4884-9	24	9	2.66	18	1.33
4881-12	10	12	0.83	24	0.41	4884-12	24	12	2.00	24	1.00
4881-15	10	15	0.66	30	0.33	4884-15	24	15	1.60	30	0.80
4881-18	10	18	0.55	36	0.27	4884-18	24	18	1.33	36	0.66
4881-21	10	21	0.47	42	0.23	4884-21	24	21	1.14	42	0.57
4881-24	10	24	0.41	48	0.20	4884-24	24	24	1.00	48	0.50
4882-6	12	6	2.00	12	1.00	4885-6	30	6	5.00	12	2.50
4882-9	12	9	1.33	18	0.66	4885-9	30	9	3.33	18	1.66
4882-12	12	12	1.00	24	0.50	4885-12	30	12	2.50	24	1.25
4882-15	12	15	0.80	30	0.40	4885-15	30	15	2.00	30	1.00
4882-18	12	18	0.66	36	0.33	4885-18	30	18	1.66	36	0.83
4882-21	12	21	0.57	42	0.28	4885-21	30	21	1.42	42	0.71
4882-24	12	24	0.50	48	0.25	4885-24	30	24	1.25	48	0.62
4883-6	18	6	3.00	12	1.50						
4883-9	18	9	2.00	18	1.00						
4883-12	18	12	1.50	24	0.75						
4883-15	18	15	1.20	30	0.60						
4883-18	18	18	1.00	36	0.50						
4883-21	18	21	0.86	42	0.42						
4883-24	18	24	0.75	48	0.37						

