

# Himax AV TCON

Part No.	Features	Resolution	PKG	Status
<b>HX8801</b>	CVBS	280 x 220, 528 x 220, 480 x 234, 960 x 234(S), 1152 x 234(S), 1440 x 234(S)	48 LQFP	MP
<b>HX8806</b>	CVBS ; 8 zoom modes	Stripe : 1200, 1440 Good application in 7" Analog panel	48 LQFP	MP
<b>HX8802B</b>	Input : Serial RGB 8-bit Analog RGB	240 x 234, 320 x 240, 480 x 234, 640 x 240, 720 x 234, 960 x 234(S) 1200 x 234(S), 1440 x 234(S)	64 LQFP	MP
<b>HX8802- C (HX8802A+PWM)</b>	Input : Serial RGB 8-bit Output : Analog RGB 3ch PWM	280 x 220, 528 x 220, 1152 x 234(S) <u>320 x 240, 480 x 234, 960 x 234(S)</u> <u>1440 x 234(S)</u>	64 LQFP	MP
<b>HX8817</b>	Input : 601/656/RGB-T/RGB18 Output : Analog RGB 2ch PWM , 8 zoom modes	Delta : 480, 960 Stripe : 960, 1200, 1440	64 LQFP	MP
<b>HX8819A</b>	Input : RGB24 Output : RGB18 Dithering	800x480 : FB 640x480 : FC	64 TQFP	MP
<b>HX8824- A</b>	Input : 601/656/RGB24 Output : RGB24/RGB18 Scaler,OSD,BCHS,1DSharpness Programmable Gamma, Dithering 2ch PWM	640 x 480, 800 x 480, 852 x 480, 800 x 600,	100 LQFP	MP

光碁科技股份有限公司(台灣)  
CERAMATE TECHNICAL CO., LTD.

桃園縣蘆竹鄉南坎路二段 66-5 號 1 樓  
1F, NO.66-5, SEC.2, NAN-KAN RD., LUCHU,  
TAOYUAN, TAIWAN, R.O.C

TEL: 886-3-3214525 FAX: 886-3-3521052

E-mail: brook@ceramate.com.tw

光碁科技深圳辦事處(深圳)

CERAMATE TECHNICAL CO., LTD. (SHEN ZHEN)

深圳市上步南路國企大廈 B 棟(永輝樓) 24G 室  
ROOM 24G,(YONG HUI BUILDING) B DONG, GUO QI DA  
SHA, SHANGBU SOUTH RD., SHENZHEN, CHINA

Tel: 86-755-61637041-43 Fax : 86-755-61637040

E-mail: jun.dong@163.com

瑞基電子有限公司(蘇州)

SU ZHOU PRONICS ELECTRONICS CO., LTD.

蘇州市新區濱河路 813 號  
NO.813, BINHE ROAD, SUZHOU NEW DISTRICT,  
JIANGSU, CHINA

TEL:86-512-68410323 FAX: 86-512-68410313

E-mail: helen\_niu@pub.sz.isinfo.net



PDF  
DZSC.COM