
SCBS226J - JULY 1993 - REVISED DECEMBER 2001

- **Members of the Texas Instruments** Widebus™ Family
- Support the VME64 ETL Specification
- Reduced, TTL-Compatible, Input Threshold Range
- High-Drive Outputs ( $I_{OH} = -60 \text{ mA}$ ,  $I_{OL}$  = 90 mA) Support 25- $\Omega$  Incident-Wave Switching
- **V<sub>CC</sub>BIAS** Pin Minimizes Signal Distortion **During Live Insertion**
- Internal Pullup Resistor on OE Keeps **Outputs in High-Impedance State During Power Up or Power Down**
- Distributed V<sub>CC</sub> and GND Pins Minimize **High-Speed Switching Noise**
- Equivalent 25- $\Omega$  Series Damping Resistor on B Port
- Bus Hold on Data Inputs Eliminates the **Need for External Pullup/Pulldown** Resistors

#### description

The 'ABTE16245 devices are 16-bit (dual-octal) noninverting 3-state transceivers designed for synchronous two-way communication between data buses. The control-function implementation minimizes external timing requirements. These devices can be used as two 8-bit transceivers or

SN54ABTE16245 . . . WD PACKAGE SN74ABTE16245 . . . DGG OR DL PACKAGE (TOP VIEW)



one 16-bit transceiver. They allow data transmission from the A bus to the B bus or from the B bus to the A bus, depending on the logic level at the direction-control (DIR) input. The output-enable (OE) input can be used to disable the device so that the buses are effectively isolated. When  $\overline{OE}$  is low, the device is active.

The B port has an equivalent 25- $\Omega$  series output resistor to reduce ringing. Active bus-hold inputs also are on the B port to hold unused or floating inputs at a valid logic level.

The A port provides for the precharging of the outputs via  $V_{CC}$ BIAS, which establishes a voltage between 1.3 V and 1.7 V when V<sub>CC</sub> is not connected.

Active bus-hold circuitry holds unused or undriven inputs at a valid logic state. Use of pullup or pulldown resistors with the bus-hold circuitry is not recommended.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

Widebus is a trademark of Texas Instruments



SCBS226J - JULY 1993 - REVISED DECEMBER 2001

#### **ORDERING INFORMATION**


TA	PACKAGE†		ORDERABLE PART NUMBER	TOP-SIDE MARKING	
	SSOP – DL	ABTE16245			
–40°C to 85°C		Tape and reel	SN74ABTE16245DLR	ADTE 10245	
	TSSOP – DGG	Tape and reel	SN74ABTE16245DGGR	ABTE16245	
–55°C to 125°C	CFP – WD	Tube	SNJ54ABTE16245WD	SNJ54ABTE16245WD	

<sup>†</sup> Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at www.ti.com/sc/package.

# FUNCTION TABLE (each 8-bit section)

INP	UTS	ODED ATION					
OE	DIR	OPERATION					
L	L	A data to B bus					
L	Н	B data to A bus					
Н	X	Isolation					

## logic diagram (positive logic)



# absolute maximum ratings over operating free-air temperature range (unless otherwise noted)‡

Supply voltage range, V <sub>CC</sub> and V <sub>CC</sub> BIAS	0.5 V to 7 V
Input voltage range, V <sub>I</sub> (except I/O ports) (see Note 1)	0.5 V to 7 V
Voltage range applied to any output in the high state or power-off state, VO	–0.5 V to 5.5 V
Current into any output in the low state, I <sub>O</sub>	128 mA
Input clamp current, I <sub>IK</sub> (V <sub>I</sub> < 0)	–18 mA
Output clamp current, I <sub>OK</sub> (V <sub>O</sub> < 0)	–50 mA
Package thermal impedance, θ <sub>JA</sub> (see Note 2): DGG package	70°C/W
DL package	63°C/W
Storage temperature range, T <sub>stq</sub>	–65°C to 150°C

<sup>‡</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

The package thermal impedance is calculated in accordance with JESD 51-7.



NOTES: 1. The input and output negative-voltage ratings may be exceeded if the input and output clamp-current ratings are observed.

SCBS226J - JULY 1993 - REVISED DECEMBER 2001

# recommended operating conditions (see Note 3)

			SN54	ABTE16	6245	SN74	ABTE16	3245	UNIT
			MIN	NOM	MAX	MIN	NOM	MAX	ONII
V <sub>CC</sub> , V <sub>CC</sub> BIAS	Supply voltage		4.5	5	5.5	4.5	5	5.5	V
V	High-level input voltage	ŌĒ	2			2			V
VIH	High-level input voltage	Except OE	1.6			1.6			V
\/	Low lovel input voltage	ŌĒ			0.8			0.8	V
VIL	Low-level input voltage	Except OE			1.4			1.4	V
٧ <sub>I</sub>	Input voltage		0		VCC	0		Vcc	V
lou	High lovel output ourrent	B bus			-12			-12	mA
ЮН	High-level output current	A bus			-24			-60	mA
la.	Low lovel output oursest	B bus			12			12	A
lOL	Low-level output current	A bus			64			90	mA
Δt/Δν	Input transition rise or fall rate	Outputs enabled			10			10	ns/V
T <sub>A</sub>	Operating free-air temperature		-55		125	-40		85	°C

NOTE 3: All unused control inputs of the device must be held at V<sub>CC</sub> or GND to ensure proper device operation. Refer to the TI application report, *Implications of Slow or Floating CMOS Inputs*, literature number SCBA004.

SCBS226J - JULY 1993 - REVISED DECEMBER 2001

#### electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

DAF	DAMETED	TEST 00	NDITIONS	SN	54ABTE1	6245	SN	74ABTE	16245	LIAUT	
PAR	RAMETER	1551 CC	ONDITIONS	MIN	TYP <sup>†</sup>	MAX	MIN	TYP <sup>†</sup>	MAX	UNIT	
VIK		V <sub>CC</sub> = 4.5 V,	I <sub>I</sub> = -18 mA			-1.2			-1.2	V	
		V <sub>CC</sub> = 5.5 V,	I <sub>OH</sub> = -100 μA			V <sub>CC</sub> -0.2			V <sub>CC</sub> -0.2		
	B port	V 45V	I <sub>OH</sub> = -1 mA	2.4			2.4				
V		V <sub>CC</sub> = 4.5 V	I <sub>OH</sub> = -12 mA	2			2			V	
VOH		$V_{CC} = 5.5 \text{ V},$	$I_{OH} = -1 \text{ mA}$			4.5			4.5	V	
	A port	V 45V	I <sub>OH</sub> = -32 mA	2.4			2.4				
		V <sub>CC</sub> = 4.5 V	I <sub>OH</sub> = -64 mA				2				
	D nort	V 45V	I <sub>OL</sub> = 1 mA			0.4			0.4		
V	B port	V <sub>CC</sub> = 4.5 V	I <sub>OL</sub> = 12 mA						0.8	V	
VOL	A port	V <sub>CC</sub> = 4.5 V	I <sub>OL</sub> = 64 mA			0.55			0.55	V	
	A port	vCC = 4.5 v	I <sub>OL</sub> = 90 mA						0.9		
	(hold) B port	V 45V	V <sub>I</sub> = 0.8 V	100			100			μΑ	
I <sub>I</sub> (hold)		V <sub>CC</sub> = 4.5 V	V <sub>I</sub> = 2 V	-100			-100				
		$V_{CC} = 5.5 \text{ V},$	$V_{I} = 0 \text{ to } 5.5 \text{ V}$			±500			±500		
1.	Control inputs	V <sub>CC</sub> = 5.5 V,	$V_1 = V_{CC}$ or GND			±1			±1		
tı	A or B ports	vCC = 5.5 v,	AL = ACC OLGIAD			±20			±20	μΑ	
lozh <sup>‡</sup>	A port	$V_{CC} = 5.5 \text{ V},$	V <sub>O</sub> = 2.7 V			10			10	μΑ	
lozL <sup>‡</sup>	A port	V <sub>CC</sub> = 5.5 V,	V <sub>O</sub> = 0.5 V			-10			-10	μΑ	
1-	A port	V 55V	V- 25V	-50	-120	-180	-50		-180	mA	
Ю	B port	V <sub>CC</sub> = 5.5 V,	V <sub>O</sub> = 2.5 V	-25	-52	-90	-25		-90	mA	
l <sub>off</sub>		$V_{CC} = 0$ , $V_{I}$ or $V_{O} \le$	4.5 V, V <sub>CC</sub> BIAS = 0			±100			±100	μΑ	
			Outputs high		28	36		28	36		
Icc	I <sub>CC</sub> A or B ports	$V_{CC} = 5.5 \text{ V}, I_{O} = 0,$ $V_{I} = V_{CC} \text{ or GND}$	Outputs low		38	48		38	48	mA	
		V1 = VCC 01 014B	Outputs disabled		20	32		20	32		
loop	A an D marks	V <sub>CC</sub> = 5 V,	OE high		0.02			0.02		mA/	
ICCD	A or B ports	C <sub>L</sub> = 50 pF	OE low		0.33			0.33		MHz	
C <sub>i</sub>	Control inputs	V <sub>I</sub> = 2.5 V or 0.5 V				10		2.5	4	pF	
C <sub>io</sub>	I/O ports	$V_0 = 2.5 \text{ V or } 0.5 \text{ V}$				13		4.5	8	pF	

<sup>†</sup> All typical values are at V<sub>CC</sub> = 5 V, T<sub>A</sub> = 25°C. ‡ The parameters I<sub>OZH</sub> and I<sub>OZL</sub> include the input leakage current.

SCBS226J - JULY 1993 - REVISED DECEMBER 2001

# live-insertion specifications over recommended operating free-air temperature range

DADA	METER		SN54	ABTE16	6245	SN74ABTE16245			UNIT		
PARAI	VIETER	TEST CONDITIONS				TYP <sup>†</sup>	MAX	MIN	TYP <sup>†</sup>	MAX	UNIT
loo (Va	a PIAC)	$V_{CC} = 0 \text{ to } 4.5$ $I_{O(DC)} = 0$	CC = 0 to 4.5 V, V <sub>CC</sub> BIAS = 4.5 V to 5.5 V, (DC) = 0				700		250	700	
ICC (VC	:Сыко)	$V_{CC} = 4.5 \text{ V to}$ $I_{O(DC)} = 0$	/ to 5.5 V $^{\ddagger}$ , V <sub>CC</sub> BIAS = 4.5 V to 5.5 V,				20			20	μΑ
Va	A nort	VCC = 0	V <sub>CC</sub> BIAS = 4.5 V to 5.5 V	/	1.1	1.5	1.9	1.1	1.5	1.9	V
Vo	A port	AGC = 0	V <sub>CC</sub> BIAS = 4.75 V to 5.2	1.3	1.5	1.7	1.3	1.5	1.7	V	
la	$I_O$ A port $V_{CC} = 0$ ,		VCCBIAS = 4.5 V	V <sub>O</sub> = 0	-20		-100	-20		-100	μΑ
'0			V (ССыдо = 4.5 V	V <sub>O</sub> = 3 V	20		100	20		100	μΑ

<sup>†</sup> All typical values are at  $V_{CC} = 5 \text{ V}$ ,  $T_A = 25^{\circ}\text{C}$ .

# switching characteristics over recommended ranges of supply voltage and operating free-air temperature, $C_L$ = 50 pF (unless otherwise noted) (see Figure 2)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	۷ <sub>0</sub> ۲٫	V <sub>CC</sub> = 5 V, T <sub>A</sub> = 25°C			SN54ABTE16245		SN74ABTE16245		
	(1141 01)	(0011 01)	MIN	TYP	MAX	MIN	MAX	MIN	MAX		
<sup>t</sup> PLH	А	В	1.5	3.3	4.2	1.5	5.4	1.5	5.2	ns	
<sup>t</sup> PHL	A	Ь	1.5	3.8	4.6	1.5	5.4	1.5	5.2	115	
<sup>t</sup> PLH	ь	۸	1.5	3	3.8	1.5	4.7	1.5	4.5	no	
<sup>t</sup> PHL	В	A	1.5	3.1	4	1.5	4.7	1.5	4.5	ns	
<sup>t</sup> PZH	ŌĒ	^	2	3.9	5.3	2	6.4	2	6.2		
tpZL	OE .	Α	2	4.4	5.9	2	7	2	6.8	ns	
<sup>t</sup> PZH	<del></del>	В	2	4.5	6	2	7.3	2	7.1		
tPZL	ŌĒ	В	2	5	6.4	2	7.5	2	7.3	ns	
<sup>t</sup> PHZ	ŌĒ	Δ.	2	4.9	5.9	2	7	2	6.7		
<sup>t</sup> PLZ	] OE	А	2	3.7	4.6	2	5.4	2	5.1	ns	
<sup>t</sup> PHZ	ŌĒ	В	2	5.2	6.2	2	7.2	2	7		
<sup>t</sup> PLZ	]		2	4	5	2	5.8	2	5.5	ns	



<sup>‡</sup> VCC - 0.5 V < VCCBIAS

SCBS226J – JULY 1993 – REVISED DECEMBER 2001

# extended switching characteristics over recommended ranges of supply voltage and operating free-air temperature, $C_L = 50$ pF (unless otherwise noted) (see Figure 2)

PARAMETER	RAMETER FROM TO (INPUT) (OUTPUT)		LOAD	V <sub>CC</sub> = 5 V, T <sub>A</sub> = 25°C			SN54ABTE16245		SN74ABTE16245		UNIT
	(IIVI O1)	(0011 01)		MIN	TYP	MAX	MIN	MAX	MIN	MAX	
t <sub>PLH</sub>	В	А	Rχ = 13 Ω	1.5	3.2	4	1.5	5	1.5	4.8	ns
t <sub>PHL</sub>	ם	^	Λχ = 13 22	1.5	3.8	4.7	1.5	5.8	1.5	5.6	115
tPLH	В	А	Rχ = 26 Ω	1.5	3.1	4	1.5	4.8	1.5	4.6	ns
tPHL	ם	^	Λχ = 20 12	1.5	3.5	4.4	1.5	5.2	1.5	4.9	115
t <sub>PLH</sub>	В	А	By - 56 O	1.5	3	3.8	1.5	4.7	1.5	4.5	ns
t <sub>PHL</sub>	Б	A	$R\chi = 56 \Omega$	1.5	3.3	4.2	1.5	5.1	1.5	4.7	113
	В	Α	R <sub>X</sub> = Open		0.1	0.6		2		2	
<sup>t</sup> sk(p)	А	В	R <sub>X</sub> = Open		0.4	0.8		2		2	ns
	В	А	$R_X = 26 \Omega$		0.3	8.0		2		2	
	В	А	R <sub>X</sub> = Open		0.3	0.7		1.3		1.3	
tsk(o)	Α	В	R <sub>X</sub> = Open		0.7	1.1		1.3		1.3	ns
	В	А	$R_X = 26 \Omega$		0.5	1		1.3		1.3	
tt†	В	А	$R_X = 26 \Omega$	0.5	0.8	1.5	0.5	1.5	0.5	1.5	ns
t <sub>t</sub> ‡	Α	В	R <sub>X</sub> = Open	3.5	5.5	7.3	3.5	8.1	3.5	7.9	ns

 $<sup>\</sup>dagger$  t<sub>t</sub> is measured between 1 V and 2 V of the output waveform.

# extended output characteristics over recommended ranges of supply voltage and operating free-air temperature, $C_L = 50$ pF (see Figures 1 and 2)


PARAMETER	FROM	то	TEST CONDITIONS	LOAD	SN54ABTE	16245	SN74ABTE	16245	UNIT
PARAMETER	(INPUT)	INPUT) (OUTPUT) TEST SONDITIONS ESAB	LOAD	MIN	MAX	MIN	MAX	UNIT	
• • • •	Α	В	V <sub>CC</sub> = constant,			3		2.5	
<sup>t</sup> sk(temp)	В	Α	$\Delta T_A = 20^{\circ}C$	$R\chi = 56 \Omega$		4.5		4	ns
<sup>t</sup> sk(load)	В	В	V <sub>CC</sub> = constant, Temperature = constant	$R_X = 13, 26,$ or $56 \Omega$		4.5		4	ns



<sup>‡</sup>t<sub>t</sub> is measured between 10% and 90% of the output waveform.

SCBS226J - JULY 1993 - REVISED DECEMBER 2001

#### PARAMETER MEASUREMENT INFORMATION




- NOTES: A. Pulse skew,  $t_{sk(p)}$ , is defined as the difference in propagation-delay times  $t_{PLH1}$  and  $t_{PHL1}$  on the same terminal at identical operating conditions.
  - B. Output skew, t<sub>Sk(0)</sub>, is defined as the difference in propagation delay of any two outputs of the same device switching in the same direction (e.g., |t<sub>PLH1</sub> t<sub>PLH2</sub>|).
  - C. Temperature skew,  $t_{sk(temp)}$ , is the output skew of two devices, both having the same value of  $V_{CC} \pm 1\%$  and with package temperature differences of 20°C.
  - D. Load skew,  $t_{sk(load)}$ , is measured with R<sub>X</sub> in Figure 2 at 13  $\Omega$  for one unit and 56  $\Omega$  for the other unit.

Figure 1. Voltage Waveforms for Extended Characteristics


SCBS226J - JULY 1993 - REVISED DECEMBER 2001


#### PARAMETER MEASUREMENT INFORMATION




 $\dagger R_{X} = 13, 26, \text{ or } 56 \Omega$ 

#### LOAD CIRCUIT FOR OUTPUTS





EXTENDED SWITCHING TABLE	S1	S2
LOADS	31	32
tpLH/tpHL/tsk (A port)	Down	Х
tpLH/tpHL/tsk (B port)	Up	Open
t <sub>t</sub> (A port) (see Note E)	Down	Х
t <sub>t</sub> (B port) (see Note F)	Up	Open



**ENABLE AND DISABLE TIMES** 

- NOTES: A. C<sub>I</sub> includes probe and jig capacitance.
  - B. Waveform 1 is for an output with internal conditions such that the output is low except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high except when disabled by the output control.
  - C. All input pulses are supplied by generators having the following characteristics: PRR  $\leq$  10 MHz,  $Z_Q = 50 \Omega$ ,  $t_f \leq$  2.5 ns,  $t_f \leq$  2.5 ns.
  - D. The outputs are measured one at a time with one transition per measurement.
  - E. t<sub>t</sub> is measured between 1 V and 2 V of the output waveform.
  - F. t<sub>t</sub> is measured between 10% and 90% of the output waveform.

Figure 2. Load Circuit and Voltage Waveforms



#### PACKAGE OPTION ADDENDUM

www.ti.com 15-Oct-2009

#### PACKAGING INFORMATION

Orderable Device	Status <sup>(1)</sup>	Package Type	Package Drawing	Pins	Package Qty	Eco Plan <sup>(2)</sup>	Lead/Ball Finish	MSL Peak Temp <sup>(3)</sup>
5962-9677501QXA	ACTIVE	CFP	WD	48	1	TBD	A42	N / A for Pkg Type
74ABTE16245DGGRE4	ACTIVE	TSSOP	DGG	48	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
74ABTE16245DGGRG4	ACTIVE	TSSOP	DGG	48	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
74ABTE16245DLRG4	ACTIVE	SSOP	DL	48	1000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SN74ABTE16245DGGR	ACTIVE	TSSOP	DGG	48	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SN74ABTE16245DL	ACTIVE	SSOP	DL	48	25	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SN74ABTE16245DLG4	ACTIVE	SSOP	DL	48	25	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SN74ABTE16245DLR	ACTIVE	SSOP	DL	48	1000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SNJ54ABTE16245WD	ACTIVE	CFP	WD	48	1	TBD	A42	N / A for Pkg Type

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

**Pb-Free** (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



#### TAPE AND REEL INFORMATION



# TAPE DIMENSIONS KO P1 BO W Cavity A0

A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

## QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



#### \*All dimensions are nominal

Device	Package Type	Package Drawing			Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN74ABTE16245DGGR	TSSOP	DGG	48	2000	330.0	24.4	8.6	15.8	1.8	12.0	24.0	Q1
SN74ABTE16245DLR	SSOP	DL	48	1000	330.0	32.4	11.35	16.2	3.1	16.0	32.0	Q1





\*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)	
SN74ABTE16245DGGR	TSSOP	DGG	48	2000	346.0	346.0	41.0	
SN74ABTE16245DLR	SSOP	DL	48	1000	346.0	346.0	49.0	

#### DL (R-PDSO-G\*\*)

#### **48 PINS SHOWN**

#### PLASTIC SMALL-OUTLINE PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion not to exceed 0.006 (0,15).

D. Falls within JEDEC MO-118

## DGG (R-PDSO-G\*\*)

## PLASTIC SMALL-OUTLINE PACKAGE

#### **48 PINS SHOWN**



NOTES: A. All linear dimensions are in millimeters.

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold protrusion not to exceed 0,15.

D. Falls within JEDEC MO-153

#### WD (R-GDFP-F\*\*)

#### **CERAMIC DUAL FLATPACK**

#### **48 LEADS SHOWN**



NOTES: A. All linear dimensions are in inches (millimeters).

- B. This drawing is subject to change without notice.
- C. This package can be hermetically sealed with a ceramic lid using glass frit.
- D. Index point is provided on cap for terminal identification only
- E. Falls within MIL STD 1835: GDFP1-F48 and JEDEC MO-146AA

GDFP1-F56 and JEDEC MO-146AB

#### **IMPORTANT NOTICE**

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

**Applications Products Amplifiers** amplifier.ti.com Audio www.ti.com/audio Data Converters Automotive www.ti.com/automotive dataconverter.ti.com DLP® Products Broadband www.dlp.com www.ti.com/broadband DSP Digital Control dsp.ti.com www.ti.com/digitalcontrol Clocks and Timers www.ti.com/clocks Medical www.ti.com/medical Military Interface www.ti.com/military interface.ti.com Optical Networking Logic logic.ti.com www.ti.com/opticalnetwork Power Mgmt power.ti.com Security www.ti.com/security Telephony Microcontrollers microcontroller.ti.com www.ti.com/telephony Video & Imaging www.ti-rfid.com www.ti.com/video RF/IF and ZigBee® Solutions www.ti.com/lprf Wireless www.ti.com/wireless

> Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2009, Texas Instruments Incorporated