

**TOSHIBA**

**TC9308AF-055**

TOSHIBA CMOS DIGITAL INTEGRATED CIRCUIT SILICON MONOLITHIC

# TC9308AF-055

## DIGITAL TUNING SYSTEM (DTS-11)

The TC9308AF-055, In combination with the prescaler TD6134AF, is capable of composing a digital tuning system that is optimum to such portable as pocket radio, headphone stereo and the like. Receiving frequency bands are 2 bands of FM/AM for shipment.

### FEATURES

○ Receiving frequency bands

AREA	CODE		BAND	RECEIVING FREQUENCY [Hz]	STEP [Hz]	FREF [Hz]	IF [Hz]	PRESET MEMORY
	E0	E1						
JPN	0	0	FM	76.0~ 90.0M	100k	12.5k	- 10.7M	fixed 10 stations
			MW	530~ 1610k	10k	5k	+ 450k	
				531~ 1629k	9k	3k	+ 450k	
USA	0	1	FM	87.5~ 108.0M	100k	12.5k	+ 10.7M	fixed 10 stations
			MW	530~ 1710k	10k	5k	+ 450k	
				531~ 1602k	9k	3k	+ 450k	
Eur.	1	0	FM	87.50~108.00M	50k	12.5k	+ 10.7M	fixed 10 stations
			MW	530~ 1610k	10k	5k	+ 450k	
				531~ 1602k	9k	3k	+ 450k	

○ Functions

- Tuning function
  - Manual up/down tuning : 1 step/ 1push tuning
  - Auto-tuning (Seek system) : Continuous pushing the key automatically shifts to auto mode
  - IF count type auto stop system in combination with the TA8132F has been adopted

○ Memory function

- FM/AM each the stations

○ Other functions

- The Step frequency of MW band can choose 9kHz or 10kHz
- Beep sound output


980910EBA2

● TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.

● The products described in this document are subject to the foreign exchange and foreign trade laws.

● The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.

● The information contained herein is subject to change without notice.



TC9308AF-055 Layout

