


Small Signal Transistors TO-46 Case



TYPE NO.	DESCRIPTION	BV _{CB0}	BV _{CEO}	BV _{EBO}	I _{CB0} @	V _{CB}	h _{FE}		@ I _C	@ V _{CE}	V _{CE} (SAT) @ I _C		C _{ob}	f _T	N _F	t _{off}
		(V)	(V)	(V)	(μA)	(V)	MIN	MAX	(mA)	(V)	(V)	(mA)	(pF)	(MHz)	(dB)	(ns)
		MIN	MIN	MIN	***ICEV						MAX	MAX	MAX	MIN	MAX	MAX
2N2604	PNP LOW NOISE	60	45	6.0	0.01	45	40	120	0.01	5.0	0.5	10	6.0	30	4.0	--
2N2605	PNP LOW NOISE	60	45	6.0	0.01	45	100	300	0.01	5.0	0.5	10	6.0	30	3.0	--
2N3485*	PNP AMPL/SWITCH	60	40	5.0	0.02	50	40	120	150	10	1.6	500	8.0	200	--	180
2N3485A*	PNP AMPL/SWITCH	60	60	5.0	0.01	50	40	120	150	10	1.6	500	8.0	200	--	180
2N3486*	PNP AMPL/SWITCH	60	40	5.0	0.02	50	100	300	150	10	1.6	500	8.0	200	--	180
2N3486A*	PNP AMPL/SWITCH	60	60	5.0	0.01	50	100	300	150	10	1.6	500	8.0	200	--	180
2N3508	NPN SAT SWITCH	40	20	6.0	0.2	20	40	120	10	1.0	0.45	100	4.0	500	--	28
2N3509*	NPN SAT SWITCH	40	20	6.0	0.2	20	100	300	10	1.0	0.45	100	4.0	500	--	28
2N3647*	NPN SAT SWITCH	40	10	6.0	0.025**	10	25	150	150	1.0	0.6	300	4.0	350	--	25
2N3648*	NPN SAT SWITCH	40	15	6.0	0.025**	10	30	120	150	1.0	0.8	500	4.0	450	--	18
2N3673*	NPN AMPL/SWITCH	60	50	5.0	0.01	50	75	225	150	10	1.6	500	9.0	200	--	100
2N3736*	NPN SAT SWITCH	50	30	5.0	0.2**	25	30	120	1,000	1.5	0.9	1,000	9.0	250	--	60
2N3737*	NPN SAT SWITCH	75	50	5.0	0.2**	40	20	80	1,000	1.5	0.9	1,000	9.0	250	--	60
2N4449*	NPN AMPL/SWITCH	40	15	4.5	0.4	20	40	--	10	1.0	0.18	10	4.0	500	--	12
2N5581*	NPN AMPL/SWITCH	75	40	6.0	0.01	50	40	120	150	10	1.6	500	8.0	250	--	285
2N5582	NPN AMPL/SWITCH	75	40	6.0	0.01	50	100	300	150	10	1.6	500	8.0	300	--	285

*Available on special order; please consult factory.

Copyright © Each Manufacturing Company.

All Datasheets cannot be modified without permission.

This datasheet has been download from :

www.AllDataSheet.com

100% Free DataSheet Search Site.

Free Download.

No Register.

Fast Search System.

www.AllDataSheet.com